



3D Printer User Manual


Applicable Models:

CR-5/CR-5S/CR-3040

CR-4026/CR-4040

CR-5060/CR-5080 etc.

- ◆ Because of software or hardware upgrades and model differences, new revisions may not be listed in this Manual.
- ◆ Please plug the power cord into a three-hole power jack.
- ◆ Detailed instructions for use are available on the TF card.



Parameters

Basic Parameters			
Mode Name	CT-5	CT-5S	CT-3040S
Molding Size	300*225*320mm	300*225*320mm	300*300*400mm
Molding Technology	FDM		
Number of Nozzles	1		
Print Layer Thickness	0.1mm-0.4mm		
Nozzle Diameter	0.4mm		
Print Precision	±0.1mm		
Filament	1.75mm PLA		
File Format	STL/OBJ/AMF		
Printing Method	Online or TF Card Offline		
Slicing Software	Creality Slicer/Cura/Repetier-Host/Simplify3D		
Rated Voltage	115V/230V 50/60Hz		
Output Voltage	12V		
Rated Power	270W	270W	250W
Platform Temp.	≤100℃	≤100℃	≤75℃
Nozzle Temp.	≤250℃		
Resume Print	Yes	Yes	Yes
Filament Detector	Yes	Yes	Yes
Double Z Axis	No	Yes	Yes
Multi-Language	Support	Support	Support
Operation System	Windows XP/Vista//7/8/10 MAC/Linux		
Printing Speed	≤180mm/s, Normal 30-60mm/s		

CT-5060		CT-5080	Model Name(Customized)
400*400*426mm		400*400*400mm	Customized
FDM			
1			
0.1mm-0.4mm			
0.4mm			
±0.1mm			
1.75mm PLA			
STL/OBJ/AMF			
Online or TF Card Offline			
Creality Slicer/Cura/Repetier-Host/Simplify3D			
115V/230V 50/60Hz			
12V			
270W	270W		
≤55℃	≤55℃		
≤250℃			
Yes	Yes		
Yes	No		
Yes	No		
Support	Support		
Windows XP/Vista//7/8/10 MAC/Linux			
≤180mm/s, Normal 30-60mm/s			

CONTENTS

Dear Consumers:

Thank you for choosing our products. For the best experience, please read the instructions before operating the Printer. Our 3D team will always be ready to give you the best service. Please contact us via the phone number or e-mail address provided at the end when you encounter any problem with the Printer.

For a better experience in using our product, you may learn how to use the Printer in the following ways:

1. View the accompanied instructions and videos on the TF card.
2. Visit our official website at www.creality3d.cn You will find relevant software/hardware information, contact details and operation and maintenance instructions on the website.

Introduction.....	1
General List.....	2
Device Installation.....	3
Screen Information.....	4
Loading Filament.....	5
Bed Leveling.....	6
Software Installation.....	7
First Printing.....	8


NOTES

1. Do not use the printer any way other than described herein in order to avoid personal injury or property damage.
2. Do not place the printer near any heat source or flammable or explosive objects. We suggest placing it in a well-ventilated, low-dust environment.
3. Do not expose the printer to violent vibration or any unstable environment, as this may cause poor print quality.
4. It is recommended to use the manufacturer's recommended filaments to avoid blockage of the extrusion mechanism or damage to the machine.
5. Do not use any other power cable except the one supplied. Always use a grounded three-prong power outlet.
6. Do not touch the nozzle or printing surface during operation as they may be hot. Keep hands away from machine while in use to avoid burns or personal injury.
7. Do not wear gloves or loose clothing when operating the printer. Such cloths may become tangled in the printers moving parts leading to burns, possible bodily injury, or printer damage.
8. When cleaning debris from the printer hotend, always use the provided tools. Do not touch the nozzle directly when heated. This can cause personal injury.
9. It is necessary to do product maintenance regularly, and clean the body with a dry cloth when power off, wipe off dust ,bonded printed materials, and foreign objects on the rails.
10. Children under 10 years of age should not use the printer without supervision.



01/

Introduction

Double-color printer without Filament Detector Device




The Location Map of Proximal Extruder



The Location Map of Remote Extruder

02/

General List




Printer



Filament

Note:

Double-color printer, the filament holder tube, PTFE tube, nozzle, filament are double.



Tool box

Tool List

No.	Image	Name	Qty
1		Wrench & Screw Driver	1
2		Socket Wrench	1
3		Spade	1
4		Pliers	1
5		0.4mm Nozzle Cleaner	1


No.	Image	Name	Qty
6		Tweezers	1
7		Grease	1
8		Solid Glue	2
9		Power Cable	1
10		Filament Holder Tube	2

No.	Image	Name	Qty
11		PTFE Tube	2
12		USB Cable	1
13		TF Card & Reader	1
14		Spare Parts	1
15		Utility knife	1

*The list is for reference, subject to the actual object.



03/

Device Installtion





①

Installing the spool holder and place the filament.



②

Passing the filament through the filament doctor detector device.




③

Connect power cable and power on

04/

Screen Information

The pictures are for reference only, subject to the actual UI



ReadyPrint



Preheat



Move



Home



Printing



Extrusion



Leveling



Settings



More

ReadyPrint>Preheat



Add

E1
27/200



Dec



Extruder1



10°C



Close



Back

ReadyPrint>Move



X+



Y+



Z+



1mm



X-



Y-



Z-



Back

ReadyPrint>Home



All



X



Y



Z



Motor-off



Back

ReadyPrint>ChooseFile



01



02



03



04



05



06



Z-



Back

ReadyPrint>Extrusion



In

E1: 0mm

Temp: 27



Out



Extruder1



5mm



Low



Back

ReadyPrint>Settings



FileSys



WiFi



Fan



About



Continue



Filament



Language



Back

ReadyPrint>Leveling



Point1



Point2



Point3



Point4



Point5





Back



05/

Loading Filament

1、Preheat





1、Click Preheat, Waiting until the temperature get to 200°C.




2、Click Setting→Change Filament→Feed, Passing the filament to Extruder by hands.

2、Feeding



Or



Press the extrusion spring, insert the filament from the small hole in the extruder to the nozzle position, and see that the filament flow out from the nozzle, that the filament has been loaded.

Double-color printer ,the second extruder only need to deliver the filament above the nozzle module during loading. otherwise printing will be failure




Tips: How to Replace the Filament?

Method 1: Cut the filament that close to the extruder, and slowly feed the new filament until the filament are fed into the tube.

Method 2: After preheating the nozzle, quickly withdraw the filament and feed the new filament.

06/

Bed Levelling





1、Choose Leveling → Choose "First point ", The nozzle will move to the left front of the platform. Screw and adjust the print platform nozzles so that they are in a proper fit with a spacing of approximately 0.05 mm.



(We can use an A4 paper to level so that the nozzle just scratches the A4 paper).

2、The second point, the third point, the fourth point, and the fifth point are adjusted in sequence.



3、Repeat the above steps 1-2 times if necessary.



The nozzle is far from the platform so that the filament can't adhere to the platform.



The filament are evenly extruded and just attached to the platform.



The nozzle is too close to the platform, the filament is insufficiently extruded, and even the platform is scratched.

07/

Software Installation




Creality
Slicer_1.2.1.msi

1. Double click to
install the software.




2. Double click to
open the software.




3. Select language→Next→Select your machine→Next→Finish.

08/

First Printing




Open Creality Slicer → Load (choose file) → Change parameters → Toolpath to TF



Insert TF Card → Printing → Choose Model File

How to print in two colors (Two-Color printer)

Load all parts of models



- Dual extrusion merge
- Delete all objects
- Reload all objects
- Reset all objects positions
- Reset all objects transformations

R-Click to merge models

After– Sales Service

Service

1. The printer can be returned within seven days, 15 days replacement, one year warranty, lifetime maintenance.

Replacement requirement

1. The appearance of the product is intact, without damage, scratches, smudges, cracks, deformation, etc.;

2. Machine parts, tools and others are complete;

3. Provide a complete and valid purchase invoice and warranty, product number should be the same.

Warranty coverage

1. The following accessories are not included in the warranty coverage if they are not damaged by transportation: platform sticker; platform forming plate; acrylic cover; card reader and TF card; platform glass; USB cable; filament; rack and tools, etc.

2. Profile: Before we deliver the goods, we will test machine, so maybe there will be light scratch, or due to long-distance transportation, which scratch the profile a little bit. In the premise of not affecting the normal use, in principle, not within the scope of warranty;

3. Nozzle assembly (nozzle, heating block, throat pipe, heat sink, PTFE tube, etc.) warranty period is 3 months, if they are damaged after the warranty expires, you need to purchase another one;

4. Motherboard, LCD display, power supply, hot bed, warranty period is 12 months, if there are quality problems, you can get free maintenance; over the warranty period, can be sent back to the original factory maintenance, the users need to bear the return shipping fee and maintenance costs;

5. Not included in warranty coverage:

(1) It is not possible to provide an effective after-sales service card or serial number;

(2) The whole machine and components exceed the warranty period;

(3) Equipment failure or damage caused by unauthorized modification of the equipment (private modification includes: 1. modification of the nozzle assembly; 2. modification of the machine structure; 3. use of third-party components; 4. use of third-party firmware procedures or change the original Factory firmware program, etc.);

(4) Equipment failure or damage due to incorrect installation and use;

(5) Equipment failure or damage caused by the use of the equipment in a working environment not specified by the product;

(6) Equipment failure or damage due to improper use (beyond workload, etc.) or maintenance (moisture, etc.);

(7) Equipment failure or damage due to the use of other branded components or low quality consumables.



SHENZHEN CREALITY 3D TECHNOLOGY CO., LTD.

12/F, Block 3, JinChengYuan, Huafan Road, Tongsheng Community,
Dalang, Longhua District, Shenzhen, China, 518109

Official Website: www.creality3d.cn

Tel: +86 755-2105 9455

E-mail: info@creality3d.cn cs@creality3d.cn

