I/O LIST - TANK AND TREATMENT SYSTEMS (SCAN)

Photocopy of IO-004 Rev C

Tag	Description	Type	Unit	Range low	Range high	HH	H	L	LL	Delay s
BLR-BRN2-YS01	Burner 1 start command (bank 2)	DO								
BLR-BRN2-YS02	Burner 2 start command (bank 2)	DO								
PMS-GRB2-VT01	Main busbar voltage section 1 (bank 2)	AI	kV	0	12	10.6	9.6	1.8		30
PMS-GRB2-VT02	Main busbar voltage section 2 (bank 2)	AI	kV	0	12	11	9	2.4		15
PMS-GRB2-VT03	Main busbar voltage section 3 (bank 2)	AI	kV	0	12	10.6	9.6	3		3
PMS-GRB2-II01	Generator breaker current 1 (bank 2)	AI	A	0	3500	3080	2975			2
PMS-GRB2-II02	Generator breaker current 2 (bank 2)	AI	A	0	3500	3220	2975			10
PMS-GRB2-II03	Generator breaker current 3 (bank 2)	AI	A	0	3500	3360	2975			2
PMS-GRB2-II04	Generator breaker current 4 (bank 2)	AI	A	0	3500	3080	2975			0
PMS-GRB2-JT01	Generator active power 1 (bank 2)	AI	kW	0	5000	4400				3
PMS-GRB2-JT02	Generator active power 2 (bank 2)	AI	kW	0	5000	4800				5
PMS-GRB2-JT03	Generator active power 3 (bank 2)	AI	kW	0	5000	4400				10
PMS-GRB2-ST01	Busbar frequency 1 (bank 2)	AI	Hz	45	65	63.4	62	50	46.6	5
PMS-GRB2-ST02	Busbar frequency 2 (bank 2)	AI	Hz	45	65	63.4	60	48	47.2	10
PMS-GRB2-XS01	Generator breaker 1 closed (bank 2)	DI								
PMS-GRB2-XS02	Generator breaker 2 closed (bank 2)	DI								
PMS-GRB2-XS03	Generator breaker 3 closed (bank 2)	DI								
PMS-GRB2-XS04	Generator breaker 4 closed (bank 2)	DI								
PMS-SHR2-JT01	Shore connection power 1 (bank 2)	AI	kW	0	2500	2200				30
PMS-SHR2-JT02	Shore connection power 2 (bank 2)	AI	kW	0	2500	2200				5
PMS-SHR2-II01	Shore connection current 1 (bank 2)	AI	A	0	1600	1536	1280			3
PMS-SHR2-II02	Shore connection current 2 (bank 2)	AI	A	0	1600	1408	1200			3
PMS-SHR2-II03	Shore connection current 3 (bank 2)	AI	A	0	1600	1408	1280			3
PMS-SHR2-VT01	Shore connection voltage 1 (bank 2)	AI	V	0	480	460.8	408	96	38.4	2

Scanned copy - original held by the customer

I/O LIST - TANK AND TREATMENT SYSTEMS (SCAN)

Photocopy of IO-004 Rev C

Tag	Description	Type	Unit	Range low	Range high	HH	H	L	LL	Delay s
PMS-SHR2-VT02	Shore connection voltage 2 (bank 2)	AI	V	0	480	461	408	96	38	15
BWTS-UVR2-II01	UV reactor lamp current 1 (bank 2)	AI	A	0	30		22.5	6		2
BWTS-UVR2-II02	UV reactor lamp current 2 (bank 2)	AI	A	0	30		22.5	6		15
BWTS-UVR2-TT01	UV reactor water temperature 1 (bank 2)	AI	°C	0	80	70.4	64			10
BWTS-UVR2-TT02	UV reactor water temperature 2 (bank 2)	AI	°C	0	80	70.4	68			10
BWTS-UVR2-PT01	UV reactor pressure 1 (bank 2)	AI	bar	0	10		8	2.5	1.1	3
BWTS-UVR2-PT02	UV reactor pressure 2 (bank 2)	AI	bar	0	10		7.5	2	0.5	0
BWTS-UVR2-PT03	UV reactor pressure 3 (bank 2)	AI	bar	0	10		8	1.5	0.5	10
BWTS-UVR2-FT01	Ballast treatment flow 1 (bank 2)	AI	m3/h	0	3000		2550			15
BWTS-UVR2-FT02	Ballast treatment flow 2 (bank 2)	AI	m3/h	0	3000		2250			10
BWTS-UVR2-AT01	Residual oxidant (bank 2)	AI	ppm	0	10		8.5			30
BWTS-FLT2-PT01	Filter differential pressure 1 (bank 2)	AI	bar	0	2	1.76	1.6			15
BWTS-FLT2-PT02	Filter differential pressure 2 (bank 2)	AI	bar	0	2	1.76	1.6			5
BWTS-FLT2-PT03	Filter differential pressure 3 (bank 2)	AI	bar	0	2	1.76	1.5			10
BWTS-FLT2-XS01	Filter 1 backflush active (bank 2)	DI								
BWTS-FLT2-XS02	Filter 2 backflush active (bank 2)	DI								
BWTS-FLT2-XS03	Filter 3 backflush active (bank 2)	DI								
BWTS-FLT2-ZT01	Filter inlet valve 1 position (bank 2)	AI	%	0	100					
BWTS-FLT2-ZT02	Filter inlet valve 2 position (bank 2)	AI	%	0	100					
TANK-TK24-LT01	Cargo oil tank 24 level 1	AI	%	0	100	96	85	25	11	5
TANK-TK24-LT02	Cargo oil tank 24 level 2	AI	%	0	100	92	80	25	11	5
TANK-TK24-LT03	Cargo oil tank 24 level 3	AI	%	0	100	88	80	15	5	10
TANK-TK24-TT01	Cargo oil tank 24 temperature 1	AI	°C	0	100		85			0
TANK-TK24-TT02	Cargo oil tank 24 temperature 2	AI	°C	0	100		75			15

Scanned copy - original held by the customer