

Thorlabs OSA20X Labview Drivers 3.3.1

Installation package or ZIP-file

The drivers are available as a vi package or a zipped project. The vi package, (vip-file), created with VI Package Manager, will install the OSA20X drivers in the Labview environment for driver access through an Instrument I/O and Instrument Driver diagram palette. The vi package installation will also enable access to the driver project file, help files and example vis from the Labview Help menu.

Please make sure the OSA GUI application has been installed before installing the Labview drivers! See the Labview 32/64 bit versions section below for required settings during the application installation.

FTSLib.dll

The driver vis are based on functions in FTSLib.dll version 2.5, build 3/11/2015 or later, located under Thorlabs OSA in the OSA GUI application installation directory, (Program Files\..). The OSA GUI application installation updates the Path system environment variable with the FTSLib.dll path.

For detailed information of FTSLib.dll functions; see Thorlabs OSA\lib\FTSLib.docx and the include h-files, available from the Labview Help menu after vip package installation, and located in Thorlabs OSA\lib and \include folders.

Labview 32/64 bit versions

The driver, created in 64bit Labview 2010, must be mass compiled if using a 32 bit Labview version or a Labview version newer than 2010. When installed from the vip installation package; the drivers will be automatically mass compiled by the installed Labview version, or if several versions of Labview are installed; the target Labview version can be selected in the installation wizard. 32 bit Labview requires 32-bit FTSLib.dll - select 32-bit Compatibility while installing the OSA GUI application, (64 bit OS). Also, with 32 bit Labview and 64 bit OS; the Path system environment variable must contain the 32bit Thorlabs OSA GUI application installation path, Program (x86)\.., and not the 64bit ditto, see Installation package above.

Driver vis

See the TREE vi for a categorized overview of the driver vis and the example vis for guidelines of how to use them. For most applications the FTSLib.dll functions supported by the Labview drivers will be appropriate; however some functions have not yet been implemented. When adding new vis that call functions in FTSLib.dll we recommend the Labview import shared library tool.

Example vis

A simple example shows the basic spectrum retrieval and buffering procedure, and a more complex how to retrieve both interferogram and spectrum with some post dataprocessing. There are also examples for setting data-acquisition options, instrument properties and interferogram/spectrum analysis. A traces example shows how to make use of data buffers allocated by FTSLib.dll.

Support Files

FTSLV.dll was created for Labview calls to FTSLib functions requiring function pointer parameters. Addresses to functions within FTSLV.dll are fetched via kernel32.dll and serve as input parameter values to data acquisition functions in FTSLib.dll.

FTSLib.lvlib contains some Labview autogenerated FTSLib.dll wrappers used in some of the driver vis, (most of the vis calling FTSLib.dll functions don't have wrappers).

_goop4.llb contains vis supporting the Thorlabs_OSA_64 class.

Building Executables

See the Thorlabs OSA20X project build specification for the OSA20X_Example.vi, (regarding support files).

The path to FTSLib.dll and FTSLV.dll must be set in the PATH system environment variable, (updated during OSA GUI application installation).

OSA20X class

The fact that the driver vis are part of a GOOP class does not necessarily require any attention. When adding new driver vis we recommend starting out with existing driver vis as templates to comply with and conveniently access GOOP class/objects properties.

NI GOOP Development Suite can be downloaded from ni.com, but is only compatible with Labview 2013 and later.

Known Issues

Large Data Sets

When acquiring the largest interferogram datasets in conjunction with zero fill and other data analysis functions; see chapter 7, 'Recommended Hardware and Software Requirements' in the Thorlabs OSA manual. Data-acquisition to traces instead of to the labview buffer will in most cases improve performance/execution time.

Changes Log

2.3.0 to 2.3.1

Bugfix: convert unit vis involving conversion to or from wavenr updated according to latest FTLib help, (FTSLib.dll version 2.40).

Bugfix: optionsAcq_zeroFillFactor.vi - zeroFill input parameter range check.

Bugfix: dataProcess_peaks.vi - y-unit input parameter removed, (data taken from buffer vi, where unit is mW absolute power).

Bugfix: environment_get.vi.

2.3.2

Example added: OSA20X_example_XYarray.vi

Bugfix: dataAcq_X_wnr_create.vi

3.0.0

Support for traces - acquire to trace, trace file IO, trace parameters and trace math.

Changed: instrumentProperties_status.vi updates status regardless of acquisition state, (calls FTS_ReadInstrumentStatus).

3.1.0

Bugfix 32 bit version dataAcq_get_spectrum.

Bugfix 32 bit version dataAcq_get_spectrum_trace.

3.2.0

Bugfix: plot_update.vi

Added: plot_XY.vi

plot_example_XY

Plot vis added to OSA200 diagram palette

3.3.0

Bugfix: instrumentProperties_model.vi

Updated: trace_properties_double.vi (added property gainLevel)

3.3.1

200 C models support

Updated: instrumentProperties_model.vi