

Information Theory & Error Correcting Codes

2.2.2. Conditional Entropy	9
2.2.3. Mutual Information	10
2.2.4. Data-Processing Inequality	10
CHAPTER 3: SOURCE CODING	12
3.1. Source Coding	12
3.1.1. Principles Of Instantaneous Code Construction	13

Written by HADIOUCHE Azouaou.

Disclaimer

This document contains the lectures given by Dr. Seffah.

To separate the contents of the course to actual additions or out of context information, a black band will be added by its side like the one on this comment.

Contents

CHAPTER 0: REMAINDERS	2
1. Congruences & $\mathbb{Z}/m\mathbb{Z}$ Arithmetic	2
2. Euler φ Function	2
3. Quadratic Residues	3
CHAPTER 1: INTRODUCTION TO INFORMATION THEORY ...	6
1.1. The Communication System Model	6
1.1.1. Source & Message	6
1.1.2. Transmitter Processing	6
1.1.3. Receiver Processing	6
CHAPTER 2: INFORMATION & ENTROPY	7
2.1. Quantifying Information	7
2.2. Measures Of Entropy	8
2.2.1. Joint Entropy	8

Chapter 0

Remainders

1. Congruences & $\mathbb{Z}/m\mathbb{Z}$ Arithmetic

Definition 1.1 (Congruence Of Integers / Congruence Class): Let $a, b, m \in \mathbb{Z}$ with $m > 0$, we say that a is congruent to b modulo m and we write $a \equiv b \pmod{m}$ if $m \mid a - b$ which gives an equivalence relation. The class of a in the congruence relation by m is called the congruence class of a modulo m , which is $\bar{a} = a + m\mathbb{Z}$.

Theorem 1.2: Let $a, b, c, d \in \mathbb{Z}$ and $m \in \mathbb{N}$, with $a \equiv b \pmod{m}$ and $c \equiv d \pmod{m}$ then we have the following statements are true:

1. $a + c \equiv b + d \pmod{m}$.
2. $a - c \equiv b - d \pmod{m}$.
3. $ac \equiv bd \pmod{m}$.

We denote $\mathbb{Z}/m\mathbb{Z}$, the set of all congruence classes modulo m .

2. Euler φ Function

Definition 2.3 (φ Function): The Euler φ function is defined as $\varphi : \mathbb{Z} \rightarrow \mathbb{N}$, where $\varphi(n) = \#\{x \in \llbracket 0, m-1 \rrbracket \mid \gcd(x, m) = 1\}$.

Lemma 4: Let $r, m, p \in \mathbb{N}$ where p is prime, then $\gcd(m, p^r) \neq 1 \Leftrightarrow p \mid m$

Proof. $\Rightarrow$ let $d = \gcd(m, p^r)$, since $d \mid p^r$ and p is prime then $d = p^k$ for some $k \in \mathbb{N}$, and $p^k = d \mid m$ thus $p \mid p^k$ and $p^k \mid m$ so $p \mid m$. $\Leftarrow$ suppose that $p \mid m$ and since $p \mid p^r$ too then $p \mid \gcd(m, p^r)$ given $p > 1$ then $\gcd(m, p^r) \neq 1$. ■

Proposition 2.5: Let p be a prime number, then $\varphi(p) = p - 1$ and $\varphi(p^r) = p^r - p^{r-1} = p^r \left(1 - \frac{1}{p}\right)$.

Proof. Let $p, r \in \mathbb{N}$ with p prime. From the lemma, we have that for $m \in \mathbb{N}$, $\gcd(p^r, m) = 1 \Leftrightarrow p \nmid m$, the numbers that are divisible by p in $\llbracket 0, p^r - 1 \rrbracket$ are of the form kp where $k \in \llbracket 0, p^{r-1} - 1 \rrbracket$, so the number of numbers that are divisible by p in $\llbracket 0, p^r - 1 \rrbracket$ is $p^r - p^{r-1}$ so $\varphi(p^r) = p^r - p^{r-1}$. ■

Theorem 2.6 (Lagrange): Let G be a finite group and H a subgroup of G , then $\#H \mid \#G$.

This theorem is already done multiple times in algebra so no need to prove it here.

Lemma 2.7: Let $n \in \mathbb{N}$, $x \in (\mathbb{Z}/n\mathbb{Z})^*$ (invertible) $\Leftrightarrow \gcd(x, n) = 1$.

Proof. $\Rightarrow$ Suppose that $x \in (\mathbb{Z}/n\mathbb{Z})^*$, then $\exists y \in \mathbb{Z}/n\mathbb{Z}$ such that $xy = 1 \pmod{n}$, then $xy = 1 + kn \Rightarrow xy - kn = 1$ by Bezout theorem we have $\gcd(x, n) = 1$. $\Leftarrow$ Suppose that $\gcd(x, n) = 1$, by Bezout theorem, $\exists y, k \in \mathbb{Z}$, $xy + kn = 1$ and thus $xy + kn = 1 \pmod{n} \Rightarrow xy = 1 \pmod{n}$ so $x \in (\mathbb{Z}/n\mathbb{Z})^*$. ■

We need this lemma since $\varphi(n) = \#(\mathbb{Z}/n\mathbb{Z})^*$.

Theorem 2.8 (Euler): Let m be a positive integer modulo a be an integer relatively prime to m then $a^{\varphi(m)} \equiv 1 \pmod{m}$.

Proof. Let a relatively prime to m , then $\gcd(a, m) = 1 \Rightarrow a \in (\mathbb{Z}/m\mathbb{Z})^*$, a has finite order thus $\exists k \in \mathbb{N}$, $a^k = 1 \pmod{m}$, $\langle a \rangle$ is a subgroup of $(\mathbb{Z}/m\mathbb{Z})^*$ so $k \mid \#(\mathbb{Z}/m\mathbb{Z})^* = \varphi(m)$ and thus $\varphi(m) = kb$, thus $a^{\varphi(m)} = a^{kb} = (a^k)^b = 1^b = 1 \pmod{m}$, which completes the proof. ■

Corollary 2.9 (Fermat): Let p be a prime, if the integer a is not divisible by p then $a^p \equiv a \pmod{p}$.

Proof. Just take $m = p$ in Euler's theorem, then $\varphi(m) = p - 1$ so $a^{\varphi(m)} = a^{p-1} \equiv 1 \pmod{p}$, so $a^p \equiv a \pmod{p}$. ■

3. Quadratic Residues

Definition 3.10 (Quadratic Residue): Let p be an odd prime and a an integer not divisible by p , we say that a is a quadratic residue modulo p if there exists $x \in \mathbb{Z}$, such that $x^2 \equiv a \pmod{p}$.

Theorem 3.11: An integer a is a quadratic residue modulo p if and only if $\gcd(a, p) = 1$ and a has a square rest modulo p .

Proof. $\Rightarrow$ Suppose that a is a quadratic residue modulo p , that is, there exists $x \in \mathbb{Z}$ such that $x^2 \equiv a \pmod{p}$. If $\gcd(a, p) \neq 1$ then $p \mid a$ so $a \equiv 0 \pmod{p}$ thus $x = 0$, so necessarily $\gcd(a, p) = 1$ and a has x^2 remainder when divided by p thus the rest is a perfect square. $\Leftarrow$ Suppose now that $\gcd(a, p) = 1$ and a has a square rest modulo p , then $a \not\equiv 0 \pmod{p}$ and $a \equiv x^2 \pmod{p}$ thus a is quadratic residue. ■

Definition 3.12 (Legendre Symbol): Let p be an odd prime, define the Legendre symbol as:

$$\left(\frac{a}{p}\right) = \begin{cases} 1 & \text{if } \gcd(a, p) = 1 \text{ and } a \text{ is a quadratic residue mod } p \\ -1 & \text{if } \gcd(a, p) = 1 \text{ and } a \text{ is not a quadratic residue} \\ 0 & \text{if } p \text{ divides } a \end{cases}$$

Theorem 3.13: Let p be an odd prime, for every integer a

$$\left(\frac{a}{p}\right) \equiv a^{\frac{p-1}{2}} \pmod{p}$$

Proof. We treat by cases

1. $p \mid a$: then $a \equiv 0 \pmod{p} \Rightarrow a^{\frac{p-1}{2}} \equiv 0^{\frac{p-1}{2}} \equiv 0 \pmod{p}$.
2. $p \nmid a$: then $\gcd(a, p) = 1$, by Fermat's little theorem we have that $a^{p-1} \equiv 1 \pmod{p}$, the square roots of 1 are -1 and 1 only thus $a^{\frac{p-1}{2}} \equiv 1$ or $-1 \pmod{p}$.
 1. If a is a quadratic residue then $\exists x \in \mathbb{Z}$, $x^2 \equiv a \pmod{p} \Rightarrow a^{\frac{p-1}{2}} \equiv x^{2 \cdot \frac{p-1}{2}} \equiv x^{p-1} \equiv 1 \pmod{p}$.
 2. If $a^{\frac{p-1}{2}} \equiv -1 \pmod{p}$, we have that $\mathbb{Z}_p$ is a finite field thus there exists a generator g of $(\mathbb{Z}_p)^*$ (primitive element theorem in finite fields), then $a \equiv g^k \pmod{p}$, we have then $a^{\frac{p-1}{2}} \equiv g^{k \cdot \frac{p-1}{2}} \equiv 1 \pmod{p}$. Given that the generator g has order $p - 1$ then $k \cdot \frac{p-1}{2} \equiv 0 \pmod{p - 1}$ thus $k \cdot \frac{p-1}{2} = m(p - 1) \Rightarrow k = 2m$ so k is even, thus $a \equiv g^{2m} = (g^m)^2 \pmod{p}$ so a is a quadratic residue modulo p .

Given that a is a quadratic residue modulo p if and only if $a^{\frac{p-1}{2}} \equiv 1 \pmod{p}$ and $a^{\frac{p-1}{2}} \equiv -1$ or $-1 \pmod{p}$ then necessarily if a is not a quadratic residue, $a \equiv -1 \pmod{p}$. ■

Exercise 3.14:

1. Decompose into partial fractions in $\mathbb{R}[x]$ the rational function

$$\frac{x}{x^4 + x^2 + 1}$$

2. Let K be a commutative field, and let $p : x^2 + \lambda x + \mu$ be a monic polynomial of degree 2, show that p is reducible over K if and only if it has a root in K .
3. Let $K = \mathbb{Z}/5\mathbb{Z}$ be the field of residue classes, factor the polynomial $(x^2 + 4)(x^2 + 3)$ into irreducible factors over K .
4. Still with $K = \mathbb{Z}/5\mathbb{Z}$, decompose into partial fractions the rational function

$$\frac{x - \bar{2}}{(x^2 + \bar{4})(x^2 + \bar{3})}$$

1. Decomposing into partial fractions: we have that the denominator decomposes into the following two irreducible polynomials

$$\begin{aligned}
x^4 + x^2 + 1 &= x^4 + 2x^2 + 1 - x^2 \\
&= (x^2 + 1)^2 - x^2 \\
&= (x^2 + x + 1)(x^2 - x + 1)
\end{aligned}$$

and thus we have that the fraction decomposes as follows

$$\frac{x}{x^4 + x^2 + 1} = \frac{ax + b}{x^2 + x + 1} + \frac{cx + d}{x^2 - x + 1}$$

by multiplying both sides by $x^4 + x^2 + 1$ we get

$$\begin{aligned}
x &= (ax + b)(x^2 - x + 1) + (cx + d)(x^2 + x + 1) \\
0 &= ax^3 - ax^2 + ax + bx^2 - bx + b + cx^3 + cx^2 + cx + dx^2 + dx + d - x \\
0 &= (a + c)x^3 + (-a + b + c + d)x^2 + (a - b + c + d - 1)x + (b + d)
\end{aligned}$$

$$\Rightarrow \begin{cases} a + c = 0 \\ -a + b + c + d = 0 \\ a - b + c + d - 1 = 0 \\ b + d = 0 \end{cases} \Rightarrow \begin{cases} a = 0 \\ b = -1/2 \\ c = 0 \\ d = 1/2 \end{cases}$$

thus we get

$$\frac{x}{x^4 + x^2 + 1} = \frac{1}{2(x^2 - x + 1)} - \frac{1}{2(x^2 + x + 1)}$$

- Let K be a commutative field and let $P(x) = x^2 + \lambda x + \mu$. $\Rightarrow$ Suppose that $P(x)$ is reducible, then $P(x) = Q(x) \cdot R(x)$ with $\deg(Q) \neq 0$ and $\deg(R) \neq 0$ and since $\deg(Q) + \deg(R) = \deg(P)$ then necessarily $\deg(Q) = \deg(R) = 1$, so $Q(x) = ax + b$ and $R(x) = cx + d$ and since $a, b \in K$ then $-\frac{a}{b} \in K$ which is a root of Q and thus a root of P so P has a root in K . $\Leftarrow$ Suppose that $P(x)$ has a root α , then $(x - \alpha)$ divides P and thus we get that P is reducible.
- Let $K = \mathbb{Z}/5\mathbb{Z}$, factor $(x^2 + 4)(x^2 + 3)$ into irreducible factors over K , $-3 = 2 \bmod 5$ is not a quadratic residue since $2^{\frac{5-1}{2}} = 4 = -1 \bmod 5$ thus $x^2 + 3$ is irreducible given it has no roots. While $-4 = 1$ is a quadratic residue with roots -1 and 1 so $(x^2 + 4)(x^2 + 3) = (x^2 - 1)(x^2 + 3) = (x - 1)(x + 1)(x^2 + 3)$.
- Decomposing now the partial fraction in $\mathbb{Z}/5\mathbb{Z}$,

$$\begin{aligned}
\frac{x - 2}{(x^2 + 4)(x^2 + 3)} &= \frac{x - 2}{(x + 4)(x + 1)(x^2 + 3)} \\
&= \frac{a}{x + 4} + \frac{b}{x + 1} + \frac{cx + d}{x^2 + 3}
\end{aligned}$$

by multiplying all parts by $(x^2 + 4)(x^2 + 3)$ we get

$$x - 2 = a(x + 1)(x^2 + 3) + b(x + 4)(x^2 + 3) + (cx + d)(x + 4)(x + 1)$$

we set the following values for x

- $x = -1$: $-3 = b(-1 + 4)(1 + 3) = 12b = 2b \Rightarrow b = 3 * (-3) = -9 = 1$.
- $x = +1$: $-1 = a(1 + 1)(1 + 3) = 8a = 3a \Rightarrow a = 2 * (-1) = -2 = 3$.

Exercise 3.15:

- Decompose 561 into prime factors.
- Let a be an indeterminate, for any integer $n \geq 1$, justify the formula

$$a^n - 1 = (a - 1)(a^{n-1} + a^{n-2} + \dots + a + 1)$$

- Justify for any integer $m \geq 1$ and any integer $n \geq 1$ the formula

$$a^{mn} - 1 = (a^m - 1)(a^{(n-1)m} + a^{(n-2)m} + \dots + a^m + 1)$$

- Let $a \in \mathbb{Z}$ be an integer, prove $a^{561} - a = a(a^{2 \cdot 280} - 1) = a(a^2 - 1)m$ for some integer m .
- For any $a \in \mathbb{Z}$, show that $a(a - 1)(a + 1)$ is divisible by 3.
- Show that $a^{561} - a$ is a multiple of 3.
- Show that $a^{561} - a$ is a multiple of 17.
- Show that $a^{561} - a$ is a multiple of 11.
- Show that $a^{561} \equiv a \bmod 561$.

- The prime decomposition of 561 is $3 \cdot 11 \cdot 17$.
- Let a be a formal variable, we have

$$(a - 1) \sum_{i=0}^{n-1} a^i = \sum_{i=0}^{n-1} a^{i+1} - a^i = \sum_{i=1}^n a^i - \sum_{i=0}^{n-1} a^i = a^n - 1$$

- By taking $a = a^m$ in the previous inequality we get the result.

4. Clearly $561 = 2 \cdot 280 + 1$ thus $a^{561} - a = a(a^{560} - 1) = a(a^{2 \cdot 280} - 1)$ and we have from the previous question by taking $m = 2$ and $n = 280$ that $a^{561} - a = a(a^2 - 1) \left(\sum_{i=1}^{279} a^{2i} \right) = a(a^2 - 1)m$.
5. Let $a \in \mathbb{Z}$, we have that $a = 3q + r$ with $0 \leq r < 3$ from the Euclidean division algorithm, then $a(a-1)(a+1) = (3q+r)(3q+(r-1))(3(q+1)+(r-2))$ and since $0 \leq r < 3$ then necessarily either r , $r-1$ or $r-2$ is 0, and thus it has one of the factors divisible by 3.
6. $a^{561} - a$ is divisible by 3 since $a^{561} - a = a(a+1)(a-1)m$ which is divisible by 3 from the previous question.
7. $a^{16} = 1 \pmod{17}$ by Fermat little theorem, then $a^{560} = a^{16 \cdot 35} = 1 \pmod{17}$ thus, $a^{561} = a \pmod{17} \Rightarrow 17 \mid a^{561} - a$.
8. Same here, $a^{10} = 1 \pmod{11}$ by Fermat little theorem, then $a^{560} = a^{10 \cdot 56} = 1 \pmod{11}$ thus, $a^{561} = a \pmod{11} \Rightarrow 11 \mid a^{561} - a$.
9. Given that all the divisors of 561 divide $a^{561} - a$ then it is divisible by their product so $561 \mid a^{561} - a \Rightarrow a^{561} \equiv a \pmod{561}$.

Chapter 1

Introduction To Information Theory

The digital revolution has transformed how we communicate, store and process information. This chapter introduces the fundamental concepts of information theory, a discipline at the intersection of mathematics, computer science and telecommunication.



This diagram presents the general structure of any communication system. The communication process begins with an information source. We start by thinking what a message could be. In general, we can consider a message to be constructed by a set of symbols $\mathcal{X} = \{x_1, \dots, x_n\}$ and given a context, has a distribution of which of those symbols are sent. Thus, we consider a message consecutive realizations of a random variable X defined in $\mathcal{X}$.

Now the goal is to quantify information, thus given $X \sim P_X(x)$, we define the amount of information for some symbol x to be $I(x) = -\log_2(P_X(x))$ (justifications for these definitions will be in the next chapter). Then, we can define an average amount of information from a source X , which is called the entropy $H(X) = \mathbb{E}[I(X)]$. Such a quantity is important given Shannon's first theorem, which gives a lower bound for any data compression.

After being able to measure the amount of information, we can measure efficiency of some encodings both for source and channel by how much redundancy is added to how much is actually needed.

1.1. The Communication System Model

Shannon's groundbreaking contribution was a formal model that describes communication between two entities, whether machine or humans. This model highlights the essential components:

- Source: the originator of the information.
- Channel: The medium through which information is transmitted.
- Recipient: The receiver of the information.

1.1.1. Source & Message

The sources generate a message composed of symbols from a specific alphabet.

- Discrete data: text, numbers, symbols.
- Digitized analog data: image, voice, video converted to digital form.

1.1.2. Transmitter Processing

The transmitter performs three crucial operations.

1. Source Coding: data compression to minimize message size.
2. Channel Coding: adding redundancy for error correction.
3. Modulation: converting digital messages to physical signal.

1.1.3. Receiver Processing

The receiver performs these receiver operations.

1. Demodulation: converting physical signal into a digital message.
2. Channel Decoding: error detection and correction.
3. Source Decoding: reconstruction of the original message.

Chapter 2

Information & Entropy

Information theory is a theory founded by Claude Shannon, providing a mathematical framework for quantifying information, studying its transmission, processing, and storage. This chapter focuses on the fundamental concepts of information measurement through entropy and related measures.

2.1. Quantifying Information

Notation: Let Σ be a set:

- $\Sigma^n = \Sigma \times \dots \times \Sigma$ is the set of words of length n . We take that $\Sigma^0 = \{\varepsilon\}$ where ε is the empty word.
- $\Sigma^* = \bigcup_{i \geq 0} \Sigma^i$ the set of all possible words over Σ .
- $\Sigma^+ = \bigcup_{i \geq 1} \Sigma^i$ the set of all possible non-empty words over Σ .
- For $x \in \Sigma^*$, we define $|x| = \min\{n \in \mathbb{N} | x \in \Sigma^n\}$.
- The set of binary letters as $\mathbb{B} = \{0, 1\}$.
- For $x = x_1 \dots x_n, y = y_1 \dots y_m \in \Sigma^*, xy = x_1 \dots x_n y_1 \dots y_m \in \Sigma^*$.

Definition 1 (Symbol/Message): Let $\mathcal{X} = \{x_1, \dots, x_m\}$ be a finite set of alphabets. An element of $\mathcal{X}$ is called a symbol, and elements of $\mathcal{X}^+$ are called a message with alphabet $\mathcal{X}$.

To model information that was given from a message, we consider the fact that a message contains more information the more unpredictable it is. For example, consider a sender that keeps sending the message “Hello!” over and over again, at each iteration, it becomes predictable what the next message would be, thus there is no more information that is passed. Uncertainty is a property of a random process, thus a good way to model a message is to consider it as a random variable X that has values in $\mathcal{X}$. From the previous example too, we

can think that the information in a message is related to how uncertain it is, that is, how less probable it would be sent. Also, notice that the information from independent events should be additive, that is, if even p and q happen that are independent, then the amount of information gained from the even pq happening is the sum of information gained from both the events p and q .

Notation: For the sake of simplifying notation, we will denote $P(X = x)$ as $P(x)$, same for other random variables, like $P(Y = y)$ as $P(y)$. Same for all the remaining notations like $P(y|x)$ which is $P(Y = y | X = x)$.

To define a measure for information $I : \mathcal{X} \rightarrow \mathbb{R}$, we start by considering some random variable X that represents a source of symbols $\mathcal{X}$. As discussed before, the information will be a function of probability, thus we take $I(x) = \varphi(P(x))$ from our previous discussion it would satisfy the following postulates:

- Postulate 1: Information depends only on probability $I(A) = \varphi(P(A))$.
- Postulate 2: Certain events provide no information $\varphi(1) = 0$.
- Postulate 3: Information decreases with increasing probability, φ is decreasing.
- Postulate 4: Impossible events provide infinite information $P(0) = \infty$.
- Postulate 5: Information from independent events $\varphi(pq) = \varphi(p) + \varphi(q)$.

Also, clearly φ would be continuous since a tiny difference in probability would result in a tiny difference in the amount of information that it would result in.

We will briefly prove that $\varphi \equiv -\log_b$ for any base b . By induction we have that $\varphi(a^n) = n\varphi(a)$ and since $\varphi(a) = \varphi(a^{q/q}) = q\varphi(a^q)$ then necessarily $\varphi(a^{p/q}) = (p/q)\varphi(a)$. By continuity, we have $\forall x \in \mathbb{R}, \varphi(a^x) = x\varphi(a)$. Now take $t = \log_a x$, then $\varphi(x) = \varphi(a^t) = t\varphi(a) = \varphi(a) \log_a x$, thus $\varphi(x) = \varphi(a) \log_a(x)$, by taking $x \rightarrow 0$, we have that $\varphi(a) \log_a(x) \rightarrow +\infty$ so $\varphi(a) < 0$. Therefore, $\varphi \equiv -\log_b$ for some b .

Definition 2 (Measure Of Information): Let X be a random variable that represents the probability that a message x is sent as $P(X = x) = P(x)$, we define the measure of information of the message x as

$$I_D(x) = -\log_D P(x)$$

2.2. Measures Of Entropy

After we defined a measure of information, which we discussed to be a measure of uncertainty, we need a way to quantify the average amount of uncertainty for all the values of X . Thus, we define the entropy as follows.

Definition 3 (Entropy): Let X be a random variable with values in $\mathcal{X}$, we define the entropy $H(X)$ as the average amount of information, that is

$$H_D(X) = \mathbb{E}[I_D(X)] = - \sum_{x \in \mathcal{X}} P(x) \cdot \log_D P(x)$$

If D is not specified then we consider $D = 2$ in general. Notice that the information of some message x depends only on its unpredictability, that is, its probability of occurrence $P(x)$ not its value.

Proposition 4: Let X, Y with symbols in $\mathcal{X}, \mathcal{Y}$ be two sources.

1. Non-negativity: $H_D(X) \geq 0$.
2. Maximum Entropy: $H_D(X) \leq \log_D \# \mathcal{X}$.
3. Independent Additivity: $X \perp Y \Rightarrow H_D(XY) = H_D(X) + H_D(Y)$.

Proof.

1. $\forall x \in \mathcal{X}, I(x) \geq 0$, then $H(X) = \mathbb{E}[I(X)] \geq 0$
2. Here, we optimize on the distribution of X , $\max_P H(X) = -\min_P \sum_{x \in \mathcal{X}} P(x) \cdot \log_2 P(x)$, hence for I a finite set $\min_{\{y_i \in [0,1]\}} \sum_{i \in I} y_i \log_2(y_i)$ with $\sum_{i \in I} y_i = 1$. Notice that all the terms have the same sign so $\min \sum_{i \in I} \dots = \sum_{i \in I} \min \dots$ y_i all having the same range would mean that we just need to find c such that $y_i = c$ and satisfies the second inequality, which is clearly $c = \frac{1}{\#I}$. So X would be a uniform distribution over $\mathcal{X}$, $H_u(X) = \mathbb{E}[I(X)] = -\sum_{x \in \mathcal{X}} 1/(\# \mathcal{X}) \log_2(1/(\# \mathcal{X})) = \log_2 \# \mathcal{X} \geq H(X)$.
3. Let X, Y be two independent variables, then $H(XY) = \mathbb{E}[I(XY)] = \mathbb{E}[I(X) + I(Y)] = \mathbb{E}[I(X)] + \mathbb{E}[I(Y)] = H(X) + H(Y)$. ■

Example: Let $\mathcal{X} = \{0, 1\}$, and X a discrete random variable with values in $\mathcal{X}$, which has the distribution

$$P(x) = \begin{cases} 0.9 & \text{if } x = 0 \\ 0.1 & \text{if } x = 1 \end{cases} \Rightarrow I(x) = \begin{cases} 0.152 & \text{if } x = 0 \\ 3.321 & \text{if } x = 1 \end{cases}$$

And the measure of average amount of information is $H(X) = 0.4689$.

Example: DNA sequences provide an excellent example of entropy application.

Let's consider:

- Primate DNA: $P(A) = P(G) = P(C) = P(T) = 1/4$. $H(X) = 2$
- Bacterial DNA: $P(G) = P(C) = 0.38$, $P(A) = P(T) = 0.12$. $H(X) = 1.795$.

The entropy of bacterial DNA indicates more predictable sequences compared to the primate DNA.

2.2.1. Joint Entropy

Definition 5 (Joint Entropy): Let X, Y be two random variables with joint distribution $P(x, y)$, the joint entropy is

$$H_D(X, Y) = - \sum_{(x,y) \in \mathcal{X} \times \mathcal{Y}} P(x, y) \log_D P(x, y) = -\mathbb{E}[\log_D P(X, Y)]$$

Proposition 6: Let X, Y be two sources.

1. Symmetry: $H_D(X, Y) = H_D(Y, X)$.
2. Non-Negativity: $H_D(X, Y) \geq 0$.
3. Upperbound: $H_D(X, Y) \leq H_D(X) + H_D(Y)$.
4. Lowerbound: $H_D(X, Y) \geq \max(H_D(X), H_D(Y))$.

Proof.

1. trivial by $P(x, y) = P(X = x, Y = y) = P(Y = y, X = x) = P(y, x)$.
2. $\forall x \in \mathcal{X}, \forall y \in \mathcal{Y}, 0 \leq P(x, y) \leq 1 \Rightarrow \log_D P(x, y) \leq 0$ so we have $P(x, y) \log_D P(x, y) \leq 0$. Hence,

$$H_D(X, Y) = - \sum_{x \in \mathcal{X}} \sum_{y \in \mathcal{Y}} P(x, y) \log_D P(x, y) \geq 0$$

3. We have $H_D(X, Y) - H_D(X) - H_D(Y) = \sum_{x \in \mathcal{X}} P(x) \log_D P(x) + \sum_{y \in \mathcal{Y}} P(y) \log_D P(y) - \sum_{(x,y) \in \mathcal{X} \times \mathcal{Y}} P(x, y) \log_D P(x, y)$, by using the

fact that $P(x) = \sum_{y \in Y} P(x, y)$, we can transform all the sums to be indexed with $X \times Y$ as follows:

$$\begin{aligned} \sum_{x \in X} P(x) \log_D P(x) &= \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x) \\ \sum_{y \in Y} P(y) \log_D P(y) &= \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(y) \end{aligned}$$

Thus we obtain the writing

$$H_D(X, Y) - H_D(X) - H_D(Y) = \sum_{(x, y) \in X \times Y} P(x, y) \log_D \left(\frac{P(x)P(y)}{P(x, y)} \right)$$

We have that $\forall t \geq 0, \log_D(t) \leq t - 1$ thus

$$\begin{aligned} H_D(X, Y) - H_D(X) - H_D(Y) &= \sum_{(x, y) \in X \times Y} P(x, y) \log_D \left(\frac{P(x)P(y)}{P(x, y)} \right) \\ &\leq \sum_{(x, y) \in X \times Y} P(x, y) \left(\frac{P(x)P(y)}{P(x, y)} - 1 \right) \\ &\leq \sum_{(x, y) \in X \times Y} P(x)P(y) - P(x, y) \\ &\leq \sum_{(x, y) \in X \times Y} P(x)P(y) - \sum_{(x, y) \in X \times Y} P(x, y) \\ &\leq 1 - 1 = 0 \end{aligned}$$

Therefore

$$H_D(X, Y) \leq H_D(X) + H_D(Y)$$

4. Without loss of generality, we prove that $H_D(X, Y) \geq H_D(X)$, we have from before that $P(x) = \sum_{y \in Y} P(x, y)$ and since $\forall (x, y) \in X \times Y, P(x, y) \geq 0$ then $\forall (x, y) \in X \times Y, P(x, y) \leq P(x)$.

$$\begin{aligned} H_D(X, Y) &= - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x, y) \\ &\geq - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x) = H_D(X) \end{aligned}$$

and same to prove that $H_D(X, Y) \geq H_D(Y)$ and hence we obtain the inequality $H_D(X, Y) \geq \max(H_D(X), H_D(Y))$. ■

2.2.2. Conditional Entropy

The other useful measure of entropy is the conditional entropy, which measures the amount of information remaining in a random variable knowing another.

Definition 7 (Conditional Entropy): Let X, Y be two random variables with joint distribution $P(x, y)$, the conditional entropy is

$$H_D(X|Y) = - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x|y) = -\mathbb{E}[\log_D P(X|Y)]$$

Proposition 8: Let X, Y be two sources.

1. *Non-Negativity:* $H_D(X|Y) \geq 0$.
2. *Chain Rule:* $H_D(X, Y) = H_D(X) + H_D(Y|X)$.
3. *Reduction Of Uncertainty:* $H_D(X|Y) \leq H_D(X)$.

Proof.

1. $\forall (x, y) \in X \times Y, 0 < P(x|y) \leq 1 \Rightarrow \log_D P(x|y) \leq 0 \Rightarrow H_D(X|Y) = - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x|y) \geq 0$.
2. We have

$$\begin{aligned} H_D(X, Y) &= - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x, y) \\ &= - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(x) - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(y|x) \\ &= - \sum_{x \in X} \left(\sum_{y \in Y} P(x, y) \right) \log_D P(x) - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(y|x) \\ &= - \sum_{x \in X} P(x) \log_D P(x) - \sum_{(x, y) \in X \times Y} P(x, y) \log_D P(y|x) \\ &= H_D(X) + H_D(Y|X) \end{aligned}$$

3. $H_D(X|Y) \stackrel{a}{=} H_D(X, Y) - H_D(Y) \stackrel{b}{\leq} H_D(X) + H_D(Y) - H_D(Y) = H_D(X)$, where a comes from the chain rule and b from the subadditivity of joint entropy. ■

2.2.3. Mutual Information

Conditional entropy measures the amount of information is remaining in a random variable knowing another, it is easy to see that by subtracting the amount of information a variable has with the amount of remaining information knowing another we get the information that is “shared” between them.

Definition 9 (Mutual Information): Let X, Y be two sources, we define the mutual information as

$$I_D(X; Y) = \mathbb{E} \left[\log_D \left(\frac{P(X, Y)}{P(X)P(Y)} \right) \right] = \sum_{(x, y)} P(x, y) \log_D \left(\frac{P(x, y)}{P(x)P(y)} \right)$$

Proposition 10: Let X, Y be two sources.

1. Equivalent Formulas:

$$\begin{aligned} I_D(X; Y) &= H_D(X) - H_D(X|Y) \\ &= H_D(Y) - H_D(Y|X) \\ &= H_D(X) + H_D(Y) - H_D(X, Y) \\ &= H_D(X, Y) - H_D(X|Y) - H_D(Y|X) \end{aligned}$$

2. Symmetry: $I_D(X; Y) = I_D(Y; X)$.

3. Non-Negativity: $I_D(X; Y) \geq 0$.

4. Upperbound: $I_D(X; Y) \leq \min(H_D(X), H_D(Y))$.

5. Self-Information: $I_D(X; X) = H_D(X)$.

Proof.

1. Trivial, just write the formulas.
2. Direct consequence of the first two formulas of 1.
3. We have from the reduction of uncertainty that $H_D(X|Y) \leq H_D(X)$ thus $I_D(X; Y) = H_D(X) - H_D(X|Y) \geq 0$.

4. We have from the lowerbound of joint entropy that $H_D(X, Y) \geq \max(H_D(X), H_D(Y))$ then

$$\begin{aligned} I_D(X; Y) &= H_D(X) + H_D(Y) - H_D(X, Y) \\ &\leq H_D(X) + H_D(Y) - \max(H_D(X), H_D(Y)) = \min(H_D(X), H_D(Y)). \end{aligned}$$

5. $I_D(X; X) = H_D(X) - H_D(X|X) = H_D(X)$. ■

2.2.4. Data-Processing Inequality

Another important property is the data processing inequality, stating informally that, given some information, one cannot process it to obtain more information. So, we start with defining what is “data-processing”.

Definition 11 (Markov Chain): Let X, Y, Z be three random variables, we say that they form a Markov chain in that order, and we denote it $X \rightarrow Y \rightarrow Z$ if the conditional probability of Z depends only on Y and not on X , which can be written as

$$P(z|x, y) = P(z|y)$$

This definition is natural, since in our case, we take that we have the two random variables X and Y , and we produce Z with some processing on Y without knowing anything about X , the process can be deterministic or not.

To prove the data-processing inequality, we need the following lemma.

Lemma: $I_D(X; Y, Z) = I_D(X; Y) + I_D(X; Z|Y)$ where

- $I_D(X; Y, Z) = \mathbb{E}[\log_D(P(X, Y, Z)/(P(X)P(Y, Z)))]$.
- $I_D(X; Z|Y) = \mathbb{E}[\log_D(P(X, Z|Y)/(P(X|Y)P(Z|Y)))]$.

It is left for the reader to prove, it is mainly algebraic manipulation.

Theorem 12 (Data-Processing Inequality): Let X, Y, Z be three sources such that $X \rightarrow Y \rightarrow Z$, we have that

$$I_D(X; Y) \geq I_D(X; Z).$$

Proof. Since $X \rightarrow Y \rightarrow Z$ then there is no extra information given from Z knowing Y thus $I_D(X; Z|Y) = 0$ we have

$$I_D(X; Y, Z) = I_D(X; Y) + I_D(X; Z|Y)$$

$$I_D(X; Y, Z) = I_D(X; Z) + I_D(X; Y|Z)$$

hence

$$I_D(X; Y) + I_D(X; Z|Y) = I_D(X; Z) + I_D(X; Y|Z)$$

$$\Rightarrow I_D(X; Y) = I_D(X; Z) + I_D(X; Y|Z)$$

since $I_D(X; Y|Z) \geq 0$ then $I_D(X; Y) \geq I_D(X; Z)$. ■

Chapter 3

Source Coding

Source coding is a fundamental part of communication that deals with representing data to be sent in the most compressible manner to get an efficient communication. From Shannon's theorem, we will see that the amount of data compression is bounded, and thus we will see algorithms that achieve an average length 1 bit away from the bound.

3.1. Source Coding

The most important part of coding theory is achieving the most efficient reliable and secure coding. The first part is the focus of this section, by assigning a code from each symbol in $\mathcal{X}$, we try to achieve the minimum bound possible of letters to send to transmit our message.

Definition 1 (Coding Function): Let $c : \mathcal{X} \rightarrow \mathbb{D}^+$, we call it a coding function, which takes characters of our set of symbols, and represent it as a string in $\mathbb{D}^+$ which is the set of words with D alphabets.

To measure the efficiency of our coding function, we define the average code length, the less the average, the more efficient the transmission will be.

Definition 2 (Average Code Length): Let $c : \mathcal{X} \rightarrow \mathbb{D}^+$, a coding function, and consider the function

$$\bar{L} : \{c : \mathcal{X} \rightarrow \mathbb{D}^+\} \rightarrow \mathbb{R} \quad c \mapsto \bar{L}_c = \sum_{x \in \mathcal{X}} p(x) \cdot |c(x)|$$

Example: Take a horse race with 8 horses, we want to send a message in binary that indicates which horse has won. And suppose that the probabilities of winning for each horse is as follows

Horse	1	2	3	4	5	6	7	8
Probability Of Winning	$\frac{1}{2}$	$\frac{1}{4}$	$\frac{1}{8}$	$\frac{1}{64}$	$\frac{1}{64}$	$\frac{1}{64}$	$\frac{1}{64}$	$\frac{1}{64}$

If we just send the index of the winner horse, we get the following coding function

Horse i	1	2	3	4	5	6	7	8
$c_1(i)$	000	001	010	011	100	101	110	111

If we do it just blindly, we will need 3 bits to describe all the possible winner horses from 000, 001, 010, ..., 110, 111, calculating the average of description length we get

$$\bar{L}_{c_1} = \sum_{x \in X} 3 \cdot p(x) = 3 \text{ bits/sym}$$

Giving us an average of 3 bits for the transmission to give exactly who horse is the winner. An aspect that we did not use in the previous part is how likely do horses win in this case, which we can use to improve the amount of bits that would be sent on the channel.

Notice that if we assign a smaller message for the horses that are more probable to win, and longer message to horses that are less likely to win, then we can reduce some of the data that will be used to specify the winner. We take the following encoding

Horse i	1	2	3	4	5	6	7	8
$c_2(i)$	0	10	110	1110	111100	111101	1111110	111111

Now, we recalculate the average description length to get

$$\bar{L}_{c_2} = \sum_{x \in X} |c(x)| \cdot p(x) = 2 \text{ bits/sym}$$

we have reduced the average description length by 1 bit. If we calculate the entropy in this case we get $H(X) = -\sum_{x \in X} P(x) \cdot \log_2 P(x) = 1.83475$, we see that the reduced average code length is more than the entropy.

Definition 3 (Properties Of Codes): Let $c : \mathcal{X} \rightarrow \mathbb{D}^+$ be a coding function. We say that it is:

- *Non-Singular:* if $\forall x, y \in \mathcal{X}, c(x) \neq c(y)$.
- *Uniquely Decodable:* if $\forall y_1, \dots, y_n \in \mathbb{D}^+, \exists! x_1, \dots, x_m, y_1 y_2 \dots y_n = c(x_1) c(x_2) \dots c(x_m)$, that is, any sequence $y_1, \dots, y_n$ of $\mathbb{D}^+$ can be uniquely decoded into a sequence $x_1, \dots, x_m$ of $\mathcal{X}$.
- *Instantaneous/Prefix-Free:* if $\forall x, y \in \mathcal{X}, \nexists m \in \mathbb{D}^+, x = ym$, that is, no code-word is a prefix of another code-word.

3.1.1. Principles Of Instantaneous Code Construction

Lemma 4 (Kraft Inequality): Let $\mathcal{X} = \{x_1, \dots, x_n\}$ be a set of symbols, and c be a coding function, set $l_i = |c(x_i)|$ the length of the coding of the i^{th} symbol, then the following statements are true.

1. If c is an instantaneous code then $\sum_{i=1}^n D^{-l_i} \leq 1$.
2. If c satisfies $\sum_{i=1}^n D^{-l_i} \leq 1$, then there exists an instantaneous code $c' : \mathcal{X} \rightarrow \mathbb{D}^+$ such that $\forall i \in [1, n], |c'(x_i)| = |c(x_i)|$.

Theorem 5 (Shannon's First Theorem): Let X be a random variable with values in $\mathcal{X}$, for any coding function $c : \mathcal{X} \rightarrow \mathbb{D}^+$ we have

$$\bar{L}_c \geq H_D(X)$$

and there exists a prefix code $c' : \mathcal{X} \rightarrow \mathbb{D}^+$ such that

$$H_D(X) \leq \bar{L}_{c'} \leq H_D(X) + 1$$

Algorithm 5.1 (Shannon-Fanon):

1. Sort symbols in decreasing order of probability.
2. Partition the set into two subsets with approximately equal probability.

3. Assign 0 to one subset and 1 to the other.
4. Recursively apply steps 2-3 to each subset.

Huffman's algorithm provides a systematic way to construct an optimal prefix code, where symbols with higher probability should have shorter code words, and achieves a lower bound of average coding weight.

Algorithm 5.2 (Huffman):

1. Sort symbols by probability in descending order.
2. While there is more than one node:
 1. Find two nodes with smallest probability.
 2. Create a new node with these children, the probability of the node is the sum of the probabilities of the children.
 3. Assign 0 to one branch and 1 to another.
3. Recursively apply the steps 1-2 until only one node remains.