

Connection list — Option A (relay, recommended)

Edge	→	Relay	→	E 40:2 front GPI/GPO	Purpose
Logic Out 1	→	Relay 1 coil (+ ext PSU, flyback)	→	Amp 1 GPI — across both terminals (NO)	Amp 1 on/standby
Logic Out 2	→	Relay 2 coil (+ ext PSU, flyback)	→	Amp 2 GPI — across both terminals (NO)	Amp 2 on/standby
Logic In 1 (opt.)	←	— direct —	←	Amp 1 GPO across (Logic In, Edge GND)	Amp 1 on/healthy
Logic In 2 (opt.)	←	— direct —	←	Amp 2 GPO across (Logic In, Edge GND)	Amp 2 on/healthy

GPO feedback is optional. The Edge logic input has an internal pull-up: wire the amp's GPO dry contact across the Edge logic input and Edge GND — GPO closing (amp on) pulls the input low = active. Gives a real per-amp status indicator + protect/thermal alarm in Composer.

Composer setup

- Place a **Logic Output** control per amp; assign each to its physical Edge logic-output pin.
- Drive each output's state from your chosen trigger: ARC-WEB button, wall remote, the **event scheduler** (time-of-day venue on/off), or power-on logic / Lua. Map state → ON.
- Add a short **power-on delay** so amps come up 1–2 s after the DSP settles (no thump); on shutdown, command STANDBY before the DSP drops.
- Optional: place a **Logic Input** per amp tied to the amp GPO, wired to a status indicator.

Settle this first — auto-standby: with the Edge GPI as the master power switch, set the amp's Auto Power Down / Auto Power On so it doesn't fight the DSP — otherwise the amp can drop itself to standby on signal idle while Composer still thinks it commanded ON. Let the GPI be authoritative; relax or disable the amp's auto-standby. Note: a close→open transition also disables Auto Power On until the amp is turned on again. The front-panel POWER button still works locally.

Connector confirmed from the unit: front-panel POWER STATE CONTROL/MONITOR block — separate **GPI** and **GPO** green Euroblock dry-contact pairs. One thing to eyeball on the physical block before wiring: whether GPO shares a common terminal with GPI, and the terminal order on each Euroblock — match the silkscreen.