

GPO status feedback (rows 4–5) is optional — it lets Composer show a real per-amp on/healthy indicator and alarm on protect/thermal mute.

Composer setup

- Place a **Logic Output** control per amp; assign each to its physical Edge logic-output pin.
- Drive each output's state from your chosen trigger: ARC-WEB button, wall remote, the **event scheduler** (time-of-day venue on/off), or power-on logic / Lua. Map state → ON.
- Add a short **power-on delay** so amps come up 1–2 s after the DSP settles (no thump); on shutdown, command STANDBY before the DSP drops.
- Optional: place a **Logic Input** per amp tied to the amp GPO, wired to a status indicator.

Settle this first — auto-standby: if the Edge GPI is the master power switch, set the amp's Auto Power Down / Auto Power On so it doesn't fight the DSP. Otherwise the amp can drop itself to standby on signal idle while Composer still thinks it commanded ON. Let the GPI be authoritative; relax or disable the amp's auto-standby. Note: a close→open also disables Auto Power On until the amp is turned on again.

VERIFY BEFORE LANDING WIRES: The GPI behavior (dry contact, closed = on) is confirmed across the Lab Gruppen E-Series docs, but the exact **pin numbers** on the E 40:2's control connector are NOT yet confirmed here — this sheet lists connections by function (GPI / GPI GND / GPO). Confirm the actual pin numbers against the amp's rear-panel legend or the E 40:2 manual (or send a photo of the rear control connector) and write them into this sheet before wiring.