MACHINE GUARDIAN · MAC-ATTACK

Machine Guardian — ML Model Development and Training Results

From the original Ottawa motor model, through the redesign on Paderborn run-to-failure bearing data, to Training Run 2

850
parameters: 8 → 32 → 16 → 2 multi-task MLP

9
trained networks, leave-one-bearing-out (Runs 1–2)

8 × 8
INT8 systolic array on the ZedBoard FPGA

MAC-Attack senior capstone · Machine Guardian
Prepared with Claude Code · 3 November 2026
Sources: the project repository (code, docs/log.md, earlier reports, saved results)

Contents

01 Executive Summary

02 Model Development History

03 Dataset Overview

04 Neural Network Architecture

05 How Training Works

06 Training Run 1 Results

07 Training Run 2 Results

08 Run 1 vs. Run 2 Comparison

09 FPGA Compatibility

10 Current Limitations

11 Future Improvements

12 Conclusion

13 Sources in the repository

MAC-Attack senior capstone. From the original Ottawa motor model, through the redesign on the Paderborn run-to-failure bearing data, to Training Run 2. Prepared with Claude Code, 3 November 2026, from the project's code, logs, earlier reports and saved experiment results. Every number below is taken from a file in the repository; the main sources are listed in section 13.

1. Executive Summary

What we are trying to accomplish

Machine Guardian is an on-device condition monitor for rotating machines. A small neural network reads vibration (and, in the current design, temperature and shaft speed) from a motor and decides whether its bearing has started to deteriorate. The network is small enough to run in INT8 arithmetic on our own **8 × 8 systolic-array accelerator** on a **ZedBoard (Xilinx Zynq XC7Z020) FPGA**. The ARM processor on the same chip does the feature extraction and the alarm logic.

What we have completed

- **Hardware.** An INT8 matrix-multiply accelerator ran on the board at 250 MHz (24/24 board tests). An on-chip MLP engine was built at 214.286 MHz and passed 30/30 board tests with test models.
- **First model (Ottawa motor dataset).**
  - A healthy/faulty classifier (E3): 27 of 28 test faults found, no false alarms.
  - A single-accelerometer version: 8 → 32 → 16 → 1, the shape the current model reuses.
  - INT8 export with no decision changes, and a bit-exact check on the accelerator RTL.
- **Redesign on run-to-failure data (Paderborn bearings).**
  - Four bearings processed and validated: B01–B04, 3,221 measurements.
  - A label-free anomaly detector built as the reference to beat.
  - The new 8 → 32 → 16 → 2 multi-task MLP: 850 parameters, two output heads.
  - A locked test set, and provisional labels.
- **Training Runs 1 and 2.** The deterioration head was trained by leave-one-bearing-out validation (9 networks). Run 2 added a latched alarm, a calibration study, and an INT8 + RTL check of the **trained** networks.

Current progress in one table


Area	Status
8 × 8 INT8 accelerator on the FPGA	done; board-tested (250 MHz matrix multiply, 214.286 MHz on-chip MLP)
Paderborn data pipeline and checks (B01–B04)	done for 4 of 17 bearings
Anomaly detector (reference)	done; alarms on all three labelled bearings
Multi-task MLP, deterioration head	trained (Runs 1–2) on 3 bearings; perfect on the labelled rows, but **not yet better than the anomaly detector**
Multi-task MLP, Motor Health Index head	**not trained**: no reliable severity labels exist
Trained MLP in INT8 / on the RTL	done in simulation (Run 2); **not yet on the board**
Final test on the locked bearings B06, B07, B13, B17	not started (kept locked on purpose)

Key finding: the trained network separates documented-healthy from documented-worn-out measurements perfectly on bearings it has never seen. With Run 2's latched alarm it raises one steady alarm per bearing. But the simpler anomaly detector reaches the same result and alarms a few minutes earlier on every bearing, so the network has not yet earned its place.

Caution: the network's output is a **deterioration score**, not a validated probability of physical failure. Nothing so far measures how likely a bearing is to fail, or how far it has worn.

2. Model Development History

2.1 From the proposal to the first model




- **Original proposal:** acoustic anomaly detection with a DCASE-style autoencoder (project log, 20 Oct entry).
- **20 Oct:** the professor approved a **multi-task MLP on vibration, temperature and RPM**, to be trained first and then run on the accelerator. The Paderborn or KAIST datasets were named as candidates because they record those signals.
- **21 Oct:** the hardware rules for any model were agreed: at most 64 inputs, at most 4 layers, every width at most 64 (multiples of 8 keep all lanes busy), and linear output heads merged into one last layer.
- **27 Oct:** to build on James's existing baseline, the team first built a **single-output** model on the **University of Ottawa electric-motor dataset**, with the same dataset, sensors and split as that baseline.

2.2 The Ottawa motor model (27–28 Oct)

The Ottawa dataset has 128 ten-second recordings at 42 kHz of one electric motor: 16 healthy and 112 with one of 7 faults. The split is by speed code: train on codes 3, 4, 5, 8; validate on 2, 7; test on 1, 6. Each model was a small MLP ($K \to 32 \to 16 \to 1$) trained with Adam, and the decision averaged ten 1-second windows.

Experiment	Inputs	Test faults found (of 28)	False alarms (of 4)	Test ROC-AUC
E0 (James's baseline, rebuilt)	16 statistics, accelerometers 2 + 3, per recording	18	0	0.875
E1	log amplitudes + shape + ln f	15	0	0.929
E2	E1 on 1-s windows	24	0	1.000
E3 ($22 \to 32 \to 16 \to 1$)	7 statistics × 3 accelerometers + ln f	**27**	0	1.000
E3 single accelerometer a1 ($8 \to 32 \to 16 \to 1$, 833 parameters)	one accelerometer on the motor	28	0	1.000

Seed 42 results. E3 over three seeds: test accuracy 0.948 ± 0.029, recall 0.940 ± 0.034, F1 0.969 ± 0.018.



Further results:

- **INT8 export:** E3 and a1 were exported to INT8 with **0 decisions changed** in every split.
- **RTL:** both passed a bit-exact check on the accelerator RTL. E3 takes 566 cycles per window; a1 takes 382 cycles (1.78 µs).
- **Health index H1:** a distance from the healthy reference, built as the second output. It reached a test ROC-AUC of only **0.527**.
- **Choosing a1 for deployment was a post-test team decision,** made because of where its accelerometer is mounted. The validation rule had picked accelerometer 2, and the report flags a1's 28/28 as "not an unbiased estimate".

2.3 Why we moved to the Paderborn run-to-failure data

The project documents give four reasons the Ottawa data could not support the goal:

1. **No temperature or RPM inputs.** The approved design uses three sensors; the Ottawa models used vibration only.
2. **No degradation levels.** Each fault appears at one severity, in separate 10-s recordings. A "how far gone" output can be neither trained nor tested; that needs **run-to-failure** data, where a machine is recorded from new until it fails.
3. **Only one healthy motor.** It is quieter than every faulty recording, so "every result here may partly be 'this motor' rather than 'healthy'" (project log).
4. **Bandwidth.** The strongest early-damage band found later (20–64 kHz) is invisible at Ottawa's 42 kHz.

The **Paderborn LDM run-to-failure ball-bearing dataset** fixes the first three. Its 17 bearings were each run from new until a vibration or temperature limit stopped the test, with vibration, two housing temperatures, speed and load all recorded.

2.4 The redesign, step by step (1–3 Nov)

Date	Step	What it produced
1 Nov	B01 analysis	one abrupt change at measurement M0208 on every vibration feature; B01 supports change detection only (no labels)
1 Nov	Anomaly detector (prototype)	label-free, per-bearing detector; alarms on B01 at M0208 and B03 at M0547 (20.4 min before the logged stop)
1 Nov	Multi-task architecture	8 → 32 → 16 → 2 MLP, 850 parameters, same trunk as the Ottawa hardware model
2 Nov	Dataset validation	42.67-kHz sensor chain (A42) chosen; thermal-calibration validity rule; B04 half-scale speed logging found
2 Nov	Locked split	13 development and 4 test bearings, drawn once (seed 20261102)
2 Nov	Labels	healthy start, end-stage end, everything between unlabelled
3 Nov	Training Run 1	first trained deterioration head
3 Nov	Training Run 2	latched alarm, calibration study, INT8 + RTL check of trained networks

2.5 What improved from the Ottawa design to the Paderborn design

	Ottawa model (E3 / a1)	Paderborn multi-task model
Data	one motor, separate fault recordings	17 bearings run from new to failure (4 processed)
Inputs	vibration statistics only	6 vibration features + RPM + temperature residual
Normalisation	one global standardiser	**per motor**, against its own first 100 measurements (as a new machine would be commissioned)
Outputs	healthy / faulty	deterioration score + Motor Health Index (second head reserved)
Validation	split by speed code (one motor)	**leave one bearing out**: always tested on an unseen bearing
Reference to beat	none	label-free anomaly detector and the rig's own stop rule
Test set	used during development	4 bearings **locked** until one model is frozen
Hardware fit	8 → 32 → 16 → 1	8 → 32 → 16 → 2: same trunk, 17 more parameters, same 382 cycles

3. Dataset Overview

3.1 University of Ottawa electric motor dataset (first model)

Property	Value
Recordings	128 CSV files, 10 s each at 42 kHz (420,000 rows)
Sensors	accelerometers 1 (motor drive end), 2 and 3 (bearing housings), microphone, temperature
Classes	healthy (16 files), faulty: 7 fault types (112 files)
Speeds	constant 15, 30, 45, 60 Hz and four ramps
Split	train speed codes 3, 4, 5, 8 (8 healthy / 56 faulty); validation 2, 7 (4/28); test 1, 6 (4/28)

3.2 Paderborn LDM run-to-failure bearing dataset (current model)

- **Source:** O. K. Aimiyekagbon, *Run-to-failure data set of ball bearings subjected to time-varying load and speed conditions*, v2, 25 Mar 2024, Zenodo doi 10.5281/zenodo.10805042 (CC BY 4.0).
- **Bearings:** 17 type 61806-2RS bearings (B01–B17), 152 GB in total.
- **Measurements:** every measurement is 1.6 s of vibration, taken about every 18–19 s.
  - Accelerometers: two PCB 603C01 units (rear and front of the housing), 100 mV/g.
  - Sampling: 128 kHz for B01–B09, 64 kHz from B10.
  - Also recorded: housing temperatures T1 and T2 (Pt100, 10 Hz), set and measured speed, and static and dynamic load.
- **End of a test:** each test ends when the rear vibration exceeds a limit (set between 6 and 10 g) or the housing reaches 110 °C. B01 had no limit pre-set and B05 was deliberately interrupted.

The four processed bearings:


Bearing	Files (= measurements)	Warm-up rows	Operating rows	Segments	Recorded	Test ended by	Defect found
B01	377	51	326	3	19 Oct 2021, 08:47–10:59	no criterion set	inner race, outer race, ball
B02	1,116	51	1,065	2	25 Oct 2021, 09:00–14:37	vibration limit	inner race
B03	614	0	614	1	5 Nov 2021, 15:11–18:24	temperature (110 °C)	inner race
B04	1,114	50	1,064	1	17 Nov 2021, 12:45–18:27	vibration limit	inner race, ball

3.3 How the data were processed

- **Checking every file.** `paderborn.py` reads every `.mat` file once. It checks that file *k* is row *k* of the temperature and operating-condition tables, that the ids are contiguous with none missing, and that the file counts match the dataset description. It also writes a `checks.json` per bearing. B02 and B04 pass every hard check.
- **A 42.67 kHz signal.** A second copy of each signal is made at 42.67 kHz (128/3, or 64 × 2/3), the only rate all 17 bearings can provide. This is the **A42 profile** used for training.
- **Problems found and recorded, not hidden:**
  - B01 continues 272 measurements past its logged stop.
  - B02 was paused at 13:32 after crossing the vibration limit twice.

- B04's recorded speed and dynamic load are about **0.50 ×** the set values, a suspected logging-scale issue. The vibration spectrum supports that the shaft ran at the set speed, and the model inputs are unaffected.

- **Thermal-calibration check.** A rule was written for when a bearing's temperature model is trustworthy: an uninterrupted cold start, steady state reached before the first alarm, and a residual of at most 1 °C. B02, B03 and B04 pass. B01 fails, so its temperature input is set to 0.



3.4 How the training labels were created

The dataset never says when a bearing started to deteriorate. It only says that the bearing began new and was found damaged when it was taken apart. So the labels are a rule, fixed on 2 Nov before training:

Bearing	Healthy (label 0)	End-stage (label 1)	Unlabelled
B01	none	none	all (no labels; left out of training)
B02	first 100 operating rows, M0052–M0151	last 5, M1112–M1116	960
B03	M0001–M0100	M0610–M0614	509
B04	M0051–M0150	M1110–M1114	959

That makes 300 healthy, 15 end-stage and 2,428 unlabelled operating rows on B02–B04. Four stated assumptions go with the rule:

1. The last 5 rows are a **provisional end-stage proxy**, not a verified damage state.
2. The bearing defect caused the stop.
3. The end label is **not** the damage onset.
4. The bearing was healthy during its first 100 rows.


A 15-item manual label review with a two-person sign-off was prepared, then removed as a requirement at the team's request. **The labels have not been reviewed against the dataset documents.**

3.5 The locked split

The split was drawn once, on 2 Nov:

- The bearing is the unit, so all of a bearing's measurements are in the same set.
- One test bearing was drawn per operating regime: **B06, B07, B13 and B17**.
- The code (`splits.assert_development`) refuses to load these four until a single model has been frozen.
- The other 13 bearings are for development. Only 3 of them (B02–B04) currently have labels.

4. Neural Network Architecture



4.1 The eight inputs

All eight are computed by the ARM from one 1.6-s measurement. Each vibration feature is first corrected for shaft speed and then expressed as a z-score against **the same motor's own first 100 operating measurements** (its commissioning period).

Input	Signal	Feature	How it is normalised
x1	rear accelerometer (42.67 kHz)	ln RMS	z = (feature − b0 − b1 · ln rpm) / σ, fitted on the motor's commissioning
x2	rear accelerometer	ln peak	same
x3	rear accelerometer	kurtosis	same
x4	rear accelerometer (full-rate spectrum)	ln energy 1–5 kHz	same
x5	rear accelerometer (full-rate spectrum)	ln energy 5–20 kHz	same
x6	rear accelerometer	crest factor	same
x7	shaft speed	ln rpm	z against the commissioning mean and spread (the operating point)
x8	housing temperature T1	residual from a per-motor first-order thermal model	(T1 − T_expected) / σ_T; 0 until the thermal calibration is complete

All inputs are clipped to ±16, which also sets the INT8 input step (16/127). There is no load input and only one accelerometer, to match what the final hardware can measure.

4.2 Layers and the 850 parameters

Layer	Shape	Weights	Biases	Parameters	Passes of the 8 × 8 array
Trunk 1 + ReLU	8 → 32	256	32	288	4
Trunk 2 + ReLU	32 → 16	512	16	528	8
Deterioration head	16 → 1	16	1	17	2 (both heads as one 16 × 2 layer)
Health-index head	16 → 1	16	1	17	(shared)
Total		**800**	**50**	**850**	**14**

4.3 The two output heads

- **Deterioration head.** One logit *d*, turned into a score p = sigmoid(d) between 0 and 1. The alarm logic compares p with a threshold (0.5). This is the only head trained so far.
- **Motor Health Index head.** One raw value *h*, reported as HI = 100 % × sigmoid(h): a 0–100 % condition indicator. It needs **severity labels**, measurements whose true level of wear is known. None exist yet, so this head is kept frozen at its random initial weights and the code refuses to report it.

The two heads share the trunk, so on the accelerator they are a single 16 × 2 last layer. The chip returns the two raw sums, and the ARM adds the biases and applies the sigmoids.


5. How Training Works

5.1 Preprocessing and normalisation

1. **Warm-up rows removed.** The first 10 minutes run at 750 rpm with no dynamic load.
2. **Speed correction per feature.** On the motor's first 100 operating measurements, fit f = b0 + b1 · ln rpm by least squares. Then z = (f – fit) / σ, where σ is the spread of the commissioning residuals.
3. **Temperature model per motor.** A first-order thermal model gives the expected T1 for the current speed. x8 is the standardised difference from it, and it is 0 until the model is calibrated.
4. **Clip** every input to ±16.

The idea is the one used in industry: each machine is compared with its own first half hour, not with other machines.

5.2 Training and validation: leave one bearing out



There are only three labelled bearings, so each is held out once. The network trains on the other two and is scored on **every** measurement of the held-out bearing. Each fold is trained with three random seeds, giving 9 networks per run. A result therefore always comes from a bearing the network has never seen.

5.3 Loss function, optimiser and class balance

Setting	Value	Why
Loss	masked binary cross-entropy on the deterioration logit; the health term is 0 because no row has a health label	rows without a label (NaN) contribute nothing
Optimiser	Adam, learning rate 0.001, no weight decay	standard, stable for small networks
Steps and batch	2,000 steps of 64 rows	fixed in advance, not tuned on held-out data
Class balance	every batch is half healthy, half end-stage (by sampling)	the training rows are 200 : 10 per fold
Temperature dropout	x8 set to 0 in 50 % of training rows	so the network also works on a unit whose temperature model is not calibrated
Health head	frozen: no gradient, not in the optimiser, checked bit-identical after training	no severity labels

The masked loss for a batch is the mean, over the rows that have a label $y \in \{0, 1\}$, of $-[y \cdot \ln p + (1 - y) \cdot \ln(1 - p)]$.


5.4 Decision rule and how results are scored

- **Run 1:** the alarm is on while the last three scores are all above 0.5.
- **Run 2:** the same, but **latched**. Once on, the alarm stays on.
- **Each held-out bearing is scored on:**
  - false alarms on its 100 healthy rows;
  - the share of its 5 end-stage rows alarmed;
  - the first alarm (measurement and time);
  - the number of alarm-state changes;
  - descriptively, the alarmed share of the unlabelled middle.
- **Compared on the same bearings with two references:**
  - the **anomaly detector**: per-bearing, label-free. Its score is the root-mean-square of 7 speed-corrected feature z-scores, its threshold the 99th percentile of the commissioning scores, and it alarms after 3 scores in a row above that.
  - the rig's own stop rule (rear RMS > 6.5 g).

6. Training Run 1 Results

Run 1 (3 Nov) was the first time the deterioration head was trained. Training took 5.2 s for all 9 networks.

6.1 Training loss




Held out	Final training loss (seeds 0, 1, 2)	Held-out healthy / end-stage rows on opposite sides of 0.5 from
B02	6.6e-5, 6.6e-5, 4.2e-5	step 25 (the first checkpoint)
B03	3.5e-5, 6.1e-5, 4.4e-5	step 25
B04	3.6e-5, 7.3e-5, 8.1e-5	step 25

6.2 Accuracy, precision, recall, F1 and confusion matrices

These are computed on the labelled held-out rows: 100 healthy and 5 end-stage rows per bearing, which is 945 rows over 3 bearings × 3 seeds.

Decision	Accuracy	Precision	Recall	F1	TN / FP / FN / TP
Raw score > 0.5	1.000	1.000	1.000	1.000	900 / 0 / 0 / 45
Run 1 alarm (3 in a row)	1.000	1.000	1.000	1.000	900 / 0 / 0 / 45



Caution: perfect scores here do not mean the model is perfect. The labelled rows are the two easiest extremes, a brand-new bearing and a worn-out one, and there are only 15 end-stage rows from 3 bearings.

6.3 Alarm timing (Run 1 rule)

Held out	First alarm (id), seeds 0, 1, 2	Minutes before the last record	Anomaly detector	Rig stop rule
B02	870, 870, 879	79.5, 79.5, 76.6	864 (81.3 min)	1109 (2.1 min)
B03	590, 590, 590	7.4	549 (20.4 min)	never
B04	478, 458, 489	198.0, 204.4, 194.6	442 (209.6 min)	1113 (0.3 min)

6.4 Weaknesses found in Run 1

1. **Alarm flicker.** After first firing, the alarm switched on and off 8–16 times on B02 and 42–46 times on B04.
2. **Later than the anomaly detector** on every bearing.
3. **Over-confident outputs.** Every probability on a healthy row was below 0.003, and every one on an end-stage row was 1.000.
4. **The labels had not been reviewed.**


7. Training Run 2 Results

Run 2 kept the network, training, seeds and raw output, and changed only the alarm logic to a **latch**. The 9 networks were retrained and came out **byte-identical** to Run 1 (SHA-256 of every weight file). Run 1's files were verified unchanged afterwards.

7.1 Latched alarm: the four requested metrics, per bearing


The MLP rows give the range over seeds 0–2. "Healthy FA" is the healthy-reference rows above threshold and alarmed, out of 100. "Changes" counts every switch on or off over the whole run.

Bearing	Detector	First alarm (id, time)	Min. before end	Changes	Healthy FA	End-stage recall
B02	MLP, Run 1 rule	870–879, 13:17–13:20	76.6–79.5	9–17	0 / 0	100 %
B02	**MLP, Run 2 latched**	870–879, 13:17–13:20	76.6–79.5	**1**	0 / 0	100 %
B02	Anomaly detector (prototype)	864, 13:15:16	81.3	1	1 / 0 (in-sample)	100 %
B03	MLP, Run 1 rule	590, 18:16:15	7.4	1–3	0 / 0	100 %
B03	**MLP, Run 2 latched**	590, 18:16:15	7.4	**1**	0 / 0	100 %
B03	Anomaly detector (prototype)	549, 18:03:16	20.4	1	1 / 0 (in-sample)	100 %
B04	MLP, Run 1 rule	458–489, 15:02–15:12	194.6–204.4	43–47	0 / 0	100 %
B04	**MLP, Run 2 latched**	458–489, 15:02–15:12	194.6–204.4	**1**	0 / 0	100 %
B04	Anomaly detector (prototype)	442, 14:57:25	209.6	1	1 / 0 (in-sample)	100 %



7.2 Why the scores are so close to 0 or 1

- **87.1 % of all held-out outputs** are below 0.001 or above 0.999. Only 5.0 % of the unlabelled rows lie between 0.05 and 0.95.
- **The cause is the labels, not a bug.** Healthy labels are each motor's commissioning period, so their z-inputs sit near 0 (within about ±4.5). Every end-stage row is at the +16 clip on four vibration inputs. Five of the eight inputs separate the two classes on their own.
- **Training makes it worse.** On data this separable, cross-entropy keeps falling as the weights grow, so nothing stops the logits from growing. The mean |logit| on unlabelled rows rises from 0.9 (step 25) to 10.4 (step 2,000), and the unlatched alarm's flicker rises with it, from about 1 to about 20 state changes.
- **Balanced batches** (50 % end-stage, against 4.8 % in the labelled training rows) shift the logits by about +3.0. The score is therefore not a frequency.
- **Is it calibrated?** On the labelled rows the calibration error is tiny (ECE 0.00013), but only 2 of 10 probability bins contain any rows. Calibration in between **cannot be checked**, because the unlabelled middle has no ground truth.



7.3 A temperature-input shortcut, tested

The temperature residual x8 is 0 by construction until a bearing's thermal model is calibrated. That window covers every healthy label, while x8 is non-zero on every end-stage label, so x8 separates the classes for a reason that is not physical. Re-scoring every trained network with x8 = 0 everywhere:

- the labelled rows stayed perfectly separated on all bearings and seeds;
- the latched first alarm moved by at most 20 measurements (about 6 min) on B02 and B04, and not at all on B03.

The vibration inputs carry the decision. The input should still be redesigned (section 11).

7.4 Diagnostic retrainings (not used to choose a model)


Variant	State changes, Run 1 rule (B02 / B03 / B04)	Latched first alarm, min before end	Highest score on a healthy row
Run 1 settings	9–17 / 1–3 / 43–47	76.6–79.5 / 7.4 / 194.6–204.4	0.0021
Weight decay 0.001	1 / 1 / 15–31	80.1–80.3 / 17.5–17.8 / 208.6	0.005
Weight decay 0.01	**1 / 1 / 1**	**80.7 / 17.8 / 208.6–208.9**	0.035
Weight decay 0.1	1 / 1 / 1	80.7 / 19.1–19.5 / 209.2	0.303
Label smoothing 0.05	1–5 / 1 / 1–53	79.5 / 16.2–17.8 / 208.3–208.6	0.087

With weight decay 0.01, the flicker disappears even without the latch. The first alarms move to within 0.7–2.6 min of the anomaly detector, while healthy rows stay far below the threshold.

> **Caution:** weight decay 0.01 was found by looking at the held-out bearings, so these numbers are optimistic. It is a candidate for a pre-declared Run 3, to be judged on bearings that played no part in choosing it.

7.5 INT8 and RTL check of the trained networks


Check	Result
INT8 vs FP32, all 9 networks (golden model, 22-bit accumulator)	0–5 decisions changed per network out of 614–1,065 rows; **none on a labelled row**
Latched first alarm in INT8	identical to FP32 for all 9 networks
Logit error	mean 0.12–0.18, max 1.60
RTL simulation of a trained network (B03 held out, seed 0; Icarus Verilog, `tb_mlp.sv`)	**PASS**, bit-exact; 1,642 cycles per 64 measurements, 382 cycles (1.78 µs at 214.286 MHz) per measurement




8. Run 1 vs. Run 2 Comparison

8.1 What improved, what got worse

Metric (per bearing)	Run 1	Run 2	Change
Alarm-state changes, B02	9–17	1	**improved**
Alarm-state changes, B03	1–3	1	improved
Alarm-state changes, B04	43–47	1	**improved**
First alarm (all bearings)	as in 6.3	identical	unchanged
Healthy-reference false alarms	0 of 300 rows	0 of 300 rows	unchanged
End-stage recall	100 %	100 %	unchanged
Unlabelled rows alarmed, B04	27–32 %	65–68 %	**higher**: one false streak would now stay on until reset
Raw score	as Run 1	identical	unchanged by design
Trained model in INT8 / RTL	not checked	0 labelled decisions changed; RTL PASS	**new evidence**
Calibration understanding	none	cause identified; not calibratable with current labels	**new evidence**





8.2 Does the MLP outperform the anomaly detector?

Not yet.

Bearing	MLP (Run 2 latched), minutes before end	Anomaly detector	Detector earlier by
B02	76.6–79.5	81.3	1.9–4.7 min
B03	7.4	20.4	13.0 min
B04	194.6–204.4	209.6	5.2–15.0 min

- **Labelled rows:** both detectors are perfect.
- **Steadiness:** with the latch, both are equally steady (1 state change).
- **First alarm:** the anomaly detector is earlier on every bearing. It also needs no labels.
- **Outlook:** the weight-decay diagnostic suggests the MLP can match the detector's timing, but that has to be shown on new bearings.


9. FPGA Compatibility

9.1 The INT8 implementation

The trained network is converted with the project's export scheme (`export.py`, used by `mtl_model.int8_model`):

- **Inputs:** quantized with one scale, 16/127 per step, so ±16 maps to ±127.
- **Weights:** a scale per output channel, max |W| / 127, then rounded to INT8.
- **Biases:** INT32.
- **Between layers:** a hidden layer's 22-bit sums are requantized to INT8 with a fixed-point multiplier and shift (m0, shift) per channel, chosen from the largest activation on the calibration rows. Rounding matches the hardware's `postproc.sv`.
- **Last layer:** the chip returns its raw sums; the ARM adds the bias and applies the sigmoid.
- **Bit-exact reference:** a Python golden model (`mac.golden_mlp`) reproduces the hardware bit for bit.

9.2 The 8 × 8 systolic array



- **The array:** 64 processing elements, one DSP48E1 multiplier each, multiplying INT8 values into exact 22-bit accumulators. Matrices are up to 64 wide.
- **The interface:** the Zynq ARM drives it over AXI4-Lite.
- **The on-chip MLP engine:** runs a whole network of up to 4 layers with one control write. The weights are held in four 64 × 64 slots, and 8 post-processing units requantize each layer's output back into the input buffer.

Build	Clock	Resources	Board result
Design 1: matrix multiplier	250 MHz (timing met, WNS +0.008 ns)	LUT 1,170, FF 2,997, BRAM 4.5, DSP 64, 1.94 W	24/24 tests passed (19 Oct); 64 × 64 × 64 in 293 µs, 7.6 × faster than the ARM
Design 2: on-chip MLP	214.286 MHz (WNS +0.081 ns; 250 MHz missed by 0.029 ns)	LUT 4,402, FF 7,048, BRAM 7.5, DSP 80, 2.118 W	30/30 tests with test models (24 Oct, recorded on branch `Alex_edit`); a 64-64-64-6 model on 64 rows in 113 µs, 47.9 × faster than the ARM

9.3 Hardware simulation results for the models

Model	Check	Result
Ottawa E3 (22 → 32 → 16 → 1)	RTL vs golden model, every window	PASS, every logit bit-exact; 566 cycles per window
Ottawa a1 (8 → 32 → 16 → 1)	RTL (Vivado xsim)	PASS; 382 cycles (1.78 µs) per window
Multi-task MLP, random weights	RTL (Vivado xsim), 896 + 10 rows	PASS, both output columns bit-exact; 382 cycles
Multi-task MLP, trained (Run 2)	RTL (Icarus Verilog), 576 + 10 measurements	**PASS**, bit-exact; 1,642 cycles per 64, 382 cycles per measurement

One inference takes 1.78 µs, while Paderborn measurements arrive every 18–19 s, so compute time is not a constraint. The ARM's feature extraction will dominate.

9.4 What remains before physical FPGA deployment

1. **Freeze one model.** A model with its threshold has to be frozen, then evaluated once on the locked bearings.
2. **Re-export INT8 from the frozen model** and rerun `rtl_check` on it.
3. **Port to the ARM:**
   - the feature extraction (RMS, peak, kurtosis, band energies, crest);
   - the per-motor commissioning fit;
   - the temperature model;
   - the latched alarm, with a reset.
4. **Check on the board** against the test vectors, and measure the end-to-end time including the AXI transfers.
5. **Connect the real sensors** (one accelerometer, a temperature probe, speed), and record a commissioning run on our own motor.
6. **Run the trained network on the ZedBoard.** So far only test models have run on the board.

10. Current Limitations

- **Small training set.** Three labelled bearings, 300 healthy and **15 end-stage** rows, all from one operating regime (128 kHz, sinusoidal load). Three of the four locked test bearings come from regimes the model has never seen.
- **Provisional labels.** The end-stage labels stand for "found damaged after the test". They are not a verified state at those measurements, and they were not reviewed. For two of the three labelled bearings, they sit where the rig's vibration stop rule fired.
- **Unknown deterioration onset.** The middle of every run is unlabelled. So first-alarm times are not detection delays, and no detection rate can be stated.
- **Alarm instability.** The raw score flickers once training makes it over-confident. The latch hides this but does not remove it, and a false streak would keep the alarm on until it is reset.
- **Uncalibrated score.** The output is not a probability of failure and cannot be calibrated with the current labels.
- **Temperature-input shortcut.** "Not calibrated" and "exactly as expected" are both 0.
- **Easy healthy labels.** The healthy labels are the commissioning period the inputs are normalised on, so false alarms during later healthy operation are unmeasured.
- **Why the Motor Health Index is not trained.** A 0–100 % health output needs measurements whose true wear level is known: inspected at intervals, or with defects of known size. The run-to-failure data only document the start (new) and the end (damaged), with no measured levels between. Training the head on invented intermediate values would produce numbers that look meaningful but are not. It stays frozen until reliable severity labels exist.

11. Future Improvements

11.1 Reliability and generalisation

1. **Process more development bearings.** Priority 1 takes the labelled bearings from 3 to 7 and the end-stage rows from 15 to 35, and covers two of the three regimes the model has not seen:
    - **B08:** Gaussian load, temperature-stopped.
    - **B09:** Gaussian load, first outer-race defect.
    - **B11** and **B12:** 64 kHz, variable speed.
    - Next come B10, then B14 and B15 (constant speed, large).
2. **Declare Run 3 before running it:**
    - weight decay 0.01 and the latched alarm;
    - the threshold chosen on validation bearings only;
    - nested leave-one-out over the 7 bearings;
    - compared with the anomaly detector on first-alarm time.
3. **Fix the temperature input**, so "not calibrated" is a separate flag rather than the value 0.
4. **Measure false alarms on long healthy operation:** for example the middle of B02 before its first change, and B05 and B16 as healthy-reference data.
5. **Report the output as a "deterioration score"** everywhere until labelled intermediate states exist.

11.2 Training the health-index output

- **Severity labels:** use bearings with a known defect size (for example an external dataset with seeded damage), or inspections at intervals, to build labels.
- **Training the head:** train it only after the deterioration head is final, and keep the shared trunk frozen or nearly so, so the alarm does not change.
- **Validating it:** on held-out bearings, against the severity labels.

11.3 Preparing for FPGA deployment

- **Freeze, export, check:** freeze one model, export INT8, and run `rtl_check` on it.
- **Port the ARM side:** the feature extraction and the latched alarm with reset.
- **Test on the board:** run the end-to-end inference test on the ZedBoard against recorded vectors, then with live sensors.
- **Final test:** evaluate once on B06, B07, B13 and B17, and report it whatever the result.

12. Conclusion

Accomplishments.

- **Hardware:** a working INT8 accelerator: a board-tested 8 × 8 systolic array at 250 MHz, and an on-chip MLP engine at 214.286 MHz.
- **First model:** an Ottawa motor classifier that shaped the hardware-sized network (8 → 32 → 16 → 1).
- **Data pipeline:** a careful pipeline for the Paderborn run-to-failure data, with checks, a locked test set and stated labelling assumptions.
- **Network:** an 850-parameter, two-head network that fits the accelerator unchanged.

Results.

- **On unseen bearings:** the trained deterioration head separates documented-healthy from end-stage measurements perfectly, with zero false alarms on 300 healthy-reference rows and 100 % end-stage recall.
- **Run 2's latched alarm:** removes the flicker (from up to 47 state changes to 1) without moving the first alarm.
- **Hardware fit:** the trained network survives INT8 with no labelled decision changed, and runs bit-exact on the RTL in 1.78 µs.
- **The cost of over-confidence:** the investigation showed why the scores are so extreme, and that they cannot yet be read as probabilities.

Remaining work.

- **Beat the baseline:** the network does **not** yet beat the label-free anomaly detector, which alarms earlier on every bearing.
- **More data:** process more bearings so a model can be chosen on validation data and tested fairly.
- **Health index:** train it only when severity labels exist.
- **Board:** run the frozen model on the board.

The honest status is a working, hardware-ready pipeline whose learned model still has to prove its advantage on more data.

13. Sources in the repository

Topic	Files
Project decisions, hardware builds and board tests	`docs/log.md` (sections 1–3; board results 19 and 24 Oct; the 24 Oct on-chip MLP board run is on branch `Alex_edit`)
Ottawa models	`model/README.md`, `model/results/E0 – E3/report.md`, `model/SINGLE_ACCEL_MODEL_REPORT.md`, `model/SINGLE_ACCEL_HARDWARE_REPORT.md`, `model/export/E3*/report.md`
Paderborn data, B01, anomaly detector	`model/paderborn.py`, `model/paderborn_experiments.json`, `model/results/B01/B01_analysis_report.md`, `model/results/paderborn/PADERBORN_BASELINE_REPORT.md`
Architecture and inputs	`model/mtl_model.py`, `model/mtl_inputs.py`, `model/results/multitask/MULTITASK_ARCHITECTURE_REPORT.md`
Validation, split, labels	`model/results/phase2/DATASET_VALIDATION_REPORT.md`, `model/splits.py`, `model/labels.py`, `model/results/supervised/LABEL_REVIEW_REPORT.md`
Run 1	`model/train_deterioration.py`, `model/results/supervised/run1/` (`TRAINING_RUN1_REPORT.md`, `results.json`)
Run 2	`model/train_deterioration_run2.py`, `model/results/supervised/run2/` (`TRAINING_RUN2_REPORT.md`, `results.json`, `checkpoints.csv`, `variants.csv`)