

altairsim — Have an AI find and fix a bug — over MCP

2026-10-02 · d6623c6

This folder is a working directory for an **AI assistant driving altairsim over MCP**. It holds a CP/M Altair and a tiny program, `HELLO.ASM`, that is supposed to print `HELLO, WORLD` and does not. There is one deliberate bug in it. The exercise is that the assistant — not you — assembles it, runs it, sees the wrong output, single-steps the loop to find the fault, corrects the source, and reassembles, **all through the simulator's MCP tools**. No cutting and pasting.

If you have never wired an assistant to altairsim, read `DRIVING-WITH-AI.md` (it ships beside this folder) first — it is the briefing you drop in front of the assistant, and it explains the MCP server and the one registration step that this walkthrough assumes you have done. Give the assistant the `skills` folder too: the briefing names files in it for the build steps.

If your assistant reads Agent Skills, install the folders in `skills/` from the package instead. The assistant then loads the same briefing, and the build rules, by itself. The manual's package chapter tells you where to copy it.

Point your assistant at this machine

The machine is `cpm-ai.toml`. Register the server **from this directory**, so the host bridge (`R/W`, below) can reach the source the assistant edits:

```
cd examples/ai-mcp
claude mcp add altairsim -- altairsim cpm-ai.toml --mcp      # Claude Code; see DRIVING-WITH-AI.md for other
clients
```

This is the `claude` command line, which runs the server here in this folder, so the relative `cpm-ai.toml` and the host bridge both resolve to it. (The Claude Desktop app starts the server in your home directory instead — there, use an absolute path; `DRIVING-WITH-AI.md` covers it, along with running several machines at once.)

Then start your assistant in this directory and give it the whole job in one sentence:

Using the altairsim MCP tools, boot the CP/M machine and assemble and run `HELLO.ASM` off its disk. It should print `HELLO, WORLD` — if it doesn't, debug it in the simulator and fix the source.

Say "using the altairsim MCP tools" and "off its disk" on purpose. `HELLO.ASM` lives on the CP/M disk, reached through the MCP `run / monitor` tools — *not* as a host file to open. If you just say "fix `HELLO.ASM`," a fresh assistant is apt to find it on your machine and start editing a host copy instead of driving the simulator — and when you are running from a checkout of this repository (rather than a shipped package) there really is a pristine `HELLO.ASM` sitting loose in this folder for it to land on, which is not the file the exercise is about. Point it at the disk and that confusion never starts.

Want to watch it work live? Add `--mirror socket:2323` to the registered command (`... altairsim cpm-ai.toml --mcp --mirror socket:2323`), then `telnet localhost 2323` in another window while the assistant runs. You see the same console it is driving, character by character, and can type onto the line to take the keyboard yourself. `--mirror socket:2323?ro` watches without touching it. `DRIVING-WITH-AI.md` explains it under *Watching over its shoulder*.

The rest of this file is the session that unfolds, so you can follow along or check its work.

1 — Build it and watch it misbehave

The disk already carries `HELLO.ASM`, CP/M's `ASM` and `LOAD`, and the host-bridge utilities. The assistant boots the machine (`run {from: 65280}`), which is `FF00` — under `--mcp` the startup is not run, so it boots the disk itself), then assembles, loads and runs the program:

```
run {input: "ASM HELLO\r", until: "A>"}      -> END OF ASSEMBLY
run {input: "LOAD HELLO\r", until: "A>"}      -> FIRST ADDRESS 0100 ... HELLO.COM
run {input: "HELLO\r", until: "A>"}          -> ELLO, WORLD
```

There it is: **ELLO, WORLD**. The `H` is missing. It assembled cleanly and ran without crashing, so this is a logic bug, not a typo the assembler could catch — exactly the kind of thing the debugger is for.

2 — Stop where the program loads, and look

The assistant sets a breakpoint at `0100` — the CP/M transient program area, where `HELLO.COM` loads — and runs it. CP/M's loader jumps to `0100` and the breakpoint trips before a single instruction of the program has run:

```
monitor {command: "BREAK 0x100"}             -> breakpoint 1: pc 0100
run      {input: "HELLO\r", until: "0100"}    -> stopped at breakpoint
monitor {command: "DISASM 0x100 6"}           ->
```

```

0100 21 15 01 LXI H,0115      ; HL -> the string
0103 23      INX H           ; advance the pointer
0104 7E      MOV A,M         ; fetch the character
0105 B7      ORA A           ; the 0 terminator?
0106 CA 14 01 JZ 0114
0109 5F      MOV E,A

```

The string is at 0115, and 0115 holds 48 — 'H'. But look at the order: INX H at 0103 runs **before** MOV A,M at 0104. The pointer is advanced past the first character before that character is ever fetched. Single-stepping proves it — watch the A register:

```
monitor {command: "STEP 3"}
```

```

... H=0115 ... P=0103 INX H      ; HL points at 'H' (0115)
... H=0116 ... P=0104 MOV A,M    ; INX H has already moved it to 0116
... A=45  ... P=0105 ORA A       ; so A = 45 = 'E', never 'H'

```

A=45 is 'E'. The very first character the program prints is the second character of the string. The bug is an ordering slip: the loop increments the pointer at the top, before the load, when it should increment at the bottom, after the character has been sent.

3 — Fix the source, and reassemble

The fix is to move INX H from the top of the loop to the bottom, just before the JMP back — so the pointer advances *after* the character has been sent, not before it is fetched. The source lives on the disk, so the assistant first pulls it to a host file it can edit (W, the other half of the host bridge), corrects it, then copies it back (R) and reassembles:

```
run {input: "W HELLO.ASM HELLO.ASM T\r", until: "A>"} ; CP/M -> host (T = text, trims ^Z)
```

It edits the host `HELLO.ASM` — **keeping the file CR/LF**, or `ASM` will assemble it to nothing — so the loop reads:

```
LOOP:  MOV A,M      ;fetch the next character
      ORA A        ;the 0 terminator?
      JZ  DONE      ;yes -- finished
      MOV E,A       ;no -- character to E for BDOS
      MVI C,CONOUT
      PUSH H
      CALL BDOS
      POP H
      INX H         ;NOW advance -- after this character is sent
      JMP LOOP
```

then copies it back onto the disk and rebuilds:

```
run {input: "R HELLO.ASM\r", until: "A>"} ; host file -> CP/M (over the host bridge)
run {input: "ASM HELLO\r", until: "A>"} ; -> a new HELLO.HEX
run {input: "LOAD HELLO\r", until: "A>"} ; -> a new HELLO.COM
run {input: "HELLO\r", until: "A>"} -> HELLO, WORLD
```

`HELLO, WORLD`. The program was assembled, run, debugged, corrected and reassembled without the machine ever leaving the assistant's hands — which is the whole point.

The host bridge, in one line

`R` and `W` are how a file crosses between your directory and the CP/M disk — they are what let the assistant edit `HELLO.ASM` here and build it in there:

- `R <hostfile> [cpmfile]` — host → CP/M. `W <cpmfile> [hostfile] [B|T]` — CP/M → host.
- **B (binary) is the default**, and is what a `.COM` needs. Use **T** for text (`.PRN`, `.HEX`, `.ASM`) so the trailing `^Z` padding is trimmed. Source must be **CR/LF** — `ASM` assembles an LF-only file to nothing.

The files

File	What it is
<code>cpm-ai.toml</code>	The machine: <code>base = "default"</code> (the CP/M Altair) plus this folder's disk in drive 0.
<code>cpm22b23-56k.dsk</code>	Mike Douglas's track-buffered CP/M 2.2b, the same image <code>examples/cpm</code> boots — with the buggy <code>HELLO.ASM</code> dropped on it. Also carries <code>ASM</code> , <code>LOAD</code> , <code>DDT</code> and the host-bridge <code>R/W</code> . This is where the source is: the assistant reads and builds it here.

The buggy `HELLO.ASM` lives **on the disk**, not loose in the folder — that is what the assistant reads with `W` and builds with `ASM`. (In the source tree a pristine copy sits beside this file to rebuild the disk from; it is not part of the shipped package.)

There is no undo. The assistant writes to the disk when it reassembles, overwriting the buggy `HELLO.ASM` on it with the fix. Copy this folder first if you want the planted bug back without a `git checkout`.