

NBduino

NARROWBAND SHIELD

ARDUINO COMPLIANT

DESCRIPTION

NBduino is the new shield that allows you to send data from your Arduino board directly to the cloud via the NB-IoT network.

You can plug the shield on the "Arduino" boards or it can be standalone with a self own LiPo battery.

With simple codes and libraries (check the [link](#)), it's possible to develop fastly your application and view your data directly on the Cloud.



PLUG AND PLAY
(ARDUINO COMPATIBLE)

POWER MODES
(USB or LiPo
battery)

**LOW
POWER**
(5 μ A)

**LONG
RANGE**
(7 Km)

**CLOUD
STORAGE**
(MQTT BROKER READY)

TOPVIEW SRL

Via Pertini 25d
81020, San Nicola la
Strada (CE), Italy
+39 0823424244

www.topview.it

Mon- Fri
09-18




NARROWBAND SHIELD ARDUINO COMPLIANT

INDEX

SHIELD PINOUT DIAGRAM	pag. 3
PLUG AND PLAY (ARDUINO COMPATIBLE)	pag. 4
POWER MODES (USB or LiPo battery)	pag. 5
LOW POWER (5μA)	pag. 6
LONG RANGE (7 Km)	pag. 7
CLOUD STORAGE (MQTT BROKER READY)	pag. 8
REFERENCE	pag. 9

SHIELD PINOUT DIAGRAM



- A. ARDUINO PINOUT
- B. FTDI PORT
- C. NET LED (fast blink = wait to attach, slow blink = attached);
- D. STATUS LED (Fixed = module ON)
- E. CHARGE LED (ON = charging, OFF = charged)
- F. PowerKey PAD (to wake up the module – without arduino)
- G. Reset PAD (resets the module)
- H. GND PAD
- I. LiPo 3.7V slot
- J. EMBEDDED ANTENNA
- K. MICRO SIM SLOT





NBDUINO

NARROWBAND SHIELD ARDUINO COMPLIANT

PLUG & PLAY

You can plug this SHIELD on the follow Arduino boards:

- Diecimila
- Due
- Duemilanove
- Uno
- Leonardo
- Mega2560
- Yun



NBduino

NARROWBAND SHIELD ARDUINO COMPLIANT

POWER MODES

1. – USB –

Plug the SHIELD on the Arduino Board, connect USB cable and run the sketch

The module is powered by Arduino's 5v pin and the LiPo battery charger starts to charge (you can see the fixed CHARGE LED, it will turn off when charging is complete)




Figure 1: a) the NBduino SHIELD plugged on Arduino UNO, b) The System powered by USB cable and LiPo battery charging

2. - STANDALONE with Arduino -

Plug the SHIELD on the Arduino Board, connect 3.7V LiPo battery and run the sketch




Figure 2: the NBduino SHIELD plugged on Arduino UNO, both powered by 3.7v LiPo battery

3. - STANDALONE without Arduino –

Connect 3.7V LiPo battery, wake-up the SHIELD pushing “P” pad and GND pad together for 500 ms (it also sleep the SHIELD).

You can directly control the module with a FTDI cable by your personal computer.



Figure 2: the NBduino SHIELD “standalone” powered by 3.7v liPo battery

NB

DUINO

NARROWBAND SHIELD

ARDUINO COMPLIANT

LOW POWER

The NB chip on board is the “SIM7020E” by SIMCOM;

it has an ultra low power consumption (5 μ A in “Power Save Mode”).

You can find every specification about SIMCOM product inside “SIM7020 Hardware Design_V1.00” and “SIM7020 Series MQTT Application Note”.

NBduino


NARROWBAND SHIELD ARDUINO COMPLIANT

LONG RANGE

It can be used directly in the cloud using the mobile vendors infrastructure and it's possible to develop its own application to MQTT broker that manages all data.

TOPVIEW provides to his clients the SIM card with some traffic available and space on cloud to manage the data.

Here is the network structure for NB-iot communications:



☰ NB-IOT

NB-IOT Test page

Payload: Topic: 868333030018895/H%
 Payload: 48

Index	Timestamp	Topic	Value
0	2018-11-08T17:35:26.000Z	868333030018895/T_2	
1	2018-11-08T17:35:23.000Z	868333030018895/T	22
2	2018-11-08T17:35:23.000Z	868333030018895/H_2%	
3	2018-11-08T17:35:22.000Z	868333030018895/H%	48
4	2018-11-08T17:35:04.000Z	868333030018895/T_2	
5	2018-11-08T17:35:03.000Z	868333030018895/T	22
6	2018-11-08T17:35:00.000Z	868333030018895/H_2%	
7	2018-11-08T17:35:00.000Z	868333030018895/H%	48
8	2018-11-08T17:34:42.000Z	868333030018895/T_2	
9	2018-11-08T17:34:42.000Z	868333030018895/T	22
10	2018-11-08T17:34:38.000Z	868333030018895/H_2%	
11	2018-11-08T17:34:38.000Z	868333030018895/H%	48
12	2018-11-08T17:33:36.000Z	868333030018895/T_2	
13	2018-11-08T17:33:35.000Z	868333030018895/T	22

Cloud Storage powered by

TOPVIEW
LOOKING OVER




NARROWBAND SHIELD

ARDUINO COMPLIANT

CLOUD STORAGE

TopView provides a cloud service (optional) if it is required, you can see your data on cloud and store it on our database.

We also provide APIs to interface the personal user service with our own.



NBduino

NARROWBAND SHIELD ARDUINO COMPLIANT

Reference

<https://github.com/TopViewsrl/NBduinoShield>