

BME688



BME688 Environmental Sensor 4-in-1

v1.0
2025-07-17
Rev. A

Professional electronic component

PRODUCT OVERVIEW

The BME688 Environmental Sensor 4-in-1 is a versatile sensor module that combines temperature, humidity, pressure, and gas sensing capabilities in a single compact package. It utilizes the BME688 sensor from Bosch, which is known for its high accuracy and low power consumption. This module is ideal for applications in environmental monitoring, IoT devices, and smart home systems.

PRODUCT VIEWS

TOP VIEW



Top View

Component placement and connectors

BOTTOM VIEW



Bottom View

Underside components and connections

TECHNICAL FEATURES

Relative Humidity: Accurately measures ambient moisture for precise environmental monitoring.	Barometric Pressure: Detects atmospheric pressure changes to support dynamic weather tracking.
Excellent Temperature Stability: Delivers consistent temperature readings even under varying conditions.	Gas Sensing: Monitors a range of gases to help identify potential environmental hazards.

TECHNICAL SPECIFICATIONS

⚙️ TECHNICAL SPECIFICATIONS

PARAMETER	TECHNICAL DATA
Package dimensions	8-Pin LGA with metal 3.0 x 3.0 x 0.93 mm ³
Operation range (full accuracy)	Pressure: 300...1100 hPa Humidity: 0...100% Temperature: -40...85°C
Supply voltage VDDIO	1.2 ... 3.6 V
Supply voltage VDD	1.71 ... 3.6 V
Interface	I ² C and SPI
Average current consumption	2.1 µA at 1 Hz humidity and temperature 3.1 µA at 1 Hz pressure and temperature 3.7 µA at 1 Hz humidity, pressure and temperature 90 µA at ULP mode for p/h/T & air quality 0.9 mA at LP mode for p/h/T & air quality 3.9 mA in standard gas scan mode (gas scan mode & scan rate can be optimized on applications with BME AI studio)
Gas sensor - F1 score for H ₂ S scanning	0.94
Gas sensor - Standard scan speed	10.8 s / scan
Gas sensor - Electric charge for standard scan	0.18 mAh (5 scans ~ 1 min)
Gas sensor - Response time (τ 33-63%)	< 1 s (for new sensors)
Gas sensor - Sensor-to-sensor deviation	+/- 15%
Gas sensor - Power consumption	< 0.1 mA in ultra-low power mode
Gas sensor - Output data processing	Major direct outputs: Index for Air Quality (IAQ), bVOC- & CO ₂ -equivalents (ppm), Gas scan result (%) & many more (all listed in datasheet in Table 20: BSEC outputs)
Humidity sensor - Response time (τ0-63%)	8 s
Humidity sensor - Accuracy tolerance	± 3 % relative humidity
Humidity sensor - Hysteresis	≤ 1.5 % relative humidity
Pressure sensor - RMS Noise	0.12 Pa (equiv. to 1.7 cm)
Pressure sensor - Sensitivity Error	± 0.25 % (equiv. to 1 m at 400 m height change)
Pressure sensor - Temperature coefficient offset	±1.3 Pa/K (equiv. to ±10.9 cm at 1°C temperature change)

SUPPORTS

SYMBOL	I/O	DESCRIPTION
VCC	Input	3.3V or 5V
GND	GND	Common ground for all components

HARDWARE DOCUMENTATION

MECHANICAL DIMENSIONS



Physical dimensions and mounting specifications (measurements in millimeters)

SYSTEM TOPOLOGY



Connection topology and system integration diagram

Click image to open in full size

COMPONENT REFERENCE

REF.		DESCRIPTION	
IC1		BME688 Environmental Sensor	
L1		Power On LED	
U1		AP2112K 3V3 Regulator	
JP1		2.54 mm Castellated Holes	
J1		QWIIC Connector (JST 1 mm pitch) for I2C	

INTERFACE		SIGNALS / PINS	TYPICAL USE
UART	–		Unavailable
I²C		SDA, SCL (CSB held high)	Default interface (Qwiic connector)
SPI		CSB = GND, SDI (MOSI), SCK, SDO (MISO)	High-speed alternative
USB	–		Unavailable on this module

CIRCUIT SCHEMATIC

**Circuit Schematic**

Complete circuit schematic showing all component connections

[View Complete Schematic PDF](#)

PIN DESCRIPTION

Detailed pin assignment and electrical specifications

SIGNAL DESCRIPTION

FUNCTION		NOTES
Power Supply		3.3V or 5V
Ground		Common ground for all components

GROUP	AVAILABLE PINS	SUGGESTED USE
SPI	CSB, SDI (MOSI), SDO (MISO), SCK	High-speed SPI to read sensor data
I²C	SDA, SCL (via Qwiic connector)	Standard I²C for configuration & data acquisition

PIN CONFIGURATION LAYOUT

Physical connector layout and pin positioning



Pin Configuration Layout

Complete pin configuration diagram showing all connectors, pin assignments, and electrical connections for proper integration

