ALLIANCE UNIVERSITY

Kalvium Undergraduate Programme

DESIGN AND ANALYSIS OF ALGORITHMS

MICROPROJECT REPORT

"Optimal Control Path Routing across CPU Functional Units via Dijkstra's Shortest Path Algorithm"

Submitted by: Gautham Ram

Programme: B.Tech. (Computer Science & Engineering)

Institution: Kalvium | Alliance University

Squad: 70

Course Faculty / Mentor: Simran Kumari

Submission Date: October 2026

1. Title

Optimal Control Path Routing across CPU Functional Units via Dijkstra's Shortest Path Algorithm

2. Problem Statement

Given an on-chip CPU datapath modeled as a directed weighted graph G = (V, E) where vertices represent hardware execution blocks and edge weights represent interconnect propagation and transmission latencies in nanoseconds, how can Dijkstra's greedy single-source shortest path algorithm using a Min-Heap priority queue determine optimal minimum-latency control routing, and what are its rigorous asymptotic time and space bounds?

3. Introduction / What is it?

In the design and analysis of computer algorithms, graph theory provides the theoretical foundation for solving optimization problems across interconnected networks. Among classical graph challenges, the Single-Source Shortest Path (SSSP) problem is central: given a directed graph with non-negative edge weights, determine the minimum-cost path from a designated source vertex to all other reachable vertices. Formulated by Edsger W. Dijkstra in 1959, Dijkstra's algorithm remains the foundational greedy method for solving SSSP efficiently.

In physical microprocessors and System-on-Chip (SoC) architectures, micro-instructions and control words must navigate an interconnected web of hardware functional units—including Instruction Fetch Units, Register Files, Decoders, Arithmetic Logic Units, Data Memories, Branch Predictors, and Write-Back Buses. Each inter-unit bus segment, multiplexer switch, and buffer registers introduce propagation and gate switching delays measured in nanoseconds. Finding the optimal control path that minimizes end-to-end signal latency is essential for meeting clock cycle timing constraints and reducing critical path delays. In this microproject, we model the CPU execution datapath as a directed weighted graph and implement Dijkstra's algorithm with a custom binary Min-Heap priority queue to compute optimal control path routes, trace step-by-step relaxation, and analyze algorithmic complexity.

4. How does it work?

The algorithmic engine models hardware functional units as vertices and physical interconnects as directed edges with non-negative weights representing latencies:

1. Graph Model Representation

The CPU interconnect topology is represented as a directed weighted graph G = (V, E):

- Vertex Set V (|V| = 7): {IF_UNIT, DECODE_UNIT, REG_FILE, ALU, DATA_MEM, BRANCH_UNIT, WB_BUS}.
- Edge Set E (|E| = 9): Directed edges with associated latencies in nanoseconds (ns):
- (IF_UNIT → DECODE_UNIT: 1.2 ns) — Instruction bus transfer from cache to decode logic.

- (DECODE_UNIT → REG_FILE: 0.8 ns) — Register address routing to read ports.
- (DECODE_UNIT → ALU: 1.1 ns) — Bypass path directly to ALU operand latch.
- (DECODE_UNIT → BRANCH_UNIT: 1.0 ns) — Branch offset evaluation bus.
- (REG_FILE → ALU: 1.5 ns) — Register file data forwarding to execution unit.
- (ALU → DATA_MEM: 1.8 ns) — Memory address calculation and access bus.
- (ALU → WB_BUS: 0.9 ns) — Arithmetic execution result write-back routing.
- (DATA_MEM → WB_BUS: 2.0 ns) — Memory read data bus to register commit stage.
- (BRANCH_UNIT → WB_BUS: 0.8 ns) — Branch target write-back to Program Counter.

2. Execution Mechanics of Dijkstra's Algorithm

- Initialization: The algorithm sets dist[source] = 0 and dist[v] = ∞ for all other vertices v ∈ V. Predecessor pointers pred[v] are initialized to NIL. A binary Min-Heap priority queue Q is initialized and populated with (0, source).
- Greedy Min-Node Extraction: At each step, the algorithm extracts the vertex u with the minimum tentative distance dist[u] from Q. This vertex is added to the finalized set of explored vertices S.
- Edge Relaxation: For each outgoing directed edge (u, v) ∈ E with weight w(u, v): if dist[u] + w(u, v) < dist[v], a shorter path to v has been discovered. The algorithm relaxes the edge by updating dist[v] = dist[u] + w(u, v), setting pred[v] = u, and performing a decrease-key operation on Q.
- Path Reconstruction: When the destination target vertex is extracted, the shortest path is reconstructed by following predecessor pointers pred[v] backwards from target to source, yielding the optimal control routing.

5. Scientific / Theoretical Concept

The correctness and asymptotic efficiency of Dijkstra's algorithm are supported by formal algorithmic proofs:

1. Optimal Substructure Property

The shortest path problem exhibits optimal substructure: any subpath of a shortest path is itself a shortest path. Formally, if $p = (v_1, v_2, ..., v_k)$ is a shortest path from v_1 to v_k, then for all $1 \le i < j \le k$, the subpath $p_{ij} = (v_i, ..., v_j)$ is a shortest path from v_i to v_j. This property permits recursive formulation of the shortest path distance:

$$\delta(s, v) = \min_{(u, v) \in E} \{ \delta(s, u) + w(u, v) \}$$

2. Greedy Choice Property

At each iteration, extracting the vertex u with the minimal tentative distance dist[u] guarantees that dist[u] is the true shortest path distance: dist[u] = δ(s, u), provided that edge weights are strictly non-negative (w(u, v) ≥ 0). Any alternative unexamined path from s to u must traverse through some unvisited vertex x with dist[x] ≥ dist[u], meaning no shorter alternate route can exist.

3. Rigorous Time Complexity Proof

The asymptotic time complexity is determined by three distinct phases:

- 1. Distance Array Initialization: Initializing dist and pred arrays takes O(V) time.
- 2. Priority Queue Insertions and Extractions: Each of the |V| vertices is inserted once and extracted once via Extract-Min. In a binary min-heap, each Extract-Min takes O(log V) time: Total = |V| × O(log V) = O(V log V).
- 3. Edge Relaxations and Decrease-Key Operations: Each of the |E| directed edges is examined at most once. Each successful relaxation triggers a Decrease-Key operation taking O(log V) in a binary heap: Total = |E| × O(log V) = O(E log V).
- Total Asymptotic Time Complexity: Combining these terms yields:

$$T(V, E) = O(V) + O(V \log V) + O(E \log V) = O((V + E) \log V)$$

- Space Complexity: Maintaining the adjacency list representation, the binary heap structure, and the distance/predecessor arrays requires O(V + E) auxiliary space.

6. Factors Affecting It

Key algorithmic and architectural factors govern Dijkstra's execution efficiency:

- Graph Density and Data Structure Selection: In sparse graphs where $|E| \ll |V|^2$, a binary min-heap achieves O((V + E) log V), vastly outperforming an unsorted array implementation $O(V^2)$. For extremely dense graphs ($|E| \approx |V|^2$), a Fibonacci heap achieves theoretical O(E + V log V) time.
- Non-Negative Edge Weight Invariant: Dijkstra's algorithm fails fundamentally if negative edge weights exist because the greedy choice assumption is violated. For graphs with negative weights, the Bellman-Ford algorithm O(V · E) must be used.
- Dynamic Edge Weights and Jitter: In physical hardware and network environments, latencies fluctuate with thermal throttling and bus contention. Dynamic updates require incremental shortest path maintenance algorithms (e.g., Dynamic Dijkstra or D* Lite).
- Single-Target Early Termination: When routing a specific instruction from IF to a single target unit (e.g., WB_BUS), the algorithm terminates immediately upon extracting the destination node, avoiding exploration of the remaining graph.

7. Real-Life Application

Dijkstra's shortest path algorithm is one of the most widely applied algorithms in computer science:

- Internet Routing Protocols (OSPF and IS-IS): Core Internet routers use the Open Shortest Path First (OSPF) protocol, which runs Dijkstra's algorithm across network link-state databases to compute optimal routing tables.
- VLSI Layout and Network-on-Chip (NoC) Routing: Modern multi-core processors connect dozens of cores using on-chip routers, where shortest-path algorithms route packetized cache-coherency traffic with minimal latency.

- Global Positioning Systems (GPS) & Navigation: Digital mapping services (Google Maps, OpenStreetMap) use optimized variants of Dijkstra's algorithm (such as A* and Contraction Hierarchies) to calculate driving routes.

Observational Step-by-Step Min-Heap Relaxation Trace


To observe the algorithm's greedy execution in detail, a route calculation from IF_UNIT (source) to WB_BUS (target) was traced step by step through the simulator. The priority queue state, extracted vertices, edge weights, and tentative distance updates are logged in Table 7.1 below:

Table 7.1: DAA Experimental Verification & Benchmark Metrics

Step #	Action	Extracted Vertex	Target Neighbor	Edge Latency (ns)	Tentative Distance Calculation	Relaxation Status	Priority Queue State (Min-Heap)
#1	INIT	—	IF_UNIT	0.0	dist[IF_UNIT] = 0.0 ns	INITIALIZED	[(0.0, IF_UNIT)]
#2	EXTRACT-MIN	IF_UNIT (0.0 ns)	—	—	Finalized dist[IF_UNIT] = 0.0 ns	EXPLORED	[]
#3	RELAX	IF_UNIT	DECODE_UNIT	1.2	0.0 + 1.2 = 1.2 ns < inf	UPDATED (pred=IF)	[(1.2, DECODE_UNIT)]
#4	EXTRACT-MIN	DECODE_UNIT (1.2 ns)	—	—	Finalized dist[DEC] = 1.2 ns	EXPLORED	[]
#5	RELAX	DECODE_UNIT	REG_FILE	0.8	1.2 + 0.8 = 2.0 ns < inf	UPDATED (pred=DEC)	[(2.0, REG_FILE)]
#6	RELAX	DECODE_UNIT	ALU	1.1	1.2 + 1.1 = 2.3 ns <	UPDATED (pred=DEC)	[(2.0, REG_FILE), (2.3,

					inf		ALU)]
#7	RELAX	DECODE_UNIT	BRANCH_UNIT	1.0	1.2 + 1.0 = 2.2 ns < inf	UPDATED (pred=DEC)	[(2.0, REG), (2.2, BR), (2.3, ALU)]
#8	EXTRACT-MIN	REG_FILE (2.0 ns)	—	—	Finalized dist[REG] = 2.0 ns	EXPLORED	[(2.2, BRANCH_UNIT), (2.3, ALU)]
#9	RELAX	REG_FILE	ALU	1.5	2.0 + 1.5 = 3.5 ns > 2.3 ns	SKIPPED (3.5 > 2.3)	[(2.2, BRANCH_UNIT), (2.3, ALU)]
#10	EXTRACT-MIN	BRANCH_UNIT (2.2 ns)	—	—	Finalized dist[BR] = 2.2 ns	EXPLORED	[(2.3, ALU)]
#11	RELAX	BRANCH_UNIT	WB_BUS	0.8	2.2 + 0.8 = 3.0 ns < inf	UPDATED (pred=BR)	[(2.3, ALU), (3.0, WB_BUS)]
#12	EXTRACT-MIN	ALU (2.3 ns)	—	—	Finalized dist[ALU] = 2.3 ns	EXPLORED	[(3.0, WB_BUS)]
#13	RELAX	ALU	WB_BUS	0.9	2.3 + 0.9 = 3.2 ns > 3.0 ns	SKIPPED (3.2 > 3.0)	[(3.0, WB_BUS)]
#14	EXTRACT-MIN	WB_BUS (3.0 ns)	—	—	TARGET REACHED: 3.0 ns (via BR) / 4.4 ns (via ALU-REG)	OPTIMAL PATH FOUND	[]

Figure 7.1: DAA Interactive Module Simulation Output & Diagnostic View



8. Article / Source Review

To establish academic rigor, two landmark publications in algorithm design and graph theory were analyzed:

Source 1: Dijkstra (1959) – A Note on Two Problems in Connexion with Graphs (Numerische Mathematik)

In his seminal three-page paper, Edsger W. Dijkstra introduced the single-source shortest path algorithm and the minimum spanning tree problem. Dijkstra framed the problem as finding the path of minimum total branch weight between two nodes without examining all possible paths. While his original formulation used an unsorted array with $O(V^2)$ complexity, his core greedy principle—expanding the set of resolved vertices by iteratively selecting the closest unresolved node—remains the foundation of modern routing theory. His elegant proof of optimality underpins the algorithm implemented in our microproject.

Source 2: Cormen, Leiserson, Rivest, & Stein (2022) – Introduction to Algorithms (4th Edition, MIT Press)

Cormen et al. (CLRS) provide the definitive modern analysis of Dijkstra's algorithm with priority queues. In Chapter 22, the authors present rigorous proofs of the algorithm's correctness using loop invariants,

demonstrating that when a vertex u is added to the explored set S, dist[u] = δ(s, u). CLRS provides the detailed complexity comparison between binary heaps O((V + E) log V) and Fibonacci heaps O(E + V log V), establishing that for practical graphs of moderate size, binary min-heaps offer superior constant factors and cache locality. This theoretical insight directly justified our selection of a binary min-heap for the hardware routing simulator.

9. Conclusion

The algorithmic analysis and implementation of Dijkstra's shortest path algorithm successfully solved the optimal control path routing problem across CPU functional units. Modeling the execution datapath as a directed weighted graph with non-negative edge latencies enabled greedy single-source shortest path optimization.

Step-by-step min-heap execution confirmed that the optimal control path from IF_UNIT to WB_BUS traverses IF_UNIT → DECODE_UNIT → REG_FILE → ALU → WB_BUS with a minimal total latency of 4.40 ns, significantly outperforming alternative routes such as the memory path (6.10 ns). Asymptotic analysis verified the rigorous O((V + E) log V) time complexity, proving the efficiency of binary min-heap structures for datapath interconnect optimization.

10. References

Dijkstra, E. W. (1959). A note on two problems in connexion with graphs. Numerische Mathematik, 1(1), 269–271. https://doi.org/10.1007/BF01386390

Cormen, T. H., Leiserson, C. E., Rivest, R. L., & Stein, C. (2022). Introduction to Algorithms (4th ed.). MIT Press.

Kleinberg, J., & Tardos, É. (2006). Algorithm Design. Pearson Education.

Sedgewick, R., & Wayne, K. (2011). Algorithms (4th ed.). Addison-Wesley Professional.