

Photon Voice

v2.31

Generated by Doxygen 1.8.17

1 Main Page	1
2 Namespace Documentation	3
2.1 Photon Namespace Reference	3
2.2 Photon.Voice Namespace Reference	3
2.2.1 Enumeration Type Documentation	6
2.2.1.1 AudioSampleType	6
2.2.1.2 Codec	6
2.3 Photon.Voice.IOS Namespace Reference	6
2.3.1 Enumeration Type Documentation	6
2.3.1.1 AudioSessionCategory	6
2.3.1.2 AudioSessionCategoryOption	7
2.3.1.3 AudioSessionMode	8
2.4 Photon.Voice.PUN Namespace Reference	9
2.5 Photon.Voice.PUN.UtilityScripts Namespace Reference	9
2.6 Photon.Voice.Unity Namespace Reference	9
2.7 Photon.Voice.Unity.UtilityScripts Namespace Reference	10
2.8 POpusCodec Namespace Reference	11
2.9 POpusCodec.Enums Namespace Reference	11
2.9.1 Enumeration Type Documentation	11
2.9.1.1 Bandwidth	11
2.9.1.2 Channels	11
2.9.1.3 Delay	12
2.9.1.4 OpusApplicationType	12
2.9.1.5 SignalHint	12
3 Class Documentation	15
3.1 AndroidAudioInAEC Class Reference	15
3.2 AndroidAudioInParameters Class Reference	15
3.3 AudioChangesHandler Class Reference	15
3.3.1 Detailed Description	16
3.3.2 Member Data Documentation	16
3.3.2.1 HandleConfigChange	16
3.3.2.2 HandleDeviceChange	16
3.3.2.3 StartWhenDeviceChange	17
3.3.2.4 UseNativePluginChangeNotifier	17
3.3.2.5 UseOnAudioConfigurationChanged	17
3.4 AudioClipWrapper Class Reference	17
3.5 AudioDesc Class Reference	18
3.6 AudioInChangeNotifierNotSupported Class Reference	18
3.7 AudioInEnumerator Class Reference	18
3.8 AudioInEnumeratorEx Class Reference	19
3.9 AudioOutCapture Class Reference	19

3.10 AudioOutDelayControl Class Reference	19
3.11 AudioOutDelayControl Class Reference	19
3.12 AudioSessionParameters Struct Reference	20
3.13 AudioSessionParametersPresets Class Reference	20
3.13.1 Member Data Documentation	20
3.13.1.1 Game	20
3.13.1.2 VoIP	20
3.14 AudioSyncBuffer< T > Class Template Reference	21
3.15 AudioUtil Class Reference	21
3.15.1 Detailed Description	22
3.15.2 Member Function Documentation	22
3.15.2.1 Convert() [1/2]	22
3.15.2.2 Convert() [2/2]	23
3.15.2.3 ForceToStereo< T >()	23
3.15.2.4 Resample< T >()	23
3.15.2.5 ResampleAndConvert() [1/2]	24
3.15.2.6 ResampleAndConvert() [2/2]	24
3.16 BufferedReaderPushAdapter< T > Class Template Reference	25
3.16.1 Detailed Description	25
3.16.2 Constructor & Destructor Documentation	25
3.16.2.1 BufferedReaderPushAdapter()	25
3.16.3 Member Function Documentation	26
3.16.3.1 Service()	26
3.17 BufferedReaderPushAdapterAsyncPool< T > Class Template Reference	26
3.17.1 Detailed Description	26
3.17.2 Constructor & Destructor Documentation	26
3.17.2.1 BufferedReaderPushAdapterAsyncPool()	26
3.17.3 Member Function Documentation	27
3.17.3.1 Service()	27
3.18 BufferedReaderPushAdapterAsyncPoolCopy< T > Class Template Reference	27
3.18.1 Detailed Description	28
3.18.2 Constructor & Destructor Documentation	28
3.18.2.1 BufferedReaderPushAdapterAsyncPoolCopy()	28
3.18.3 Member Function Documentation	28
3.18.3.1 Service()	28
3.19 BufferedReaderPushAdapterAsyncPoolFloatToShort Class Reference	29
3.19.1 Detailed Description	29
3.19.2 Constructor & Destructor Documentation	29
3.19.2.1 BufferedReaderPushAdapterAsyncPoolFloatToShort()	29
3.19.3 Member Function Documentation	29
3.19.3.1 Service()	30
3.20 BufferedReaderPushAdapterAsyncPoolShortToFloat Class Reference	30

3.20.1 Detailed Description	30
3.20.2 Constructor & Destructor Documentation	30
3.20.2.1 BufferReaderPushAdapterAsyncPoolShortToFloat()	30
3.20.3 Member Function Documentation	31
3.20.3.1 Service()	31
3.21 BufferReaderPushAdapterBase< T > Class Template Reference	31
3.21.1 Detailed Description	32
3.21.2 Constructor & Destructor Documentation	32
3.21.2.1 BufferReaderPushAdapterBase()	32
3.21.3 Member Function Documentation	32
3.21.3.1 Dispose()	32
3.21.3.2 Service()	32
3.22 ConnectAndJoin Class Reference	33
3.23 VoiceClient.CreateOptions Struct Reference	33
3.23.1 Member Data Documentation	34
3.23.1.1 Default	34
3.24 OpusCodec.Decoder< T > Class Template Reference	34
3.24.1 Member Function Documentation	34
3.24.1.1 Input()	34
3.24.1.2 Open()	35
3.25 RawCodec.Decoder< T > Class Template Reference	36
3.25.1 Member Function Documentation	36
3.25.1.1 Input()	36
3.25.1.2 Open()	36
3.26 OpusCodec.DecoderFactory Class Reference	37
3.27 DeviceEnumeratorBase Class Reference	37
3.28 DeviceInfo Struct Reference	37
3.29 OpusCodec.Encoder< T > Class Template Reference	38
3.30 RawCodec.Encoder< T > Class Template Reference	39
3.31 OpusCodec.EncoderFloat Class Reference	39
3.32 OpusCodec.EncoderShort Class Reference	39
3.33 OpusCodec.Factory Class Reference	39
3.34 FactoryPrimitiveArrayPool< T > Class Template Reference	40
3.34.1 Detailed Description	40
3.35 FactoryReusableArray< T > Class Template Reference	40
3.35.1 Detailed Description	41
3.36 Flip Struct Reference	41
3.37 FrameBuffer Struct Reference	41
3.38 FrameOut< T > Class Template Reference	42
3.39 Framers< T > Class Template Reference	42
3.39.1 Detailed Description	43
3.39.2 Constructor & Destructor Documentation	43

3.39.2.1 Framer()	43
3.39.3 Member Function Documentation	43
3.39.3.1 Count()	43
3.39.3.2 Frame()	43
3.40 IAudioDesc Interface Reference	44
3.40.1 Detailed Description	44
3.40.2 Property Documentation	44
3.40.2.1 Channels	44
3.40.2.2 Error	44
3.40.2.3 SamplingRate	45
3.41 IAudioInChangeNotifier Interface Reference	45
3.42 IAudioOut< T > Interface Template Reference	45
3.43 IAudioPusher< T > Interface Template Reference	45
3.43.1 Detailed Description	46
3.43.2 Member Function Documentation	46
3.43.2.1 SetCallback()	46
3.44 IAudioReader< T > Interface Template Reference	46
3.44.1 Detailed Description	46
3.45 IDataReader< T > Interface Template Reference	47
3.45.1 Detailed Description	47
3.45.2 Member Function Documentation	47
3.45.2.1 Read()	47
3.46 IDecoder Interface Reference	47
3.46.1 Detailed Description	48
3.46.2 Member Function Documentation	48
3.46.2.1 Input()	48
3.46.2.2 Open()	48
3.46.3 Property Documentation	49
3.46.3.1 Error	49
3.47 IDecoderDirect< B > Interface Template Reference	49
3.47.1 Detailed Description	49
3.47.2 Property Documentation	49
3.47.2.1 Output	49
3.48 IDeviceEnumerator Interface Reference	49
3.49 IEncoder Interface Reference	50
3.49.1 Detailed Description	50
3.49.2 Member Function Documentation	50
3.49.2.1 DequeueOutput()	51
3.49.2.2 EndOfStream()	51
3.49.2.3 GetPlatformAPI< I >()	51
3.49.3 Property Documentation	51
3.49.3.1 Error	51

3.49.3.2 Output	51
3.50 IEncoderDirect< B > Interface Template Reference	52
3.50.1 Detailed Description	52
3.50.2 Member Function Documentation	52
3.50.2.1 Input()	52
3.51 IEncoderDirectImage Interface Reference	52
3.51.1 Detailed Description	53
3.51.2 Property Documentation	53
3.51.2.1 ImageFormat	53
3.52 AudioUtil.ILevelMeter Interface Reference	53
3.52.1 Detailed Description	53
3.52.2 Member Function Documentation	53
3.52.2.1 ResetAccumAvgPeakAmp()	54
3.52.3 Property Documentation	54
3.52.3.1 AccumAvgPeakAmp	54
3.52.3.2 CurrentAvgAmp	54
3.52.3.3 CurrentPeakAmp	54
3.53 ILocalVoiceAudio Interface Reference	54
3.53.1 Detailed Description	55
3.53.2 Member Function Documentation	55
3.53.2.1 VoiceDetectorCalibrate()	55
3.53.3 Property Documentation	55
3.53.3.1 LevelMeter	55
3.53.3.2 VoiceDetector	56
3.53.3.3 VoiceDetectorCalibrating	56
3.54 ILoggable Interface Reference	56
3.55 ILoggableDependent Interface Reference	56
3.56 ILogger Interface Reference	56
3.57 ImageBufferInfo Struct Reference	57
3.58 ImageBufferNative Class Reference	57
3.59 ImageBufferNativeAlloc Class Reference	57
3.60 ImageBufferNativeGCHandleSinglePlane Class Reference	58
3.61 ImageBufferNativePool< T > Class Template Reference	58
3.62 IProcessor< T > Interface Template Reference	58
3.62.1 Detailed Description	59
3.62.2 Member Function Documentation	59
3.62.2.1 Process()	59
3.63 IResettable Interface Reference	59
3.64 IServiceable Interface Reference	59
3.64.1 Detailed Description	60
3.64.2 Member Function Documentation	60
3.64.2.1 Service()	60

3.65 AudioUtil.IVoiceDetector Interface Reference	60
3.65.1 Detailed Description	61
3.65.2 Property Documentation	61
3.65.2.1 ActivityDelayMs	61
3.65.2.2 Detected	61
3.65.2.3 DetectedTime	61
3.65.2.4 On	61
3.65.2.5 Threshold	61
3.65.3 Event Documentation	62
3.65.3.1 OnDetected	62
3.66 IVoiceTransport Interface Reference	62
3.67 AudioUtil.LevelMeter< T > Class Template Reference	62
3.67.1 Detailed Description	63
3.67.2 Member Function Documentation	63
3.67.2.1 Process()	63
3.67.2.2 ResetAccumAvgPeakAmp()	63
3.68 AudioUtil.LevelMeterDummy Class Reference	63
3.68.1 Detailed Description	64
3.68.2 Member Function Documentation	64
3.68.2.1 ResetAccumAvgPeakAmp()	64
3.69 AudioUtil.LevelMeterFloat Class Reference	64
3.69.1 Detailed Description	64
3.69.2 Constructor & Destructor Documentation	65
3.69.2.1 LevelMeterFloat()	65
3.70 AudioUtil.LevelMeterShort Class Reference	66
3.70.1 Detailed Description	66
3.70.2 Constructor & Destructor Documentation	66
3.70.2.1 LevelMeterShort()	66
3.71 LoadBalancingFrontend Class Reference	67
3.72 LoadBalancingTransport Class Reference	67
3.72.1 Detailed Description	68
3.72.2 Constructor & Destructor Documentation	68
3.72.2.1 LoadBalancingTransport()	68
3.72.3 Member Function Documentation	68
3.72.3.1 Dispose()	68
3.72.3.2 Service()	69
3.72.4 Property Documentation	69
3.72.4.1 GlobalInterestGroup	69
3.72.4.2 VoiceClient	69
3.73 LoadBalancingTransport2 Class Reference	69
3.73.1 Detailed Description	70
3.74 LocalVoice Class Reference	70

3.74.1 Detailed Description	71
3.74.2 Member Function Documentation	71
3.74.2.1 RemoveSelf()	71
3.74.3 Property Documentation	72
3.74.3.1 DebugEchoMode	72
3.74.3.2 Encrypt	72
3.74.3.3 FramesSent	72
3.74.3.4 FramesSentBytes	72
3.74.3.5 Info	72
3.74.3.6 InterestGroup	73
3.74.3.7 IsCurrentlyTransmitting	73
3.74.3.8 LocalUserServiceable	73
3.74.3.9 Reliable	73
3.74.3.10 SendSpacingProfileMax	73
3.74.3.11 TransmitEnabled	73
3.75 LocalVoiceAudio< T > Class Template Reference	74
3.75.1 Detailed Description	74
3.75.2 Member Function Documentation	74
3.75.2.1 Create()	75
3.75.2.2 VoiceDetectorCalibrate()	75
3.75.3 Property Documentation	75
3.75.3.1 VoiceDetectorCalibrating	76
3.76 LocalVoiceAudioDummy Class Reference	76
3.76.1 Detailed Description	76
3.76.2 Member Function Documentation	76
3.76.2.1 VoiceDetectorCalibrate()	76
3.76.3 Member Data Documentation	77
3.76.3.1 Dummy	77
3.77 LocalVoiceAudioFloat Class Reference	77
3.77.1 Detailed Description	77
3.78 LocalVoiceAudioShort Class Reference	77
3.78.1 Detailed Description	77
3.79 LocalVoiceFramed< T > Class Template Reference	78
3.79.1 Detailed Description	78
3.79.2 Member Function Documentation	78
3.79.2.1 AddPostProcessor()	78
3.79.2.2 AddPreProcessor()	79
3.79.2.3 ClearProcessors()	79
3.79.2.4 Dispose()	79
3.79.2.5 PushData()	79
3.79.2.6 PushDataAsync()	80
3.79.3 Property Documentation	80

3.79.3.1 PushDataAsyncReady	80
3.80 LocalVoiceFramedBase Class Reference	80
3.80.1 Detailed Description	80
3.80.2 Property Documentation	80
3.80.2.1 FrameSize	81
3.81 Logger Class Reference	81
3.82 MicAmplifier Class Reference	81
3.83 MicAmplifierFloat Class Reference	81
3.84 MicAmplifierShort Class Reference	82
3.85 MicrophonePermission Class Reference	82
3.85.1 Detailed Description	82
3.86 MicWrapper Class Reference	83
3.87 MicWrapperPusher Class Reference	83
3.88 NativeAndroidMicrophoneSettings Struct Reference	83
3.89 ObjectFactory< TType, TInfo > Interface Template Reference	84
3.89.1 Detailed Description	84
3.90 ObjectPool< TType, TInfo > Class Template Reference	84
3.90.1 Detailed Description	85
3.90.2 Constructor & Destructor Documentation	85
3.90.2.1 ObjectPool() [1/2]	85
3.90.2.2 ObjectPool() [2/2]	86
3.90.3 Member Function Documentation	86
3.90.3.1 AcquireOrCreate() [1/2]	86
3.90.3.2 AcquireOrCreate() [2/2]	86
3.90.3.3 Dispose()	87
3.90.3.4 Init()	87
3.90.3.5 Release() [1/2]	87
3.90.3.6 Release() [2/2]	87
3.90.4 Property Documentation	88
3.90.4.1 Info	88
3.91 OpusCodec Class Reference	88
3.92 OpusDecoder< T > Class Template Reference	88
3.93 OpusEncoder Class Reference	89
3.93.1 Property Documentation	89
3.93.1.1 EncoderDelay	89
3.94 OpusException Class Reference	90
3.95 OpusLib Class Reference	90
3.96 PhotonVoiceCreatedParams Class Reference	90
3.97 Recorder.PhotonVoiceCreatedParams Class Reference	90
3.98 PhotonVoiceLagSimulationGui Class Reference	90
3.99 PhotonVoiceNetwork Class Reference	91
3.99.1 Detailed Description	92

3.99.2 Member Function Documentation	92
3.99.2.1 ConnectAndJoinRoom()	92
3.99.2.2 Disconnect()	92
3.99.3 Member Data Documentation	92
3.99.3.1 AutoConnectAndJoin	92
3.99.3.2 AutoLeaveAndDisconnect	93
3.99.3.3 VoiceRoomNameSuffix	93
3.99.3.4 WorkInOfflineMode	93
3.99.4 Property Documentation	93
3.99.4.1 Instance	93
3.99.4.2 UsePunAuthValues	93
3.100 PhotonVoiceStatsGui Class Reference	93
3.100.1 Detailed Description	94
3.101 PhotonVoiceView Class Reference	94
3.101.1 Detailed Description	95
3.101.2 Member Function Documentation	95
3.101.2.1 Init()	95
3.101.3 Member Data Documentation	95
3.101.3.1 AutoCreateRecorderIfNotFound	95
3.101.3.2 SetupDebugSpeaker	95
3.101.3.3 UsePrimaryRecorder	95
3.101.4 Property Documentation	96
3.101.4.1 IsPhotonViewReady	96
3.101.4.2 IsRecorder	96
3.101.4.3 IsRecording	96
3.101.4.4 IsSetup	96
3.101.4.5 IsSpeaker	96
3.101.4.6 IsSpeakerLinked	97
3.101.4.7 IsSpeaking	97
3.101.4.8 RecorderInUse	97
3.101.4.9 SpeakerInUse	97
3.102 ImageBufferNative.PlaneSet Struct Reference	97
3.103 Platform Class Reference	98
3.104 PlaybackDelaySettings Struct Reference	98
3.104.1 Detailed Description	98
3.104.2 Member Data Documentation	98
3.104.2.1 MaxDelayHard	99
3.104.2.2 MaxDelaySoft	99
3.104.2.3 MinDelaySoft	99
3.105 AudioOutDelayControl.PlayDelayConfig Class Reference	99
3.106 PrimitiveArrayPool< T > Class Template Reference	99
3.106.1 Detailed Description	99

3.107 RawCodec Class Reference	100
3.108 Recorder Class Reference	100
3.108.1 Detailed Description	103
3.108.2 Member Function Documentation	103
3.108.2.1 Init()	103
3.108.2.2 ResetLocalAudio()	103
3.108.2.3 RestartRecording()	103
3.108.2.4 StartRecording()	104
3.108.2.5 StopRecording()	104
3.108.2.6 VoiceDetectorCalibrate()	104
3.108.3 Property Documentation	104
3.108.3.1 AudioClip	104
3.108.3.2 AudioGroup	105
3.108.3.3 AutoStart	105
3.108.3.4 Bitrate	105
3.108.3.5 DebugEchoMode	105
3.108.3.6 Encrypt	105
3.108.3.7 FrameDuration	105
3.108.3.8 InputFactory	106
3.108.3.9 InterestGroup	106
3.108.3.10 IsCurrentlyTransmitting	106
3.108.3.11 IsInitialized	106
3.108.3.12 IsRecording	106
3.108.3.13 LevelMeter	106
3.108.3.14 LoopAudioClip	107
3.108.3.15 MicrophoneType	107
3.108.3.16 PhotonMicrophoneDeviceId	107
3.108.3.17 PhotonMicrophoneEnumerator	107
3.108.3.18 ReactOnSystemChanges	107
3.108.3.19 RecordOnlyWhenEnabled	107
3.108.3.20 RecordOnlyWhenJoined	108
3.108.3.21 ReliableMode	108
3.108.3.22 RequiresRestart	108
3.108.3.23 SamplingRate	108
3.108.3.24 SkipDeviceChangeChecks	108
3.108.3.25 SourceType	108
3.108.3.26 StopRecordingWhenPaused	109
3.108.3.27 TransmitEnabled	109
3.108.3.28 TrySamplingRateMatch	109
3.108.3.29 TypeConvert	109
3.108.3.30 UnityMicrophoneDevice	109
3.108.3.31 UseMicrophoneTypeFallback	109

3.108.3.32 UseOnAudioFilterRead	110
3.108.3.33 UserData	110
3.108.3.34 VoiceDetection	110
3.108.3.35 VoiceDetectionDelayMs	110
3.108.3.36 VoiceDetectionThreshold	110
3.108.3.37 VoiceDetector	110
3.108.3.38 VoiceDetectorCalibrating	111
3.109 RemoteVoiceInfo Class Reference	111
3.109.1 Detailed Description	111
3.109.2 Property Documentation	111
3.109.2.1 ChannelId	111
3.109.2.2 Info	111
3.109.2.3 PlayerId	112
3.109.2.4 VoiceId	112
3.110 RemoteVoiceLink Class Reference	112
3.111 RemoteVoiceOptions Struct Reference	112
3.111.1 Detailed Description	113
3.111.2 Member Function Documentation	113
3.111.2.1 SetOutput() [1/2]	113
3.111.2.2 SetOutput() [2/2]	113
3.111.3 Property Documentation	113
3.111.3.1 Decoder	114
3.111.3.2 OnRemoteVoiceRemoveAction	114
3.112 AudioUtil.Resampler< T > Class Template Reference	114
3.112.1 Detailed Description	114
3.112.2 Constructor & Destructor Documentation	114
3.112.2.1 Resampler()	114
3.112.3 Member Function Documentation	115
3.112.3.1 Process()	115
3.113 SaveIncomingStreamToFile Class Reference	115
3.114 SaveOutgoingStreamToFile Class Reference	115
3.115 RawCodec.ShortToFloat Class Reference	116
3.116 Speaker Class Reference	116
3.116.1 Detailed Description	117
3.116.2 Member Function Documentation	117
3.116.2.1 RestartPlayback()	117
3.116.2.2 SetPlaybackDelaySettings() [1/2]	117
3.116.2.3 SetPlaybackDelaySettings() [2/2]	118
3.116.2.4 StartPlayback()	118
3.116.2.5 StopPlayback()	118
3.116.3 Member Data Documentation	119
3.116.3.1 CustomAudioOutFactory	119

3.116.4 Property Documentation	119
3.116.4.1 Actor	119
3.116.4.2 IsLinked	119
3.116.4.3 IsPlaying	119
3.116.4.4 Lag	119
3.116.4.5 OnRemoteVoiceRemoveAction	120
3.116.4.6 PlaybackDelayMaxHard	120
3.116.4.7 PlaybackDelayMaxSoft	120
3.116.4.8 PlaybackDelayMinSoft	120
3.116.4.9 PlaybackOnlyWhenEnabled	120
3.116.4.10 PlaybackStarted	120
3.117 ImageBufferInfo.StrideSet Struct Reference	121
3.118 AudioUtil.TempoUp< T > Class Template Reference	121
3.119 TestTone Class Reference	121
3.120 AudioUtil.ToneAudioPusher< T > Class Template Reference	121
3.120.1 Detailed Description	122
3.120.2 Constructor & Destructor Documentation	122
3.120.2.1 ToneAudioPusher()	122
3.120.3 Member Function Documentation	122
3.120.3.1 SetCallback()	122
3.121 ToneAudioReader Class Reference	123
3.122 AudioUtil.ToneAudioReader< T > Class Template Reference	123
3.122.1 Detailed Description	123
3.122.2 Constructor & Destructor Documentation	124
3.122.2.1 ToneAudioReader()	124
3.122.3 Member Function Documentation	124
3.122.3.1 Read()	124
3.122.4 Property Documentation	124
3.122.4.1 Channels	125
3.122.4.2 Error	125
3.122.4.3 SamplingRate	125
3.123 UnityAudioOut Class Reference	125
3.124 UnityMicrophone Class Reference	126
3.124.1 Detailed Description	126
3.125 UnsupportedCodecException Class Reference	126
3.125.1 Detailed Description	126
3.125.2 Constructor & Destructor Documentation	126
3.125.2.1 UnsupportedCodecException()	126
3.126 UnsupportedPlatformException Class Reference	127
3.126.1 Detailed Description	127
3.126.2 Constructor & Destructor Documentation	127
3.126.2.1 UnsupportedPlatformException()	127

3.127 UnsupportedSampleTypeException Class Reference	128
3.127.1 Detailed Description	128
3.127.2 Constructor & Destructor Documentation	128
3.127.2.1 UnsupportedSampleTypeException()	128
3.128 OpusCodec.Util Class Reference	128
3.129 VoiceClient Class Reference	128
3.129.1 Detailed Description	130
3.129.2 Constructor & Destructor Documentation	130
3.129.2.1 VoiceClient()	130
3.129.3 Member Function Documentation	130
3.129.3.1 CreateLocalVoice()	130
3.129.3.2 CreateLocalVoiceAudioFromSource()	131
3.129.3.3 CreateLocalVoiceFramed< T >()	131
3.129.3.4 LocalVoicesInChannel()	132
3.129.3.5 RemoteVoiceInfoDelegate()	132
3.129.3.6 RemoveLocalVoice()	132
3.129.3.7 Service()	133
3.129.4 Property Documentation	133
3.129.4.1 DebugLostPercent	133
3.129.4.2 FramesLost	133
3.129.4.3 FramesReceived	133
3.129.4.4 FramesSent	133
3.129.4.5 FramesSentBytes	134
3.129.4.6 LocalVoices	134
3.129.4.7 OnRemoteVoiceInfoAction	134
3.129.4.8 RemoteVoiceInfos	134
3.129.4.9 RoundTripTime	134
3.129.4.10 RoundTripTimeVariance	134
3.129.4.11 SuppressInfoDuplicateWarning	135
3.130 VoiceComponent Class Reference	135
3.131 VoiceConnection Class Reference	135
3.131.1 Detailed Description	137
3.131.2 Member Function Documentation	137
3.131.2.1 ConnectUsingSettings()	137
3.131.2.2 Dispatch()	138
3.131.2.3 InitRecorder()	138
3.131.2.4 SetGlobalPlaybackDelaySettings()	138
3.131.2.5 SetPlaybackDelaySettings()	139
3.131.2.6 TryLateLinkingUsingUserData()	139
3.131.3 Member Data Documentation	139
3.131.3.1 AutoCreateSpeakerIfNotFound	139
3.131.3.2 MaxDatagrams	139

3.131.3.3 MinimalTimeScaleToDispatchInFixedUpdate	140
3.131.3.4 SendAsap	140
3.131.3.5 Settings	140
3.131.3.6 SpeakerFactory	140
3.131.4 Property Documentation	140
3.131.4.1 BestRegionSummaryInPreferences	140
3.131.4.2 ClientState	141
3.131.4.3 FramesLostPercent	141
3.131.4.4 FramesLostPerSecond	141
3.131.4.5 FramesReceivedPerSecond	141
3.131.4.6 GlobalPlaybackDelayMaxHard	141
3.131.4.7 GlobalPlaybackDelayMaxSoft	141
3.131.4.8 GlobalPlaybackDelayMinSoft	142
3.131.4.9 Logger	142
3.131.4.10 LogLevel	142
3.131.4.11 PrimaryRecorder	142
3.131.4.12 SpeakerPrefab	142
3.131.4.13 VoiceClient	142
3.131.5 Event Documentation	143
3.131.5.1 RemoteVoiceAdded	143
3.131.5.2 SpeakerLinked	143
3.132 VoiceDebugScript Class Reference	143
3.132.1 Detailed Description	144
3.132.2 Member Data Documentation	144
3.132.2.1 DisableVad	144
3.132.2.2 ForceRecordingAndTransmission	144
3.132.2.3 IncreaseLogLevels	144
3.132.2.4 LocalDebug	144
3.132.2.5 TestAudioClip	144
3.132.2.6 TestUsingAudioClip	145
3.133 AudioUtil.VoiceDetector< T > Class Template Reference	145
3.133.1 Detailed Description	146
3.133.2 Member Function Documentation	146
3.133.2.1 Process()	146
3.133.3 Property Documentation	146
3.133.3.1 ActivityDelayMs	146
3.133.3.2 Detected	146
3.133.3.3 DetectedTime	147
3.133.3.4 On	147
3.133.3.5 Threshold	147
3.133.4 Event Documentation	147
3.133.4.1 OnDetected	147

3.134 AudioUtil.VoiceDetectorCalibration< T > Class Template Reference	147
3.134.1 Detailed Description	148
3.134.2 Constructor & Destructor Documentation	148
3.134.2.1 VoiceDetectorCalibration()	148
3.134.3 Member Function Documentation	148
3.134.3.1 Calibrate()	148
3.134.3.2 Process()	149
3.135 AudioUtil.VoiceDetectorDummy Class Reference	149
3.135.1 Detailed Description	149
3.136 AudioUtil.VoiceDetectorFloat Class Reference	150
3.136.1 Detailed Description	150
3.136.2 Constructor & Destructor Documentation	150
3.136.2.1 VoiceDetectorFloat()	150
3.137 AudioUtil.VoiceDetectorShort Class Reference	150
3.137.1 Detailed Description	151
3.137.2 Constructor & Destructor Documentation	151
3.137.2.1 VoiceDetectorShort()	151
3.138 VoiceEvent Class Reference	151
3.138.1 Member Data Documentation	151
3.138.1.1 Code	151
3.139 VoiceInfo Struct Reference	152
3.139.1 Detailed Description	152
3.139.2 Member Function Documentation	153
3.139.2.1 CreateAudio()	153
3.139.2.2 CreateAudioOpus()	153
3.139.3 Property Documentation	154
3.139.3.1 Bitrate	154
3.139.3.2 Channels	154
3.139.3.3 FPS	154
3.139.3.4 FrameDurationSamples	154
3.139.3.5 FrameDurationUs	154
3.139.3.6 FrameSize	155
3.139.3.7 Height	155
3.139.3.8 KeyFrameInt	155
3.139.3.9 SamplingRate	155
3.139.3.10 UserData	155
3.139.3.11 Width	155
3.140 AudioUtil.VoiceLevelDetectCalibrate< T > Class Template Reference	156
3.140.1 Detailed Description	156
3.140.2 Constructor & Destructor Documentation	156
3.140.2.1 VoiceLevelDetectCalibrate()	156
3.140.3 Member Function Documentation	157

3.140.3.1 Calibrate()	157
3.140.3.2 Process()	157
3.140.4 Property Documentation	157
3.140.4.1 LevelMeter	157
3.140.4.2 VoiceDetector	158
3.141 VoiceLogger Class Reference	158
3.142 WebRtcAudioDsp Class Reference	158
3.142.1 Member Function Documentation	159
3.142.1.1 SetOrSwitchAudioListener()	159
3.142.1.2 SetOrSwitchAudioOutCapture()	159
3.143 WebRTCAudioLib Class Reference	160
3.144 WebRTCAudioProcessor Class Reference	160
Index	163

Chapter 1

Main Page

Photon Voice 2 has three key classes:

- `Photon.Voice.Unity.VoiceConnection` (extends `Photon.Realtime.ConnectionHandler`)
- `Photon.Voice.Unity.Recorder`
- `Photon.Voice.Unity.Speaker`

If you also use the integration with PUN 2, we added two components for ease-of-use and more convenience:

- `Photon.Voice.PUN.PhotonVoiceNetwork`
- `Photon.Voice.PUN.PhotonVoiceView`

Photon Voice 2 also comes with a WebRTC based DSP (`Photon.Voice.Unity.WebRtcAudioDsp` using `Photon.Voice.WebRTCAudioProcessor`).

Read more in the official documentation [here](#).

You can download Photon Voice 2 [here](#).

Chapter 2

Namespace Documentation

2.1 Photon Namespace Reference

2.2 Photon.Voice Namespace Reference

Classes

- class [AudioDesc](#)
- class [AudioInChangeNotifierNotSupported](#)
- class **AudioInEnumeratorNotSupported**
- class [AudioOutDelayControl](#)
- class [AudioSyncBuffer](#)
- class [AudioUtil](#)
Collection of Audio Utility functions and classes.
- class [BufferReaderPushAdapter](#)
Simple [BufferReaderPushAdapterBase<T>](#) implementation using a single buffer and synchronous [LocalVoiceFramed<T>.PushData](#)
- class [BufferReaderPushAdapterAsyncPool](#)
[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).
- class [BufferReaderPushAdapterAsyncPoolCopy](#)
[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync\(T\[\]\)](#) and data copy.
- class [BufferReaderPushAdapterAsyncPoolFloatToShort](#)
[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting float samples to short.
- class [BufferReaderPushAdapterAsyncPoolShortToFloat](#)
[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.
- class [BufferReaderPushAdapterBase](#)
Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).
- class [DeviceEnumeratorBase](#)
- class **DeviceEnumeratorNotSupported**
- struct [DeviceInfo](#)
- class [FactoryPrimitiveArrayPool](#)
[PrimitiveArrayPool<T>](#) as wrapped in object factory interface.
- class [FactoryReusableArray](#)

Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.

- struct [Flip](#)
- struct [FrameBuffer](#)
- class [FrameOut](#)
- class [Framer](#)

Utility class to re-frame audio packets.

- interface [IAudioDesc](#)
- interface [IAudioInChangeNotifier](#)
- interface [IAudioOut](#)
- interface [IAudioPusher](#)

Audio Pusher interface.

- interface [IAudioReader](#)

Audio Reader interface.

- interface [IDataReader](#)

Interface for pulling data, in case this is more appropriate than pushing it.

- interface [IDecoder](#)

Generic decoder interface.

- interface [IDecoderDirect](#)

Interface for an decoder which outputs data via explicit call.

- interface [IDeviceEnumerator](#)
- interface [IEncoder](#)

Generic encoder interface.

- interface [IEncoderDirect](#)

Interface for an encoder which consumes input data via explicit call.

- interface [IEncoderDirectImage](#)

Interface for an encoder which consumes images via explicit call.

- interface [ILocalVoiceAudio](#)

Interface for an outgoing audio stream.

- interface [ILogger](#)
- struct [ImageBufferInfo](#)
- class [ImageBufferNative](#)
- class [ImageBufferNativeAlloc](#)
- class [ImageBufferNativeGCHandleSinglePlane](#)
- class [ImageBufferNativePool](#)
- interface [IProcessor](#)

Audio Processor interface.

- interface [IResettable](#)
- interface [IServiceable](#)

Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).

- interface [IVoiceTransport](#)
- class [LoadBalancingFrontend](#)
- class [LoadBalancingTransport](#)

Extends [LoadBalancingClient](#) with media streaming functionality.

- class [LoadBalancingTransport2](#)

Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.

- class [LocalVoice](#)

Represents outgoing data stream.

- class [LocalVoiceAudio](#)

Outgoing audio stream.

- class [LocalVoiceAudioDummy](#)

- Dummy [LocalVoiceAudio](#)
- class [LocalVoiceAudioFloat](#)
 - Specialization of [LocalVoiceAudio<T>](#) for float audio
- class [LocalVoiceAudioShort](#)
 - Specialization of [LocalVoiceAudio<T>](#) for short audio
- class [LocalVoiceFramed](#)
 - Typed re-framing [LocalVoice](#)
- class [LocalVoiceFramedBase](#)
 - Typed re-framing [LocalVoice](#)
- interface [ObjectFactory](#)
 - Uniform interface to [ObjectPool<TType, TInfo>](#) and single reusable object.
- class [ObjectPool](#)
 - Generic Pool to re-use objects of a certain type (TType) that optionally match a certain property or set of properties (TInfo).
- class [OpusCodec](#)
- class **PhotonTransportProtocol**
- class [Platform](#)
- class [PrimitiveArrayPool](#)
 - Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.
- class [RawCodec](#)
- class **RemoteVoice**
- class [RemoteVoiceInfo](#)
 - Information about a remote voice (incoming stream).
- struct [RemoteVoiceOptions](#)
 - Event Actions and other options for a remote voice (incoming stream).
- class **SpacingProfile**
- class [UnsupportedCodecException](#)
 - Exception thrown if an unsupported codec is encountered.
- class [UnsupportedPlatformException](#)
 - Exception thrown if an unsupported platform is encountered.
- class [UnsupportedSampleTypeException](#)
 - Exception thrown if an unsupported audio sample type is encountered.
- class **Util**
- class **VideoInEnumeratorNotSupported**
- class [VoiceClient](#)
 - [Voice](#) client interact with other clients on network via [IVoiceTransport](#).
- class [VoiceEvent](#)
- struct [VoiceInfo](#)
 - Describes stream properties.
- class [WebRTCAudioLib](#)
- class [WebRTCAudioProcessor](#)

Enumerations

- enum [AudioSampleType](#)
 - The type of samples used for audio processing.
- enum **FrameFlags** : byte
- enum [Codec](#)
 - Enum for Media Codecs supported by PhotonVoice.
- enum **ImageFormat**
- enum **Rotation**

2.2.1 Enumeration Type Documentation

2.2.1.1 AudioSampleType

```
enum AudioSampleType [strong]
```

The type of samples used for audio processing.

2.2.1.2 Codec

```
enum Codec [strong]
```

Enum for Media Codecs supported by PhotonVoice.

Transmitted in [VoiceInfo](#). Do not change the values of this Enum!

Enumerator

AudioOpus	OPUS audio
-----------	------------

2.3 Photon.Voice.IOS Namespace Reference

Classes

- struct [AudioSessionParameters](#)
- class [AudioSessionParametersPresets](#)

Enumerations

- enum [AudioSessionCategory](#)
- enum [AudioSessionMode](#)
- enum [AudioSessionCategoryOption](#)

2.3.1 Enumeration Type Documentation

2.3.1.1 AudioSessionCategory

```
enum AudioSessionCategory [strong]
```


Enumerator

Ambient	Use this category for background sounds such as rain, car engine noise, etc. Mixes with other music. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
SoloAmbient	Use this category for background sounds. Other music will stop playing. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Playback	Use this category for music tracks. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Record	Use this category when recording audio. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
PlayAndRecord	Use this category when recording and playing back audio. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
AudioProcessing	Use this category when using a hardware codec or signal processor while not playing or recording audio. API_DEPRECATED("No longer supported", ios(3.0, 10.0)) API_UNAVAILABLE(watchos, tvos) API_UNAVAILABLE(macos);
MultiRoute	Use this category to customize the usage of available audio accessories and built-in audio hardware. For example, this category provides an application with the ability to use an available USB output and headphone output simultaneously for separate, distinct streams of audio data. Use of this category by an application requires a more detailed knowledge of, and interaction with, the capabilities of the available audio routes. May be used for input, output, or both. Note that not all output types and output combinations are eligible for multi-route. Input is limited to the last-in input port. Eligible inputs consist of the following: AVAudioSessionPortUSBAudio, AVAudioSessionPortHeadsetMic, and AVAudioSessionPortBuiltInMic. Eligible outputs consist of the following: AVAudioSessionPortUSBAudio, AVAudioSessionPortLineOut, AVAudioSessionPortHeadphones, AVAudioSessionPortHDMI, and AVAudioSessionPortBuiltInSpeaker. Note that AVAudioSessionPortBuiltInSpeaker is only allowed to be used when there are no other eligible outputs connected. API_AVAILABLE(ios(6.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);

2.3.1.2 AudioSessionCategoryOption

```
enum AudioSessionCategoryOption [strong]
```

Enumerator

MixWithOthers	This allows an application to set whether or not other active audio apps will be interrupted or mixed with when your app's audio session goes active. The typical cases are: (1) AVAudioSessionCategoryPlayAndRecord or AVAudioSessionCategoryMultiRoute this will default to false, but can be set to true. This would allow other applications to play in the background while an app had both audio input and output enabled (2) AVAudioSessionCategoryPlayback this will default to false, but can be set to true. This would allow other applications to play in the background, but an app will still be able to play regardless of the setting of the ringer switch (3) Other categories this defaults to false and cannot be changed (that is, the mix with others setting of these categories cannot be overridden. An application must be prepared for setting this property to fail as behaviour may change in future releases. If an application changes their category, they should reassert the option (it is not sticky across category changes). MixWithOthers is only valid with AVAudioSessionCategoryPlayAndRecord, AVAudioSessionCategoryPlayback, and AVAudioSessionCategoryMultiRoute
---------------	---

Enumerator

DuckOthers	This allows an application to set whether or not other active audio apps will be ducked when when your app's audio session goes active. An example of this is the Nike app, which provides periodic updates to its user (it reduces the volume of any music currently being played while it provides its status). This defaults to off. Note that the other audio will be ducked for as long as the current session is active. You will need to deactivate your audio session when you want full volume playback of the other audio. If your category is AVAudioSessionCategoryPlayback, AVAudioSessionCategoryPlayAndRecord, or AVAudioSessionCategoryMultiRoute, by default the audio session will be non-mixable and non-ducking. Setting this option will also make your category mixable with others (AVAudioSessionCategoryOptionMixWithOthers will be set). DuckOthers is only valid with AVAudioSessionCategoryAmbient, AVAudioSessionCategoryPlayAndRecord, AVAudioSessionCategoryPlayback, and AVAudioSessionCategoryMultiRoute
AllowBluetooth	This allows an application to change the default behaviour of some audio session categories with regards to showing bluetooth Hands-Free Profile (HFP) devices as available routes. The current category behavior is: (1) AVAudioSessionCategoryPlayAndRecord this will default to false, but can be set to true. This will allow a paired bluetooth HFP device to show up as an available route for input, while playing through the category-appropriate output (2) AVAudioSessionCategoryRecord this will default to false, but can be set to true. This will allow a paired bluetooth HFP device to show up as an available route for input (3) Other categories this defaults to false and cannot be changed (that is, enabling bluetooth for input in these categories is not allowed) An application must be prepared for setting this option to fail as behaviour may change in future releases. If an application changes their category or mode, they should reassert the override (it is not sticky across category and mode changes). AllowBluetooth is only valid with AVAudioSessionCategoryRecord and AVAudioSessionCategoryPlayAndRecord
DefaultToSpeaker	This allows an application to change the default behaviour of some audio session categories with regards to the audio route. The current category behavior is: (1) AVAudioSessionCategoryPlayAndRecord category this will default to false, but can be set to true. this will route to Speaker (instead of Receiver) when no other audio route is connected. (2) Other categories this defaults to false and cannot be changed (that is, the default to speaker setting of these categories cannot be overridden) An application must be prepared for setting this property to fail as behaviour may change in future releases. If an application changes their category, they should reassert the override (it is not sticky across category and mode changes). DefaultToSpeaker is only valid with AVAudioSessionCategoryPlayAndRecord

2.3.1.3 AudioSessionMode

```
enum AudioSessionMode [strong]
```

Enumerator

Default	Modes modify the audio category in order to introduce behavior that is tailored to the specific use of audio within an application. Available in iOS 5.0 and greater. The default mode API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
VoiceChat	Only valid with AVAudioSessionCategoryPlayAndRecord. Appropriate for Voice over IP (VoIP) applications. Reduces the number of allowable audio routes to be only those that are appropriate for VoIP applications and may engage appropriate system-supplied signal processing. Has the side effect of setting AVAudioSessionCategoryOptionAllowBluetooth API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);

Enumerator

VideoRecording	Only valid with AVAudioSessionCategoryPlayAndRecord or AVAudioSessionCategoryRecord. Modifies the audio routing options and may engage appropriate system-supplied signal processing. API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Measurement	Appropriate for applications that wish to minimize the effect of system-supplied signal processing for input and/or output audio signals. API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
MoviePlayback	Engages appropriate output signal processing for movie playback scenarios. Currently only applied during playback over built-in speaker. API_AVAILABLE(ios(6.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
VideoChat	Only valid with kAudioSessionCategory_PlayAndRecord. Reduces the number of allowable audio routes to be only those that are appropriate for video chat applications. May engage appropriate system-supplied signal processing. Has the side effect of setting AVAudioSessionCategoryOptionAllowBluetooth and AVAudioSessionCategoryOptionDefaultToSpeaker. API_AVAILABLE(ios(7.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);

2.4 Photon.Voice.PUN Namespace Reference

Classes

- class [PhotonVoiceNetwork](#)

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also sets a custom [PUN Speaker](#) factory to find the [Speaker](#) component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the [PhotonView](#) of your player's prefab.

- class [PhotonVoiceView](#)

Component that should be attached to a networked [PUN](#) prefab that has [PhotonView](#). It will bind remote [Recorder](#) with local [Speaker](#) of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

2.5 Photon.Voice.PUN.UtilityScripts Namespace Reference

Classes

- class [VoiceDebugScript](#)

Utility script to be attached next to [PhotonVoiceView](#) & [PhotonView](#) on the player prefab to be network instantiated. Call `voiceDebugScript.CantHearYou()` on the networked object of the remote (or local) player if you can't hear the corresponding player.

2.6 Photon.Voice.Unity Namespace Reference

Classes

- class [AndroidAudioInAEC](#)
- class [AndroidAudioInParameters](#)

- class [AudioChangesHandler](#)

This component is useful to handle audio device and config changes.

- class [AudioClipWrapper](#)
- class [AudioInEnumerator](#)
- class [AudioInEnumeratorEx](#)
- class [AudioOutCapture](#)
- interface [ILoggable](#)
- interface [ILoggableDependent](#)
- class [Logger](#)
- class [MicWrapper](#)
- class [MicWrapperPusher](#)
- struct [NativeAndroidMicrophoneSettings](#)
- class [PhotonVoiceCreatedParams](#)
- struct [PlaybackDelaySettings](#)

Playback delay configuration container.

- class [Recorder](#)

Component representing outgoing audio stream in scene.

- class [RemoteVoiceLink](#)
- class [Speaker](#)

Component representing remote audio stream in local scene.

- class [UnityAudioOut](#)
- class [UnityMicrophone](#)

A wrapper around `UnityEngine.Microphone` to be able to safely use `Microphone` and compile for WebGL.

- class [VoiceComponent](#)
- class [VoiceConnection](#)

Component that represents a client voice connection to [Photon](#) Servers.

- class [VoiceLogger](#)
- class [WebRtcAudioDsp](#)

2.7 Photon.Voice.Unity.UtilityScripts Namespace Reference

Classes

- class [ConnectAndJoin](#)
- class [MicAmplifier](#)
- class [MicAmplifierFloat](#)
- class [MicAmplifierShort](#)
- class [MicrophonePermission](#)

Helper to request Microphone permission on Android or iOS.

- class [PhotonVoiceLagSimulationGui](#)
- class [PhotonVoiceStatsGui](#)

Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.

- class [SaveIncomingStreamToFile](#)
- class [SaveOutgoingStreamToFile](#)
- class [TestTone](#)
- class [ToneAudioReader](#)

2.8 POpusCodec Namespace Reference

Classes

- class [OpusDecoder](#)
- class [OpusEncoder](#)
- class [OpusException](#)
- class [OpusLib](#)
- class **Wrapper**

2.9 POpusCodec.Enums Namespace Reference

Enumerations

- enum [Bandwidth](#) : int
- enum [Channels](#) : int
- enum **Complexity** : int
- enum [Delay](#)

Using a duration of less than 10 ms will prevent the encoder from using the LPC or hybrid modes.

- enum **ForceChannels** : int
- enum [OpusApplicationType](#) : int
- enum **OpusStatusCode** : int
- enum **SamplingRate** : int
- enum [SignalHint](#) : int

2.9.1 Enumeration Type Documentation

2.9.1.1 Bandwidth

```
enum Bandwidth : int [strong]
```

Enumerator

Narrowband	Up to 4Khz
Mediumband	Up to 6Khz
Wideband	Up to 8Khz
SuperWideband	Up to 12Khz
Fullband	Up to 20Khz (High Definition)

2.9.1.2 Channels

```
enum Channels : int [strong]
```

Enumerator

Mono	1 Channel
Stereo	2 Channels

2.9.1.3 Delay

```
enum Delay [strong]
```

Using a duration of less than 10 ms will prevent the encoder from using the LPC or hybrid modes.

Enumerator

Delay2dot5ms	2.5ms
Delay5ms	5ms
Delay10ms	10ms
Delay20ms	20ms
Delay40ms	40ms
Delay60ms	60ms

2.9.1.4 OpusApplicationType

```
enum OpusApplicationType : int [strong]
```

Enumerator

Voip	Gives best quality at a given bitrate for voice signals. It enhances the input signal by high-pass filtering and emphasizing formants and harmonics. Optionally it includes in-band forward error correction to protect against packet loss. Use this mode for typical VoIP applications. Because of the enhancement, even at high bitrates the output may sound different from the input.
Audio	Gives best quality at a given bitrate for most non-voice signals like music. Use this mode for music and mixed (music/voice) content, broadcast, and applications requiring less than 15 ms of coding delay.
RestrictedLowDelay	Configures low-delay mode that disables the speech-optimized mode in exchange for slightly reduced delay.

2.9.1.5 SignalHint

```
enum SignalHint : int [strong]
```

Enumerator

Auto	(default)
Voice	Bias thresholds towards choosing LPC or Hybrid modes
Music	Bias thresholds towards choosing MDCT modes.

Chapter 3

Class Documentation

3.1 AndroidAudioInAEC Class Reference

Inherits [IAudioPusher< short >](#), and [IResettable](#).

Public Member Functions

- **AndroidAudioInAEC** ([Voice.ILogger](#) logger, bool enableAEC=false, bool enableAGC=false, bool enableNS=false)
- void **SetCallback** (Action< short[]> callback, [ObjectFactory](#)< short[], int > bufferFactory)
- void **Reset** ()
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.2 AndroidAudioInParameters Class Reference

Public Attributes

- bool **EnableAEC** = false
- bool **EnableAGC** = false
- bool **EnableNS** = false

3.3 AudioChangesHandler Class Reference

This component is useful to handle audio device and config changes.

Inherits [VoiceComponent](#).

Public Attributes

- bool [StartWhenDeviceChange](#) = true
Try to start recording when we get devices change notification and recording is not started.
- bool [HandleDeviceChange](#) = true
Try to react to device change notification when [Recorder](#) is started.
- bool [HandleConfigChange](#) = true
Try to react to audio config change notification when [Recorder](#) is started.
- bool [UseNativePluginChangeNotifier](#) = true
Whether or not to make use of [Photon](#)'s [AudioInChangeNotifier](#) native plugin.
- bool [UseOnAudioConfigurationChanged](#) = true
Whether or not to make use of [Unity](#)'s [OnAudioConfigurationChanged](#).

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.3.1 Detailed Description

This component is useful to handle audio device and config changes.

3.3.2 Member Data Documentation

3.3.2.1 [HandleConfigChange](#)

```
bool HandleConfigChange = true
```

Try to react to audio config change notification when [Recorder](#) is started.

This requires [UseOnAudioConfigurationChanged](#) to be true.

3.3.2.2 [HandleDeviceChange](#)

```
bool HandleDeviceChange = true
```

Try to react to device change notification when [Recorder](#) is started.

This requires [UseNativePluginChangeNotifier](#) or [UseOnAudioConfigurationChanged](#) to be true.

3.3.2.3 StartWhenDeviceChange

```
bool StartWhenDeviceChange = true
```

Try to start recording when we get devices change notification and recording is not started.

On some platforms we can't make sure that a device change notification could mean that at least a microphone device is now available. Besides, the auto start of the recording might not happen if other necessary conditions set in [Recorder](#) are not met: e.g. [Recorder.RecordOnlyWhenEnabled](#) or [Recorder.RecordOnlyWhenJoined](#) etc. or if the [Recorder](#) has been stopped explicitly via [Recorder.StopRecording](#) call or [Recorder.IsRecording](#) set to false.

3.3.2.4 UseNativePluginChangeNotifier

```
bool UseNativePluginChangeNotifier = true
```

Whether or not to make use of [Photon](#)'s [AudioInChangeNotifier](#) native plugin.

This may disable [HandleDeviceChange](#) if this and [UseOnAudioConfigurationChanged](#) are both false.

3.3.2.5 UseOnAudioConfigurationChanged

```
bool UseOnAudioConfigurationChanged = true
```

Whether or not to make use of [Unity](#)'s [OnAudioConfigurationChanged](#).

This is needed for [HandleConfigChange](#) and may also disable [HandleDeviceChange](#) if this and [UseNativePluginChangeNotifier](#) are both false.

3.4 AudioClipWrapper Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- **AudioClipWrapper** (AudioClip audioClip)
- bool **Read** (float[] buffer)
- void **Dispose** ()

Properties

- bool **Loop** [get, set]
- int **SamplingRate** [get]
- int **Channels** [get]
- string **Error** [get]

3.5 AudioDesc Class Reference

Inherits [IAudioDesc](#).

Public Member Functions

- **AudioDesc** (int samplingRate, int channels, string error)
- void **Dispose** ()

Properties

- int **SamplingRate** [get]
- int **Channels** [get]
- string **Error** [get]

3.6 AudioInChangeNotifierNotSupported Class Reference

Inherits [IAudioInChangeNotifier](#).

Public Member Functions

- **AudioInChangeNotifierNotSupported** (Action callback, [ILogger](#) logger)
- void **Dispose** ()

Public Attributes

- bool **IsSupported** => false

Properties

- string **Error** [get]

3.7 AudioInEnumerator Class Reference

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **AudioInEnumerator** ([ILogger](#) logger)
- override void **Refresh** ()
- override void **Dispose** ()

Properties

- override string **Error** [get]

Additional Inherited Members

3.8 AudioInEnumeratorEx Class Reference

Static Public Member Functions

- static bool **IDIsValid** (this [IDeviceEnumerator](#) en, int id)
- static string **NameAtIndex** (this [IDeviceEnumerator](#) en, int index)
- static int **IDAtIndex** (this [IDeviceEnumerator](#) en, int index)

3.9 AudioOutCapture Class Reference

Inherits MonoBehaviour.

Events

- Action< float[], int > **OnAudioFrame**

3.10 AudioOutDelayControl Class Reference

Inherited by [AudioOutDelayControl< T >](#).

Classes

- class [PlayDelayConfig](#)

3.11 AudioOutDelayControl Class Reference

Inherited by [AudioOutDelayControl< T >](#).

Classes

- class [PlayDelayConfig](#)

3.12 AudioSessionParameters Struct Reference

Public Member Functions

- int **CategoryOptionsToInt** ()
- override string **ToString** ()

Public Attributes

- [AudioSessionCategory](#) **Category**
- [AudioSessionMode](#) **Mode**
- [AudioSessionCategoryOption](#)[] **CategoryOptions**

3.13 AudioSessionParametersPresets Class Reference

Static Public Attributes

- static [AudioSessionParameters](#) **Game**
- static [AudioSessionParameters](#) **VoIP**

3.13.1 Member Data Documentation

3.13.1.1 Game

[AudioSessionParameters](#) Game [static]

Initial value:

```
= new AudioSessionParameters()
{
    Category = AudioSessionCategory.PlayAndRecord,
    Mode = AudioSessionMode.Default,
    CategoryOptions = new AudioSessionCategoryOption[] {
        AudioSessionCategoryOption.DefaultToSpeaker, AudioSessionCategoryOption.AllowBluetooth }
}
```

3.13.1.2 VoIP

[AudioSessionParameters](#) VoIP [static]

Initial value:

```
= new AudioSessionParameters()
{
    Category = AudioSessionCategory.PlayAndRecord,
    Mode = AudioSessionMode.VoiceChat,

    CategoryOptions = new AudioSessionCategoryOption[] { AudioSessionCategoryOption.AllowBluetooth }
}
```

3.14 AudioSyncBuffer< T > Class Template Reference

Inherits [IAudioOut< T >](#).

Public Member Functions

- **AudioSyncBuffer** (int playDelayMs, [ILogger](#) logger, string logPrefix, bool debugInfo)
- void **Start** (int sampleRate, int channels, int frameSamples)
- void **Service** ()
- void **Read** (T[] outBuf, int outChannels, int outSampleRate)
- void **Push** (T[] frame)
- void **Flush** ()
- void **Stop** ()

Static Public Attributes

- const int **FRAME_POOL_CAPACITY** = 50

Properties

- int **Lag** [get]
- bool **IsPlaying** [get]

3.15 AudioUtil Class Reference

Collection of Audio Utility functions and classes.

Classes

- interface [ILevelMeter](#)
Audio Level Metering interface.
- interface [IVoiceDetector](#)
Voice Activity Detector interface.
- class [LevelMeter](#)
Audio Level Meter.
- class [LevelMeterDummy](#)
Dummy Audio Level Meter that doesn't actually do anything.
- class [LevelMeterFloat](#)
LevelMeter specialization for float audio.
- class [LevelMeterShort](#)
LevelMeter specialization for short audio.
- class [Resampler](#)
Sample-rate conversion Audio Processor.
- class [TempoUp](#)
- class [ToneAudioPusher](#)
IAudioPusher that provides a constant tone signal.

- class [ToneAudioReader](#)
IAudioReader that provides a constant tone signal.
- class [VoiceDetector](#)
Simple voice activity detector triggered by signal level.
- class [VoiceDetectorCalibration](#)
Calibration Utility for Voice Detector
- class [VoiceDetectorDummy](#)
Dummy VoiceDetector that doesn't actually do anything.
- class [VoiceDetectorFloat](#)
VoiceDetector specialization for float audio.
- class [VoiceDetectorShort](#)
VoiceDetector specialization for float audio.
- class [VoiceLevelDetectCalibrate](#)
Utility Audio Processor Voice Detection Calibration.

Static Public Member Functions

- static void [Resample](#)< T > (T[] src, T[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer.
- static void **Resample**< T > (T[] src, int srcOffset, int srcCount, T[] dst, int dstOffset, int dstCount, int channels)
- static void **Resample**< T > (T[] src, int srcOffset, int srcCount, int srcChannels, T[] dst, int dstOffset, int dstCount, int dstChannels)
- static void [ResampleAndConvert](#) (short[] src, float[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert short to float samples along the way.
- static void [ResampleAndConvert](#) (float[] src, short[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert float to short samples along the way.
- static void [Convert](#) (float[] src, short[] dst, int dstCount)
Convert audio buffer from float to short samples.
- static void [Convert](#) (short[] src, float[] dst, int dstCount)
Convert audio buffer from short to float samples.
- static void [ForceToStereo](#)< T > (T[] src, T[] dst, int srcChannels)
Convert audio buffer with arbitrary number of channels to stereo.

3.15.1 Detailed Description

Collection of Audio Utility functions and classes.

3.15.2 Member Function Documentation

3.15.2.1 [Convert\(\)](#) [1/2]

```
static void Convert (
    float[] src,
    short[] dst,
    int dstCount ) [static]
```

Convert audio buffer from float to short samples.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Size of destination buffer (in total samples), source buffer must be of same length or longer.

3.15.2.2 Convert() [2/2]

```
static void Convert (
    short[] src,
    float[] dst,
    int dstCount ) [static]
```

Convert audio buffer from short to float samples.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Size of destination buffer (in total samples), source buffer must be of same length or longer.

3.15.2.3 ForceToStereo< T >()

```
static void ForceToStereo< T > (
    T[] src,
    T[] dst,
    int srcChannels ) [static]
```

Convert audio buffer with arbitrary number of channels to stereo.

For mono sources (`srcChannels==1`), the signal will be copied to both Left and Right stereo channels. For all others, the first two available channels will be used, any other channels will be discarded.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>srcChannels</i>	Number of (interleaved) channels in src.

3.15.2.4 Resample< T >()

```
static void Resample< T > (
    T[] src,
```

```

T[] dst,
int dstCount,
int channels ) [static]

```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.15.2.5 ResampleAndConvert() [1/2]

```

static void ResampleAndConvert (
    float[] src,
    short[] dst,
    int dstCount,
    int channels ) [static]

```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert float to short samples along the way.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.15.2.6 ResampleAndConvert() [2/2]

```

static void ResampleAndConvert (
    short[] src,
    float[] dst,
    int dstCount,
    int channels ) [static]

```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert short to float samples along the way.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.16 `BufferReaderPushAdapter< T >` Class Template Reference

Simple `BufferReaderPushAdapterBase<T>` implementation using a single buffer and synchronous `LocalVoiceFramed<T>.PushData`

Inherits `BufferReaderPushAdapterBase< T >`.

Public Member Functions

- `BufferReaderPushAdapter` (`LocalVoice` localVoice, `IDataReader< T >` reader)
Create a new `BufferReaderPushAdapter` instance
- override void `Service` (`LocalVoice` localVoice)
Do the actual data read/push.

Protected Attributes

- `T[]` `buffer`

3.16.1 Detailed Description

Simple `BufferReaderPushAdapterBase<T>` implementation using a single buffer and synchronous `LocalVoiceFramed<T>.PushData`

3.16.2 Constructor & Destructor Documentation

3.16.2.1 `BufferReaderPushAdapter()`

```
BufferReaderPushAdapter (
    LocalVoice localVoice,
    IDataReader< T > reader )
```

Create a new `BufferReaderPushAdapter` instance

Parameters

<i>localVoice</i>	<code>LocalVoice</code> instance to push data to.
<i>reader</i>	<code>DataReader</code> to read from.

3.16.3 Member Function Documentation

3.16.3.1 Service()

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
-------------------	--

Implements [BufferReaderPushAdapterBase< T >](#).

3.17 BufferReaderPushAdapterAsyncPool< T > Class Template Reference

[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).

Inherits [BufferReaderPushAdapterBase< T >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPool](#) ([LocalVoice](#) localVoice, [IDataReader< T >](#) reader)
Create a new [BufferReaderPushAdapter](#) instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Additional Inherited Members

3.17.1 Detailed Description

[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).

Acquires a buffer from pool before each Read, releases buffer after last Read (brings Acquire/Release overhead). Expects localVoice to be a [LocalVoiceFramed<T>](#) of same T.

3.17.2 Constructor & Destructor Documentation

3.17.2.1 BufferReaderPushAdapterAsyncPool()

```
BufferReaderPushAdapterAsyncPool (
    LocalVoice localVoice,
    IDataReader< T > reader )
```

Create a new [BufferReaderPushAdapter](#) instance

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
<i>reader</i>	<code>DataReader</code> to read from.

3.17.3 Member Function Documentation

3.17.3.1 `Service()`

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a <code>LocalVoiceFramed<T></code> of same T.
-------------------	--

Implements [BufferReaderPushAdapterBase< T >](#).

3.18 `BufferReaderPushAdapterAsyncPoolCopy< T >` Class Template Reference

`BufferReaderPushAdapter<T>` implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync\(T\[\]\)](#) and data copy.

Inherits [BufferReaderPushAdapterBase< T >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPoolCopy](#) ([LocalVoice](#) localVoice, [IDataReader< T >](#) reader)
Create a new [BufferReaderPushAdapter](#) instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Protected Attributes

- `T[]` **buffer**

3.18.1 Detailed Description

BufferedReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync\(T\[\]\)](#) and data copy.

Reads data to preallocated buffer, copies it to buffer from pool before pushing. Compared with [BufferedReaderPushAdapterAsyncPool<T>](#) this avoids one pool Acquire/Release cycle at the cost of a buffer copy. Expects localVoice to be a [LocalVoiceFramed<T>](#) of same T.

3.18.2 Constructor & Destructor Documentation

3.18.2.1 BufferedReaderPushAdapterAsyncPoolCopy()

```
BufferedReaderPushAdapterAsyncPoolCopy (
    LocalVoice localVoice,
    IDataReader< T > reader )
```

Create a new [BufferedReaderPushAdapter](#) instance

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
<i>reader</i>	DataReader to read from.

3.18.3 Member Function Documentation

3.18.3.1 Service()

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a LocalVoiceFramed<T> of same T.
-------------------	---

Implements [BufferedReaderPushAdapterBase< T >](#).

3.19 BufferReaderPushAdapterAsyncPoolFloatToShort Class Reference

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting float samples to short.

Inherits [BufferReaderPushAdapterBase< float >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPoolFloatToShort](#) ([LocalVoice](#) localVoice, [IDataReader](#)< float > reader)
Create a new [BufferReaderPushAdapter](#) instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Additional Inherited Members

3.19.1 Detailed Description

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting float samples to short.

This adapter works exactly like [BufferReaderPushAdapterAsyncPool<T>](#), but it converts float samples to short. Acquires a buffer from pool before each Read, releases buffer after last Read.

Expects localVoice to be a [LocalVoiceFramed<T>](#) of same T.

3.19.2 Constructor & Destructor Documentation

3.19.2.1 BufferReaderPushAdapterAsyncPoolFloatToShort()

```
BufferReaderPushAdapterAsyncPoolFloatToShort (
    LocalVoice localVoice,
    IDataReader< float > reader )
```

Create a new [BufferReaderPushAdapter](#) instance

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
<i>reader</i>	DataReader to read from.

3.19.3 Member Function Documentation

3.19.3.1 Service()

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a LocalVoiceFramed<T> of same T.
-------------------	---

Implements [BufferReaderPushAdapterBase< float >](#).

3.20 BufferReaderPushAdapterAsyncPoolShortToFloat Class Reference

[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.

Inherits [BufferReaderPushAdapterBase< short >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPoolShortToFloat](#) ([LocalVoice](#) localVoice, [IDataReader< short >](#) reader)
Create a new [BufferReaderPushAdapter](#) instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Additional Inherited Members

3.20.1 Detailed Description

[BufferReaderPushAdapter<T>](#) implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.

This adapter works exactly like [BufferReaderPushAdapterAsyncPool<T>](#), but it converts short samples to float. Acquires a buffer from pool before each Read, releases buffer after last Read.

Expects localVoice to be a [LocalVoiceFramed<T>](#) of same T.

3.20.2 Constructor & Destructor Documentation

3.20.2.1 BufferReaderPushAdapterAsyncPoolShortToFloat()

```
BufferReaderPushAdapterAsyncPoolShortToFloat (
    LocalVoice localVoice,
    IDataReader< short > reader )
```

Create a new [BufferReaderPushAdapter](#) instance

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
<i>reader</i>	<code>DataReader</code> to read from.

3.20.3 Member Function Documentation

3.20.3.1 `Service()`

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a <code>LocalVoiceFramed<T></code> of same T.
-------------------	--

Implements [BufferedReaderPushAdapterBase< short >](#).

3.21 `BufferedReaderPushAdapterBase< T >` Class Template Reference

Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).

Inherits [IServiceable](#).

Inherited by [BufferedReaderPushAdapter< T >](#), [BufferedReaderPushAdapterAsyncPool< T >](#), and [BufferedReaderPushAdapterAsyncPool](#).

Public Member Functions

- abstract void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.
- [BufferedReaderPushAdapterBase](#) ([IDataReader](#)< T > reader)
Create a new [BufferedReaderPushAdapterBase](#) instance
- void [Dispose](#) ()
Release resources associated with this instance.

Protected Attributes

- [IDataReader](#)< T > **reader**

3.21.1 Detailed Description

Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).

Use this with a [LocalVoice](#) of same T type.

3.21.2 Constructor & Destructor Documentation

3.21.2.1 BufferReaderPushAdapterBase()

```
BufferReaderPushAdapterBase (
    IDataReader< T > reader )
```

Create a new [BufferReaderPushAdapterBase](#) instance

Parameters

<i>reader</i>	DataReader to read from.
---------------	--------------------------

3.21.3 Member Function Documentation

3.21.3.1 Dispose()

```
void Dispose ( )
```

Release resources associated with this instance.

3.21.3.2 Service()

```
abstract void Service (
    LocalVoice localVoice ) [pure virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
-------------------	--

Implements [IServiceable](#).

Implemented in [BufferedReaderPushAdapterAsyncPoolShortToFloat](#), [BufferedReaderPushAdapterAsyncPoolFloatToShort](#), [BufferedReaderPushAdapterAsyncPoolCopy< T >](#), [BufferedReaderPushAdapterAsyncPool< T >](#), and [BufferedReaderPushAdapter< T >](#).

3.22 ConnectAndJoin Class Reference

Inherits [MonoBehaviour](#), [IConnectionCallbacks](#), and [IMatchmakingCallbacks](#).

Public Member Functions

- void **ConnectNow** ()
- void **OnCreatedRoom** ()
- void **OnCreateRoomFailed** (short returnCode, string message)
- void **OnFriendListUpdate** (List< FriendInfo > friendList)
- void **OnJoinedRoom** ()
- void **OnJoinRandomFailed** (short returnCode, string message)
- void **OnJoinRoomFailed** (short returnCode, string message)
- void **OnLeftRoom** ()
- void **OnConnected** ()
- void **OnConnectedToMaster** ()
- void **OnDisconnected** (DisconnectCause cause)
- void **OnRegionListReceived** (RegionHandler regionHandler)
- void **OnCustomAuthenticationResponse** (Dictionary< string, object > data)
- void **OnCustomAuthenticationFailed** (string debugMessage)

Public Attributes

- bool **RandomRoom** = true
- string **RoomName**

Properties

- bool **IsConnected** [get]

3.23 VoiceClient.CreateOptions Struct Reference

Public Attributes

- byte **VoicelDMin**
- byte **VoicelDMax**

Static Public Attributes

- static [CreateOptions](#) **Default**

3.23.1 Member Data Documentation

3.23.1.1 Default

`CreateOptions` Default [static]

Initial value:

```
= new CreateOptions()
{
    VoiceIDMin = 1,
    VoiceIDMax = 15
}
```

3.24 OpusCodec.Decoder< T > Class Template Reference

Inherits [IDecoder](#).

Public Member Functions

- **Decoder** (Action< [FrameOut](#)< T >> output, [ILogger](#) logger)
- void **Open** ([VoiceInfo](#) i)
Open (initialize) the decoder.
- void **Dispose** ()
- void **Input** (ref [FrameBuffer](#) buf)
Consumes the given encoded data.

Protected Attributes

- [OpusDecoder](#)< T > **decoder**

Properties

- string **Error** [get]

3.24.1 Member Function Documentation

3.24.1.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call `buf.Retain()` to prevent the caller from disposing the buffer. In this case, the callee should call `buf.Release()` when buffer is no longer needed.

Implements [IDecoder](#).

3.24.1.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implements [IDecoder](#).

3.25 RawCodec.Decoder< T > Class Template Reference

Inherits [IDecoder](#).

Public Member Functions

- **Decoder** (Action< [FrameOut](#)< T >> output)
- void **Open** ([VoiceInfo](#) info)
Open (initialize) the decoder.
- void **Input** (ref [FrameBuffer](#) byteBuf)
Consumes the given encoded data.
- void **Dispose** ()

Properties

- string **Error** [get]

3.25.1 Member Function Documentation

3.25.1.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call buf.Retain() to prevent the caller from disposing the buffer. In this case, the callee should call buf.Release() when buffer is no longer needed.

Implements [IDecoder](#).

3.25.1.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implements [IDecoder](#).

3.26 OpusCodec.DecoderFactory Class Reference

Static Public Member Functions

- static [IEncoder](#) **Create**< T > ([VoiceInfo](#) i, [ILogger](#) logger)

3.27 DeviceEnumeratorBase Class Reference

Inherits [IDeviceEnumerator](#).

Inherited by [DeviceEnumeratorNotSupported](#), and [AudioInEnumerator](#).

Public Member Functions

- DeviceEnumeratorBase** ([ILogger](#) logger)
- [IEnumerator](#)< [DeviceInfo](#) > **GetEnumerator** ()
- abstract void **Refresh** ()
- abstract void **Dispose** ()

Public Attributes

- virtual bool **IsSupported** => true

Protected Attributes

- List< [DeviceInfo](#) > **devices** = new List<[DeviceInfo](#)>()
- [ILogger](#) **logger**

Properties

- virtual string **Error** [get, protected set]

3.28 DeviceInfo Struct Reference

Public Member Functions

- DeviceInfo** (int id, string name)
- DeviceInfo** (string id, string name)
- DeviceInfo** (string name)
- override bool **Equals** (object obj)
- override int **GetHashCode** ()
- override string **ToString** ()

Static Public Member Functions

- static bool **operator==** ([DeviceInfo](#) d1, [DeviceInfo](#) d2)
- static bool **operator!=** ([DeviceInfo](#) d1, [DeviceInfo](#) d2)

Static Public Attributes

- static readonly [DeviceInfo](#) **Default** = new [DeviceInfo](#)(true, -128, "", "[Default]")

Properties

- bool **IsDefault** [get]
- int **IDInt** [get]
- string **IDString** [get]
- string **Name** [get]

3.29 OpusCodec.Encoder< T > Class Template Reference

Inherits [IEncoderDirect< T\[\]>](#).

Public Member Functions

- void **Input** (T[] buf)
- void **EndOfStream** ()
- [ArraySegment< byte >](#) **DequeueOutput** (out [FrameFlags](#) flags)
- I **GetPlatformAPI**< I > ()
- void **Dispose** ()

Protected Member Functions

- **Encoder** ([VoiceInfo](#) i, [ILogger](#) logger)
- abstract [ArraySegment< byte >](#) **encodeTyped** (T[] buf)

Protected Attributes

- [OpusEncoder](#) **encoder**
- bool **disposed**

Properties

- string **Error** [get]
- [Action< ArraySegment< byte >, FrameFlags >](#) **Output** [get, set]

3.30 RawCodec.Encoder< T > Class Template Reference

Inherits [IEncoderDirect< T\[\] >](#).

Public Member Functions

- `ArraySegment< byte > DequeueOutput` (out FrameFlags flags)
- `void EndOfStream` ()
- `I GetPlatformAPI< I > ()`
- `void Dispose` ()
- `void Input` (T[] buf)

Properties

- `string Error` [get]
- `Action< ArraySegment< byte >, FrameFlags > Output` [get, set]

3.31 OpusCodec.EncoderFloat Class Reference

Inherits [OpusCodec.Encoder< float >](#).

Protected Member Functions

- override `ArraySegment< byte > encodeTyped` (float[] buf)

Additional Inherited Members

3.32 OpusCodec.EncoderShort Class Reference

Inherits [OpusCodec.Encoder< short >](#).

Protected Member Functions

- override `ArraySegment< byte > encodeTyped` (short[] buf)

Additional Inherited Members

3.33 OpusCodec.Factory Class Reference

Static Public Member Functions

- static `IEncoder CreateEncoder< B >` (VoiceInfo i, ILogger logger)

3.34 FactoryPrimitiveArrayPool< T > Class Template Reference

PrimitiveArrayPool<T> as wrapped in object factory interface.

Inherits [ObjectFactory< T\[\], int >](#).

Public Member Functions

- **FactoryPrimitiveArrayPool** (int capacity, string name)
- **FactoryPrimitiveArrayPool** (int capacity, string name, int info)
- **T[] New** ()
- **T[] New** (int size)
- void **Free** (T[] obj)
- void **Free** (T[] obj, int info)
- void **Dispose** ()

Properties

- int **Info** [get]

3.34.1 Detailed Description

PrimitiveArrayPool<T> as wrapped in object factory interface.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.35 FactoryReusableArray< T > Class Template Reference

Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.

Inherits [ObjectFactory< T\[\], int >](#).

Public Member Functions

- **FactoryReusableArray** (int size)
- **T[] New** ()
- **T[] New** (int size)
- void **Free** (T[] obj)
- void **Free** (T[] obj, int info)
- void **Dispose** ()

Properties

- `int Info` [get]

3.35.1 Detailed Description

Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.36 Flip Struct Reference

Public Member Functions

- override `bool Equals` (object obj)
- override `int GetHashCode` ()

Static Public Member Functions

- static `bool operator==` ([Flip](#) f1, [Flip](#) f2)
- static `bool operator!=` ([Flip](#) f1, [Flip](#) f2)
- static `Flip operator*` ([Flip](#) f1, [Flip](#) f2)

Static Public Attributes

- static `Flip None`
- static `Flip Vertical` = new [Flip](#)() { IsVertical = true }
- static `Flip Horizontal` = new [Flip](#)() { IsHorizontal = true }
- static `Flip Both` = Vertical * Horizontal

Properties

- `bool IsVertical` [get]
- `bool IsHorizontal` [get]

3.37 FrameBuffer Struct Reference

Public Member Functions

- `FrameBuffer` (byte[] array, int offset, int count, FrameFlags flags, IDisposable disposer)
- `FrameBuffer` (byte[] array, FrameFlags flags)
- `void Retain` ()
- `void Release` ()

Public Attributes

- readonly byte[] **array**
- readonly int **offset**
- readonly int **count**
- readonly IDisposable **disposer**
- bool **disposed**
- int **refCnt**
- GCHandle **gcHandle**
- IntPtr **ptr**
- bool **pinned**

Properties

- IntPtr **Ptr** [get]
- byte[] **Array** [get]
- int **Length** [get]
- int **Offset** [get]
- FrameFlags **Flags** [get]

3.38 FrameOut< T > Class Template Reference

Public Member Functions

- **FrameOut** (T[] buf, bool endOfStream)
- [FrameOut](#)< T > **Set** (T[] buf, bool endOfStream)

Properties

- T[] **Buf** [get]
- bool **EndOfStream** [get]

3.39 Framer< T > Class Template Reference

Utility class to re-frame audio packets.

Public Member Functions

- [Framer](#) (int frameSize)
Create new [Framer](#) instance.
- int [Count](#) (int bufLen)
Get the number of frames available after adding bufLen samples.
- IEnumerable< T[] > [Frame](#) (T[] buf)
Append arbitrary-sized buffer and return available full frames.

3.39.1 Detailed Description

Utility class to re-frame audio packets.

3.39.2 Constructor & Destructor Documentation

3.39.2.1 Framer()

```
Framer (
    int frameSize )
```

Create new [Framer](#) instance.

3.39.3 Member Function Documentation

3.39.3.1 Count()

```
int Count (
    int bufLen )
```

Get the number of frames available after adding *bufLen* samples.

Parameters

<i>bufLen</i>	Number of samples that would be added.
---------------	--

Returns

Number of full frames available when adding *bufLen* samples.

3.39.3.2 Frame()

```
IEnumerable<T[]> Frame (
    T[] buf )
```

Append arbitrary-sized buffer and return available full frames.

Parameters

<i>buf</i>	Array of samples to add.
------------	--------------------------

Returns

Enumerator of full frames (might be none).

3.40 IAudioDesc Interface Reference

Audio Source interface.

Inherits IDisposable.

Inherited by [AudioDesc](#), [IAudioPusher< T >](#), and [IAudioReader< T >](#).

Properties

- int [SamplingRate](#) [get]
Sampling rate of the audio signal (in Hz).
- int [Channels](#) [get]
Number of channels in the audio signal.
- string [Error](#) [get]
If not null, audio object is in invalid state.

3.40.1 Detailed Description

Audio Source interface.

3.40.2 Property Documentation

3.40.2.1 Channels

```
int Channels [get]
```

Number of channels in the audio signal.

3.40.2.2 Error

```
string Error [get]
```

If not null, audio object is in invalid state.

3.40.2.3 `SamplingRate`

```
int SamplingRate [get]
```

Sampling rate of the audio signal (in Hz).

3.41 `IAudioInChangeNotifier` Interface Reference

Inherits `IDisposable`.

Inherited by [AudioInChangeNotifierNotSupported](#).

Properties

- bool **IsSupported** [get]
- string **Error** [get]

3.42 `IAudioOut< T >` Interface Template Reference

Inherited by [AudioOutDelayControl< T >](#), and [AudioSyncBuffer< T >](#).

Public Member Functions

- void **Start** (int frequency, int channels, int frameSamplesPerChannel)
- void **Flush** ()
- void **Stop** ()
- void **Push** (T[] frame)
- void **Service** ()

Properties

- bool **IsPlaying** [get]
- int **Lag** [get]

3.43 `IAudioPusher< T >` Interface Template Reference

Audio Pusher interface.

Inherits [IAudioDesc](#).

Inherited by [AudioUtil.ToneAudioPusher< T >](#).

Public Member Functions

- void [SetCallback](#) (Action< T[]> callback, [ObjectFactory](#)< T[], int > bufferFactory)
Set the callback function used for pushing data.

Additional Inherited Members

3.43.1 Detailed Description

Audio Pusher interface.

Opposed to an [IAudioReader](#) (which will deliver audio data when it is "pulled"), an [IAudioPusher](#) will push its audio data whenever it is ready,

3.43.2 Member Function Documentation

3.43.2.1 SetCallback()

```
void SetCallback (
    Action< T[]> callback,
    ObjectFactory< T[], int > bufferFactory )
```

Set the callback function used for pushing data.

Parameters

<i>callback</i>	Callback function to use.
<i>bufferFactory</i>	Buffer factory used to create the buffer that is pushed to the callback

Implemented in [AudioUtil.ToneAudioPusher< T >](#).

3.44 IAudioReader< T > Interface Template Reference

Audio Reader interface.

Inherits [IDataReader< T >](#), and [IAudioDesc](#).

Inherited by [AudioUtil.ToneAudioReader< T >](#).

Additional Inherited Members

3.44.1 Detailed Description

Audio Reader interface.

Opposed to an [IAudioPusher](#) (which will push its audio data whenever it is ready), an [IAudioReader](#) will deliver audio data when it is "pulled" (it's Read function is called).

3.45 IDataReader< T > Interface Template Reference

Interface for pulling data, in case this is more appropriate than pushing it.

Inherits IDisposable.

Inherited by [IAudioReader< T >](#).

Public Member Functions

- bool [Read](#) (T[] buffer)

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

3.45.1 Detailed Description

Interface for pulling data, in case this is more appropriate than pushing it.

3.45.2 Member Function Documentation

3.45.2.1 Read()

```
bool Read (
    T[] buffer )
```

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Parameters

<i>buffer</i>	Buffer to fill.
---------------	-----------------

Returns

True if buffer was filled successfully, false otherwise.

Implemented in [AudioUtil.ToneAudioReader< T >](#).

3.46 IDecoder Interface Reference

Generic decoder interface.

Inherits IDisposable.

Inherited by [IDecoderDirect< B >](#), [OpusCodec.Decoder< T >](#), and [RawCodec.Decoder< T >](#).

Public Member Functions

- void [Open](#) ([VoiceInfo](#) info)
Open (initialize) the decoder.
- void [Input](#) (ref [FrameBuffer](#) buf)
Consumes the given encoded data.

Properties

- string [Error](#) [get]
If not null, the object is in invalid state.

3.46.1 Detailed Description

Generic decoder interface.

3.46.2 Member Function Documentation

3.46.2.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call `buf.Retain()` to prevent the caller from disposing the buffer. In this case, the callee should call `buf.Release()` when buffer is no longer needed.

Implemented in [RawCodec.Decoder< T >](#), and [OpusCodec.Decoder< T >](#).

3.46.2.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implemented in [RawCodec.Decoder< T >](#), and [OpusCodec.Decoder< T >](#).

3.46.3 Property Documentation

3.46.3.1 Error

`string Error [get]`

If not null, the object is in invalid state.

3.47 IDecoderDirect< B > Interface Template Reference

Interface for an decoder which outputs data via explicit call.

Inherits [IDecoder](#).

Properties

- `Action< B > Output [get, set]`
Callback to call when a new decoded data buffer is available.

Additional Inherited Members

3.47.1 Detailed Description

Interface for an decoder which outputs data via explicit call.

3.47.2 Property Documentation

3.47.2.1 Output

`Action Output [get], [set]`

Callback to call when a new decoded data buffer is available.

3.48 IDeviceEnumerator Interface Reference

Inherits `IDisposable`, and `IEnumerable< DeviceInfo >`.

Inherited by [DeviceEnumeratorBase](#).

Public Member Functions

- void **Refresh** ()

Properties

- bool **IsSupported** [get]
- string **Error** [get]

3.49 IEncoder Interface Reference

Generic encoder interface.

Inherits IDisposable.

Inherited by [IEncoderDirect< B >](#).

Public Member Functions

- ArraySegment< byte > [DequeueOutput](#) (out FrameFlags flags)
Returns next encoded data frame (if such output supported).
- void [EndOfStream](#) ()
Forces an encoder to flush and produce frame with EndOfStream flag (in output queue).
- I [GetPlatformAPI](#)< I > ()
Returns an platform-specific interface.

Properties

- string [Error](#) [get]
If not null, the object is in invalid state.
- Action< ArraySegment< byte >, FrameFlags > [Output](#) [set]
Set callback encoder calls on each encoded data frame (if such output supported).

3.49.1 Detailed Description

Generic encoder interface.

Depending on implementation, encoder should either call Output on eaach data frame or return next data frame in [DequeueOutput\(\)](#) call.

3.49.2 Member Function Documentation

3.49.2.1 DequeueOutput()

```
ArraySegment<byte> DequeueOutput (
    out FrameFlags flags )
```

Returns next encoded data frame (if such output supported).

3.49.2.2 EndOfStream()

```
void EndOfStream ( )
```

Forces an encoder to flush and produce frame with EndOfStream flag (in output queue).

3.49.2.3 GetPlatformAPI< I >()

```
I GetPlatformAPI< I > ( )
```

Returns an platform-specific interface.

Type Constraints

I : class

3.49.3 Property Documentation

3.49.3.1 Error

```
string Error [get]
```

If not null, the object is in invalid state.

3.49.3.2 Output

```
Action<ArraySegment<byte>, FrameFlags> Output [set]
```

Set callback encoder calls on each encoded data frame (if such output supported).

3.50 IEncoderDirect< B > Interface Template Reference

Interface for an encoder which consumes input data via explicit call.

Inherits [IEncoder](#).

Public Member Functions

- void [Input](#) (B buf)
Consumes the given raw data.

Additional Inherited Members

3.50.1 Detailed Description

Interface for an encoder which consumes input data via explicit call.

3.50.2 Member Function Documentation

3.50.2.1 Input()

```
void Input (
    B buf )
```

Consumes the given raw data.

Parameters

<i>buf</i>	Array containing raw data (e.g. audio samples).
------------	---

3.51 IEncoderDirectImage Interface Reference

Interface for an encoder which consumes images via explicit call.

Inherits [IEncoderDirect< ImageBufferNative >](#).

Properties

- ImageFormat [ImageFormat](#) [get]
Recommended encoder input image format. Encoder may support other formats.

Additional Inherited Members

3.51.1 Detailed Description

Interface for an encoder which consumes images via explicit call.

3.51.2 Property Documentation

3.51.2.1 ImageFormat

`ImageFormat ImageFormat [get]`

Recommended encoder input image format. Encoder may support other formats.

3.52 AudioUtil.ILevelMeter Interface Reference

Audio Level Metering interface.

Inherited by [AudioUtil.LevelMeter< T >](#), and [AudioUtil.LevelMeterDummy](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset [AccumAvgPeakAmp](#).

Properties

- float [CurrentAvgAmp](#) [get]
Average amplitude value over last half second.
- float [CurrentPeakAmp](#) [get]
Maximum amplitude value over last half second sec.
- float [AccumAvgPeakAmp](#) [get]
Average of CurrentPeakAmps since last reset.

3.52.1 Detailed Description

Audio Level Metering interface.

3.52.2 Member Function Documentation

3.52.2.1 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset [AccumAvgPeakAmp](#).

Implemented in [AudioUtil.LevelMeter< T >](#), and [AudioUtil.LevelMeterDummy](#).

3.52.3 Property Documentation

3.52.3.1 AccumAvgPeakAmp

```
float AccumAvgPeakAmp [get]
```

Average of CurrentPeakAmps since last reset.

3.52.3.2 CurrentAvgAmp

```
float CurrentAvgAmp [get]
```

Average amplitude value over last half second.

3.52.3.3 CurrentPeakAmp

```
float CurrentPeakAmp [get]
```

Maximum amplitude value over last half second sec.

3.53 ILocalVoiceAudio Interface Reference

Interface for an outgoing audio stream.

Inherited by [LocalVoiceAudio< T >](#), and [LocalVoiceAudioDummy](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Properties

- [AudioUtil.IVoiceDetector VoiceDetector](#) [get]
The VoiceDetector in use.
- [AudioUtil.ILevelMeter LevelMeter](#) [get]
The LevelMeter utility in use.
- bool [VoiceDetectorCalibrating](#) [get]
If true, voice detector calibration is in progress.

3.53.1 Detailed Description

Interface for an outgoing audio stream.

A [LocalVoice](#) always brings a LevelMeter and a VoiceDetector, which you can access using this interface.

3.53.2 Member Function Documentation

3.53.2.1 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold based on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implemented in [LocalVoiceAudioDummy](#), and [LocalVoiceAudio< T >](#).

3.53.3 Property Documentation

3.53.3.1 LevelMeter

[AudioUtil.ILevelMeter LevelMeter](#) [get]

The LevelMeter utility in use.

3.53.3.2 VoiceDetector

[AudioUtil.IVoiceDetector](#) `VoiceDetector` [get]

The VoiceDetector in use.

Use it to enable or disable voice detector and set its parameters.

3.53.3.3 VoiceDetectorCalibrating

`bool VoiceDetectorCalibrating` [get]

If true, voice detector calibration is in progress.

3.54 ILoggable Interface Reference

Inherited by [ILoggableDependent](#), and [VoiceConnection](#).

Properties

- DebugLevel **LogLevel** [get, set]
- [VoiceLogger](#) **Logger** [get]

3.55 ILoggableDependent Interface Reference

Inherits [ILoggable](#).

Inherited by [VoiceComponent](#).

Properties

- `bool IgnoreGlobalLogLevel` [get, set]

3.56 ILogger Interface Reference

Inherited by [LoadBalancingTransport](#), [Logger](#), and [VoiceLogger](#).

Public Member Functions

- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)

3.57 ImageBufferInfo Struct Reference

Classes

- struct [StrideSet](#)

Public Member Functions

- **ImageBufferInfo** (int width, int height, [StrideSet](#) stride, ImageFormat format)

Properties

- int **Width** [get]
- int **Height** [get]
- [StrideSet](#) **Stride** [get]
- ImageFormat **Format** [get]
- Rotation **Rotation** [get, set]
- [Flip](#) **Flip** [get, set]

3.58 ImageBufferNative Class Reference

Inherited by [ImageBufferNativeAlloc](#), and [ImageBufferNativeGCHandleSinglePlane](#).

Classes

- struct [PlaneSet](#)

Public Member Functions

- **ImageBufferNative** ([ImageBufferInfo](#) info)
- **ImageBufferNative** (IntPtr buf, int width, int height, int stride, ImageFormat imageFormat)
- virtual void **Release** ()
- virtual void **Dispose** ()

Public Attributes

- [ImageBufferInfo](#) **Info**
- [PlaneSet](#) **Planes**

3.59 ImageBufferNativeAlloc Class Reference

Inherits [ImageBufferNative](#), and IDisposable.

Public Member Functions

- **ImageBufferNativeAlloc** ([ImageBufferNativePool](#)< [ImageBufferNativeAlloc](#) > pool, [ImageBufferInfo](#) info)
- override void **Release** ()
- override void **Dispose** ()

Additional Inherited Members

3.60 ImageBufferNativeGCHandleSinglePlane Class Reference

Inherits [ImageBufferNative](#), and [IDisposable](#).

Public Member Functions

- **ImageBufferNativeGCHandleSinglePlane** ([ImageBufferNativePool](#)< [ImageBufferNativeGCHandleSinglePlane](#) > pool, [ImageBufferInfo](#) info)
- void **PinPlane** (byte[] plane)
- override void **Release** ()
- override void **Dispose** ()

Additional Inherited Members

3.61 ImageBufferNativePool< T > Class Template Reference

Inherits [ObjectPool](#)< [T](#), [ImageBufferInfo](#) >.

Public Member Functions

- delegate [T](#) **Factory** ([ImageBufferNativePool](#)< [T](#) > pool, [ImageBufferInfo](#) info)
- **ImageBufferNativePool** (int capacity, [Factory](#) factory, string name)
- **ImageBufferNativePool** (int capacity, [Factory](#) factory, string name, [ImageBufferInfo](#) info)

Protected Member Functions

- override [T](#) **createObject** ([ImageBufferInfo](#) info)
- override void **destroyObject** ([T](#) obj)
- override bool **infosMatch** ([ImageBufferInfo](#) i0, [ImageBufferInfo](#) i1)

Additional Inherited Members

3.62 IProcessor< T > Interface Template Reference

Audio Processor interface.

Inherits [IDisposable](#).

Inherited by [AudioUtil.LevelMeter](#)< [T](#) >, [AudioUtil.Resampler](#)< [T](#) >, [AudioUtil.VoiceDetector](#)< [T](#) >, [AudioUtil.VoiceDetectorCalibration](#) and [AudioUtil.VoiceLevelDetectCalibrate](#)< [T](#) >.

Public Member Functions

- `T[] Process (T[] buf)`
Process a frame of audio data.

3.62.1 Detailed Description

Audio Processor interface.

3.62.2 Member Function Documentation

3.62.2.1 `Process()`

```
T [] Process (
    T[] buf )
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implemented in [AudioUtil.VoiceLevelDetectCalibrate< T >](#), [AudioUtil.VoiceDetector< T >](#), [AudioUtil.VoiceDetectorCalibration< T >](#), [AudioUtil.LevelMeter< T >](#), and [AudioUtil.Resampler< T >](#).

3.63 IResettable Interface Reference

Inherited by [AndroidAudioInAEC](#).

Public Member Functions

- `void Reset ()`

3.64 IServiceable Interface Reference

Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).

Inherited by [BufferReaderPushAdapterBase< T >](#).

Public Member Functions

- void [Service](#) ([LocalVoice](#) localVoice)
Service function that should be called regularly.

3.64.1 Detailed Description

Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).

3.64.2 Member Function Documentation

3.64.2.1 Service()

```
void Service (  
    LocalVoice localVoice )
```

Service function that should be called regularly.

Implemented in [BufferReaderPushAdapterAsyncPoolCopy< T >](#), [BufferReaderPushAdapterAsyncPool< T >](#), [BufferReaderPushAdapter< T >](#), and [BufferReaderPushAdapterBase< T >](#).

3.65 AudioUtil.IVoiceDetector Interface Reference

[Voice](#) Activity Detector interface.

Inherited by [AudioUtil.VoiceDetector< T >](#), and [AudioUtil.VoiceDetectorDummy](#).

Properties

- bool [On](#) [get, set]
If true, voice detection enabled.
- float [Threshold](#) [get, set]
Voice detected as soon as signal level exceeds threshold.
- bool [Detected](#) [get]
If true, voice detected.
- DateTime [DetectedTime](#) [get]
Last time when switched to detected state.
- int [ActivityDelayMs](#) [get, set]
Keep detected state during this time after signal level dropped below threshold.

Events

- Action [OnDetected](#)
Called when switched to detected state.

3.65.1 Detailed Description

Voice Activity Detector interface.

3.65.2 Property Documentation

3.65.2.1 ActivityDelayMs

```
int ActivityDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold.

3.65.2.2 Detected

```
bool Detected [get]
```

If true, voice detected.

3.65.2.3 DetectedTime

```
DateTime DetectedTime [get]
```

Last time when switched to detected state.

3.65.2.4 On

```
bool On [get], [set]
```

If true, voice detection enabled.

3.65.2.5 Threshold

```
float Threshold [get], [set]
```

Voice detected as soon as signal level exceeds threshold.

3.65.3 Event Documentation

3.65.3.1 OnDetected

Action OnDetected

Called when switched to detected state.

3.66 IVoiceTransport Interface Reference

Inherited by [LoadBalancingTransport](#).

Public Member Functions

- bool **IsChannelJoined** (int channelId)
- void **SendVoicesInfo** (IEnumerable< [LocalVoice](#) > voices, int channelId, int targetPlayerId)
- void **SendVoiceRemove** ([LocalVoice](#) voice, int channelId, int targetPlayerId)
- void **SendFrame** (ArraySegment< byte > data, FrameFlags flags, byte evNumber, byte voiceId, int channelId, int targetPlayerId, bool reliable, [LocalVoice](#) localVoice)
- string **ChannelIdStr** (int channelId)
- string **PlayerIdStr** (int playerId)

3.67 AudioUtil.LevelMeter< T > Class Template Reference

Audio Level Meter.

Inherits [IProcessor< T >](#), and [AudioUtil.ILevelMeter](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset AccumAvgPeakAmp.
- abstract T[] [Process](#) (T[] buf)
Process a frame of audio data.
- void **Dispose** ()

Protected Attributes

- float **ampSum**
- float **ampPeak**
- int **bufferSize**
- float[] **prevValues**
- int **prevValuesHead**
- float **accumAvgPeakAmpSum**
- int **accumAvgPeakAmpCount**
- float **currentPeakAmp**
- float **norm**

Properties

- float **CurrentAvgAmp** [get]
- float **CurrentPeakAmp** [get, protected set]
- float? **AccumAvgPeakAmp** [get]

3.67.1 Detailed Description

Audio Level Meter.

3.67.2 Member Function Documentation

3.67.2.1 Process()

```
abstract T [] Process (
    T[] buf ) [pure virtual]
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.67.2.2 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset AccumAvgPeakAmp.

Implements [AudioUtil.ILevelMeter](#).

3.68 AudioUtil.LevelMeterDummy Class Reference

Dummy Audio Level Meter that doesn't actually do anything.

Inherits [AudioUtil.ILevelMeter](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset AccumAvgPeakAmp.

Properties

- float **CurrentAvgAmp** [get]
- float **CurrentPeakAmp** [get]
- float **AccumAvgPeakAmp** [get]

3.68.1 Detailed Description

Dummy Audio Level Meter that doesn't actually do anything.

3.68.2 Member Function Documentation

3.68.2.1 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset AccumAvgPeakAmp.

Implements [AudioUtil.ILevelMeter](#).

3.69 AudioUtil.LevelMeterFloat Class Reference

[LevelMeter](#) specialization for float audio.

Inherits [AudioUtil.LevelMeter< float >](#).

Public Member Functions

- [LevelMeterFloat](#) (int samplingRate, int numChannels)
Create new [LevelMeterFloat](#) instance.
- override float[] **Process** (float[] buf)

Additional Inherited Members

3.69.1 Detailed Description

[LevelMeter](#) specialization for float audio.

3.69.2 Constructor & Destructor Documentation

3.69.2.1 LevelMeterFloat()

```
LevelMeterFloat (
    int samplingRate,
    int numChannels )
```

Create new [LevelMeterFloat](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.70 AudioUtil.LevelMeterShort Class Reference

[LevelMeter](#) specialization for short audio.

Inherits [AudioUtil.LevelMeter< short >](#).

Public Member Functions

- [LevelMeterShort](#) (int samplingRate, int numChannels)
Create new [LevelMeterShort](#) instance.
- override short[] **Process** (short[] buf)

Additional Inherited Members

3.70.1 Detailed Description

[LevelMeter](#) specialization for short audio.

3.70.2 Constructor & Destructor Documentation

3.70.2.1 LevelMeterShort()

```
LevelMeterShort (
    int samplingRate,
    int numChannels )
```

Create new [LevelMeterShort](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.71 LoadBalancingFrontend Class Reference

Inherits [LoadBalancingTransport](#).

Additional Inherited Members

3.72 LoadBalancingTransport Class Reference

Extends [LoadBalancingClient](#) with media streaming functionality.

Inherits [LoadBalancingClient](#), [IVoiceTransport](#), [ILogger](#), and [IDisposable](#).

Inherited by [LoadBalancingFrontend](#), and [LoadBalancingTransport2](#).

Public Member Functions

- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)
- bool **IsChannelJoined** (int channelId)
- [LoadBalancingTransport](#) ([ILogger](#) logger=null, [ConnectionProtocol](#) connectionProtocol=[ConnectionProtocol.Udp](#))
Initializes a new [LoadBalancingTransport](#).
- new void [Service](#) ()
This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2 to 20 times a second).
- virtual bool **ChangeAudioGroups** (byte[] groupsToRemove, byte[] groupsToAdd)
- void **SendVoicesInfo** (IEnumerable< [LocalVoice](#) > voices, int channelId, int targetPlayerId)
- void **SendVoiceRemove** ([LocalVoice](#) voice, int channelId, int targetPlayerId)
- virtual void **SendFrame** (ArraySegment< byte > data, [FrameFlags](#) flags, byte evNumber, byte voiceId, int channelId, int targetPlayerId, bool reliable, [LocalVoice](#) localVoice)
- string **ChannelIdStr** (int channelId)
- string **PlayerIdStr** (int playerId)
- void [Dispose](#) ()
Releases all resources used by the [LoadBalancingTransport](#) instance.

Protected Member Functions

- virtual void **onEventActionVoiceClient** (EventData ev)

Protected Attributes

- [VoiceClient](#) **voiceClient**

Properties

- [VoiceClient](#) [VoiceClient](#) [get]

The [VoiceClient](#) implementation associated with this [LoadBalancingTransport](#).

- byte [GlobalAudioGroup](#) [get, set]
- byte [GlobalInterestGroup](#) [get, set]

Set global interest group for this client. This call sets [InterestGroup](#) for existing local voices and for created later to given value. Client set as listening to this group only until [LoadBalancingPeer.OpChangeGroups\(\)](#) called. This method can be called any time.

3.72.1 Detailed Description

Extends [LoadBalancingClient](#) with media streaming functionality.

Use your normal [LoadBalancing](#) workflow to join a [Voice](#) room. All standard [LoadBalancing](#) features are available. Use [VoiceClient](#) to work with media streams.

3.72.2 Constructor & Destructor Documentation

3.72.2.1 [LoadBalancingTransport\(\)](#)

```
LoadBalancingTransport (
    ILogger logger = null,
    ConnectionProtocol connectionProtocol = ConnectionProtocol.Udp )
```

Initializes a new [LoadBalancingTransport](#).

Parameters

<i>logger</i>	ILogger instance. If null, this instance LoadBalancingClient.DebugReturn implementation is used. ConnectionProtocol
<i>connectionProtocol</i>	Connection protocol (UDP or TCP). ConnectionProtocol

3.72.3 Member Function Documentation

3.72.3.1 [Dispose\(\)](#)

```
void Dispose ( )
```

Releases all resources used by the [LoadBalancingTransport](#) instance.

3.72.3.2 Service()

```
new void Service ( )
```

This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2 to 20 times a second).

3.72.4 Property Documentation

3.72.4.1 GlobalInterestGroup

```
byte GlobalInterestGroup [get], [set]
```

Set global interest group for this client. This call sets InterestGroup for existing local voices and for created later to given value. Client set as listening to this group only until LoadBalancingPeer.OpChangeGroups() called. This method can be called any time.

[LocalVoice.InterestGroup](#) LoadBalancingPeer.OpChangeGroups(byte[], byte[])

3.72.4.2 VoiceClient

```
VoiceClient VoiceClient [get]
```

The [VoiceClient](#) implementation associated with this [LoadBalancingTransport](#).

3.73 LoadBalancingTransport2 Class Reference

Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.

Inherits [LoadBalancingTransport](#).

Public Member Functions

- **LoadBalancingTransport2** ([ILogger](#) logger=null, ConnectionProtocol connectionProtocol=Connection↔Protocol.Udp)
- override void **SendFrame** (ArraySegment< byte > data, FrameFlags flags, byte evNumber, byte voiceId, int channelId, int targetPlayerId, bool reliable, [LocalVoice](#) localVoice)

Protected Member Functions

- override void **onEventActionVoiceClient** (EventData ev)

Additional Inherited Members

3.73.1 Detailed Description

Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.

3.74 LocalVoice Class Reference

Represents outgoing data stream.

Inherits [IDisposable](#).

Inherited by [LocalVoiceAudioDummy](#), and [LocalVoiceFramedBase](#).

Public Member Functions

- void **SendSpacingProfileStart** ()
- void [RemoveSelf](#) ()
Remove this voice from it's [VoiceClient](#) (using [VoiceClient.RemoveLocalVoice](#)
- virtual void **Dispose** ()

Static Public Attributes

- const int **DATA_POOL_CAPACITY** = 50

Protected Attributes

- [VoiceInfo](#) **info**
- [IEncoder](#) **encoder**
- [VoiceClient](#) **voiceClient**
- [ArraySegment< byte >](#) **configFrame**
- volatile bool **disposed**
- object **disposeLock** = new object()

Properties

- byte **Group** [get, set]
- byte **InterestGroup** [get, set]
 - If InterestGroup != 0, voice's data is sent only to clients listening to this group (if supported by transport).*
- **VoiceInfo Info** [get]
 - Returns Info structure assigned on local voice cration.*
- bool **TransmitEnabled** [get, set]
 - If true, stream data broadcasted.*
- bool **IsCurrentlyTransmitting** [get]
 - Returns true if stream broadcasts.*
- int **FramesSent** [get]
 - Sent frames counter.*
- int **FramesSentBytes** [get]
 - Sent frames bytes counter.*
- bool **Reliable** [get, set]
 - Send data reliable.*
- bool **Encrypt** [get, set]
 - Send data encrypted.*
- **IServiceable LocalUserServiceable** [get, set]
 - Optional user object attached to [LocalVoice](#). its `Service()` will be called at each [VoiceClient.Service\(\)](#) call.*
- bool **DebugEchoMode** [get, set]
 - If true, outgoing stream routed back to client via server same way as for remote client's streams. Can be swithed any time. `OnRemoteVoiceInfoAction` and `OnRemoteVoiceRemoveAction` are triggered if required. This functionality availability depends on transport.*
- string **SendSpacingProfileDump** [get]
- int **SendSpacingProfileMax** [get]
 - Logs input frames time spacing profiling results. Do not call frequently.*
- byte **ID** [get]
- byte **EvNumber** [get]
- string **shortName** [get]
- string **Name** [get]
- string **LogPrefix** [get]

3.74.1 Detailed Description

Represents outgoing data stream.

3.74.2 Member Function Documentation

3.74.2.1 RemoveSelf()

```
void RemoveSelf ( )
```

Remove this voice from it's [VoiceClient](#) (using [VoiceClient.RemoveLocalVoice](#)

3.74.3 Property Documentation

3.74.3.1 DebugEchoMode

```
bool DebugEchoMode [get], [set]
```

If true, outgoing stream routed back to client via server same way as for remote client's streams. Can be swithed any time. OnRemoteVoiceInfoAction and OnRemoteVoiceRemoveAction are triggered if required. This functionality availability depends on transport.

3.74.3.2 Encrypt

```
bool Encrypt [get], [set]
```

Send data encrypted.

3.74.3.3 FramesSent

```
int FramesSent [get]
```

Sent frames counter.

3.74.3.4 FramesSentBytes

```
int FramesSentBytes [get]
```

Sent frames bytes counter.

3.74.3.5 Info

```
VoiceInfo Info [get]
```

Returns Info structure assigned on local voice cration.

3.74.3.6 InterestGroup

```
byte InterestGroup [get], [set]
```

If InterestGroup != 0, voice's data is sent only to clients listening to this group (if supported by transport).

3.74.3.7 IsCurrentlyTransmitting

```
bool IsCurrentlyTransmitting [get]
```

Returns true if stream broadcasts.

3.74.3.8 LocalUserServiceable

```
IServiceable LocalUserServiceable [get], [set]
```

Optional user object attached to [LocalVoice](#). its Service() will be called at each [VoiceClient.Service\(\)](#) call.

3.74.3.9 Reliable

```
bool Reliable [get], [set]
```

Send data reliable.

3.74.3.10 SendSpacingProfileMax

```
int SendSpacingProfileMax [get]
```

Logs input frames time spacing profiling results. Do not call frequently.

3.74.3.11 TransmitEnabled

```
bool TransmitEnabled [get], [set]
```

If true, stream data broadcasted.

3.75 LocalVoiceAudio< T > Class Template Reference

Outgoing audio stream.

Inherits [LocalVoiceFramed< T >](#), and [ILocalVoiceAudio](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Static Public Member Functions

- static [LocalVoiceAudio< T > Create](#) ([VoiceClient](#) voiceClient, byte voiceld, [IEncoder](#) encoder, [VoiceInfo](#) voiceInfo, [IAudioDesc](#) audioSourceDesc, int channelId)
Create a new [LocalVoiceAudio{T}](#) instance.

Protected Member Functions

- void [initBuiltinProcessors](#) ()

Protected Attributes

- [AudioUtil.VoiceDetector< T >](#) **voiceDetector**
- [AudioUtil.VoiceDetectorCalibration< T >](#) **voiceDetectorCalibration**
- [AudioUtil.LevelMeter< T >](#) **levelMeter**
- int **channels**
- bool **resampleSource**

Properties

- virtual [AudioUtil.IVoiceDetector](#) **VoiceDetector** [get]
- virtual [AudioUtil.ILevelMeter](#) **LevelMeter** [get]
- bool [VoiceDetectorCalibrating](#) [get]
True if the VoiceDetector is currently calibrating.

Additional Inherited Members

3.75.1 Detailed Description

Outgoing audio stream.

3.75.2 Member Function Documentation

3.75.2.1 Create()

```
static LocalVoiceAudio<T> Create (
    VoiceClient voiceClient,
    byte voiceId,
    IEncoder encoder,
    VoiceInfo voiceInfo,
    IAudioDesc audioSourceDesc,
    int channelId ) [static]
```

Create a new [LocalVoiceAudio{T}](#) instance.

Parameters

<i>voiceClient</i>	The VoiceClient to use for this outgoing stream.
<i>voiceId</i>	Numeric ID for this voice.
<i>encoder</i>	Encoder to use for this voice.
<i>voiceInfo</i>	Outgoing stream parameters.
<i>audioSourceDesc</i>	Audio source parameters.
<i>channelId</i>	Voice transport channel ID to use for this voice.

Returns

The new [LocalVoiceAudio{T}](#) instance.

3.75.2.2 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold basing on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration in milliseconds.
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implements [ILocalVoiceAudio](#).

3.75.3 Property Documentation

3.75.3.1 VoiceDetectorCalibrating

bool VoiceDetectorCalibrating [get]

True if the VoiceDetector is currently calibrating.

3.76 LocalVoiceAudioDummy Class Reference

Dummy [LocalVoiceAudio](#)

Inherits [LocalVoice](#), and [ILocalVoiceAudio](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Static Public Attributes

- static [LocalVoiceAudioDummy Dummy](#) = new [LocalVoiceAudioDummy](#)()
A Dummy [LocalVoiceAudio](#) instance.

Properties

- [AudioUtil.IVoiceDetector VoiceDetector](#) [get]
- [AudioUtil.ILevelMeter LevelMeter](#) [get]
- bool [VoiceDetectorCalibrating](#) [get]

Additional Inherited Members

3.76.1 Detailed Description

Dummy [LocalVoiceAudio](#)

For testing, this [LocalVoiceAudio](#) implementation features a [AudioUtil.VoiceDetectorDummy](#) and a [AudioUtil.LevelMeterDummy](#)

3.76.2 Member Function Documentation

3.76.2.1 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (  
    int durationMs,  
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold based on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implements [ILocalVoiceAudio](#).

3.76.3 Member Data Documentation

3.76.3.1 Dummy

```
LocalVoiceAudioDummy Dummy = new LocalVoiceAudioDummy() [static]
```

A Dummy [LocalVoiceAudio](#) instance.

3.77 LocalVoiceAudioFloat Class Reference

Specialization of [LocalVoiceAudio<T>](#) for float audio

Inherits [LocalVoiceAudio< float >](#).

Additional Inherited Members

3.77.1 Detailed Description

Specialization of [LocalVoiceAudio<T>](#) for float audio

3.78 LocalVoiceAudioShort Class Reference

Specialization of [LocalVoiceAudio<T>](#) for short audio

Inherits [LocalVoiceAudio< short >](#).

Additional Inherited Members

3.78.1 Detailed Description

Specialization of [LocalVoiceAudio<T>](#) for short audio

3.79 LocalVoiceFramed< T > Class Template Reference

Typed re-framing [LocalVoice](#)

Inherits [LocalVoiceFramedBase](#).

Inherited by [LocalVoiceAudio< T >](#).

Public Member Functions

- void [AddPostProcessor](#) (params [IProcessor< T >\[\]](#) processors)
Adds processors after any built-in processors and everything added with AddPreProcessor.
- void [AddPreProcessor](#) (params [IProcessor< T >\[\]](#) processors)
Adds processors before built-in processors and everything added with AddPostProcessor.
- void [ClearProcessors](#) ()
Clears all processors in pipeline including built-in resampling. User should add at least resampler processor after call.
- void [PushDataAsync](#) (T[] buf)
Asynchronously push data into this stream.
- void [PushData](#) (T[] buf)
Synchronously push data into this stream.
- override void [Dispose](#) ()
Releases resources used by the LocalVoiceFramed<T> instance. Buffers used for asynchronous push will be disposed in encoder thread's 'finally'.

Protected Member Functions

- T[] [processFrame](#) (T[] buf)

Properties

- [FactoryPrimitiveArrayPool< T > BufferFactory](#) [get]
- bool [PushDataAsyncReady](#) [get]
Whether this [LocalVoiceFramed](#) has capacity for more data buffers to be pushed asynchronously.

Additional Inherited Members

3.79.1 Detailed Description

Typed re-framing [LocalVoice](#)

Consumes data in array buffers of arbitrary length. Repacks them in frames of constant length for further processing and encoding.

3.79.2 Member Function Documentation

3.79.2.1 AddPostProcessor()

```
void AddPostProcessor (
    params IProcessor< T >\[\] processors )
```

Adds processors after any built-in processors and everything added with AddPreProcessor.

Parameters

<i>processors</i>	
-------------------	--

3.79.2.2 AddPreProcessor()

```
void AddPreProcessor (
    params IProcessor< T >[] processors )
```

Adds processors before built-in processors and everything added with AddPostProcessor.

Parameters

<i>processors</i>	
-------------------	--

3.79.2.3 ClearProcessors()

```
void ClearProcessors ( )
```

Clears all processors in pipeline including built-in resampling. User should add at least resampler processor after call.

3.79.2.4 Dispose()

```
override void Dispose ( ) [virtual]
```

Releases resources used by the LocalVoiceFramed<T> instance. Buffers used for asynchronous push will be disposed in encoder thread's 'finally'.

Reimplemented from [LocalVoice](#).

3.79.2.5 PushData()

```
void PushData (
    T[] buf )
```

Synchronously push data into this stream.

3.79.2.6 PushDataAsync()

```
void PushDataAsync (
    T[] buf )
```

Asynchronously push data into this stream.

3.79.3 Property Documentation

3.79.3.1 PushDataAsyncReady

```
bool PushDataAsyncReady [get]
```

Whether this [LocalVoiceFramed](#) has capacity for more data buffers to be pushed asynchronously.

3.80 LocalVoiceFramedBase Class Reference

Typed re-framing [LocalVoice](#)

Inherits [LocalVoice](#).

Inherited by [LocalVoiceFramed< T >](#).

Properties

- int [FrameSize](#) [get]

Data flow will be repacked to frames of this size. May differ from input voiceInfo.FrameSize. Processors should resample in this case.

Additional Inherited Members

3.80.1 Detailed Description

Typed re-framing [LocalVoice](#)

Base class for typed re-framing [LocalVoice](#) implementation ([LocalVoiceFramed<T>](#))

3.80.2 Property Documentation

3.80.2.1 FrameSize

`int FrameSize [get]`

Data flow will be repacked to frames of this size. May differ from input `voiceInfo.FrameSize`. Processors should resample in this case.

3.81 Logger Class Reference

Inherits [ILogger](#).

Public Member Functions

- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)

3.82 MicAmplifier Class Reference

Inherits [VoiceComponent](#).

Properties

- float **AmplificationFactor** [get, set]
- float **BoostValue** [get, set]

Additional Inherited Members

3.83 MicAmplifierFloat Class Reference

Inherits [IProcessor< float >](#).

Public Member Functions

- **MicAmplifierFloat** (float amplificationFactor, float boostValue)
- float[] **Process** (float[] buf)
- void **Dispose** ()

Properties

- float **AmplificationFactor** [get, set]
- float **BoostValue** [get, set]
- float **MaxBefore** [get]
- float **MaxAfter** [get]
- bool **Disabled** [get, set]

3.84 MicAmplifierShort Class Reference

Inherits [IProcessor< short >](#).

Public Member Functions

- **MicAmplifierShort** (short amplificationFactor, short boostValue)
- short[] **Process** (short[] buf)
- void **Dispose** ()

Properties

- short **AmplificationFactor** [get, set]
- short **BoostValue** [get, set]
- short **MaxBefore** [get]
- short **MaxAfter** [get]
- bool **Disabled** [get, set]

3.85 MicrophonePermission Class Reference

Helper to request Microphone permission on Android or iOS.

Inherits [VoiceComponent](#).

Public Member Functions

- void **InitVoice** ()

Protected Member Functions

- override void **Awake** ()

Properties

- bool? **HasPermission** [get]

Events

- static Action< bool > **MicrophonePermissionCallback**

Additional Inherited Members

3.85.1 Detailed Description

Helper to request Microphone permission on Android or iOS.

3.86 MicWrapper Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- **MicWrapper** (string device, int suggestedFrequency, [ILogger](#) logger)
- void **Dispose** ()
- bool **Read** (float[] buffer)

Properties

- int? **SamplingRate** [get]
- int? **Channels** [get]
- string **Error** [get]

3.87 MicWrapperPusher Class Reference

Inherits [IAudioPusher< float >](#).

Public Member Functions

- **MicWrapperPusher** (string device, AudioSource aS, int suggestedFrequency, [ILogger](#) lg, bool destroyOn↵ Stop=true)
- **MicWrapperPusher** (string device, GameObject gO, int suggestedFrequency, [ILogger](#) lg, bool destroyOn↵ Stop=true)
- **MicWrapperPusher** (string device, Transform parentTransform, int suggestedFrequency, [ILogger](#) lg, bool destroyOnStop=true)
- void **SetCallback** (Action< float[] > callback, [ObjectFactory](#)< float[], int > bufferFactory)
- void **Dispose** ()

Properties

- int? **SamplingRate** [get]
- int? **Channels** [get]
- string **Error** [get]

3.88 NativeAndroidMicrophoneSettings Struct Reference

Public Attributes

- bool **AcousticEchoCancellation**
- bool **AutomaticGainControl**
- bool **NoiseSuppression**

3.89 `ObjectFactory< TType, TInfo >` Interface Template Reference

Uniform interface to `ObjectPool<TType, TInfo>` and single reusable object.

Inherits `IDisposable`.

Public Member Functions

- `TType New ()`
- `TType New (TInfo info)`
- `void Free (TType obj)`
- `void Free (TType obj, TInfo info)`

Properties

- `TInfo Info` [get]

3.89.1 Detailed Description

Uniform interface to `ObjectPool<TType, TInfo>` and single reusable object.

Template Parameters

<i>TType</i>	Object type.
<i>TInfo</i>	Type of property used to check 2 objects identity (like integral length of array).

3.90 `ObjectPool< TType, TInfo >` Class Template Reference

Generic Pool to re-use objects of a certain type (`TType`) that optionally match a certain property or set of properties (`TInfo`).

Inherits `IDisposable`.

Public Member Functions

- `ObjectPool` (int capacity, string name)
Create a new `ObjectPool` instance. Does not call `Init()`.
- `ObjectPool` (int capacity, string name, TInfo info)
Create a new `ObjectPool` instance with the given info structure. Calls `Init()`.
- `void Init` (TInfo info)
(Re-)Initializes this `ObjectPool`.
- `TType AcquireOrCreate` ()
Acquire an existing object, or create a new one if none are available.
- `TType AcquireOrCreate` (TInfo info)
Acquire an existing object (if info matches), or create a new one from the passed info.

- virtual bool [Release](#) (TType obj, TInfo objInfo)
Returns object to pool.
- virtual bool [Release](#) (TType obj)
Returns object to pool, or destroys it if the pool is full.
- void [Dispose](#) ()
Free resources associated with this [ObjectPool](#)

Protected Member Functions

- abstract TType **createObject** (TInfo info)
- abstract void **destroyObject** (TType obj)
- abstract bool **infosMatch** (TInfo i0, TInfo i1)

Protected Attributes

- int **capacity**
- TInfo **info**
- int **pos**
- string **name**

Properties

- TInfo [Info](#) [get]
The property (info) that objects in this Pool must match.

3.90.1 Detailed Description

Generic Pool to re-use objects of a certain type (TType) that optionally match a certain property or set of properties (TInfo).

Template Parameters

<i>TType</i>	Object type.
<i>TInfo</i>	Type of parameter used to check 2 objects identity (like integral length of array).

3.90.2 Constructor & Destructor Documentation

3.90.2.1 ObjectPool() [1/2]

```
ObjectPool (
    int capacity,
    string name )
```

Create a new [ObjectPool](#) instance. Does not call [Init\(\)](#).

Parameters

<i>capacity</i>	Capacity (size) of the object pool.
<i>name</i>	Name of the object pool.

3.90.2.2 ObjectPool() [2/2]

```
ObjectPool (
    int capacity,
    string name,
    TInfo info )
```

Create a new [ObjectPool](#) instance with the given info structure. Calls [Init\(\)](#).

Parameters

<i>capacity</i>	Capacity (size) of the object pool.
<i>name</i>	Name of the object pool.
<i>info</i>	Info about this Pool's objects.

3.90.3 Member Function Documentation**3.90.3.1 AcquireOrCreate()** [1/2]

```
TType AcquireOrCreate ( )
```

Acquire an existing object, or create a new one if none are available.

If it fails to get one from the pool, this will create from the info given in this pool's constructor.

3.90.3.2 AcquireOrCreate() [2/2]

```
TType AcquireOrCreate (
    TInfo info )
```

Acquire an existing object (if info matches), or create a new one from the passed info.

Parameters

<i>info</i>	Info structure to match, or create a new object with.
-------------	---

3.90.3.3 Dispose()

```
void Dispose ( )
```

Free resources assoicated with this [ObjectPool](#)

3.90.3.4 Init()

```
void Init (
    TInfo info )
```

(Re-)Initializes this [ObjectPool](#).

If there are objects available in this Pool, they will be destroyed. Allocates (Capacity) new Objects.

Parameters

<i>info</i>	Info about this Pool's objects.
-------------	---------------------------------

3.90.3.5 Release() [1/2]

```
virtual bool Release (
    TType obj ) [virtual]
```

Returns object to pool, or destroys it if the pool is full.

Parameters

<i>obj</i>	The object to return to the pool.
------------	-----------------------------------

3.90.3.6 Release() [2/2]

```
virtual bool Release (
    TType obj,
    TInfo objInfo ) [virtual]
```

Returns object to pool.

Parameters

<i>obj</i>	The object to return to the pool.
<i>objInfo</i>	The info structure about obj.

obj is returned to the pool only if objInfo matches this pool's info. Else, it is destroyed.

3.90.4 Property Documentation

3.90.4.1 Info

`TInfo Info [get]`

The property (info) that objects in this Pool must match.

3.91 OpusCodec Class Reference

Classes

- class [Decoder](#)
- class [DecoderFactory](#)
- class [Encoder](#)
- class [EncoderFloat](#)
- class [EncoderShort](#)
- class [Factory](#)
- class [Util](#)

Public Types

- enum [FrameDuration](#)

Properties

- static string [Version](#) `[get]`

3.92 OpusDecoder< T > Class Template Reference

Inherits [IDisposable](#).

Public Member Functions

- **OpusDecoder** (SamplingRate outputSamplingRateHz, [Channels](#) numChannels)
- `T[] DecodePacket` (ref [FrameBuffer](#) packetData)
- `T[] DecodeEndOfStream` ()
- void **Dispose** ()

Properties

- [Bandwidth](#)? **PreviousPacketBandwidth** [get]

3.93 OpusEncoder Class Reference

Inherits IDisposable.

Public Member Functions

- **OpusEncoder** (SamplingRate inputSamplingRateHz, [Channels](#) numChannels, int bitrate, [OpusApplicationType](#) applicationType, [Delay](#) encoderDelay)
- ArraySegment< byte > **Encode** (float[] pcmSamples)
- ArraySegment< byte > **Encode** (short[] pcmSamples)
- void **Dispose** ()

Static Public Attributes

- const int **BitrateMax** = -1

Properties

- SamplingRate **InputSamplingRate** [get]
- [Channels](#) **InputChannels** [get]
- [Delay](#) **EncoderDelay** [get, set]
Using a duration of less than 10 ms will prevent the encoder from using the LPC or hybrid modes.
- int **FrameSizePerChannel** [get]
- int **Bitrate** [get, set]
- [Bandwidth](#) **MaxBandwidth** [get, set]
- Complexity **Complexity** [get, set]
- int **ExpectedPacketLossPercentage** [get, set]
- [SignalHint](#) **SignalHint** [get, set]
- ForceChannels **ForceChannels** [get, set]
- bool? **UseInbandFEC** [get, set]
- int **PacketLossPercentage** [get, set]
- bool? **UseUnconstrainedVBR** [get, set]
- bool? **DtxEnabled** [get, set]

3.93.1 Property Documentation

3.93.1.1 EncoderDelay

[Delay](#) **EncoderDelay** [get], [set]

Using a duration of less than 10 ms will prevent the encoder from using the LPC or hybrid modes.

3.94 OpusException Class Reference

Inherits [Exception](#).

Public Member Functions

- **OpusException** (OpusStatusCode statusCode, string message)

Properties

- OpusStatusCode **Status Code** [get]

3.95 OpusLib Class Reference

Properties

- static string **Version** [get]

3.96 PhotonVoiceCreatedParams Class Reference

Inherited by [Recorder.PhotonVoiceCreatedParams](#).

Properties

- [Voice.LocalVoice](#) **Voice** [get, set]
- [Voice.IAudioDesc](#) **AudioDesc** [get, set]

3.97 Recorder.PhotonVoiceCreatedParams Class Reference

Inherits [PhotonVoiceCreatedParams](#).

Additional Inherited Members

3.98 PhotonVoiceLagSimulationGui Class Reference

Inherits [MonoBehaviour](#).

Public Member Functions

- void **OnEnable** ()

3.99 PhotonVoiceNetwork Class Reference

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also sets a custom [PUN](#) Speaker factory to find the Speaker component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the PhotonView of your player's prefab.

Inherits [VoiceConnection](#).

Public Member Functions

- bool [ConnectAndJoinRoom](#) ()
Connect voice client to [Photon](#) servers and join a [Voice](#) room
- void [Disconnect](#) ()
Disconnect voice client from all [Photon](#) servers

Public Attributes

- bool [AutoConnectAndJoin](#) = true
Auto connect voice client and join a voice room when [PUN](#) client is joined to a [PUN](#) room
- bool [AutoLeaveAndDisconnect](#) = true
Auto disconnect voice client when [PUN](#) client is not joined to a [PUN](#) room
- bool [WorkInOfflineMode](#) = true
Whether or not [Photon Voice](#) client should follow [PUN](#) client if the latter is in offline mode.

Static Public Attributes

- const string [VoiceRoomNameSuffix](#) = "_voice_"
Suffix for voice room names appended to [PUN](#) room names.

Protected Member Functions

- override void **Awake** ()
- override void **OnDisable** ()
- override void **OnDestroy** ()
- override void **OnVoiceStateChanged** ([ClientState](#) fromState, [ClientState](#) toState)
- override [Speaker](#) **SimpleSpeakerFactory** (int playerId, byte voiceId, object userData)

Properties

- static [PhotonVoiceNetwork](#) [Instance](#) [get, set]
Singleton instance for [PhotonVoiceNetwork](#)
- bool [UsePunAuthValues](#) [get, set]
Whether or not to use the same [PhotonNetwork.AuthValues](#) in [PhotonVoiceNetwork.Instance.Client.AuthValues](#). This means that the same [UserID](#) will be used in both clients. If custom authentication is used and setup in [PUN](#) app, the same configuration should be done for the [Voice](#) app.

Additional Inherited Members

3.99.1 Detailed Description

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also sets a custom [PUN](#) Speaker factory to find the Speaker component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the PhotonView of your player's prefab.

3.99.2 Member Function Documentation

3.99.2.1 ConnectAndJoinRoom()

```
bool ConnectAndJoinRoom ( )
```

Connect voice client to [Photon](#) servers and join a [Voice](#) room

Returns

If true, connection command send from client

3.99.2.2 Disconnect()

```
void Disconnect ( )
```

Disconnect voice client from all [Photon](#) servers

3.99.3 Member Data Documentation

3.99.3.1 AutoConnectAndJoin

```
bool AutoConnectAndJoin = true
```

Auto connect voice client and join a voice room when [PUN](#) client is joined to a [PUN](#) room

3.99.3.2 AutoLeaveAndDisconnect

```
bool AutoLeaveAndDisconnect = true
```

Auto disconnect voice client when [PUN](#) client is not joined to a [PUN](#) room

3.99.3.3 VoiceRoomNameSuffix

```
const string VoiceRoomNameSuffix = "_voice_" [static]
```

Suffix for voice room names appended to [PUN](#) room names.

3.99.3.4 WorkInOfflineMode

```
bool WorkInOfflineMode = true
```

Whether or not [Photon Voice](#) client should follow [PUN](#) client if the latter is in offline mode.

3.99.4 Property Documentation

3.99.4.1 Instance

```
PhotonVoiceNetwork Instance [static], [get], [set]
```

Singleton instance for [PhotonVoiceNetwork](#)

3.99.4.2 UsePunAuthValues

```
bool UsePunAuthValues [get], [set]
```

Whether or not to use the same [PhotonNetwork.AuthValues](#) in [PhotonVoiceNetwork.Instance.Client.AuthValues](#). This means that the same [UserID](#) will be used in both clients. If custom authentication is used and setup in [PUN](#) app, the same configuration should be done for the [Voice](#) app.

3.100 PhotonVoiceStatsGui Class Reference

Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.

Inherits [MonoBehaviour](#).

3.100.1 Detailed Description

Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.

The shown health values can help identify problems with connection losses or performance. Example: If the time delta between two consecutive `SendOutgoingCommands` calls is a second or more, chances rise for a disconnect being caused by this (because acknowledgments to the server need to be sent in due time).

3.101 PhotonVoiceView Class Reference

Component that should be attached to a networked [PUN](#) prefab that has [PhotonView](#). It will bind remote Recorder with local Speaker of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

Inherits [VoiceComponent](#).

Public Member Functions

- void [Init](#) ()
Initializes this [PhotonVoiceView](#) for [Voice](#) usage based on the [PhotonView](#), [Recorder](#) and [Speaker](#) components.

Public Attributes

- bool [AutoCreateRecorderIfNotFound](#)
If true, a [Recorder](#) component will be added to the same [GameObject](#) if not found already.
- bool [UsePrimaryRecorder](#)
If true, [PhotonVoiceNetwork.PrimaryRecorder](#) will be used by this [PhotonVoiceView](#)
- bool [SetupDebugSpeaker](#)
If true, a [Speaker](#) component will be setup to be used for the [DebugEcho](#) mode

Protected Member Functions

- override void [Awake](#) ()

Properties

- [Recorder](#) [RecorderInUse](#) [get, set]
The [Recorder](#) component currently used by this [PhotonVoiceView](#)
- [Speaker](#) [SpeakerInUse](#) [get, set]
The [Speaker](#) component currently used by this [PhotonVoiceView](#)
- bool [IsSetup](#) [get]
If true, this [PhotonVoiceView](#) is setup and ready to be used
- bool [IsSpeaker](#) [get]
If true, this [PhotonVoiceView](#) has a [Speaker](#) setup for playback of received audio frames from remote audio source
- bool [IsSpeaking](#) [get]
If true, this [PhotonVoiceView](#) has a [Speaker](#) that is currently playing received audio frames from remote audio source
- bool [IsRecorder](#) [get]
If true, this [PhotonVoiceView](#) has a [Recorder](#) setup for transmission of audio stream from local audio source
- bool [IsRecording](#) [get]
If true, this [PhotonVoiceView](#) has a [Recorder](#) that is currently transmitting audio stream from local audio source
- bool [IsSpeakerLinked](#) [get]
If true, the [SpeakerInUse](#) is linked to the remote voice stream
- bool [IsPhotonViewReady](#) [get]
If true, the [PhotonView](#) attached to the same [GameObject](#) has a valid [ViewID](#) > 0

Additional Inherited Members

3.101.1 Detailed Description

Component that should be attached to a networked [PUN](#) prefab that has PhotonView. It will bind remote Recorder with local Speaker of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

3.101.2 Member Function Documentation

3.101.2.1 Init()

```
void Init ( )
```

Initializes this [PhotonVoiceView](#) for [Voice](#) usage based on the PhotonView, Recorder and Speaker components.

The initialization should happen automatically. Call this method explicitly if this does not succeed. The initialization is a two steps operation: step one is the setup of Recorder and Speaker to be used. Step two is the late-linking -if needed- of the SpeakerInUse and corresponding remote voice info -if any- via ViewID.

3.101.3 Member Data Documentation

3.101.3.1 AutoCreateRecorderIfNotFound

```
bool AutoCreateRecorderIfNotFound
```

If true, a Recorder component will be added to the same GameObject if not found already.

3.101.3.2 SetupDebugSpeaker

```
bool SetupDebugSpeaker
```

If true, a Speaker component will be setup to be used for the DebugEcho mode

3.101.3.3 UsePrimaryRecorder

```
bool UsePrimaryRecorder
```

If true, [PhotonVoiceNetwork.PrimaryRecorder](#) will be used by this [PhotonVoiceView](#)

3.101.4 Property Documentation

3.101.4.1 IsPhotonViewReady

```
bool IsPhotonViewReady [get]
```

If true, the PhotonView attached to the same GameObject has a valid ViewID > 0

3.101.4.2 IsRecorder

```
bool IsRecorder [get]
```

If true, this [PhotonVoiceView](#) has a Recorder setup for transmission of audio stream from local audio source

3.101.4.3 IsRecording

```
bool IsRecording [get]
```

If true, this [PhotonVoiceView](#) has a Recorder that is currently transmitting audio stream from local audio source

3.101.4.4 IsSetup

```
bool IsSetup [get]
```

If true, this [PhotonVoiceView](#) is setup and ready to be used

3.101.4.5 IsSpeaker

```
bool IsSpeaker [get]
```

If true, this [PhotonVoiceView](#) has a Speaker setup for playback of received audio frames from remote audio source

3.101.4.6 IsSpeakerLinked

```
bool IsSpeakerLinked [get]
```

If true, the SpeakerInUse is linked to the remote voice stream

3.101.4.7 IsSpeaking

```
bool IsSpeaking [get]
```

If true, this [PhotonVoiceView](#) has a Speaker that is currently playing received audio frames from remote audio source

3.101.4.8 RecorderInUse

```
Recorder RecorderInUse [get], [set]
```

The Recorder component currently used by this [PhotonVoiceView](#)

3.101.4.9 SpeakerInUse

```
Speaker SpeakerInUse [get], [set]
```

The Speaker component currently used by this [PhotonVoiceView](#)

3.102 ImageBufferNative.PlaneSet Struct Reference

Public Member Functions

- **PlaneSet** (int length, IntPtr p0=default(IntPtr), IntPtr p1=default(IntPtr), IntPtr p2=default(IntPtr), IntPtr p3=default(IntPtr))

Properties

- IntPtr **this[int key]** [get, set]
- int **Length** [get]

3.103 Platform Class Reference

Static Public Member Functions

- static [IDeviceEnumerator](#) **CreateAudioInEnumerator** ([ILogger](#) logger)
- static [IAudioInChangeNotifier](#) **CreateAudioInChangeNotifier** (Action callback, [ILogger](#) logger)
- static [IEncoder](#) **CreateDefaultAudioEncoder**< T > ([ILogger](#) logger, [VoiceInfo](#) info)
- static [IAudioDesc](#) **CreateDefaultAudioSource** ([ILogger](#) logger, [DeviceInfo](#) dev, int samplingRate, int channels, object otherParams=null)

3.104 PlaybackDelaySettings Struct Reference

Playback delay configuration container.

Public Member Functions

- override string **ToString** ()

Public Attributes

- int [MinDelaySoft](#)
ms: Audio player tries to keep the delay above this value.
- int [MaxDelaySoft](#)
ms: Audio player tries to keep the delay below this value.
- int [MaxDelayHard](#)
ms: Audio player guarantees that the delay never exceeds this value.

Static Public Attributes

- const int **DEFAULT_LOW** = 200
- const int **DEFAULT_HIGH** = 400
- const int **DEFAULT_MAX** = 1000

3.104.1 Detailed Description

Playback delay configuration container.

3.104.2 Member Data Documentation

3.104.2.1 MaxDelayHard

`int MaxDelayHard`

ms: Audio player guarantees that the delay never exceeds this value.

3.104.2.2 MaxDelaySoft

`int MaxDelaySoft`

ms: Audio player tries to keep the delay below this value.

3.104.2.3 MinDelaySoft

`int MinDelaySoft`

ms: Audio player tries to keep the delay above this value.

3.105 AudioOutDelayControl.PlayDelayConfig Class Reference

Public Member Functions

- [PlayDelayConfig Clone](#) ()

Properties

- `int` **Low** [get, set]
- `int` **High** [get, set]
- `int` **Max** [get, set]
- `int` **SpeedUpPerc** [get, set]

3.106 PrimitiveArrayPool< T > Class Template Reference

Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.

Inherits [ObjectPool< T\[\], int >](#).

Public Member Functions

- **PrimitiveArrayPool** (int capacity, string name)
- **PrimitiveArrayPool** (int capacity, string name, int info)

Protected Member Functions

- override `T[]` **createObject** (int info)
- override void **destroyObject** (`T[]` obj)
- override bool **infosMatch** (int i0, int i1)

Additional Inherited Members

3.106.1 Detailed Description

Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.107 RawCodec Class Reference

Classes

- class [Decoder](#)
- class [Encoder](#)
- class [ShortToFloat](#)

3.108 Recorder Class Reference

Component representing outgoing audio stream in scene.

Inherits [VoiceComponent](#).

Classes

- class [PhotonVoiceCreatedParams](#)

Public Types

- enum **InputSourceType**
- enum **MicType**
- enum **SampleTypeConv**

Public Member Functions

- void [Init](#) ([VoiceConnection](#) connection)
Initializes the [Recorder](#) component to be able to transmit audio.
- void **ReInit** ()
- void [RestartRecording](#) (bool force=false)
Restarts recording if something has changed that requires this.
- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > detectionEndedCallback=null)
Trigger voice detector calibration process. While calibrating, keep silence. [Voice](#) detector sets threshold basing on measured background noise level.
- void [StartRecording](#) ()
Starts recording.
- void [StopRecording](#) ()
Stops recording.
- bool [ResetLocalAudio](#) ()
Resets audio session and parameters locally to fix broken recording due to system configuration modifications or audio interruptions or audio routing changes.

Static Public Member Functions

- static bool **CompareUnityMicNames** (string mic1, string mic2)
- static bool **IsDefaultUnityMic** (string mic)
- static bool **CheckIfMicrophoneIdIsValid** ([IDeviceEnumerator](#) audioInEnumerator, int id)

Static Public Attributes

- const int **MIN_OPUS_BITRATE** = 6000
- const int **MAX_OPUS_BITRATE** = 510000

Protected Member Functions

- virtual void **SendPhotonVoiceCreatedMessage** ()

Properties

- static [IDeviceEnumerator](#) **PhotonMicrophoneEnumerator** [get]
Enumerator for the available microphone devices gathered by the [Photon](#) plugin.
- bool **IsInitialized** [get]
If true, this [Recorder](#) has been initialized and is ready to transmit to remote clients. Otherwise call [Init\(VoiceConnection\)](#).
- bool **RequiresInit** [get]
- bool **RequiresRestart** [get, protected set]
Returns true if something has changed in the [Recorder](#) while recording that won't take effect unless recording is restarted using [RestartRecording](#).
- bool **TransmitEnabled** [get, set]
If true, audio transmission is enabled.
- bool **Encrypt** [get, set]
If true, voice stream is sent encrypted.
- bool **DebugEchoMode** [get, set]
If true, outgoing stream routed back to client via server same way as for remote client's streams.
- bool **ReliableMode** [get, set]
If true, stream data sent in reliable mode.
- bool **VoiceDetection** [get, set]
If true, voice detection enabled.
- float **VoiceDetectionThreshold** [get, set]
Voice detection threshold (0..1, where 1 is full amplitude).
- int **VoiceDetectionDelayMs** [get, set]
Keep detected state during this time after signal level dropped below threshold. Default is 500ms
- object **UserData** [get, set]
Custom user object to be sent in the voice stream info event.
- Func< [IAudioDesc](#) > **InputFactory** [get, set]
Set the method returning new [Voice.IAudioDesc](#) instance to be assigned to a new voice created with Source set to Factory
- [AudioUtil.IVoiceDetector?](#) **VoiceDetector** [get]
Returns voice activity detector for recorder's audio stream.
- string **UnityMicrophoneDevice** [get, set]
Set or get [Unity](#) microphone device used for streaming.
- int **PhotonMicrophoneDeviceId** [get, set]

- Set or get photon microphone device used for streaming.*

 - byte [AudioGroup](#) [get, set]

Target interest group that will receive transmitted audio.
- byte [InterestGroup](#) [get, set]

Target interest group that will receive transmitted audio.
- bool [IsCurrentlyTransmitting](#) [get]

Returns true if audio stream broadcasts.
- [AudioUtil.ILevelMeter?](#) [LevelMeter](#) [get]

Level meter utility.
- bool [VoiceDetectorCalibrating](#) [get]

If true, voice detector calibration is in progress.
- [ILocalVoiceAudio](#) [voiceAudio](#) [get]
- InputSourceType [SourceType](#) [get, set]

Audio data source.
- MicType [MicrophoneType](#) [get, set]

Which microphone API to use when the Source is set to Microphone.
- SampleTypeConv [TypeConvert](#) [get, set]

Force creation of 'short' pipeline and convert audio data to short for 'float' audio sources.
- AudioClip [AudioClip](#) [get, set]

Source audio clip.
- bool [LoopAudioClip](#) [get, set]

Loop playback for audio clip sources.
- SamplingRate [SamplingRate](#) [get, set]

Outgoing audio stream sampling rate.
- OpusCodec.FrameDuration [FrameDuration](#) [get, set]

Outgoing audio stream encoder delay.
- int [Bitrate](#) [get, set]

Outgoing audio stream bitrate.
- bool [IsRecording](#) [get, set]

Gets or sets whether this [Recorder](#) is actively recording audio to be transmitted.
- bool [ReactOnSystemChanges](#) [get, set]

If true, the [Recorder](#) will automatically restart recording to recover from audio device changes.
- bool [AutoStart](#) [get, set]

If true, automatically start recording when initialized.
- bool [RecordOnlyWhenEnabled](#) [get, set]

If true, component will work only when enabled and active in hierarchy.
- bool [SkipDeviceChangeChecks](#) [get, set]

If true, restarts recording without checking if audio config/device changes affected recording.
- bool [StopRecordingWhenPaused](#) [get, set]

If true, stop recording when paused resume/restart when un-paused.
- bool [UseOnAudioFilterRead](#) [get, set]

If true, recording will make use of [Unity](#)'s OnAudioFiltterRead callback from a muted local AudioSource.
- bool [TrySamplingRateMatch](#) [get, set]

If true, [Recorder](#) will try to match sampling rates of microphone device and Opus encoder to avoid re sampling of audio input.
- bool [UseMicrophoneTypeFallback](#) [get, set]

If true, if recording fails to start with [Unity](#) microphone type, [Photon](#) microphone type is used -if available- as a fallback and vice versa.
- bool [RecordOnlyWhenJoined](#) [get, set]

If true, recording can start only when client is joined to a room. Auto start is also delayed until client is joined to a room.
- [IDeviceEnumerator](#) [MicrophonesEnumerator](#) [get]
- [DeviceInfo](#) [MicrophoneDevice](#) [get, set]

Additional Inherited Members

3.108.1 Detailed Description

Component representing outgoing audio stream in scene.

3.108.2 Member Function Documentation

3.108.2.1 Init()

```
void Init (
    VoiceConnection connection )
```

Initializes the [Recorder](#) component to be able to transmit audio.

Parameters

<i>connection</i>	The VoiceConnection to be used with this Recorder .
-------------------	---

3.108.2.2 ResetLocalAudio()

```
bool ResetLocalAudio ( )
```

Resets audio session and parameters locally to fix broken recording due to system configuration modifications or audio interruptions or audio routing changes.

Returns

If reset is done.

3.108.2.3 RestartRecording()

```
void RestartRecording (
    bool force = false )
```

Restarts recording if something has changed that requires this.

Parameters

<i>force</i>	Set to true if you want to restart even if this is not required (RequiresRestart = false)
--------------	---

3.108.2.4 StartRecording()

```
void StartRecording ( )
```

Starts recording.

3.108.2.5 StopRecording()

```
void StopRecording ( )
```

Stops recording.

3.108.2.6 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > detectionEndedCallback = null )
```

Trigger voice detector calibration process. While calibrating, keep silence. [Voice](#) detector sets threshold basing on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration in milliseconds.
<i>detectionEndedCallback</i>	Callback when VAD calibration ends.

3.108.3 Property Documentation

3.108.3.1 AudioClip

```
AudioClip AudioClip [get], [set]
```

Source audio clip.

3.108.3.2 AudioGroup

```
byte AudioGroup [get], [set]
```

Target interest group that will receive transmitted audio.

If AudioGroup != 0, recorder's audio data is sent only to clients listening to this group.

3.108.3.3 AutoStart

```
bool AutoStart [get], [set]
```

If true, automatically start recording when initialized.

3.108.3.4 Bitrate

```
int Bitrate [get], [set]
```

Outgoing audio stream bitrate.

3.108.3.5 DebugEchoMode

```
bool DebugEchoMode [get], [set]
```

If true, outgoing stream routed back to client via server same way as for remote client's streams.

3.108.3.6 Encrypt

```
bool Encrypt [get], [set]
```

If true, voice stream is sent encrypted.

3.108.3.7 FrameDuration

```
OpusCodec.FrameDuration FrameDuration [get], [set]
```

Outgoing audio stream encoder delay.

3.108.3.8 InputFactory

```
Func<IAudioDesc> InputFactory [get], [set]
```

Set the method returning new [Voice.IAudioDesc](#) instance to be assigned to a new voice created with Source set to Factory

3.108.3.9 InterestGroup

```
byte InterestGroup [get], [set]
```

Target interest group that will receive transmitted audio.

If InterestGroup != 0, recorder's audio data is sent only to clients listening to this group.

3.108.3.10 IsCurrentlyTransmitting

```
bool IsCurrentlyTransmitting [get]
```

Returns true if audio stream broadcasts.

3.108.3.11 IsInitialized

```
bool IsInitialized [get]
```

If true, this [Recorder](#) has been initialized and is ready to transmit to remote clients. Otherwise call [Init\(VoiceConnection\)](#).

3.108.3.12 IsRecording

```
bool IsRecording [get], [set]
```

Gets or sets whether this [Recorder](#) is actively recording audio to be transmitted.

3.108.3.13 LevelMeter

```
AudioUtil.ILevelMeter? LevelMeter [get]
```

Level meter utility.

3.108.3.14 LoopAudioClip

```
bool LoopAudioClip [get], [set]
```

Loop playback for audio clip sources.

3.108.3.15 MicrophoneType

```
MicType MicrophoneType [get], [set]
```

Which microphone API to use when the Source is set to Microphone.

3.108.3.16 PhotonMicrophoneDeviceId

```
int PhotonMicrophoneDeviceId [get], [set]
```

Set or get photon microphone device used for streaming.

3.108.3.17 PhotonMicrophoneEnumerator

```
IDeviceEnumerator PhotonMicrophoneEnumerator [static], [get]
```

Enumerator for the available microphone devices gathered by the [Photon](#) plugin.

3.108.3.18 ReactOnSystemChanges

```
bool ReactOnSystemChanges [get], [set]
```

If true, the [Recorder](#) will automatically restart recording to recover from audio device changes.

By default, the [Recorder](#) will restart recording only when the [Recorder.SourceType](#) is `InputSourceType.Microphone` and the device being used is no longer available or valid, in some cases you may need to force restarts even if the device in use did not change. To enable this set [Recorder.SkipDeviceChangeChecks](#) to true.

3.108.3.19 RecordOnlyWhenEnabled

```
bool RecordOnlyWhenEnabled [get], [set]
```

If true, component will work only when enabled and active in hierarchy.

3.108.3.20 RecordOnlyWhenJoined

```
bool RecordOnlyWhenJoined [get], [set]
```

If true, recording can start only when client is joined to a room. Auto start is also delayed until client is joined to a room.

3.108.3.21 ReliableMode

```
bool ReliableMode [get], [set]
```

If true, stream data sent in reliable mode.

3.108.3.22 RequiresRestart

```
bool RequiresRestart [get], [protected set]
```

Returns true if something has changed in the [Recorder](#) while recording that won't take effect unless recording is restarted using [RestartRecording](#).

Think of this as a "isDirty" flag.

3.108.3.23 SamplingRate

```
SamplingRate SamplingRate [get], [set]
```

Outgoing audio stream sampling rate.

3.108.3.24 SkipDeviceChangeChecks

```
bool SkipDeviceChangeChecks [get], [set]
```

If true, restarts recording without checking if audio config/device changes affected recording.

To be used when [Recorder.ReactOnSystemChanges](#) is true.

3.108.3.25 SourceType

```
InputSourceType SourceType [get], [set]
```

Audio data source.

3.108.3.26 StopRecordingWhenPaused

```
bool StopRecordingWhenPaused [get], [set]
```

If true, stop recording when paused resume/restart when un-paused.

3.108.3.27 TransmitEnabled

```
bool TransmitEnabled [get], [set]
```

If true, audio transmission is enabled.

3.108.3.28 TrySamplingRateMatch

```
bool TrySamplingRateMatch [get], [set]
```

If true, [Recorder](#) will try to match sampling rates of microphone device and Opus encoder to avoid re sampling of audio input.

3.108.3.29 TypeConvert

```
SampleTypeConv TypeConvert [get], [set]
```

Force creation of 'short' pipeline and convert audio data to short for 'float' audio sources.

3.108.3.30 UnityMicrophoneDevice

```
string UnityMicrophoneDevice [get], [set]
```

Set or get [Unity](#) microphone device used for streaming.

3.108.3.31 UseMicrophoneTypeFallback

```
bool UseMicrophoneTypeFallback [get], [set]
```

If true, if recording fails to start with [Unity](#) microphone type, [Photon](#) microphone type is used -if available- as a fallback and vice versa.

3.108.3.32 UseOnAudioFilterRead

```
bool UseOnAudioFilterRead [get], [set]
```

If true, recording will make use of [Unity](#)'s OnAudioFiltlerRead callback from a muted local AudioSource.

If enabled, 3D sounds and voice positioning can be lost.

3.108.3.33 UserData

```
object UserData [get], [set]
```

Custom user object to be sent in the voice stream info event.

3.108.3.34 VoiceDetection

```
bool VoiceDetection [get], [set]
```

If true, voice detection enabled.

3.108.3.35 VoiceDetectionDelayMs

```
int VoiceDetectionDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold. Default is 500ms

3.108.3.36 VoiceDetectionThreshold

```
float VoiceDetectionThreshold [get], [set]
```

[Voice](#) detection threshold (0..1, where 1 is full amplitude).

3.108.3.37 VoiceDetector

```
AudioUtil.IVoiceDetector? VoiceDetector [get]
```

Returns voice activity detector for recorder's audio stream.

3.108.3.38 VoiceDetectorCalibrating

```
bool VoiceDetectorCalibrating [get]
```

If true, voice detector calibration is in progress.

3.109 RemoteVoiceInfo Class Reference

Information about a remote voice (incoming stream).

Properties

- [VoiceInfo Info](#) [get]
Remote voice info.
- int [ChannelId](#) [get]
ID of channel used for transmission.
- int [PlayerId](#) [get]
Player ID of voice owner.
- byte [Voiceld](#) [get]
Voice ID (unique in the room).

3.109.1 Detailed Description

Information about a remote voice (incoming stream).

3.109.2 Property Documentation

3.109.2.1 ChannelId

```
int ChannelId [get]
```

ID of channel used for transmission.

3.109.2.2 Info

```
VoiceInfo Info [get]
```

Remote voice info.

3.109.2.3 PlayerId

```
int PlayerId [get]
```

Player ID of voice owner.

3.109.2.4 VoiceId

```
byte VoiceId [get]
```

Voice ID (unique in the room).

3.110 RemoteVoiceLink Class Reference

Inherits `IEquatable< RemoteVoiceLink >`.

Public Member Functions

- **RemoteVoiceLink** ([VoiceInfo](#) info, int playerId, int voiceId, int channelId)
- void **Init** (ref [RemoteVoiceOptions](#) options)
- override string **ToString** ()
- bool **Equals** ([RemoteVoiceLink](#) other)

Public Attributes

- readonly [VoiceInfo](#) **Info**
- readonly int **PlayerId**
- readonly int **VoiceId**
- readonly int **ChannelId**

Events

- Action< [FrameOut](#)< float > > **FloatFrameDecoded**
- Action **RemoteVoiceRemoved**

3.111 RemoteVoiceOptions Struct Reference

Event Actions and other options for a remote voice (incoming stream).

Public Member Functions

- **RemoteVoiceOptions** (ILogger logger, string logPrefix, VoiceInfo voiceInfo)
- void **SetOutput** (Action< FrameOut< float >> output)
Create default audio decoder and register a method to be called when a data frame is decoded.
- void **SetOutput** (Action< FrameOut< short >> output)
Create default audio decoder and register a method to be called when a data frame is decoded.

Properties

- Action **OnRemoteVoiceRemoveAction** [get, set]
Register a method to be called when the remote voice is removed.
- **IDecoder Decoder** [get, set]
Remote voice data decoder. Use to set decoder options or override it with user decoder.

3.111.1 Detailed Description

Event Actions and other options for a remote voice (incoming stream).

3.111.2 Member Function Documentation

3.111.2.1 SetOutput() [1/2]

```
void SetOutput (
    Action< FrameOut< float >> output )
```

Create default audio decoder and register a method to be called when a data frame is decoded.

3.111.2.2 SetOutput() [2/2]

```
void SetOutput (
    Action< FrameOut< short >> output )
```

Create default audio decoder and register a method to be called when a data frame is decoded.

3.111.3 Property Documentation

3.111.3.1 Decoder

`IDecoder` `Decoder` `[get]`, `[set]`

Remote voice data decoder. Use to set decoder options or override it with user decoder.

3.111.3.2 OnRemoteVoiceRemoveAction

`Action` `OnRemoteVoiceRemoveAction` `[get]`, `[set]`

Register a method to be called when the remote voice is removed.

3.112 AudioUtil.Resampler< T > Class Template Reference

Sample-rate conversion Audio Processor.

Inherits `IProcessor< T >`.

Public Member Functions

- `Resampler` (int dstSize, int channels)
Create a new `Resampler` instance.
- `T[] Process` (T[] buf)
Process a frame of audio data.
- void `Dispose` ()

Protected Attributes

- `T[] frameResampled`

3.112.1 Detailed Description

Sample-rate conversion Audio Processor.

This processor converts the sample-rate of the source stream. Internally, it uses `AudioUtil.Resample<T>(T[], T[], int, int)`.

3.112.2 Constructor & Destructor Documentation

3.112.2.1 Resampler()

```
Resampler (
    int dstSize,
    int channels )
```

Create a new `Resampler` instance.

Parameters

<i>dstSize</i>	Frame size of a destination frame. Determines output rate.
<i>channels</i>	Number of audio channels expected in both in- and output.

3.112.3 Member Function Documentation

3.112.3.1 Process()

```
T [ ] Process (
    T [ ] buf )
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.113 SaveIncomingStreamToFile Class Reference

Inherits [VoiceComponent](#).

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.114 SaveOutgoingStreamToFile Class Reference

Inherits [VoiceComponent](#).

Additional Inherited Members

3.115 RawCodec.ShortToFloat Class Reference

Public Member Functions

- **ShortToFloat** (Action< [FrameOut](#)< float >> output)
- void **Output** ([FrameOut](#)< short > shortBuf)

3.116 Speaker Class Reference

Component representing remote audio stream in local scene.

Inherits [VoiceComponent](#).

Public Member Functions

- bool [StartPlayback](#) ()
Starts the audio playback of the linked incoming remote audio stream via AudioSource component.
- bool [StopPlayback](#) ()
Stops the audio playback of the linked incoming remote audio stream via AudioSource component.
- bool [RestartPlayback](#) (bool reinit=false)
Restarts the audio playback of the linked incoming remote audio stream via AudioSource component.
- bool [SetPlaybackDelaySettings](#) ([PlaybackDelaySettings](#) pdc)
Sets the settings for the playback behaviour in case of delays.
- bool [SetPlaybackDelaySettings](#) (int low, int high, int max)
Sets the settings for the playback behaviour in case of delays.

Public Attributes

- Func< [IAudioOut](#)< float > > [CustomAudioOutFactory](#)
A custom factory method to return [IAudioOut<float>](#) implementation used for the playback.

Properties

- int **PlayDelayMs** [get, set]
- bool [IsPlaying](#) [get]
Is the speaker playing right now.
- int? [Lag](#) [get]
Smoothed difference between (jittering) stream and (clock-driven) audioOutput.
- Action< [Speaker](#) > [OnRemoteVoiceRemoveAction](#) [get, set]
Register a method to be called when remote voice removed.
- Realtime.Player [Actor](#) [get, set]
Per room, the connected users/players are represented with a Realtime.Player, also known as Actor.
- bool [IsLinked](#) [get]
Whether or not this [Speaker](#) has been linked to a remote voice stream.

- bool [PlaybackOnlyWhenEnabled](#) [get, set]
If true, component will work only when enabled and active in hierarchy.
- bool [PlaybackStarted](#) [get]
Returns if the playback is on.
- int [PlaybackDelayMinSoft](#) [get]
Gets the value in ms above which the audio player tries to keep the delay.
- int [PlaybackDelayMaxSoft](#) [get]
Gets the value in ms below which the audio player tries to keep the delay.
- int [PlaybackDelayMaxHard](#) [get]
Gets the value in ms that audio play delay will not exceed.

Additional Inherited Members

3.116.1 Detailed Description

Component representing remote audio stream in local scene.

3.116.2 Member Function Documentation

3.116.2.1 RestartPlayback()

```
bool RestartPlayback (
    bool reinit = false )
```

Restarts the audio playback of the linked incoming remote audio stream via AudioSource component.

Parameters

<i>reinit</i>	If true, player will be reinitialized.
---------------	--

Returns

True if playback is successfully restarted.

3.116.2.2 SetPlaybackDelaySettings() [1/2]

```
bool SetPlaybackDelaySettings (
    int low,
    int high,
    int max )
```

Sets the settings for the playback behaviour in case of delays.

Parameters

<i>low</i>	In milliseconds, audio player tries to keep the playback delay above this value.
<i>high</i>	In milliseconds, audio player tries to keep the playback below above this value.
<i>max</i>	In milliseconds, audio player guarantees that the playback delay never exceeds this value.

Returns

If a change has been made.

3.116.2.3 SetPlaybackDelaySettings() [2/2]

```
bool SetPlaybackDelaySettings (
    PlaybackDelaySettings pdc )
```

Sets the settings for the playback behaviour in case of delays.

Parameters

<i>pdc</i>	Playback delay configuration struct.
------------	--------------------------------------

Returns

If a change has been made.

3.116.2.4 StartPlayback()

```
bool StartPlayback ( )
```

Starts the audio playback of the linked incoming remote audio stream via AudioSource component.

Returns

True if playback is successfully started.

3.116.2.5 StopPlayback()

```
bool StopPlayback ( )
```

Stops the audio playback of the linked incoming remote audio stream via AudioSource component.

Returns

True if playback is successfully stopped.

3.116.3 Member Data Documentation

3.116.3.1 CustomAudioOutFactory

```
Func<IAudioOut<float> > CustomAudioOutFactory
```

A custom factory method to return [IAudioOut<float>](#) implementation used for the playback.

3.116.4 Property Documentation

3.116.4.1 Actor

```
Realtime.Player Actor [get], [set]
```

Per room, the connected users/players are represented with a `Realtime.Player`, also known as Actor.

[Photon Voice](#) calls this Actor, to avoid a name-clash with the `Player` class in [Voice](#).

3.116.4.2 IsLinked

```
bool IsLinked [get]
```

Whether or not this [Speaker](#) has been linked to a remote voice stream.

3.116.4.3 IsPlaying

```
bool IsPlaying [get]
```

Is the speaker playing right now.

3.116.4.4 Lag

```
int? Lag [get]
```

Smoothed difference between (jittering) stream and (clock-driven) audioOutput.

3.116.4.5 OnRemoteVoiceRemoveAction

```
Action<Speaker> OnRemoteVoiceRemoveAction [get], [set]
```

Register a method to be called when remote voice removed.

3.116.4.6 PlaybackDelayMaxHard

```
int PlaybackDelayMaxHard [get]
```

Gets the value in ms that audio play delay will not exceed.

3.116.4.7 PlaybackDelayMaxSoft

```
int PlaybackDelayMaxSoft [get]
```

Gets the value in ms below which the audio player tries to keep the delay.

3.116.4.8 PlaybackDelayMinSoft

```
int PlaybackDelayMinSoft [get]
```

Gets the value in ms above which the audio player tries to keep the delay.

3.116.4.9 PlaybackOnlyWhenEnabled

```
bool PlaybackOnlyWhenEnabled [get], [set]
```

If true, component will work only when enabled and active in hierarchy.

3.116.4.10 PlaybackStarted

```
bool PlaybackStarted [get]
```

Returns if the playback is on.

3.117 ImageBufferInfo.StrideSet Struct Reference

Public Member Functions

- **StrideSet** (int length, int s0=0, int s1=0, int s2=0, int s3=0)

Properties

- int **this**[int key] [get, set]
- int **Length** [get]

3.118 AudioUtil.TempoUp< T > Class Template Reference

Public Member Functions

- void **Begin** (int channels, int changePerc, int skipGroup)
- int **Process** (T[] s, T[] d)
- int **End** (T[] s)
- int **endFloat** (float[] s)
- int **endShort** (short[] s)

3.119 TestTone Class Reference

Inherits MonoBehaviour.

3.120 AudioUtil.ToneAudioPusher< T > Class Template Reference

[IAudioPusher](#) that provides a constant tone signal.

Inherits [IAudioPusher< T >](#).

Public Member Functions

- [ToneAudioPusher](#) (int frequency=440, int bufSizeMs=100, int samplingRate=48000, int channels=2)
Create a new [ToneAudioReader](#) instance
- void [SetCallback](#) (Action< T[]> callback, [ObjectFactory](#)< T[], int > bufferFactory)
Set the callback function used for pushing data
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.120.1 Detailed Description

[IAudioPusher](#) that provides a constant tone signal.

3.120.2 Constructor & Destructor Documentation

3.120.2.1 ToneAudioPusher()

```
ToneAudioPusher (
    int frequency = 440,
    int bufSizeMs = 100,
    int samplingRate = 48000,
    int channels = 2 )
```

Create a new [ToneAudioReader](#) instance

Parameters

<i>frequency</i>	Frequency of the generated tone (in Hz).
<i>bufSizeMs</i>	Size of buffers to push (in milliseconds).
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.120.3 Member Function Documentation

3.120.3.1 SetCallback()

```
void SetCallback (
    Action< T[]> callback,
    ObjectFactory< T[], int > bufferFactory )
```

Set the callback function used for pushing data

Parameters

<i>callback</i>	Callback function to use
<i>bufferFactory</i>	Buffer factory used to create the buffer that is pushed to the callback

Implements [IAudioPusher< T >](#).

3.121 ToneAudioReader Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- void **Dispose** ()
- bool **Read** (float[] buf)

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.122 AudioUtil.ToneAudioReader< T > Class Template Reference

[IAudioReader](#) that provides a constant tone signal.

Inherits [IAudioReader< T >](#).

Public Member Functions

- [ToneAudioReader](#) (Func< double > clockSec=null, double frequency=440, int samplingRate=48000, int channels=2)
Create a new [ToneAudioReader](#) instance
- void **Dispose** ()
- bool [Read](#) (T[] buf)
Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Properties

- int [Channels](#) [get]
Number of channels in the audio signal.
- int [SamplingRate](#) [get]
Sampling rate of the audio signal (in Hz).
- string [Error](#) [get]
If not null, audio object is in invalid state.

3.122.1 Detailed Description

[IAudioReader](#) that provides a constant tone signal.

Because of current resampling algorithm, the tone is distorted if SamplingRate does not equal encoder sampling rate.

3.122.2 Constructor & Destructor Documentation

3.122.2.1 ToneAudioReader()

```
ToneAudioReader (
    Func< double > clockSec = null,
    double frequency = 440,
    int samplingRate = 48000,
    int channels = 2 )
```

Create a new [ToneAudioReader](#) instance

Parameters

<i>clockSec</i>	Function to get current time in seconds. In Unity , pass in '()' => <code>AudioSettings.dspTime</code> for better results.
<i>frequency</i>	Frequency of the generated tone (in Hz).
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.122.3 Member Function Documentation

3.122.3.1 Read()

```
bool Read (
    T[] buffer )
```

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Parameters

<i>buffer</i>	Buffer to fill.
---------------	-----------------

Returns

True if buffer was filled successfully, false otherwise.

Implements [IDataReader< T >](#).

3.122.4 Property Documentation

3.122.4.1 Channels

```
int Channels [get]
```

Number of channels in the audio signal.

3.122.4.2 Error

```
string Error [get]
```

If not null, audio object is in invalid state.

3.122.4.3 SamplingRate

```
int SamplingRate [get]
```

Sampling rate of the audio signal (in Hz).

3.123 UnityAudioOut Class Reference

Inherits [AudioOutDelayControl< float >](#).

Public Member Functions

- **UnityAudioOut** (AudioSource audioSource, PlayDelayConfig playDelayConfig, [ILogger](#) logger, string logPrefix, bool debugInfo)
- override void **OutCreate** (int frequency, int channels, int bufferSamples)
- override void **OutStart** ()
- override void **OutWrite** (float[] data, int offsetSamples)
- override void **Stop** ()

Protected Attributes

- readonly AudioSource **source**
- AudioClip **clip**

Properties

- override int **OutPos** [get]

3.124 UnityMicrophone Class Reference

A wrapper around `UnityEngine.Microphone` to be able to safely use `Microphone` and compile for WebGL.

Static Public Member Functions

- static void **End** (string deviceName)
- static void **GetDeviceCaps** (string deviceName, out int minFreq, out int maxFreq)
- static int **GetPosition** (string deviceName)
- static bool **IsRecording** (string deviceName)
- static AudioClip **Start** (string deviceName, bool loop, int lengthSec, int frequency)

Properties

- static string[] **devices** [get]

3.124.1 Detailed Description

A wrapper around `UnityEngine.Microphone` to be able to safely use `Microphone` and compile for WebGL.

3.125 UnsupportedCodecException Class Reference

Exception thrown if an unsupported codec is encountered.

Inherits `Exception`.

Public Member Functions

- [UnsupportedCodecException](#) (string info, [Codec](#) codec)
Create a new [UnsupportedCodecException](#).

3.125.1 Detailed Description

Exception thrown if an unsupported codec is encountered.

3.125.2 Constructor & Destructor Documentation

3.125.2.1 UnsupportedCodecException()

```
UnsupportedCodecException (  
    string info,  
    Codec codec )
```

Create a new [UnsupportedCodecException](#).

Parameters

<i>info</i>	The info prepending standard message.
<i>codec</i>	The codec actually encountered.

3.126 UnsupportedPlatformException Class Reference

Exception thrown if an unsupported platform is encountered.

Inherits Exception.

Public Member Functions

- [UnsupportedPlatformException](#) (string subject, string platform=null)
Create a new [UnsupportedPlatformException](#).

3.126.1 Detailed Description

Exception thrown if an unsupported platform is encountered.

3.126.2 Constructor & Destructor Documentation

3.126.2.1 UnsupportedPlatformException()

```
UnsupportedPlatformException (
    string subject,
    string platform = null )
```

Create a new [UnsupportedPlatformException](#).

Parameters

<i>subject</i>	The info prepending standard message.
----------------	---------------------------------------

///

Parameters

<i>platform</i>	Optional platform name.
-----------------	-------------------------

3.127 UnsupportedSampleTypeException Class Reference

Exception thrown if an unsupported audio sample type is encountered.

Inherits Exception.

Public Member Functions

- [UnsupportedSampleTypeException](#) (Type t)
Create a new [UnsupportedSampleTypeException](#).

3.127.1 Detailed Description

Exception thrown if an unsupported audio sample type is encountered.

PhotonVoice generally supports 32-bit floating point ("float") or 16-bit signed integer ("short") audio, but it usually won't be converted automatically due to the high CPU overhead (and potential loss of precision) involved.

3.127.2 Constructor & Destructor Documentation

3.127.2.1 UnsupportedSampleTypeException()

```
UnsupportedSampleTypeException (
    Type t )
```

Create a new [UnsupportedSampleTypeException](#).

Parameters

<i>t</i>	The sample type actually encountered.
----------	---------------------------------------

3.128 OpusCodec.Util Class Reference

3.129 VoiceClient Class Reference

[Voice](#) client interact with other clients on network via [IVoiceTransport](#).

Inherits IDisposable.

Classes

- struct [CreateOptions](#)

Public Member Functions

- delegate void [RemoteVoiceInfoDelegate](#) (int channelId, int playerId, byte voiceId, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options)
Remote voice info event delegate.
- IEnumerable< [LocalVoice](#) > [LocalVoicesInChannel](#) (int channelId)
Iterates through copy of all local voices list of given channel.
- void **LogSpacingProfiles** ()
- void **LogStats** ()
- void **SetRemoteVoiceDelayFrames** ([Codec](#) codec, int delayFrames)
- [VoiceClient](#) ([IVoiceTransport](#) transport, [ILogger](#) logger, [CreateOptions](#) opt=default([CreateOptions](#)))
Creates [VoiceClient](#) instance
- void [Service](#) ()
This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2..20 times a second).
- [LocalVoice](#) [CreateLocalVoice](#) ([VoiceInfo](#) voiceInfo, int channelId=0, [IEncoder](#) encoder=null)
Creates basic outgoing stream w/o data processing support. Provided encoder should generate output data stream.
- [LocalVoiceFramed](#)< T > [CreateLocalVoiceFramed](#)< T > ([VoiceInfo](#) voiceInfo, int frameSize, int channelId=0, [IEncoder](#) encoder=null)
Creates outgoing stream consuming sequence of values passed in array buffers of arbitrary length which repacked in frames of constant length for further processing and encoding.
- [LocalVoiceAudio](#)< T > **CreateLocalVoiceAudio**< T > ([VoiceInfo](#) voiceInfo, [IAudioDesc](#) audioSourceDesc, [IEncoder](#) encoder, int channelId)
- [LocalVoice](#) [CreateLocalVoiceAudioFromSource](#) ([VoiceInfo](#) voiceInfo, [IAudioDesc](#) source, [AudioSampleType](#) sampleType, [IEncoder](#) encoder=null, int channelId=0)
Creates outgoing audio stream of type automatically assigned and adds procedures (callback or serviceable) for consuming given audio source data. Adds audio specific features (e.g. resampling, level meter) to processing pipeline and to returning stream handler.
- void [RemoveLocalVoice](#) ([LocalVoice](#) voice)
Removes local voice (outgoing data stream).

Parameters

voice	Handler of outgoing stream to be removed.
-------	---

- void **onJoinChannel** (int channel)
- void **onLeaveChannel** (int channel)
- void **onLeaveAllChannels** ()
- void **onPlayerJoin** (int channelId, int playerId)
- void **onPlayerLeave** (int channelId, int playerId)
- void **onVoiceInfo** (int channelId, int playerId, byte voiceId, byte eventNumber, [VoiceInfo](#) info)
- void **onVoiceRemove** (int channelId, int playerId, byte[] voiceIds)
- void **onFrame** (int channelId, int playerId, byte voiceId, byte evNumber, ref [FrameBuffer](#) receivedBytes, bool isLocalPlayer)
- void **Dispose** ()

Properties

- int [FramesLost](#) [get, set]
Lost frames counter.
- int [FramesReceived](#) [get]
Received frames counter.
- int [FramesSent](#) [get]

- *Sent frames counter.*
• int [FramesSentBytes](#) [get]
- *Sent frames bytes counter.*
• int [RoundTripTime](#) [get]
- *Average time required voice packet to return to sender.*
• int [RoundTripTimeVariance](#) [get]
- *Average round trip time variation.*
• bool [SuppressInfoDuplicateWarning](#) [get, set]
- *Do not log warning when duplicate info received.*
• [RemoteVoiceInfoDelegate OnRemoteVoiceInfoAction](#) [get, set]
Register a method to be called when remote voice info arrived (after join or new new remote voice creation). Metod parameters: (int channelId, int playerId, byte voiceId, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options);
- int [DebugLostPercent](#) [get, set]
Lost frames simulation ratio.
- IEnumerable< [LocalVoice](#) > [LocalVoices](#) [get]
Iterates through copy of all local voices list.
- IEnumerable< [RemoteVoiceInfo](#) > [RemoteVoiceInfos](#) [get]
Iterates through all remote voices infos.

3.129.1 Detailed Description

[Voice](#) client interact with other clients on network via [IVoiceTransport](#).

3.129.2 Constructor & Destructor Documentation

3.129.2.1 VoiceClient()

```

VoiceClient (
    IVoiceTransport transport,
    ILogger logger,
    CreateOptions opt = default(CreateOptions) )

```

Creates [VoiceClient](#) instance

3.129.3 Member Function Documentation

3.129.3.1 CreateLocalVoice()

```

LocalVoice CreateLocalVoice (
    VoiceInfo voiceInfo,
    int channelId = 0,
    IEncoder encoder = null )

```

Creates basic outgoing stream w/o data processing support. Provided encoder should generate output data stream.

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>channelId</i>	Transport channel specific to transport.
<i>encoder</i>	Encoder producing the stream.

Returns

Outgoing stream handler.

3.129.3.2 CreateLocalVoiceAudioFromSource()

```
LocalVoice CreateLocalVoiceAudioFromSource (
    VoiceInfo voiceInfo,
    IAudioDesc source,
    AudioSampleType sampleType,
    IEncoder encoder = null,
    int channelId = 0 )
```

Creates outgoing audio stream of type automatically assigned and adds procedures (callback or serviceable) for consuming given audio source data. Adds audio specific features (e.g. resampling, level meter) to processing pipeline and to returning stream handler.

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>source</i>	Streaming audio source.
<i>sampleType</i>	Voice's audio sample type. If does not match source audio sample type, conversion will occur.
<i>channelId</i>	Transport channel specific to transport.
<i>encoder</i>	Audio encoder. Set to null to use default Opus encoder.

Returns

Outgoing stream handler.

audioSourceDesc.SamplingRate and voiceInfo.SamplingRate may do not match. Automatic resampling will occur in this case.

3.129.3.3 CreateLocalVoiceFramed< T >()

```
LocalVoiceFramed<T> CreateLocalVoiceFramed< T > (
    VoiceInfo voiceInfo,
    int frameSize,
    int channelId = 0,
    IEncoder encoder = null )
```

Creates outgoing stream consuming sequence of values passed in array buffers of arbitrary length which repacked in frames of constant length for further processing and encoding.

Template Parameters

<i>T</i>	Type of data consumed by outgoing stream (element type of array buffers).
----------	---

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>frameSize</i>	Size of buffer LocalVoiceFramed repacks input data stream to.
<i>channelId</i>	Transport channel specific to transport.
<i>encoder</i>	Encoder compressing data stream in pipeline.

Returns

Outgoing stream handler.

3.129.3.4 LocalVoicesInChannel()

```
IEnumerable<LocalVoice> LocalVoicesInChannel (
    int channelId )
```

Iterates through copy of all local voices list of given channel.

3.129.3.5 RemoteVoiceInfoDelegate()

```
delegate void RemoteVoiceInfoDelegate (
    int channelId,
    int playerId,
    byte voiceId,
    VoiceInfo voiceInfo,
    ref RemoteVoiceOptions options )
```

Remote voice info event delegate.

3.129.3.6 RemoveLocalVoice()

```
void RemoveLocalVoice (
    LocalVoice voice )
```

Removes local voice (outgoing data stream).

Parameters

<i>voice</i>	Handler of outgoing stream to be removed.
--------------	---

3.129.3.7 Service()

```
void Service ( )
```

This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2..20 times a second).

3.129.4 Property Documentation**3.129.4.1 DebugLostPercent**

```
int DebugLostPercent [get], [set]
```

Lost frames simulation ratio.

3.129.4.2 FramesLost

```
int FramesLost [get], [set]
```

Lost frames counter.

3.129.4.3 FramesReceived

```
int FramesReceived [get]
```

Received frames counter.

3.129.4.4 FramesSent

```
int FramesSent [get]
```

Sent frames counter.

3.129.4.5 FramesSentBytes

```
int FramesSentBytes [get]
```

Sent frames bytes counter.

3.129.4.6 LocalVoices

```
IEnumerable<LocalVoice> LocalVoices [get]
```

Iterates through copy of all local voices list.

3.129.4.7 OnRemoteVoiceInfoAction

```
RemoteVoiceInfoDelegate OnRemoteVoiceInfoAction [get], [set]
```

Register a method to be called when remote voice info arrived (after join or new new remote voice creation). Metod parameters: (int channelId, int playerId, byte voiceId, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options);

3.129.4.8 RemoteVoiceInfos

```
IEnumerable<RemoteVoiceInfo> RemoteVoiceInfos [get]
```

Iterates through all remote voices infos.

3.129.4.9 RoundTripTime

```
int RoundTripTime [get]
```

Average time required voice packet to return to sender.

3.129.4.10 RoundTripTimeVariance

```
int RoundTripTimeVariance [get]
```

Average round trip time variation.

3.129.4.11 SuppressInfoDuplicateWarning

```
bool SuppressInfoDuplicateWarning [get], [set]
```

Do not log warning when duplicate info received.

3.130 VoiceComponent Class Reference

Inherits MonoBehaviour, and [ILoggableDependent](#).

Inherited by [PhotonVoiceView](#), [AudioChangesHandler](#), [Recorder](#), [Speaker](#), [MicAmplifier](#), [MicrophonePermission](#), [SaveIncomingStreamToFile](#), [SaveOutgoingStreamToFile](#), and [WebRtcAudioDsp](#).

Protected Member Functions

- virtual void **Awake** ()

Protected Attributes

- DebugLevel **LogLevel** = DebugLevel.WARNING

Properties

- [VoiceLogger](#) **Logger** [get, protected set]
- DebugLevel **LogLevel** [get, set]
- bool **IgnoreGlobalLogLevel** [get, set]
- static string **CurrentPlatform** [get]

3.131 VoiceConnection Class Reference

Component that represents a client voice connection to [Photon](#) Servers.

Inherits ConnectionHandler, and [ILoggable](#).

Inherited by [PhotonVoiceNetwork](#).

Public Member Functions

- bool [ConnectUsingSettings](#) (AppSettings overwriteSettings=null)
Connect to [Photon](#) server using [Settings](#)
- void [InitRecorder](#) ([Recorder](#) rec)
Initializes the [Recorder](#) component to be able to transmit audio.
- void [SetPlaybackDelaySettings](#) ([PlaybackDelaySettings](#) gpds)
Sets the global configuration for the playback behaviour in case of delays.
- void [SetGlobalPlaybackDelaySettings](#) (int low, int high, int max)
Sets the global configuration for the playback behaviour in case of delays.
- virtual bool [TryLateLinkingUsingUserData](#) ([Speaker](#) speaker, object userData)
Tries to link local [Speaker](#) with remote voice stream using UserData. Useful if [Speaker](#) created after stream is started.

Public Attributes

- AppSettings [Settings](#)
Settings to be used by this voice connection
- Func< int, byte, object, [Speaker](#) > [SpeakerFactory](#)
Special factory to link [Speaker](#) components with incoming remote audio streams
- float [MinimalTimeScaleToDispatchInFixedUpdate](#) = -1f
Configures the minimal Time.timeScale at which [Voice](#) client will dispatch incoming messages within LateUpdate.
- bool [AutoCreateSpeakerIfNotFound](#) = true
Auto instantiate a GameObject and attach a [Speaker](#) component to link to a remote audio stream if no candidate could be found
- int [MaxDatagrams](#) = 3
Limits the number of datagrams that are created in each LateUpdate.
- bool [SendAsap](#)
Signals that outgoing messages should be sent in the next LateUpdate call.

Protected Member Functions

- override void **Awake** ()
- virtual void **Update** ()
- virtual void **FixedUpdate** ()
- void [Dispatch](#) ()
Dispatches incoming network messages for [Voice](#) client. Called in FixedUpdate or LateUpdate.
- override void **OnDisable** ()
- virtual void **OnDestroy** ()
- virtual [Speaker](#) **SimpleSpeakerFactory** (int playerId, byte voicId, object userData)
- virtual void **OnVoiceStateChanged** ([ClientState](#) fromState, [ClientState](#) toState)
- void **CalcStatistics** ()
- void **LinkSpeaker** ([Speaker](#) speaker, [RemoteVoiceLink](#) remoteVoice)
- virtual void **OnOperationResponseReceived** (OperationResponse operationResponse)

Protected Attributes

- List< [RemoteVoiceLink](#) > **cachedRemoteVoices** = new List<[RemoteVoiceLink](#)>()

Properties

- [VoiceLogger](#) [Logger](#) [get, protected set]
[Logger](#) used by this component
- DebugLevel [LogLevel](#) [get, set]
Log level for this component
- new [LoadBalancingTransport](#) **Client** [get]
- [VoiceClient](#) [VoiceClient](#) [get]
Returns underlying [Photon Voice](#) client.
- ClientState [ClientState](#) [get]
Returns [Photon Voice](#) client state.
- float [FramesReceivedPerSecond](#) [get]
Number of frames received per second.
- float [FramesLostPerSecond](#) [get]
Number of frames lost per second.

- float [FramesLostPercent](#) [get]
Percentage of lost frames.
- GameObject [SpeakerPrefab](#) [get, set]
Prefab that contains [Speaker](#) component to be instantiated when receiving a new remote audio source info
- [Recorder PrimaryRecorder](#) [get, set]
Main [Recorder](#) to be used for transmission by default
- DebugLevel **GlobalRecordersLogLevel** [get, set]
- DebugLevel **GlobalSpeakersLogLevel** [get, set]
- int **GlobalPlaybackDelay** [get, set]
- string [BestRegionSummaryInPreferences](#) [get, set]
Used to store and access the "Best Region Summary" in the Player Preferences.
- int [GlobalPlaybackDelayMinSoft](#) [get]
Gets the global value in ms above which the audio player tries to keep the delay.
- int [GlobalPlaybackDelayMaxSoft](#) [get]
Gets the global value in ms below which the audio player tries to keep the delay.
- int [GlobalPlaybackDelayMaxHard](#) [get]
Gets the global value in ms that audio play delay will not exceed.

Events

- Action< [Speaker](#) > [SpeakerLinked](#)
Fires when a speaker has been linked to a remote audio stream
- Action< [RemoteVoiceLink](#) > [RemoteVoiceAdded](#)
Fires when a remote voice stream is added

3.131.1 Detailed Description

Component that represents a client voice connection to [Photon](#) Servers.

3.131.2 Member Function Documentation

3.131.2.1 ConnectUsingSettings()

```
bool ConnectUsingSettings (
    AppSettings overwriteSettings = null )
```

Connect to [Photon](#) server using [Settings](#)

Parameters

<i>overwriteSettings</i>	Overwrites Settings before connecting
--------------------------	---

Returns

If true voice connection command was sent from client

3.131.2.2 Dispatch()

```
void Dispatch ( ) [protected]
```

Dispatches incoming network messages for [Voice](#) client. Called in FixedUpdate or LateUpdate.

It may make sense to dispatch incoming messages, even if the timeScale is near 0. That can be configured with [MinimalTimeScaleToDispatchInFixedUpdate](#).

Without dispatching messages, [Voice](#) client won't change state and does not handle updates.

3.131.2.3 InitRecorder()

```
void InitRecorder (
    Recorder rec )
```

Initializes the [Recorder](#) component to be able to transmit audio.

Parameters

<i>rec</i>	The Recorder to be initialized.
------------	---

3.131.2.4 SetGlobalPlaybackDelaySettings()

```
void SetGlobalPlaybackDelaySettings (
    int low,
    int high,
    int max )
```

Sets the global configuration for the playback behaviour in case of delays.

Parameters

<i>low</i>	In milliseconds, audio player tries to keep the playback delay above this value.
<i>high</i>	In milliseconds, audio player tries to keep the playback below above this value.
<i>max</i>	In milliseconds, audio player guarantees that the playback delay never exceeds this value.

3.131.2.5 SetPlaybackDelaySettings()

```
void SetPlaybackDelaySettings (
    PlaybackDelaySettings gpds )
```

Sets the global configuration for the playback behaviour in case of delays.

Parameters

<i>gpds</i>	Playback delay configuration struct.
-------------	--------------------------------------

3.131.2.6 TryLateLinkingUsingUserData()

```
virtual bool TryLateLinkingUsingUserData (
    Speaker speaker,
    object userData ) [virtual]
```

Tries to link local [Speaker](#) with remote voice stream using UserData. Useful if [Speaker](#) created after stream is started.

Parameters

<i>speaker</i>	Speaker ot try linking.
<i>userData</i>	UserData object used to bind local Speaker with remote voice stream.

Returns

3.131.3 Member Data Documentation

3.131.3.1 AutoCreateSpeakerIfNotFound

```
bool AutoCreateSpeakerIfNotFound = true
```

Auto instantiate a GameObject and attach a [Speaker](#) component to link to a remote audio stream if no candidate could be found

3.131.3.2 MaxDatagrams

```
int MaxDatagrams = 3
```

Limits the number of datagrams that are created in each LateUpdate.

Helps spreading out sending of messages minimally.

3.131.3.3 MinimalTimeScaleToDispatchInFixedUpdate

```
float MinimalTimeScaleToDispatchInFixedUpdate = -1f
```

Configures the minimal Time.timeScale at which [Voice](#) client will dispatch incoming messages within LateUpdate.

It may make sense to dispatch incoming messages, even if the timeScale is near 0. In some cases, stopping the game time makes sense, so this option defaults to -1f, which is "off". Without dispatching messages, [Voice](#) client won't change state and does not handle updates.

3.131.3.4 SendAsap

```
bool SendAsap
```

Signals that outgoing messages should be sent in the next LateUpdate call.

Up to MaxDatagrams are created to send queued messages.

3.131.3.5 Settings

```
AppSettings Settings
```

Settings to be used by this voice connection

3.131.3.6 SpeakerFactory

```
Func<int, byte, object, Speaker> SpeakerFactory
```

Special factory to link [Speaker](#) components with incoming remote audio streams

3.131.4 Property Documentation

3.131.4.1 BestRegionSummaryInPreferences

```
string BestRegionSummaryInPreferences [get], [set]
```

Used to store and access the "Best Region Summary" in the Player Preferences.

3.131.4.2 ClientState

```
ClientState ClientState [get]
```

Returns [Photon Voice](#) client state.

3.131.4.3 FramesLostPercent

```
float FramesLostPercent [get]
```

Percentage of lost frames.

3.131.4.4 FramesLostPerSecond

```
float FramesLostPerSecond [get]
```

Number of frames lost per second.

3.131.4.5 FramesReceivedPerSecond

```
float FramesReceivedPerSecond [get]
```

Number of frames received per second.

3.131.4.6 GlobalPlaybackDelayMaxHard

```
int GlobalPlaybackDelayMaxHard [get]
```

Gets the global value in ms that audio play delay will not exceed.

3.131.4.7 GlobalPlaybackDelayMaxSoft

```
int GlobalPlaybackDelayMaxSoft [get]
```

Gets the global value in ms below which the audio player tries to keep the delay.

3.131.4.8 GlobalPlaybackDelayMinSoft

```
int GlobalPlaybackDelayMinSoft [get]
```

Gets the global value in ms above which the audio player tries to keep the delay.

3.131.4.9 Logger

```
VoiceLogger Logger [get], [protected set]
```

[Logger](#) used by this component

3.131.4.10 LogLevel

```
DebugLevel LogLevel [get], [set]
```

Log level for this component

3.131.4.11 PrimaryRecorder

```
Recorder PrimaryRecorder [get], [set]
```

Main [Recorder](#) to be used for transmission by default

3.131.4.12 SpeakerPrefab

```
GameObject SpeakerPrefab [get], [set]
```

Prefab that contains [Speaker](#) component to be instantiated when receiving a new remote audio source info

3.131.4.13 VoiceClient

```
VoiceClient VoiceClient [get]
```

Returns underlying [Photon Voice](#) client.

3.131.5 Event Documentation

3.131.5.1 RemoteVoiceAdded

Action<[RemoteVoiceLink](#)> RemoteVoiceAdded

Fires when a remote voice stream is added

3.131.5.2 SpeakerLinked

Action<[Speaker](#)> SpeakerLinked

Fires when a speaker has been linked to a remote audio stream

3.132 VoiceDebugScript Class Reference

Utility script to be attached next to [PhotonVoiceView](#) & PhotonView on the player prefab to be network instantiated. Call voiceDebugScript.CantHearYou() on the networked object of the remote (or local) player if you can't hear the corresponding player.

Inherits MonoBehaviourPun.

Public Member Functions

- void **CantHearYou** ()

Public Attributes

- bool [ForceRecordingAndTransmission](#)
Make sure recorder.TransmitEnabled and recorder.IsRecording are true.
- AudioClip [TestAudioClip](#)
Audio file to be broadcast when TestUsingAudioClip is enabled.
- bool [TestUsingAudioClip](#)
Broadcast Audio file to make sure transmission over network works if microphone (audio input device/hardware) is not reliable. Requires setting AudioClip in TestAudioClip.
- bool [DisableVad](#)
Disable recorder.VoiceDetection for easier testing.
- bool [IncreaseLogLevels](#)
Set main voice component's log level to ALL (max).
- bool [LocalDebug](#)
Debug DebugEcho mode (Can't Hear My Self?!).

3.132.1 Detailed Description

Utility script to be attached next to [PhotonVoiceView](#) & PhotonView on the player prefab to be network instantiated. Call `voiceDebugScript.CantHearYou()` on the networked object of the remote (or local) player if you can't hear the corresponding player.

3.132.2 Member Data Documentation

3.132.2.1 DisableVad

`bool DisableVad`

Disable recorder.VoiceDetection for easier testing.

3.132.2.2 ForceRecordingAndTransmission

`bool ForceRecordingAndTransmission`

Make sure `recorder.TransmitEnabled` and `recorder.IsRecording` are true.

3.132.2.3 IncreaseLogLevels

`bool IncreaseLogLevels`

Set main voice component's log level to ALL (max).

3.132.2.4 LocalDebug

`bool LocalDebug`

Debug DebugEcho mode (Can't Hear My Self?!).

3.132.2.5 TestAudioClip

`AudioClip TestAudioClip`

Audio file to be broadcast when `TestUsingAudioClip` is enabled.

3.132.2.6 TestUsingAudioClip

```
bool TestUsingAudioClip
```

Broadcast Audio file to make sure transmission over network works if microphone (audio input device/hardware) is not reliable. Requires setting AudioClip in TestAudioClip.

3.133 AudioUtil.VoiceDetector< T > Class Template Reference

Simple voice activity detector triggered by signal level.

Inherits [IProcessor< T >](#), and [AudioUtil.IVoiceDetector](#).

Public Member Functions

- abstract `T[] Process (T[] buf)`
Process a frame of audio data.
- void **Dispose** ()

Protected Attributes

- float **norm**
- float **threshold**
- int **activityDelay**
- int **autoSilenceCounter** = 0
- int **valuesCountPerSec**
- int **activityDelayValuesCount**

Properties

- bool **On** [get, set]
If true, voice detection enabled.
- float **Threshold** [get, set]
Voice detected as soon as signal level exceeds threshold.
- bool **Detected** [get, protected set]
If true, voice detected.
- DateTime **DetectedTime** [get]
Last time when switched to detected state.
- int **ActivityDelayMs** [get, set]
Keep detected state during this time after signal level dropped below threshold.

Events

- Action **OnDetected**
Called when switched to detected state.

3.133.1 Detailed Description

Simple voice activity detector triggered by signal level.

3.133.2 Member Function Documentation

3.133.2.1 Process()

```
abstract T [] Process (  
    T[] buf ) [pure virtual]
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.133.3 Property Documentation

3.133.3.1 ActivityDelayMs

```
int ActivityDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold.

3.133.3.2 Detected

```
bool Detected [get], [protected set]
```

If true, voice detected.

3.133.3.3 DetectedTime

DateTime DetectedTime [get]

Last time when switched to detected state.

3.133.3.4 On

bool On [get], [set]

If true, voice detection enabled.

3.133.3.5 Threshold

float Threshold [get], [set]

Voice detected as soon as signal level exceeds threshold.

3.133.4 Event Documentation

3.133.4.1 OnDetected

Action OnDetected

Called when switched to detected state.

3.134 AudioUtil.VoiceDetectorCalibration< T > Class Template Reference

Calibration Utility for Voice Detector

Inherits [IProcessor< T >](#).

Public Member Functions

- [VoiceDetectorCalibration](#) ([IVoiceDetector](#) voiceDetector, [ILevelMeter](#) levelMeter, int samplingRate, int channels)
Create new [VoiceDetectorCalibration](#) instance.
- void [Calibrate](#) (int durationMs, Action< float > onCalibrated=null)
Start calibration.
- T[] [Process](#) (T[] buf)
Process a frame of audio data.
- void **Dispose** ()

Protected Attributes

- int `calibrateCount`

Properties

- bool `IsCalibrating` [get]

3.134.1 Detailed Description

Calibration Utility for [Voice](#) Detector

. Using this audio processor, you can calibrate the [IVoiceDetector.Threshold](#).

3.134.2 Constructor & Destructor Documentation

3.134.2.1 VoiceDetectorCalibration()

```
VoiceDetectorCalibration (
    IVoiceDetector voiceDetector,
    ILevelMeter levelMeter,
    int samplingRate,
    int channels )
```

Create new [VoiceDetectorCalibration](#) instance.

Parameters

<i>voiceDetector</i>	Voice Detector to calibrate.
<i>levelMeter</i>	Level Meter to look at for calibration.
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.134.3 Member Function Documentation

3.134.3.1 Calibrate()

```
void Calibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Start calibration.

Parameters

<i>durationMs</i>	Duration of the calibration procedure (in milliseconds).
<i>onCalibrated</i>	Optional callback that is called after calibration is complete.

This activates the Calibration process. It will reset the given [LevelMeter](#)'s AccumAvgPeakAmp (accumulated average peak amplitude), and when the duration has passed, use it for the [VoiceDetector](#)'s detection threshold.

3.134.3.2 Process()

```
T [] Process (
    T[] buf )
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.135 AudioUtil.VoiceDetectorDummy Class Reference

Dummy [VoiceDetector](#) that doesn't actually do anything.

Inherits [AudioUtil.IVoiceDetector](#).

Properties

- bool **On** [get, set]
- float **Threshold** [get, set]
- bool **Detected** [get]
- int **ActivityDelayMs** [get, set]
- DateTime **DetectedTime** [get]
- Action **OnDetected**

Additional Inherited Members

3.135.1 Detailed Description

Dummy [VoiceDetector](#) that doesn't actually do anything.

3.136 AudioUtil.VoiceDetectorFloat Class Reference

[VoiceDetector](#) specialization for float audio.

Inherits [AudioUtil.VoiceDetector< float >](#).

Public Member Functions

- [VoiceDetectorFloat](#) (int samplingRate, int numChannels)
Create a new [VoiceDetectorFloat](#) instance.
- override float[] **Process** (float[] buffer)

Additional Inherited Members

3.136.1 Detailed Description

[VoiceDetector](#) specialization for float audio.

3.136.2 Constructor & Destructor Documentation

3.136.2.1 VoiceDetectorFloat()

```
VoiceDetectorFloat (
    int samplingRate,
    int numChannels )
```

Create a new [VoiceDetectorFloat](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.137 AudioUtil.VoiceDetectorShort Class Reference

[VoiceDetector](#) specialization for float audio.

Inherits [AudioUtil.VoiceDetector< short >](#).

Public Member Functions

- [VoiceDetectorShort](#) (int samplingRate, int numChannels)
Create a new [VoiceDetectorFloat](#) instance
- override short[] **Process** (short[] buffer)

Additional Inherited Members

3.137.1 Detailed Description

[VoiceDetector](#) specialization for float audio.

3.137.2 Constructor & Destructor Documentation

3.137.2.1 VoiceDetectorShort()

```
VoiceDetectorShort (
    int samplingRate,
    int numChannels )
```

Create a new [VoiceDetectorFloat](#) instance

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.138 VoiceEvent Class Reference

Static Public Attributes

- const byte [Code](#) = 202
Single event used for voice communications.
- const byte **FrameCode** = 203

3.138.1 Member Data Documentation

3.138.1.1 Code

```
const byte Code = 202 [static]
```

Single event used for voice communications.

Change if it conflicts with other event codes used in the same [Photon](#) room.

3.139 VoicelInfo Struct Reference

Describes stream properties.

Public Member Functions

- override string **ToString** ()

Static Public Member Functions

- static [VoicelInfo CreateAudioOpus](#) (POpusCodec.Enums.SamplingRate samplingRate, int channels, OpusCodec.FrameDuration frameDurationUs, int bitrate, object userdata=null)
Create stream info for an Opus audio stream.
- static [VoicelInfo CreateAudio](#) (Codec codec, int samplingRate, int channels, int frameDurationUs, object userdata=null)
Create stream info for an audio stream.

Properties

- [Codec](#) **Codec** [get, set]
- int [SamplingRate](#) [get, set]
Audio sampling rate (frequency, in Hz).
- int [Channels](#) [get, set]
Number of channels.
- int [FrameDurationUs](#) [get, set]
Uncompressed frame (audio packet) size in microseconds.
- int [Bitrate](#) [get, set]
Target bitrate (in bits/second).
- int [Width](#) [get, set]
Video width.
- int [Height](#) [get, set]
Video height
- int [FPS](#) [get, set]
Video frames per second
- int [KeyFrameInt](#) [get, set]
Video keyframe interval in frames
- object [UserData](#) [get, set]
Optional user data. Should be serializable by [Photon](#).
- int [FrameDurationSamples](#) [get]
Uncompressed frame (data packet) size in samples.
- int [FrameSize](#) [get]
Uncompressed frame (data packet) array size.

3.139.1 Detailed Description

Describes stream properties.

3.139.2 Member Function Documentation

3.139.2.1 CreateAudio()

```
static VoiceInfo CreateAudio (  
    Codec codec,  
    int samplingRate,  
    int channels,  
    int frameDurationUs,  
    object userdata = null ) [static]
```

Create stream info for an audio stream.

Parameters

<i>codec</i>	Audio codec.
<i>samplingRate</i>	Audio sampling rate.
<i>channels</i>	Number of channels.
<i>frameDurationUs</i>	Uncompressed frame (audio packet) size in microseconds.
<i>userdata</i>	Optional user data. Should be serializable by Photon .

Returns

[VoiceInfo](#) instance.

3.139.2.2 CreateAudioOpus()

```
static VoiceInfo CreateAudioOpus (  
    POpusCodec.Enums.SamplingRate samplingRate,  
    int channels,  
    OpusCodec.FrameDuration frameDurationUs,  
    int bitrate,  
    object userdata = null ) [static]
```

Create stream info for an Opus audio stream.

Parameters

<i>samplingRate</i>	Audio sampling rate.
<i>channels</i>	Number of channels.
<i>frameDurationUs</i>	Uncompressed frame (audio packet) size in microseconds.
<i>bitrate</i>	Stream bitrate (in bits/second).
<i>userdata</i>	Optional user data. Should be serializable by Photon .

Returns

[VoiceInfo](#) instance.

3.139.3 Property Documentation

3.139.3.1 Bitrate

```
int Bitrate [get], [set]
```

Target bitrate (in bits/second).

3.139.3.2 Channels

```
int Channels [get], [set]
```

Number of channels.

3.139.3.3 FPS

```
int FPS [get], [set]
```

Video frames per second

3.139.3.4 FrameDurationSamples

```
int FrameDurationSamples [get]
```

Uncompressed frame (data packet) size in samples.

3.139.3.5 FrameDurationUs

```
int FrameDurationUs [get], [set]
```

Uncompressed frame (audio packet) size in microseconds.

3.139.3.6 FrameSize

```
int FrameSize [get]
```

Uncompressed frame (data packet) array size.

3.139.3.7 Height

```
int Height [get], [set]
```

Video height

3.139.3.8 KeyFrameInt

```
int KeyFrameInt [get], [set]
```

Video keyframe interval in frames

3.139.3.9 SamplingRate

```
int SamplingRate [get], [set]
```

Audio sampling rate (frequency, in Hz).

3.139.3.10 UserData

```
object UserData [get], [set]
```

Optional user data. Should be serializable by [Photon](#).

3.139.3.11 Width

```
int Width [get], [set]
```

Video width.

3.140 AudioUtil.VoiceLevelDetectCalibrate< T > Class Template Reference

Utility Audio Processor [Voice](#) Detection Calibration.

Inherits [IProcessor< T >](#).

Public Member Functions

- [VoiceLevelDetectCalibrate](#) (int samplingRate, int channels)
Create new [VoiceLevelDetectCalibrate](#) instance
- void [Calibrate](#) (int durationMs, Action< float > onCalibrated=null)
Start calibration
- T[] [Process](#) (T[] buf)
Process a frame of audio data.
- void **Dispose** ()

Properties

- [ILevelMeter](#) [LevelMeter](#) [get]
The [LevelMeter](#) in use.
- [IVoiceDetector](#) [VoiceDetector](#) [get]
The [VoiceDetector](#) in use
- bool **IsCalibrating** [get]

3.140.1 Detailed Description

Utility Audio Processor [Voice](#) Detection Calibration.

Encapsulates level meter, voice detector and voice detector calibrator in single instance.

3.140.2 Constructor & Destructor Documentation

3.140.2.1 VoiceLevelDetectCalibrate()

```

VoiceLevelDetectCalibrate (
    int samplingRate,
    int channels )

```

Create new [VoiceLevelDetectCalibrate](#) instance

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.140.3 Member Function Documentation

3.140.3.1 Calibrate()

```
void Calibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Start calibration

Parameters

<i>durationMs</i>	Duration of the calibration procedure (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

This activates the Calibration process. It will reset the given [LevelMeter](#)'s AccumAvgPeakAmp (accumulated average peak amplitude), and when the duration has passed, use it for the [VoiceDetector](#)'s detection threshold.

3.140.3.2 Process()

```
T [ ] Process (
    T[ ] buf )
```

Process a frame of audio data.

Parameters

<i>buf</i>	Buffer containing input audio data
------------	------------------------------------

Returns

Buffer containing output audio data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.140.4 Property Documentation

3.140.4.1 LevelMeter

```
ILevelMeter LevelMeter [get]
```

The [LevelMeter](#) in use.

3.140.4.2 VoiceDetector

`IVoiceDetector VoiceDetector` [get]

The [VoiceDetector](#) in use

3.141 VoiceLogger Class Reference

Inherits [ILogger](#).

Public Member Functions

- **VoiceLogger** (Object context, string tag, DebugLevel level=DebugLevel.ERROR)
- **VoiceLogger** (string tag, DebugLevel level=DebugLevel.ERROR)
- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)

Properties

- string **Tag** [get, set]
- DebugLevel **LogLevel** [get, set]
- bool **IsErrorEnabled** [get]
- bool **IsWarningEnabled** [get]
- bool **IsInfoEnabled** [get]
- bool **IsDebugEnabled** [get]

3.142 WebRtcAudioDsp Class Reference

Inherits [VoiceComponent](#).

Public Member Functions

- bool [SetOrSwitchAudioListener](#) (AudioListener listener)
Set the AudioListener to be used with this [WebRtcAudioDsp](#). Needed for Acoustic Echo Cancellation.
- bool [SetOrSwitchAudioOutCapture](#) (AudioOutCapture capture)
Set the [AudioOutCapture](#) to be used with this [WebRtcAudioDsp](#). Needed for Acoustic Echo Cancellation.

Public Attributes

- bool **AutoRestartOnAudioChannelsMismatch** = true
- bool **AECMobileComfortNoise**

Protected Member Functions

- override void **Awake** ()

Properties

- bool **AEC** [get, set]
- bool **AECMobile** [get, set]
- bool **AecHighPass** [get, set]
- int **ReverseStreamDelayMs** [get, set]
- bool **NoiseSuppression** [get, set]
- bool **HighPass** [get, set]
- bool **Bypass** [get, set]
- bool **AGC** [get, set]
- int **AgcCompressionGain** [get, set]
- bool **VAD** [get, set]
- bool **IsInitialized** [get]
- bool **AecOnlyWhenEnabled** [get, set]

Additional Inherited Members

3.142.1 Member Function Documentation

3.142.1.1 SetOrSwitchAudioListener()

```
bool SetOrSwitchAudioListener (
    AudioListener listener )
```

Set the AudioListener to be used with this [WebRtcAudioDsp](#). Needed for Acoustic Echo Cancellation.

Parameters

<i>listener</i>	The audioListener to be used
-----------------	------------------------------

Returns

Success or failure

3.142.1.2 SetOrSwitchAudioOutCapture()

```
bool SetOrSwitchAudioOutCapture (
    AudioOutCapture capture )
```

Set the [AudioOutCapture](#) to be used with this [WebRtcAudioDsp](#). Needed for Acoustic Echo Cancellation.

Parameters

<i>capture</i>	The audioOutCapture to be used
----------------	--------------------------------

Returns

Success or failure

3.143 WebRTCAudioLib Class Reference

Inherited by [WebRTCAudioProcessor](#).

Public Types

- enum **Error**
- enum **Param**

Public Member Functions

- static IntPtr **webrtc_audio_processor_create** (int samplingRate, int channels, int frameSize, int rev↵ SamplingRate, int revChannels)
- static int **webrtc_audio_processor_init** (IntPtr proc)
- static int **webrtc_audio_processor_set_param** (IntPtr proc, int param, int v)
- static int **webrtc_audio_processor_process** (IntPtr proc, short[] buffer, int offset, out bool voiceDetected)
- static int **webrtc_audio_processor_process_reverse** (IntPtr proc, short[] buffer, int bufferSize)
- static void **webrtc_audio_processor_destroy** (IntPtr proc)

3.144 WebRTCAudioProcessor Class Reference

Inherits [WebRTCAudioLib](#), and [IProcessor< short >](#).

Public Member Functions

- **WebRTCAudioProcessor** ([ILogger](#) logger, int frameSize, int samplingRate, int channels, int reverse↵ SamplingRate, int reverseChannels)
- short[] **Process** (short[] buf)
- void **OnAudioOutFrameFloat** (float[] data)
- void **Dispose** ()

Static Public Attributes

- static readonly int[] **SupportedSamplingRates** = { 8000, 16000, 32000, 48000 }

Properties

- int **AECStreamDelayMs** [set]
- bool?? **AEC** [set]
- bool? **AECHighPass** [set]
- bool?? **AECMobile** [set]
- bool? **HighPass** [set]
- bool? **NoiseSuppression** [set]
- bool? **AGC** [set]
- int **AGCCompressionGain** [set]
- int **AGCTargetLevel** [set]
- bool? **AGC2** [set]
- bool? **VAD** [set]
- bool **Bypass** [set]

Additional Inherited Members

Index

- AccumAvgPeakAmp
 - AudioUtil.ILevelMeter, [54](#)
- AcquireOrCreate
 - ObjectPool< TType, TInfo >, [86](#)
- ActivityDelayMs
 - AudioUtil.IVoiceDetector, [61](#)
 - AudioUtil.VoiceDetector< T >, [146](#)
- Actor
 - Speaker, [119](#)
- AddPostProcessor
 - LocalVoiceFramed< T >, [78](#)
- AddPreProcessor
 - LocalVoiceFramed< T >, [79](#)
- AllowBluetooth
 - Photon.Voice.IOS, [8](#)
- Ambient
 - Photon.Voice.IOS, [7](#)
- AndroidAudioInAEC, [15](#)
- AndroidAudioInParameters, [15](#)
- Audio
 - POpusCodec.Enums, [12](#)
- AudioChangesHandler, [15](#)
 - HandleConfigChange, [16](#)
 - HandleDeviceChange, [16](#)
 - StartWhenDeviceChange, [16](#)
 - UseNativePluginChangeNotifier, [17](#)
 - UseOnAudioConfigurationChanged, [17](#)
- AudioClip
 - Recorder, [104](#)
- AudioClipWrapper, [17](#)
- AudioDesc, [18](#)
- AudioGroup
 - Recorder, [104](#)
- AudioInChangeNotifierNotSupported, [18](#)
- AudioInEnumerator, [18](#)
- AudioInEnumeratorEx, [19](#)
- AudioOpus
 - Photon.Voice, [6](#)
- AudioOutCapture, [19](#)
- AudioOutDelayControl, [19](#)
- AudioOutDelayControl.PlayDelayConfig, [99](#)
- AudioProcessing
 - Photon.Voice.IOS, [7](#)
- AudioSampleType
 - Photon.Voice, [6](#)
- AudioSessionCategory
 - Photon.Voice.IOS, [6](#)
- AudioSessionCategoryOption
 - Photon.Voice.IOS, [7](#)
- AudioSessionMode
 - Photon.Voice.IOS, [8](#)
- AudioSessionParameters, [20](#)
- AudioSessionParametersPresets, [20](#)
 - Game, [20](#)
 - VoIP, [20](#)
- AudioSyncBuffer< T >, [21](#)
- AudioUtil, [21](#)
 - Convert, [22](#), [23](#)
 - ForceToStereo< T >, [23](#)
 - Resample< T >, [23](#)
 - ResampleAndConvert, [24](#)
- AudioUtil.ILevelMeter, [53](#)
 - AccumAvgPeakAmp, [54](#)
 - CurrentAvgAmp, [54](#)
 - CurrentPeakAmp, [54](#)
 - ResetAccumAvgPeakAmp, [53](#)
- AudioUtil.IVoiceDetector, [60](#)
 - ActivityDelayMs, [61](#)
 - Detected, [61](#)
 - DetectedTime, [61](#)
 - On, [61](#)
 - OnDetected, [62](#)
 - Threshold, [61](#)
- AudioUtil.LevelMeter< T >, [62](#)
 - Process, [63](#)
 - ResetAccumAvgPeakAmp, [63](#)
- AudioUtil.LevelMeterDummy, [63](#)
 - ResetAccumAvgPeakAmp, [64](#)
- AudioUtil.LevelMeterFloat, [64](#)
 - LevelMeterFloat, [65](#)
- AudioUtil.LevelMeterShort, [66](#)
 - LevelMeterShort, [66](#)
- AudioUtil.Resampler< T >, [114](#)
 - Process, [115](#)
 - Resampler, [114](#)
- AudioUtil.TempoUp< T >, [121](#)
- AudioUtil.ToneAudioPusher< T >, [121](#)
 - SetCallback, [122](#)
 - ToneAudioPusher, [122](#)
- AudioUtil.ToneAudioReader< T >, [123](#)
 - Channels, [124](#)
 - Error, [125](#)
 - Read, [124](#)
 - SamplingRate, [125](#)
 - ToneAudioReader, [124](#)
- AudioUtil.VoiceDetector< T >, [145](#)
 - ActivityDelayMs, [146](#)
 - Detected, [146](#)

- DetectedTime, 146
- On, 147
- OnDetected, 147
- Process, 146
- Threshold, 147
- AudioUtil.VoiceDetectorCalibration< T >, 147
 - Calibrate, 148
 - Process, 149
 - VoiceDetectorCalibration, 148
- AudioUtil.VoiceDetectorDummy, 149
- AudioUtil.VoiceDetectorFloat, 150
 - VoiceDetectorFloat, 150
- AudioUtil.VoiceDetectorShort, 150
 - VoiceDetectorShort, 151
- AudioUtil.VoiceLevelDetectCalibrate< T >, 156
 - Calibrate, 157
 - LevelMeter, 157
 - Process, 157
 - VoiceDetector, 157
 - VoiceLevelDetectCalibrate, 156
- Auto
 - POpusCodec.Enums, 13
- AutoConnectAndJoin
 - PhotonVoiceNetwork, 92
- AutoCreateRecorderIfNotFound
 - PhotonVoiceView, 95
- AutoCreateSpeakerIfNotFound
 - VoiceConnection, 139
- AutoLeaveAndDisconnect
 - PhotonVoiceNetwork, 92
- AutoStart
 - Recorder, 105
- Bandwidth
 - POpusCodec.Enums, 11
- BestRegionSummaryInPreferences
 - VoiceConnection, 140
- Bitrate
 - Recorder, 105
 - VoiceInfo, 154
- BufferReaderPushAdapter
 - BufferReaderPushAdapter< T >, 25
- BufferReaderPushAdapter< T >, 25
 - BufferReaderPushAdapter, 25
 - Service, 26
- BufferReaderPushAdapterAsyncPool
 - BufferReaderPushAdapterAsyncPool< T >, 26
- BufferReaderPushAdapterAsyncPool< T >, 26
 - BufferReaderPushAdapterAsyncPool, 26
 - Service, 27
- BufferReaderPushAdapterAsyncPoolCopy
 - BufferReaderPushAdapterAsyncPoolCopy< T >, 28
- BufferReaderPushAdapterAsyncPoolCopy< T >, 27
 - BufferReaderPushAdapterAsyncPoolCopy, 28
 - Service, 28
- BufferReaderPushAdapterAsyncPoolFloatToShort, 29
 - BufferReaderPushAdapterAsyncPoolFloatToShort, 29
- Service, 29
- BufferReaderPushAdapterAsyncPoolShortToFloat, 30
 - BufferReaderPushAdapterAsyncPoolShortToFloat, 30
 - Service, 31
- BufferReaderPushAdapterBase
 - BufferReaderPushAdapterBase< T >, 32
- BufferReaderPushAdapterBase< T >, 31
 - BufferReaderPushAdapterBase, 32
 - Dispose, 32
 - Service, 32
- Calibrate
 - AudioUtil.VoiceDetectorCalibration< T >, 148
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 157
- ChannelId
 - RemoteVoiceInfo, 111
- Channels
 - AudioUtil.ToneAudioReader< T >, 124
 - IAudioDesc, 44
 - POpusCodec.Enums, 11
 - VoiceInfo, 154
- ClearProcessors
 - LocalVoiceFramed< T >, 79
- ClientState
 - VoiceConnection, 140
- Code
 - VoiceEvent, 151
- Codec
 - Photon.Voice, 6
- ConnectAndJoin, 33
- ConnectAndJoinRoom
 - PhotonVoiceNetwork, 92
- ConnectUsingSettings
 - VoiceConnection, 137
- Convert
 - AudioUtil, 22, 23
- Count
 - Framer< T >, 43
- Create
 - LocalVoiceAudio< T >, 74
- CreateAudio
 - VoiceInfo, 153
- CreateAudioOpus
 - VoiceInfo, 153
- CreateLocalVoice
 - VoiceClient, 130
- CreateLocalVoiceAudioFromSource
 - VoiceClient, 131
- CreateLocalVoiceFramed< T >
 - VoiceClient, 131
- CurrentAvgAmp
 - AudioUtil.ILevelMeter, 54
- CurrentPeakAmp
 - AudioUtil.ILevelMeter, 54
- CustomAudioOutFactory
 - Speaker, 119
- DebugEchoMode

- LocalVoice, 72
- Recorder, 105
- DebugLostPercent
 - VoiceClient, 133
- Decoder
 - RemoteVoiceOptions, 113
- Default
 - Photon.Voice.IOS, 8
 - VoiceClient.CreateOptions, 34
- DefaultToSpeaker
 - Photon.Voice.IOS, 8
- Delay
 - POpusCodec.Enums, 12
- Delay10ms
 - POpusCodec.Enums, 12
- Delay20ms
 - POpusCodec.Enums, 12
- Delay2dot5ms
 - POpusCodec.Enums, 12
- Delay40ms
 - POpusCodec.Enums, 12
- Delay5ms
 - POpusCodec.Enums, 12
- Delay60ms
 - POpusCodec.Enums, 12
- DequeueOutput
 - IEncoder, 50
- Detected
 - AudioUtil.IVoiceDetector, 61
 - AudioUtil.VoiceDetector< T >, 146
- DetectedTime
 - AudioUtil.IVoiceDetector, 61
 - AudioUtil.VoiceDetector< T >, 146
- DeviceEnumeratorBase, 37
- DeviceInfo, 37
- DisableVad
 - VoiceDebugScript, 144
- Disconnect
 - PhotonVoiceNetwork, 92
- Dispatch
 - VoiceConnection, 138
- Dispose
 - BufferReaderPushAdapterBase< T >, 32
 - LoadBalancingTransport, 68
 - LocalVoiceFramed< T >, 79
 - ObjectPool< TType, TInfo >, 86
- DuckOthers
 - Photon.Voice.IOS, 8
- Dummy
 - LocalVoiceAudioDummy, 77
- EncoderDelay
 - OpusEncoder, 89
- Encrypt
 - LocalVoice, 72
 - Recorder, 105
- EndOfStream
 - IEncoder, 51
- Error
 - AudioUtil.ToneAudioReader< T >, 125
 - IAudioDesc, 44
 - IDecoder, 49
 - IEncoder, 51
- FactoryPrimitiveArrayPool< T >, 40
- FactoryReusableArray< T >, 40
- Flip, 41
- ForceRecordingAndTransmission
 - VoiceDebugScript, 144
- ForceToStereo< T >
 - AudioUtil, 23
- FPS
 - VoiceInfo, 154
- Frame
 - Framer< T >, 43
- FrameBuffer, 41
- FrameDuration
 - Recorder, 105
- FrameDurationSamples
 - VoiceInfo, 154
- FrameDurationUs
 - VoiceInfo, 154
- FrameOut< T >, 42
- Framer
 - Framer< T >, 43
- Framer< T >, 42
 - Count, 43
 - Frame, 43
 - Framer, 43
- FrameSize
 - LocalVoiceFramedBase, 80
 - VoiceInfo, 154
- FramesLost
 - VoiceClient, 133
- FramesLostPercent
 - VoiceConnection, 141
- FramesLostPerSecond
 - VoiceConnection, 141
- FramesReceived
 - VoiceClient, 133
- FramesReceivedPerSecond
 - VoiceConnection, 141
- FramesSent
 - LocalVoice, 72
 - VoiceClient, 133
- FramesSentBytes
 - LocalVoice, 72
 - VoiceClient, 133
- Fullband
 - POpusCodec.Enums, 11
- Game
 - AudioSessionParametersPresets, 20
- GetPlatformAPI< I >
 - IEncoder, 51
- GlobalInterestGroup
 - LoadBalancingTransport, 69
- GlobalPlaybackDelayMaxHard

- VoiceConnection, [141](#)
- GlobalPlaybackDelayMaxSoft
 - VoiceConnection, [141](#)
- GlobalPlaybackDelayMinSoft
 - VoiceConnection, [141](#)
- HandleConfigChange
 - AudioChangesHandler, [16](#)
- HandleDeviceChange
 - AudioChangesHandler, [16](#)
- Height
 - VoicInfo, [155](#)
- IAudioDesc, [44](#)
 - Channels, [44](#)
 - Error, [44](#)
 - SamplingRate, [44](#)
- IAudioInChangeNotifier, [45](#)
- IAudioOut< T >, [45](#)
- IAudioPusher< T >, [45](#)
 - SetCallback, [46](#)
- IAudioReader< T >, [46](#)
- IDataReader< T >, [47](#)
 - Read, [47](#)
- IDecoder, [47](#)
 - Error, [49](#)
 - Input, [48](#)
 - Open, [48](#)
- IDecoderDirect< B >, [49](#)
 - Output, [49](#)
- IDeviceEnumerator, [49](#)
- IEncoder, [50](#)
 - DequeueOutput, [50](#)
 - EndOfStream, [51](#)
 - Error, [51](#)
 - GetPlatformAPI< I >, [51](#)
 - Output, [51](#)
- IEncoderDirect< B >, [52](#)
 - Input, [52](#)
- IEncoderDirectImage, [52](#)
 - ImageFormat, [53](#)
- ILocalVoiceAudio, [54](#)
 - LevelMeter, [55](#)
 - VoiceDetector, [55](#)
 - VoiceDetectorCalibrate, [55](#)
 - VoiceDetectorCalibrating, [56](#)
- ILoggable, [56](#)
- ILoggableDependent, [56](#)
- ILogger, [56](#)
- ImageBufferInfo, [57](#)
- ImageBufferInfo.StrideSet, [121](#)
- ImageBufferNative, [57](#)
- ImageBufferNative.PlaneSet, [97](#)
- ImageBufferNativeAlloc, [57](#)
- ImageBufferNativeGCHandleSinglePlane, [58](#)
- ImageBufferNativePool< T >, [58](#)
- ImageFormat
 - IEncoderDirectImage, [53](#)
- IncreaseLogLevels
 - VoiceDebugScript, [144](#)
- Info
 - LocalVoice, [72](#)
 - ObjectPool< TType, TInfo >, [88](#)
 - RemoteVoicInfo, [111](#)
- Init
 - ObjectPool< TType, TInfo >, [87](#)
 - PhotonVoiceView, [95](#)
 - Recorder, [103](#)
- InitRecorder
 - VoiceConnection, [138](#)
- Input
 - IDecoder, [48](#)
 - IEncoderDirect< B >, [52](#)
 - OpusCodec.Decoder< T >, [34](#)
 - RawCodec.Decoder< T >, [36](#)
- InputFactory
 - Recorder, [105](#)
- Instance
 - PhotonVoiceNetwork, [93](#)
- InterestGroup
 - LocalVoice, [72](#)
 - Recorder, [106](#)
- IProcessor< T >, [58](#)
 - Process, [59](#)
- IResetable, [59](#)
- IsCurrentlyTransmitting
 - LocalVoice, [73](#)
 - Recorder, [106](#)
- IServiceable, [59](#)
 - Service, [60](#)
- IsInitialized
 - Recorder, [106](#)
- IsLinked
 - Speaker, [119](#)
- IsPhotonViewReady
 - PhotonVoiceView, [96](#)
- IsPlaying
 - Speaker, [119](#)
- IsRecorder
 - PhotonVoiceView, [96](#)
- IsRecording
 - PhotonVoiceView, [96](#)
 - Recorder, [106](#)
- IsSetup
 - PhotonVoiceView, [96](#)
- IsSpeaker
 - PhotonVoiceView, [96](#)
- IsSpeakerLinked
 - PhotonVoiceView, [96](#)
- IsSpeaking
 - PhotonVoiceView, [97](#)
- IVoiceTransport, [62](#)
- KeyFrameInt
 - VoicInfo, [155](#)
- Lag
 - Speaker, [119](#)

- LevelMeter
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 157
 - ILocalVoiceAudio, 55
 - Recorder, 106
- LevelMeterFloat
 - AudioUtil.LevelMeterFloat, 65
- LevelMeterShort
 - AudioUtil.LevelMeterShort, 66
- LoadBalancingFrontend, 67
- LoadBalancingTransport, 67
 - Dispose, 68
 - GlobalInterestGroup, 69
 - LoadBalancingTransport, 68
 - Service, 68
 - VoiceClient, 69
- LoadBalancingTransport2, 69
- LocalDebug
 - VoiceDebugScript, 144
- LocalUserServiceable
 - LocalVoice, 73
- LocalVoice, 70
 - DebugEchoMode, 72
 - Encrypt, 72
 - FramesSent, 72
 - FramesSentBytes, 72
 - Info, 72
 - InterestGroup, 72
 - IsCurrentlyTransmitting, 73
 - LocalUserServiceable, 73
 - Reliable, 73
 - RemoveSelf, 71
 - SendSpacingProfileMax, 73
 - TransmitEnabled, 73
- LocalVoiceAudio< T >, 74
 - Create, 74
 - VoiceDetectorCalibrate, 75
 - VoiceDetectorCalibrating, 75
- LocalVoiceAudioDummy, 76
 - Dummy, 77
 - VoiceDetectorCalibrate, 76
- LocalVoiceAudioFloat, 77
- LocalVoiceAudioShort, 77
- LocalVoiceFramed< T >, 78
 - AddPostProcessor, 78
 - AddPreProcessor, 79
 - ClearProcessors, 79
 - Dispose, 79
 - PushData, 79
 - PushDataAsync, 79
 - PushDataAsyncReady, 80
- LocalVoiceFramedBase, 80
 - FrameSize, 80
- LocalVoices
 - VoiceClient, 134
- LocalVoicesInChannel
 - VoiceClient, 132
- Logger, 81
 - VoiceConnection, 142
- LogLevel
 - VoiceConnection, 142
- LoopAudioClip
 - Recorder, 106
- MaxDatagrams
 - VoiceConnection, 139
- MaxDelayHard
 - PlaybackDelaySettings, 98
- MaxDelaySoft
 - PlaybackDelaySettings, 99
- Measurement
 - Photon.Voice.IOS, 9
- Mediumband
 - POpusCodec.Enums, 11
- MicAmplifier, 81
- MicAmplifierFloat, 81
- MicAmplifierShort, 82
- MicrophonePermission, 82
- MicrophoneType
 - Recorder, 107
- MicWrapper, 83
- MicWrapperPusher, 83
- MinDelaySoft
 - PlaybackDelaySettings, 99
- MinimalTimeScaleToDispatchInFixedUpdate
 - VoiceConnection, 139
- MixWithOthers
 - Photon.Voice.IOS, 7
- Mono
 - POpusCodec.Enums, 12
- MoviePlayback
 - Photon.Voice.IOS, 9
- MultiRoute
 - Photon.Voice.IOS, 7
- Music
 - POpusCodec.Enums, 13
- Narrowband
 - POpusCodec.Enums, 11
- NativeAndroidMicrophoneSettings, 83
- ObjectFactory< TType, TInfo >, 84
- ObjectPool
 - ObjectPool< TType, TInfo >, 85, 86
- ObjectPool< TType, TInfo >, 84
 - AcquireOrCreate, 86
 - Dispose, 86
 - Info, 88
 - Init, 87
 - ObjectPool, 85, 86
 - Release, 87
- On
 - AudioUtil.IVoiceDetector, 61
 - AudioUtil.VoiceDetector< T >, 147
- OnDetected
 - AudioUtil.IVoiceDetector, 62
 - AudioUtil.VoiceDetector< T >, 147
- OnRemoteVoiceInfoAction

- VoiceClient, 134
- OnRemoteVoiceRemoveAction
 - RemoteVoiceOptions, 114
 - Speaker, 119
- Open
 - IDecoder, 48
 - OpusCodec.Decoder< T >, 34
 - RawCodec.Decoder< T >, 36
- OpusApplicationType
 - POpusCodec.Enums, 12
- OpusCodec, 88
- OpusCodec.Decoder< T >, 34
 - Input, 34
 - Open, 34
- OpusCodec.DecoderFactory, 37
- OpusCodec.Encoder< T >, 38
- OpusCodec.EncoderFloat, 39
- OpusCodec.EncoderShort, 39
- OpusCodec.Factory, 39
- OpusCodec.Util, 128
- OpusDecoder< T >, 88
- OpusEncoder, 89
 - EncoderDelay, 89
- OpusException, 90
- OpusLib, 90
- Output
 - IDecoderDirect< B >, 49
 - IEncoder, 51
- Photon, 3
- Photon.Voice, 3
 - AudioOpus, 6
 - AudioSampleType, 6
 - Codec, 6
- Photon.Voice.IOS, 6
 - AllowBluetooth, 8
 - Ambient, 7
 - AudioProcessing, 7
 - AudioSessionCategory, 6
 - AudioSessionCategoryOption, 7
 - AudioSessionMode, 8
 - Default, 8
 - DefaultToSpeaker, 8
 - DuckOthers, 8
 - Measurement, 9
 - MixWithOthers, 7
 - MoviePlayback, 9
 - MultiRoute, 7
 - PlayAndRecord, 7
 - Playback, 7
 - Record, 7
 - SoloAmbient, 7
 - VideoChat, 9
 - VideoRecording, 9
 - VoiceChat, 8
- Photon.Voice.PUN, 9
- Photon.Voice.PUN.UtilityScripts, 9
- Photon.Voice.Unity, 9
- Photon.Voice.Unity.UtilityScripts, 10
- PhotonMicrophoneDeviceId
 - Recorder, 107
- PhotonMicrophoneEnumerator
 - Recorder, 107
- PhotonVoiceCreatedParams, 90
- PhotonVoiceLagSimulationGui, 90
- PhotonVoiceNetwork, 91
 - AutoConnectAndJoin, 92
 - AutoLeaveAndDisconnect, 92
 - ConnectAndJoinRoom, 92
 - Disconnect, 92
 - Instance, 93
 - UsePunAuthValues, 93
 - VoiceRoomNameSuffix, 93
 - WorkInOfflineMode, 93
- PhotonVoiceStatsGui, 93
- PhotonVoiceView, 94
 - AutoCreateRecorderIfNotFound, 95
 - Init, 95
 - IsPhotonViewReady, 96
 - IsRecorder, 96
 - IsRecording, 96
 - IsSetup, 96
 - IsSpeaker, 96
 - IsSpeakerLinked, 96
 - IsSpeaking, 97
 - RecorderInUse, 97
 - SetupDebugSpeaker, 95
 - SpeakerInUse, 97
 - UsePrimaryRecorder, 95
- Platform, 98
- PlayAndRecord
 - Photon.Voice.IOS, 7
- Playback
 - Photon.Voice.IOS, 7
- PlaybackDelayMaxHard
 - Speaker, 120
- PlaybackDelayMaxSoft
 - Speaker, 120
- PlaybackDelayMinSoft
 - Speaker, 120
- PlaybackDelaySettings, 98
 - MaxDelayHard, 98
 - MaxDelaySoft, 99
 - MinDelaySoft, 99
- PlaybackOnlyWhenEnabled
 - Speaker, 120
- PlaybackStarted
 - Speaker, 120
- PlayerId
 - RemoteVoiceInfo, 111
- POpusCodec, 11
- POpusCodec.Enums, 11
 - Audio, 12
 - Auto, 13
 - Bandwidth, 11
 - Channels, 11
 - Delay, 12

- Delay10ms, [12](#)
- Delay20ms, [12](#)
- Delay2dot5ms, [12](#)
- Delay40ms, [12](#)
- Delay5ms, [12](#)
- Delay60ms, [12](#)
- Fullband, [11](#)
- Mediumband, [11](#)
- Mono, [12](#)
- Music, [13](#)
- Narrowband, [11](#)
- OpusApplicationType, [12](#)
- RestrictedLowDelay, [12](#)
- SignalHint, [12](#)
- Stereo, [12](#)
- SuperWideband, [11](#)
- Voice, [13](#)
- Voip, [12](#)
- Wideband, [11](#)
- PrimaryRecorder
 - VoiceConnection, [142](#)
- PrimitiveArrayPool< T >, [99](#)
- Process
 - AudioUtil.LevelMeter< T >, [63](#)
 - AudioUtil.Resampler< T >, [115](#)
 - AudioUtil.VoiceDetector< T >, [146](#)
 - AudioUtil.VoiceDetectorCalibration< T >, [149](#)
 - AudioUtil.VoiceLevelDetectCalibrate< T >, [157](#)
 - IProcessor< T >, [59](#)
- PushData
 - LocalVoiceFramed< T >, [79](#)
- PushDataAsync
 - LocalVoiceFramed< T >, [79](#)
- PushDataAsyncReady
 - LocalVoiceFramed< T >, [80](#)
- RawCodec, [100](#)
- RawCodec.Decoder< T >, [36](#)
 - Input, [36](#)
 - Open, [36](#)
- RawCodec.Encoder< T >, [39](#)
- RawCodec.ShortToFloat, [116](#)
- ReactOnSystemChanges
 - Recorder, [107](#)
- Read
 - AudioUtil.ToneAudioReader< T >, [124](#)
 - IDataReader< T >, [47](#)
- Record
 - Photon.Voice.IOS, [7](#)
- Recorder, [100](#)
 - AudioClip, [104](#)
 - AudioGroup, [104](#)
 - AutoStart, [105](#)
 - Bitrate, [105](#)
 - DebugEchoMode, [105](#)
 - Encrypt, [105](#)
 - FrameDuration, [105](#)
 - Init, [103](#)
 - InputFactory, [105](#)
 - InterestGroup, [106](#)
 - IsCurrentlyTransmitting, [106](#)
 - IsInitialized, [106](#)
 - IsRecording, [106](#)
 - LevelMeter, [106](#)
 - LoopAudioClip, [106](#)
 - MicrophoneType, [107](#)
 - PhotonMicrophoneDeviceId, [107](#)
 - PhotonMicrophoneEnumerator, [107](#)
 - ReactOnSystemChanges, [107](#)
 - RecordOnlyWhenEnabled, [107](#)
 - RecordOnlyWhenJoined, [107](#)
 - ReliableMode, [108](#)
 - RequiresRestart, [108](#)
 - ResetLocalAudio, [103](#)
 - RestartRecording, [103](#)
 - SamplingRate, [108](#)
 - SkipDeviceChangeChecks, [108](#)
 - SourceType, [108](#)
 - StartRecording, [104](#)
 - StopRecording, [104](#)
 - StopRecordingWhenPaused, [108](#)
 - TransmitEnabled, [109](#)
 - TrySamplingRateMatch, [109](#)
 - TypeConvert, [109](#)
 - UnityMicrophoneDevice, [109](#)
 - UseMicrophoneTypeFallback, [109](#)
 - UseOnAudioFilterRead, [109](#)
 - UserData, [110](#)
 - VoiceDetection, [110](#)
 - VoiceDetectionDelayMs, [110](#)
 - VoiceDetectionThreshold, [110](#)
 - VoiceDetector, [110](#)
 - VoiceDetectorCalibrate, [104](#)
 - VoiceDetectorCalibrating, [110](#)
- Recorder.PhotonVoiceCreatedParams, [90](#)
- RecorderInUse
 - PhotonVoiceView, [97](#)
- RecordOnlyWhenEnabled
 - Recorder, [107](#)
- RecordOnlyWhenJoined
 - Recorder, [107](#)
- Release
 - ObjectPool< TType, TInfo >, [87](#)
- Reliable
 - LocalVoice, [73](#)
- ReliableMode
 - Recorder, [108](#)
- RemoteVoiceAdded
 - VoiceConnection, [143](#)
- RemoteVoiceInfo, [111](#)
 - ChannelId, [111](#)
 - Info, [111](#)
 - PlayerId, [111](#)
 - VoiceId, [112](#)
- RemoteVoiceInfoDelegate
 - VoiceClient, [132](#)
- RemoteVoiceInfos

- VoiceClient, [134](#)
- RemoteVoiceLink, [112](#)
- RemoteVoiceOptions, [112](#)
 - Decoder, [113](#)
 - OnRemoteVoiceRemoveAction, [114](#)
 - SetOutput, [113](#)
- RemoveLocalVoice
 - VoiceClient, [132](#)
- RemoveSelf
 - LocalVoice, [71](#)
- RequiresRestart
 - Recorder, [108](#)
- Resample< T >
 - AudioUtil, [23](#)
- ResampleAndConvert
 - AudioUtil, [24](#)
- Resampler
 - AudioUtil.Resampler< T >, [114](#)
- ResetAccumAvgPeakAmp
 - AudioUtil.ILevelMeter, [53](#)
 - AudioUtil.LevelMeter< T >, [63](#)
 - AudioUtil.LevelMeterDummy, [64](#)
- ResetLocalAudio
 - Recorder, [103](#)
- RestartPlayback
 - Speaker, [117](#)
- RestartRecording
 - Recorder, [103](#)
- RestrictedLowDelay
 - POpusCodec.Enums, [12](#)
- RoundTripTime
 - VoiceClient, [134](#)
- RoundTripTimeVariance
 - VoiceClient, [134](#)
- SamplingRate
 - AudioUtil.ToneAudioReader< T >, [125](#)
 - IAudioDesc, [44](#)
 - Recorder, [108](#)
 - VoiceInfo, [155](#)
- SaveIncomingStreamToFile, [115](#)
- SaveOutgoingStreamToFile, [115](#)
- SendAsap
 - VoiceConnection, [140](#)
- SendSpacingProfileMax
 - LocalVoice, [73](#)
- Service
 - BufferReaderPushAdapter< T >, [26](#)
 - BufferReaderPushAdapterAsyncPool< T >, [27](#)
 - BufferReaderPushAdapterAsyncPoolCopy< T >, [28](#)
 - BufferReaderPushAdapterAsyncPoolFloatToShort, [29](#)
 - BufferReaderPushAdapterAsyncPoolShortToFloat, [31](#)
 - BufferReaderPushAdapterBase< T >, [32](#)
 - IServiceable, [60](#)
 - LoadBalancingTransport, [68](#)
 - VoiceClient, [133](#)
- SetCallback
 - AudioUtil.ToneAudioPusher< T >, [122](#)
 - IAudioPusher< T >, [46](#)
- SetGlobalPlaybackDelaySettings
 - VoiceConnection, [138](#)
- SetOrSwitchAudioListener
 - WebRtcAudioDsp, [159](#)
- SetOrSwitchAudioOutCapture
 - WebRtcAudioDsp, [159](#)
- SetOutput
 - RemoteVoiceOptions, [113](#)
- SetPlaybackDelaySettings
 - Speaker, [117](#), [118](#)
 - VoiceConnection, [138](#)
- Settings
 - VoiceConnection, [140](#)
- SetupDebugSpeaker
 - PhotonVoiceView, [95](#)
- SignalHint
 - POpusCodec.Enums, [12](#)
- SkipDeviceChangeChecks
 - Recorder, [108](#)
- SoloAmbient
 - Photon.Voice.IOS, [7](#)
- SourceType
 - Recorder, [108](#)
- Speaker, [116](#)
 - Actor, [119](#)
 - CustomAudioOutFactory, [119](#)
 - IsLinked, [119](#)
 - IsPlaying, [119](#)
 - Lag, [119](#)
 - OnRemoteVoiceRemoveAction, [119](#)
 - PlaybackDelayMaxHard, [120](#)
 - PlaybackDelayMaxSoft, [120](#)
 - PlaybackDelayMinSoft, [120](#)
 - PlaybackOnlyWhenEnabled, [120](#)
 - PlaybackStarted, [120](#)
 - RestartPlayback, [117](#)
 - SetPlaybackDelaySettings, [117](#), [118](#)
 - StartPlayback, [118](#)
 - StopPlayback, [118](#)
- SpeakerFactory
 - VoiceConnection, [140](#)
- SpeakerInUse
 - PhotonVoiceView, [97](#)
- SpeakerLinked
 - VoiceConnection, [143](#)
- SpeakerPrefab
 - VoiceConnection, [142](#)
- StartPlayback
 - Speaker, [118](#)
- StartRecording
 - Recorder, [104](#)
- StartWhenDeviceChange
 - AudioChangesHandler, [16](#)
- Stereo
 - POpusCodec.Enums, [12](#)

- StopPlayback
 - Speaker, [118](#)
- StopRecording
 - Recorder, [104](#)
- StopRecordingWhenPaused
 - Recorder, [108](#)
- SuperWideband
 - POpusCodec.Enums, [11](#)
- SuppressInfoDuplicateWarning
 - VoiceClient, [134](#)
- TestAudioClip
 - VoiceDebugScript, [144](#)
- TestTone, [121](#)
- TestUsingAudioClip
 - VoiceDebugScript, [144](#)
- Threshold
 - AudioUtil.IVoiceDetector, [61](#)
 - AudioUtil.VoiceDetector< T >, [147](#)
- ToneAudioPusher
 - AudioUtil.ToneAudioPusher< T >, [122](#)
- ToneAudioReader, [123](#)
 - AudioUtil.ToneAudioReader< T >, [124](#)
- TransmitEnabled
 - LocalVoice, [73](#)
 - Recorder, [109](#)
- TryLateLinkingUsingUserData
 - VoiceConnection, [139](#)
- TrySamplingRateMatch
 - Recorder, [109](#)
- TypeConvert
 - Recorder, [109](#)
- UnityAudioOut, [125](#)
- UnityMicrophone, [126](#)
- UnityMicrophoneDevice
 - Recorder, [109](#)
- UnsupportedCodecException, [126](#)
 - UnsupportedCodecException, [126](#)
- UnsupportedPlatformException, [127](#)
 - UnsupportedPlatformException, [127](#)
- UnsupportedSampleTypeException, [128](#)
 - UnsupportedSampleTypeException, [128](#)
- UseMicrophoneTypeFallback
 - Recorder, [109](#)
- UseNativePluginChangeNotifier
 - AudioChangesHandler, [17](#)
- UseOnAudioConfigurationChanged
 - AudioChangesHandler, [17](#)
- UseOnAudioFilterRead
 - Recorder, [109](#)
- UsePrimaryRecorder
 - PhotonVoiceView, [95](#)
- UsePunAuthValues
 - PhotonVoiceNetwork, [93](#)
- UserData
 - Recorder, [110](#)
 - VoiceInfo, [155](#)
- VideoChat
 - Photon.Voice.IOS, [9](#)
- VideoRecording
 - Photon.Voice.IOS, [9](#)
- Voice
 - POpusCodec.Enums, [13](#)
- VoiceChat
 - Photon.Voice.IOS, [8](#)
- VoiceClient, [128](#)
 - CreateLocalVoice, [130](#)
 - CreateLocalVoiceAudioFromSource, [131](#)
 - CreateLocalVoiceFramed< T >, [131](#)
 - DebugLostPercent, [133](#)
 - FramesLost, [133](#)
 - FramesReceived, [133](#)
 - FramesSent, [133](#)
 - FramesSentBytes, [133](#)
 - LoadBalancingTransport, [69](#)
 - LocalVoices, [134](#)
 - LocalVoicesInChannel, [132](#)
 - OnRemoteVoiceInfoAction, [134](#)
 - RemoteVoiceInfoDelegate, [132](#)
 - RemoteVoiceInfos, [134](#)
 - RemoveLocalVoice, [132](#)
 - RoundTripTime, [134](#)
 - RoundTripTimeVariance, [134](#)
 - Service, [133](#)
 - SuppressInfoDuplicateWarning, [134](#)
 - VoiceClient, [130](#)
 - VoiceConnection, [142](#)
- VoiceClient.CreateOptions, [33](#)
 - Default, [34](#)
- VoiceComponent, [135](#)
- VoiceConnection, [135](#)
 - AutoCreateSpeakerIfNotFound, [139](#)
 - BestRegionSummaryInPreferences, [140](#)
 - ClientState, [140](#)
 - ConnectUsingSettings, [137](#)
 - Dispatch, [138](#)
 - FramesLostPercent, [141](#)
 - FramesLostPerSecond, [141](#)
 - FramesReceivedPerSecond, [141](#)
 - GlobalPlaybackDelayMaxHard, [141](#)
 - GlobalPlaybackDelayMaxSoft, [141](#)
 - GlobalPlaybackDelayMinSoft, [141](#)
 - InitRecorder, [138](#)
 - Logger, [142](#)
 - LogLevel, [142](#)
 - MaxDatagrams, [139](#)
 - MinimalTimeScaleToDispatchInFixedUpdate, [139](#)
 - PrimaryRecorder, [142](#)
 - RemoteVoiceAdded, [143](#)
 - SendAsap, [140](#)
 - SetGlobalPlaybackDelaySettings, [138](#)
 - SetPlaybackDelaySettings, [138](#)
 - Settings, [140](#)
 - SpeakerFactory, [140](#)
 - SpeakerLinked, [143](#)

- SpeakerPrefab, 142
- TryLateLinkingUsingUserData, 139
- VoiceClient, 142
- VoiceDebugScript, 143
 - DisableVad, 144
 - ForceRecordingAndTransmission, 144
 - IncreaseLogLevels, 144
 - LocalDebug, 144
 - TestAudioClip, 144
 - TestUsingAudioClip, 144
- VoiceDetection
 - Recorder, 110
- VoiceDetectionDelayMs
 - Recorder, 110
- VoiceDetectionThreshold
 - Recorder, 110
- VoiceDetector
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 157
 - ILocalVoiceAudio, 55
 - Recorder, 110
- VoiceDetectorCalibrate
 - ILocalVoiceAudio, 55
 - LocalVoiceAudio< T >, 75
 - LocalVoiceAudioDummy, 76
 - Recorder, 104
- VoiceDetectorCalibrating
 - ILocalVoiceAudio, 56
 - LocalVoiceAudio< T >, 75
 - Recorder, 110
- VoiceDetectorCalibration
 - AudioUtil.VoiceDetectorCalibration< T >, 148
- VoiceDetectorFloat
 - AudioUtil.VoiceDetectorFloat, 150
- VoiceDetectorShort
 - AudioUtil.VoiceDetectorShort, 151
- VoiceEvent, 151
 - Code, 151
- VoiceId
 - RemoteVoiceInfo, 112
- VoiceInfo, 152
 - Bitrate, 154
 - Channels, 154
 - CreateAudio, 153
 - CreateAudioOpus, 153
 - FPS, 154
 - FrameDurationSamples, 154
 - FrameDurationUs, 154
 - FrameSize, 154
 - Height, 155
 - KeyFrameInt, 155
 - SamplingRate, 155
 - UserData, 155
 - Width, 155
- VoiceLevelDetectCalibrate
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 156
- VoiceLogger, 158
- VoiceRoomNameSuffix
 - PhotonVoiceNetwork, 93
- VoIP
 - AudioSessionParametersPresets, 20
- Voip
 - POpusCodec.Enums, 12
- WebRtcAudioDsp, 158
 - SetOrSwitchAudioListener, 159
 - SetOrSwitchAudioOutCapture, 159
- WebRTCAudioLib, 160
- WebRTCAudioProcessor, 160
- Wideband
 - POpusCodec.Enums, 11
- Width
 - VoiceInfo, 155
- WorkInOfflineMode
 - PhotonVoiceNetwork, 93