

Quiz: defining data

This quiz has 5 questions. The passing grade is 4.

[Back](#)[Next](#)

Started on	Wednesday, January 15, 2025, 2:23 PM
State	Finished
Completed on	Wednesday, January 15, 2025, 2:27 PM
Time taken	4 mins 53 secs
Grade	2.00 out of 5.00 (40%)

Question **1**

Incorrect

0.00 points out of 1.00

To specify a character field containing a single quote, we must enclose the value with double quotes, like this:

DC C"O'Sullivan"

Select one:

- ☒ True ✕
- ☐ False

To specify a single quote in a character value, we must use two consecutive single quotes:

DC C'O"Sullivan'

The correct answer is 'False'.

Question **2**

Incorrect

0.00 points out of 1.00

[Back](#)[Next](#)

To specify the length of a field in DC or DS, we must use a duplication factor

Select one:

☒ True ✖

☐ False

To specify the length of a field we must use the "**L**" (length modifier) option, not duplication factor. Duplication factor is for defining repeated, consecutive instances, of a field.

The correct answer is 'False'.

Question 3

Incorrect

0.00 points out of 1.00

Back

Next

Which of these statements generates 3 bytes containing X'F1F2F3' (EBCDIC '123')? (Select 3)

Select one or more:

- ☒ A. Fld3 DC CL3'0123' ✕
- ☒ B. Fld1 DC C'123' ✓
- ☒ C. Fld5 DC XL3'F0F1F2F3' ✓
- ☐ D. Fld2 DC CL3'1234'
- ☐ E. Fld4 DC XL3'F1F2F3F4'

The correct answers are:

Fld1 DC C'123'

This generates 3 bytes that contain the characters '123', as per the DC statement. No surprises here!

Fld2 DC CL3'1234'

The explicit length is 3, and character fields are truncated on the right. The '4' is dropped, leaving '123'.

Fld5 DC XL3'F0F1F2F3'

The explicit length is 3, and hexadecimal fields are truncated on the left. X'F0' is dropped, leaving X'F1F2F3'.

The incorrect answers are:

Fld3 DC CL3'0123'

Truncated on the right, this leaves '012'.

Fld4 DC XL3'F1F2F3F4'

Truncated on the left, this leaves X'F2F3F4'.

The correct answers are:

Fld1 DC C'123'

,

Fld2 DC CL3'1234'

,

Fld5 DC XL3'F0F1F2F3'

Question **4**

Correct

1.00 points out of 1.00

[Back](#)[Next](#)

The Assembler instruction DEFINE STORAGE (DS) reserves an area of storage without an initial value

Select one:

☒ True ✓☐ False

The correct answer is 'True'.

Question **5**

Correct

1.00 points out of 1.00

The DC type for a binary fullword integer is “F”

Select one:

☒ True ✓☐ False

Correct!

The correct answer is 'True'.