

MS 5607 BARO 1 | I2C 3

- Registers

Addr (Hex)	Register Name	Data
0B	INTERRUPT_CFG	0b1100
0F	WHO_AM_I	
10	CTRL_REG1	0b01010010
11	CTRL_REG2	0b00010010
12	CTRL_REG3	0b00000100
28	PRESSURE_OUT_XL	POUT[7:0]
29	PRESSURE_OUT_L	POUT[15:8]
2A	PRESSURE_OUT_H	POUT[23:16]
2B	TEMP_OUT_L	TOUT[7:0]
2C	TEMP_OUT_H	TOUT[15:8]

- Characteristics

- Range: 260 to 1260 hPa
- ODR: 75 Hz (low noise mode)
- Pressure Sensitivity: 4096 LSB/hPa
- Temperature Sensitivity: 100 LSB/C
- Resolution: 0.5 hPa

- I2C

- Address: 0b1011100
- Data delivered MSB first LSB last
- Data transitioned on falling edge of SCLK

- Interrupts

- INT fire pull: HIGH
- Use INT 1
- INT fired when DATA READY, cleared when INT STATUS bit READ

- Sequence

1. Read pressure data stored in 3 registers
2. Divide by 4096 LSB/hPa
3. Read temperature data stored in 2 registers
4. Divide by 100 LSB/C

Visit datasheet page 9 for step-by-step calculations