

Fiber Optic Project

Vincent Edwards, Ali Mortada

Mt. San Antonio College, Physics 4C, CRN 20889
Nov 30, 2023

1. Purpose and Hypothesis

The goal of the experiment is to examine the relationship between the speed of light in a vacuum and wavelength of light. Using the *Industrial Fiber Optics Speed of Light Apparatus* and an oscilloscope, the time for light to pass through a fiber optic cable of known length and index of refraction can be measured. From there, the speed of light can be calculated. Wavelength will be varied by soldering different colored LEDs onto the apparatus. In theory, wave speed should be independent of wavelength.

2. Materials

- Caliper
- Tray
 - Large enough to support the long fiber optic cable
 - As lightweight as possible
- Balance 1
 - Able to support the short fiber optic cable
 - More precision, lower weight limit
- Balance 2
 - Able to support the tray and the long fiber optic cable simultaneously
 - Less precision, higher weight limit
- *Industrial Fiber Optics Speed of Light Apparatus*
 - Also referred to as the “speed of light kit”
 - Top part is the circuit board, which is screwed onto a base
- 110 VAC-to-DC power adapter
- Short fiber optic cable
 - About 15 cm long
- Long fiber optic cable
 - About 20 m long
- Dual-channel oscilloscope and its power cable
- 2 oscilloscope probes
- Fiber optic red LED
 - IF-E96E
 - Included with the speed of light kit
- Fiber optic green LED
 - IF-E93

- Fiber optic blue LED
 - IF-E92B
- Phillips head screwdriver
- Pliers
- Circuit board holder
- Soldering iron
- Solder
- Desoldering solder sucker **OR** Desoldering wick
- If fiber preparation is required
 - 600-grit polishing paper
 - Polishing liquid (water, glycerin, or light oil)
 - Sharp knife or single-edge razor blade

3. Procedures

1. Check the ends of the fiber optic cable to see if they are polished and flat. If not, they need to be prepared.
 - Cut 1 to 2 mm off the end of the fiber cable with the sharp knife or single-edge razor blade. Try to get as square a cut as possible.
 - Wet the 600-grit polishing paper with the polishing liquid (water, glycerin, or light oil) and place the paper, abrasive side facing up, on a hard surface.
 - Polish the end of the fiber by moving it in a “figure 8” pattern while holding it perpendicular against the polishing paper.
 - Check the end of the fiber. If it is cloudy, not flat, or has scratches, repeat the previous step.
 - Repeat the previous two steps for both ends of each fiber.
2. If needed, desolder the two pins that connect the fiber optic LED to the speed of light kit. Afterwards, different fiber optic LEDs can be swapped in and out of the slot without re-soldering.
 - Unscrew the 6 screws connecting the top of the speed of light kit, the circuit board, to its base.
 - Remove the screw and nut keeping the LED secure on the circuit board. Pliers might be helpful for keeping the nut in place while the screw is loosened.
 - Wet with water the sponge used for cooling the tip of the soldering iron.
 - Plug in and turn on the soldering iron. Wait for it to get hot (about 750°F).
 - Turn on the overhead vent to capture any fumes.
 - Use the circuit board holder to keep the board secure, with the pins to be desoldered easily accessible.

- Use the soldering iron to melt the solder at the pins where the fiber optic LED is connected to the circuit board. Use the solder sucker or the desoldering wick to remove the solder, and ultimately remove the LED. Alternatively, use pliers to gently wiggle and pull the LED away from the board. At the same time, use the soldering iron to heat each pin.
 - Reattach the LED and secure it with the screw and nut.
 - Reconnect the circuit board to its base, and secure it with the 6 screws.
3. Measure the length of the short fiber optic cable.
 - Using the caliber, measure the length of the short fiber cable. Make sure the cable is straight.
 4. Measure the mass of both the short and long fiber optic cables.
 - Using balance 1, measure the mass of the short fiber optic cable.
 - Place the tray on balance 2 and zero the balance.
 - Place the long fiber optic cable on the tray, and measure the mass of the cable using balance 2.
 5. Connect both the speed of light kit and the dual-channel oscilloscope to power and to each other.
 - Connect the oscilloscope to power and turn it on.
 - Connect one of the oscilloscope probes to channel 1, and the other probe to channel 2.
 - Connect the probe of channel 1 to the blue test point marked “REFERENCE” on the speed of light kit. Connect the ground lead of the same probe to the test point labeled “GND” just below the “REFERENCE” test point.
 - Connect the probe of channel 2 to the blue test point marked “DELAY” on the speed of light kit. Connect the ground lead of the same probe to the test point labeled “GND” just below the “DELAY” test point.
 - Using the 110 VAC-to-DC power adapter, connect the speed of light kit to power.
 6. Calibrate the speed of light kit using the short fiber optic cable.
 - Turn the “Calibration Delay” knob on the speed of light kit to the 12 o’clock position.
 - Loosen the fiber optic cinch nuts on the fiber optic LED and detector. Insert one end of the short fiber optic cable into the LED until it is seated, then lightly tighten the cinch nut. Afterwards, insert the other end of the cable into the detector until it is seated, then lightly tighten the cinch nut.
 - Set the triggering mode of the oscilloscope to auto, channel 1, rising edge. Adjust the trigger level so that the pulses on channels 1 and 2 can be seen.
 - Adjust the voltage scaling and offset for both channels so that the pulses can be clearly seen.

- Adjust the time scaling and offset such that only one pulse from each channel is fully visible on the screen.
 - Using the measure functionality, set the oscilloscope to measure the time between the first rising edge of channel 1 and the following first rising edge of channel 2 at the 50% crossing (Channel Delay FRFR[1-2]). Make sure the statistics display is on.
 - Using the measure functionality, set the oscilloscope to measure the time between the first rising edge of channel 2 and the following first rising edge of channel 1 at the 50% crossing (Channel Delay FRFR[2-1]). Make sure the statistics display is on.
 - If pulse 1 occurs before pulse 2, then FRFR[1-2] will give a reading and FRFR[2-1] will not. If pulse 2 occurs before pulse 1, then FRFR[2-1] will give a reading and FRFR[1-2] will not. Turning the “Calibration Delay” knob on the speed of light kit will move pulse 2 left and right, changing the time it occurs. Adjust the calibration knob such that the two pulses occur at the same time. This will be the case when FRFR[1-2] and FRFR[2-1] repeatedly toggle between which one is giving a reading.
7. Measure the time for light to pass through the long fiber optic cable.
- Loosen the fiber optic cinch nuts on the fiber optic LED and detector. Remove the short fiber optic cable.
 - Insert one end of the long fiber optic cable into the LED until it is seated, then lightly tighten the cinch nut. Afterwards, insert the other end of the cable into the detector until it is seated, then lightly tighten the cinch nut.
 - If needed, adjust the time scaling and offset such that only one pulse from each channel is fully visible on the screen.
 - FRFR[1-2] should be giving a reading, while FRFR[2-1] should not be reading. Turn the statistics menu off and back on, as this will clear the data it has measured already. Allow FRFR[1-2] to take at least 1000 time measurements. Then, record the mean and standard deviation.
 - With the measurement made, the speed of light kit and oscilloscope can be turned off. Loosen the fiber optic cinch nuts and remove the long fiber optic cable.
8. Switch out the fiber optic LED for one of a different color.
- Unscrew the 6 screws connecting the top of the speed of light kit, the circuit board, to its base.
 - Remove the screw and nut keeping the LED secure on the circuit board. Pliers might be helpful for keeping the nut in place while the screw is loosened.
 - Pull out the old fiber optic LED.
 - Attach the new fiber optic LED and secure it with the screw and nut.
 - Reconnect the circuit board to its base, and secure it with the 6 screws.
9. Repeat steps 5-8 for the each fiber optic LED color (red, green, blue).

- The kit starts with the red LED installed, so start with that color and install it back at the end.

4. Results

5. Uncertainty

6. Conclusion

7. Citations

[1] Karen Schnurbusch, *Physics 4C Equations*, Mt. San Antonio College, 2023, pp. 4, 10.