

```

; MSP430 Two operand instruction - Addressing modes with LED blink
;*****
.cdecls C,LIST, "msp430.h"
;-----
        .def      RESET                ; Export program entry-point to
                                           ; make it known to linker.

        .data
p1:      .word     2
p2:      .word     2
p3:      .word     2
;-----
        .text                          ; Program Start
;-----
RESET    mov.w     #0280h,SP            ; Initialize stackpointer
StopWDT  mov.w     #WDTPW+WDTHOLD,&WDTCTL ; Stop WDT
SetupP1  bis.b     #001h,&P1DIR         ; P1.0 output

Ins1     mov       #0x0240, R10
Ins2     mov       R10, R11
Ins3     mov       #0x0200, R10
Ins4     mov       #0xABCD, 4(R10)
Ins5     mov       4(R10), 2(R11)
Ins6     mov       #0xEF01, &0x0200
Ins7     mov       @R10, 0(R11)
Ins8     mov       @R10+, 4(R11)
Ins9     mov       #0xFEDC,p2
Inst10   mov       p2,R14
Inst11   mov       &p2,&p1
Inst12   mov       p1,p2
Inst13   mov       p1,p3

Mainloop xor.b     #001h,&P1OUT         ; Toggle P1.0
Wait     mov.w     #050000,R15          ; Delay to R15
L1       dec.w     R15                  ; Decrement R15
        jnz       L1                  ; Delay over?
        jmp       Mainloop            ; Again
;-----
;
;      Interrupt Vectors
;-----
        .sect     ".reset"             ; MSP430 RESET Vector
        .short    RESET                ;
        .end

```