

Peripheral Troubleshooting Theory

Task 1: USB Keyboard & Mouse Issues

- **Dead Battery (Wireless):** Replace the batteries or charge the device.
- **Not Responding (Wired):** Unplug the device and try connecting it to a different USB port.
- **Cursor Lagging/Jumping:** Clean the optical sensor under the mouse.
- **Sticky Keys:** Clean under the affected keys using a can of compressed air.
- **Driver Glitch:** Unplug the device, restart the laptop completely, and plug it back in.

Task 2: Bluetooth Headphones Troubleshooting Flow

1. **Check Power:** Ensure the headphones are fully charged and turned on.
2. **Pairing Mode:** Put the headphones into pairing mode (usually indicated by a flashing LED).
3. **Phone Settings:** Open the phone's Settings > Bluetooth and toggle it OFF, then back ON.
4. **Forget Device:** If it was previously connected, find the headphones in the saved devices list and select "Forget" or "Unpair".
5. **Reconnect:** Tap the headphone's name under the "Available Devices" list to establish a fresh connection.

Task 3: Webcam Not Detected in Zoom (Windows 10) Checklist

1. **Physical Connection:** Verify the USB cable is securely plugged in without any fraying.
2. **Privacy Settings (Global):** Go to Windows Settings > Privacy > Camera. Ensure "Allow apps to access your camera" is toggled ON.
3. **Privacy Settings (App):** Scroll down in the same menu and ensure "Allow desktop apps to access your camera" (or Zoom specifically) is enabled.
4. **Device Manager (Status):** Open Device Manager. Look under "Cameras" or "Imaging devices" to ensure the device is listed and not disabled.
5. **Device Manager (Drivers):** Right-click the webcam in Device Manager and select "Update driver."
6. **Zoom Settings:** Open Zoom, go to Video Settings, and ensure the correct camera is selected from the dropdown menu instead of a blank default.

Task 4: Printer "Offline" Windows Troubleshooter Guide

- **How to run it:** Go to Windows Settings > Devices > Printers & scanners. Click on the offline printer, select "Manage," and click "Run the troubleshooter."
- **What it does:** The tool automatically checks for communication errors, clears stuck print jobs by restarting the Print Spooler service, and verifies network connectivity.
- **Information provided:** It will display a summary report showing exactly what components it tested, what problems were found, and whether it successfully applied an automatic fix or if you need to manually intervene (like plugging in a cable).