

## BOM - WLANThermo Nano v1 Pitmaster-Erweiterung Cuboid

Kennung im Schaltplan	Bauteilbezeichnung	Anmerkung	Größe	Menge	Händler	enthalten in
F1	OZCJ0150FF2C	Resetable Fuse, IH 1.5A, IT 3.0A, 6V	SMD 1206	1	<a href="#">Mouser</a>	<a href="#">Mouser-Warenkorb</a>
F2	OZCJ0050AF2E	Resetable Fuse, IH 0.5A, IT 1.0A, 24V	SMD 1206	1	<a href="#">Mouser</a>	Mouser-Warenkorb
IC1	MT3608	DC-DC-Converter	SOT 23-6	1	<a href="#">ALI</a>	<a href="#">Cuboid-Bauteil-Kit</a>
IC2	TLV271CDBVR	Rail-to-Rail Operational Amplifier	SOT 23-5	1	<a href="#">Mouser</a>	Mouser-Warenkorb
T1	2SC3303	Transistoren NPN	TO-252-3	1	<a href="#">ALI /</a> <a href="#">reichelt</a>	Cuboid-Bauteil-Kit
D1 / D2	PMEG4030ER/8X	Schottky Rectifiers, If 3A	SOD-123-2	2	<a href="#">Mouser</a>	Mouser-Warenkorb
D3	HT-193NB-5589	LED BLUE	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
R1	RC0603DR-0747KL	47K, 0.5%, 100 ppm/K	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
R2	RC0603FR-072K32L	2.32K, 1%, 100 ppm/K	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
R3 / R8	RC0603FR-0710KL	10K, 1%, 100 ppm/K	SMD 0603	2	<a href="#">Mouser</a>	Mouser-Warenkorb
R4	RC0603JR-070RL	0R	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
R5	RC0603FR-0712KL	12K, 1%, 100 ppm/K	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
R6 / R9	RC0603FR-072KL	2K, 1%, 100 ppm/K	SMD 0603	2	<a href="#">Mouser</a>	Mouser-Warenkorb
R7	RC0603FR-073K48L	3.48K, 1%, 100ppm/K, (PROG)	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
C1 / C2	GRT21BR61E226ME13L	22uF, 25V, 20%, X5R	SMD 0805	2	<a href="#">Mouser</a>	Mouser-Warenkorb
C3	GRM188R71C105KE15D	1uF, 16V, 10%, X5R	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
C4	GRM188R71H104KA93D	100nF, 50V, X7R	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
C5	GRM188R71H102KA01D	1nF, 50V, X7R	SMD 0603	1	<a href="#">Mouser</a>	Mouser-Warenkorb
L1	SRN6045TA-220M	22uH, 2.3A	SMD 6x6x4.2	1	<a href="#">Mouser</a>	Mouser-Warenkorb
K1	10118192-0001LF	Micro-USB Connector	SMD	1	<a href="#">Mouser</a>	Mouser-Warenkorb
K2 / K4	DC031A	DAC Connector	SMD	2	<a href="#">ALI</a>	Cuboid-Bauteil-Kit

K2* / K4*	171-PA35135-1-E	3.5x 1.3 mm Stecker	---	2 <a href="#">Mouser</a>	Mouser-Warenkorb
P1	Platine	0,8 mm Platinendicke	---	1 <a href="#">GSV-Forum</a>	Cuboid-Bauteil-Kit
G1	Gehäuse		---	1 <a href="#">3Dhubs</a>	---
M1	Schrauben	M2x10 Zylinderkopfschraube DIN 84	---	4 <a href="#">Ebay</a>	Cuboid-Bauteil-Kit
M2	Verbindungskabel	2 Adern, Verbindung Nano zu Cubiod	---	1	---
K3	RT5MPR	Mini (Tiny) XLR	TH	1 <a href="#">Mouser / reichelt</a>	optional
K3*	RT5FC-B	Mini (Tiny) XLR Stecker	---	1 <a href="#">Mouser / reichelt</a>	optional
U3	HK 21	DC-Kupplung 5,5x2,1 mm Hohlstecker	---	1 <a href="#">reichelt</a>	optional
U3	HK 25	DC-Kupplung 5,5x2,5 mm Hohlstecker	---	1 <a href="#">reichelt</a>	optional