

Tenth St. at Peachtree St.

```

GEORGIA DOT      Tenth St at Peachtree St      Intersection # 51
                  PHASE BANK 1                  ID: 223
10:05:25  1/27/06  -- PHASE TIMING PARAMETERS --  Last Change: 9/21/99 1
                  WBL  EBL  NBL  SBL  WBT  SBL  NBT
                  <1>  <2>  <3>  <4>  <5>  <6>  <7>  <8>  ( 0F 2)
                  ----
<0>  WALK          0      7      0      7      0      7      0      7
<1>  FLASH D/W     0     17      0     13      0     17      0     13
<2>  MIN INITIAL   5     15      8     12      8     15      5     16
<3>  TYP 3 LIMIT   5     15      8     12      8     15      5     16
<4>  ADD/VEH      0.0    0.0    0.0    0.0    0.0    0.0    0.0    0.0
<5>  VEH EXT      2.0    5.0    3.0    3.0    2.0    5.0    2.0    3.0
<6>  MAX GAP      2.0    5.0    3.0    3.0    2.0    5.0    2.0    3.0
<7>  MIN GAP      2.0    5.0    3.0    3.0    2.0    5.0    2.0    3.0
<8>  MAX LIMIT    10     45     15     30     10     45     15     30
<9>  MAX 2        10     45     15     30     10     45     15     30
<A>  DELAY WALK    0      0      0      0      0      0      0      0
<B>  PREMT PD CLR  0      0      0      0      0      0      0      0
<C>  COND SVC MIN  0      0      0      0      0      0      0      0
<D>  REDUCE EVERY  0.0    0.0    0.0    0.0    0.0    0.0    0.0    0.0
<E>  YELLOW       3.6    3.8    3.6    3.6    3.6    3.8    3.6    3.6
<F>  RED CLEAR    1.2    2.2    1.2    1.9    1.2    2.2    1.2    1.9
                  <F-column-row>
                  PgDn to view Alternate Timing
                  < Change/Repeat data, select phase Bank or display Menu >

```

```

GEORGIA DOT      Tenth St at Peachtree St      Intersection # 51
                  ID: 223
10:05:41  1/27/06  -- PHASE FUNCTIONS --      Last Change: 1/27/06

                  Enter at <F-F-row>
                  <C-0-F> = 1  PHASES: 12345678  <C-0-F> = 2  PHASES: 12345678
                  -----
<0>  PERMIT        12345678  FAST G FLASH
<1>  RED LOCK      2 6      GREEN FLASH
<2>  YELLOW LOCK   2 6      FLASH WALK
<3>  VEH RECALL    2 6      GUAR. PASSAGE
<4>  PED RECALL    2 6      SIMULT. GAP
<5>  PEDS (VIEW)   2 4 6 8  SEQ'L TIMING
<6>  REST IN WALK  2 6      ADVANCED WALK
<7>  RED REST      2 6      DELAYED WALK
<8>  DOUBLE ENTRY  2 4 6 8  EXTERN RECALL
<9>  MAX RECALL    2 6      OVLP GRN STRT
<A>  SOFT RECALL   2 6      MAX EXTEN
<B>  MAX 2         2 6      INH PED RSRV
<C>  COND SERVE    2 6      SEMI ACTUATED
<D>  EXT COND      2 6      STRT OVLP YEL
<E>  YELLOW START  2 6      STRT VEH CALL 12345678
<F>  FIRST PHASES  2 6      STRT PED CALL 12345678
                  PgDn to view Dimming Assignments
                  < Change data, Repeat last data, display Menu > <Esc> to exit

```

GEORGIA DOT Tenth St at Peachtree St Intersection # 51
 ID: 223
 10:06:09 1/27/06 -- TIME BASE COORDINATION -- Last Change: 9/21/99 ↑

	-- Bank 1 --			DOW	-- Bank 2 --			DOW
	TIME	PLAN	OFS	1234567	TIME	PLAN	OFS	1234567
EVENT 0	06:45	4	A	23456	00:00			
EVENT 1	09:30	1	A	23456	00:00			
EVENT 2	15:45	7	A	23456	00:00			
EVENT 3	18:15	1	A	23456	00:00			
EVENT 4	07:00	1	A	7	00:00			
EVENT 5	08:30	1	A	1	00:00			
EVENT 6	00:00	0			00:00			
EVENT 7	00:00	0			00:00			
EVENT 8	00:00	0			00:00			
EVENT 9	00:00	0			00:00			
EVENT A	00:00	0			00:00			
EVENT B	00:00	0			00:00			
EVENT C	00:00	0			00:00			
EVENT D	00:00	0			00:00			
EVENT E	00:00	0			00:00			
EVENT F	00:00	0			00:00			

<see Help (?) for keystrokes>
 < Change data, Repeat last data, display Menu > <Esc> to exit

GEORGIA DOT Tenth St at Peachtree St Intersection # 51
 ID: 223
 10:06:12 1/27/06 -- COORDINATION SHEET 1 -- Last Change: 7/31/03

PLAN:	<1>	<2>	<3>	<4>	<5>	<6>	<7>	<8>	<9>
<0> CYCLE TIME	95	80	80	100	90	80	100	90	80
<1> FORCE PH. 1	76	69	69	79	74	69	79	74	68
<2> FORCE PH. 2	0	0	0	0	0	0	0	0	0
<3> FORCE PH. 3	33	31	31	34	31	30	34	32	30
<4> FORCE PH. 4	62	56	56	64	60	57	64	60	57
<5> FORCE PH. 5	76	69	69	79	74	69	79	74	68
<6> FORCE PH. 6	0	0	0	0	0	0	0	0	0
<7> FORCE PH. 7	33	31	31	34	31	30	34	30	30
<8> FORCE PH. 8	62	56	56	64	60	57	64	60	57
<9> RING OFFSET	0	0	0	0	0	0	0	0	0
<A> OFFSET A	75	79	79	65	49	49	37	28	5
 OFFSET B	0	0	0	0	0	0	0	0	0
<C> OFFSET C	0	0	0	0	0	0	0	0	0
<D> END PERM 1	19	19	19	19	19	19	19	19	19
<E> HOLD REL.	255	255	255	255	255	255	255	255	255
<F> ZONE OFFSET	0	0	0	0	0	0	0	0	0

<C-plan#-row>
 < Change data, Repeat last data, display Menu > <Esc> to exit