

Current Revision	1.0	
Revision History		
Date	Revision	Description
2025/2/22	1.0	Initial Release,WeAct-N006 Pinmux

WeAct-N006 A1 Pinmux				
Carrier Board Function(载板)			SOM Connector (核心板)	
Signal Name	Position	Level	Signal Name	Pin
HDMI				
HDMI TXC P		/	DP1 TXD3	83
HDMI TXC N		/	DP1 TXD3	81
HDMI TX0 P		/	DP1 TXD2	77
HDMI TX0 N		/	DP1 TXD2	75
HDMI TX1 P		/	DP1 TXD1	71
HDMI TX1 N		/	DP1 TXD1	69
HDMI TX2 P		/	DP1 TXD0	65
HDMI TX2 N		/	DP1 TXD0	63
HDMI DDC SCL		/	DP1 AUX P	100
HDMI DDC SDA		/	DP1 AUX N	98
HDMI HPD		/	DP1 HPD	96
HDMI CEC		/	HDMI CEC	94
GigaEthernet				
GBE MDIO P		/	GBE MDIO	186
GBE MDIO N		/	GBE MDIO	184
GBE MDI1 P		/	GBE MDI1	192
GBE MDI1 N		/	GBE MDI1	190
GBE MDI2 P		/	GBE MDI2	198
GBE MDI2 N		/	GBE MDI2	196
GBE MDI3 P		/	GBE MDI3	204
GBE MDI3 N		/	GBE MDI3	202
GBE LINK ACT		/	GBE LINK ACT	194
GBE LED LINK		/	GBE LINK1000	188
PCIe KEY(MSSD)				
PCIE0 CLK P		/	PCIE0 CLK	162
PCIE0 CLK N		/	PCIE0 CLK	160
PCIE0 TX0 P		/	PCIE0 TX0	136
PCIE0 TX0 N		/	PCIE0 TX0	134
PCIE0 RX0 P		/	PCIE0 RX0	133
PCIE0 RX0 N		/	PCIE0 RX0	131
PCIE0 TX1 P		/	PCIE0 TX1	142
PCIE0 TX1 N		/	PCIE0 TX1	140
PCIE0 RX1 P		/	PCIE0 RX1	139
PCIE0 RX1 N		/	PCIE0 RX1	137
PCIE0 TX2 P		/	PCIE0 TX2	150
PCIE0 TX2 N		/	PCIE0 TX2	148
PCIE0 RX2 P		/	PCIE0 RX2	151
PCIE0 RX2 N		/	PCIE0 RX2	149
PCIE0 TX3 P		/	PCIE0 TX3	156
PCIE0 TX3 N		/	PCIE0 TX3	154
PCIE0 RX3 P		/	PCIE0 RX3	157
PCIE0 RX3 N		/	PCIE0 RX3	155
PCIE WAKE#		/	PCIE WAKE	179
PCIE0 RST#		/	PCIE0 RST	181
PCIE0 CLKREQ#		/	PCIE0 CLKREQ	180
PCIe KEY(WIFI/4G)				
PCIE1 CLK P		/	PCIE1 CLK	175
PCIE1 CLK N		/	PCIE1 CLK	173
PCIE1 TX0 P		/	PCIE1 TX0	174
PCIE1 TX0 N		/	PCIE1 TX0	172
PCIE1 RX0 P		/	PCIE1 RX0	169
PCIE1 RX0 N		/	PCIE1 RX0	167
PCIE WAKE#		/	PCIE WAKE	179
PCIE1 RST#		/	PCIE1 RST	183
PCIE1 CLKREQ#		/	PCIE1 CLKREQ	182
TypeC(USB3.2 Gen2x1) [10Gbps]				
USBSS1 RX P		/	USBSS1 RX	41
USBSS1 RX N		/	USBSS1 RX	39
USBSS1 TX P		/	USBSS1 TX	47
USBSS1 TX N		/	USBSS1 TX	45
USB0 DP		/	USB0 D	111
USB0 DN		/	USB0 D	109
USB0 VBUS DET		/	GPIO0	87
USB3.2 Gen2x1 (10Gbps)				
USB1 SS RXP		/	USBSS RX	163
USB1 SS RXN		/	USBSS RX	161
USB1 SS TXP		/	USBSS TX	168
USB1 SS TXN		/	USBSS TX	166
USB1 DP		/	USB1 D	117
USB1 DN		/	USB1 D	115
USB2 SS RXP		/	USBSS2 RX P	53
USB2 SS RXN		/	USBSS2 RX N	51
USB2 SS TXP		/	USBSS2 TX P	59
USB2 SS TXN		/	USBSS2 TX N	57
USB2 DP		/	USB2 D	123
USB2 DN		/	USB2 D	121
MIPI CSIO 4Lane				
CSIO D0 P		/	CSIO D0	6
CSIO D0 N		/	CSIO D0	4
CSIO D1 P		/	CSIO D1	18
CSIO D1 N		/	CSIO D1	16
CS11 CLK P		/	CS11 CLK	11
CS11 CLK N		/	CS11 CLK	9
CS11 D0 P		/	CSIO D0	5
CS11 D0 N		/	CSIO D0	3
CS11 D1 P		/	CSIO D1	17
CS11 D1 N		/	CSIO D1	15
CAM0 PWDN		/	CAM0 PWDN	144
CAM0 MCLK		/	CAM0 MCLK	146
CAM I2C SCL		/	CAM I2C SCL	213
CAM I2C SDA		/	CAM I2C SDA	215
CAM MUX SEL		/	GPIO6	130
MIPI CSI1 4Lane				
CSI2 D0 P		/	CSI2 D0	24
CSI2 D0 N		/	CSI2 D0	22
CSI2 D1 P		/	CSI2 D1	36
CSI2 D1 N		/	CSI2 D1	34
CSI2 CLK P		/	CSI2 CLK	30
CSI2 CLK N		/	CSI2 CLK	28
CSI3 D0 P		/	CSI3 D0	23
CSI3 D0 N		/	CSI3 D0	21
CSI3 D1 P		/	CSI3 D1	35
CSI3 D1 N		/	CSI3 D1	33
CAM1 PWDN		/	CAM1 PWDN	120
CAM1 MCLK		/	CAM1 MCLK	122
CAM I2C SCL		/	CAM I2C SCL	213
CAM I2C SDA		/	CAM I2C SDA	215
CAM MUX SEL		/	GPIO6	130
CAN				
5V(左)		/	/	/
GND		/	/	/
CAN H		3V3	CAN RX	143
CAN L		3V3	CAN TX	145
UART0				
3V3(左)		/	/	/
GND		/	/	/
UART0 TX		3V3	UART0 TX	99
UART0 RX		3V3	UART0 RX	101
UART1				
3V3(左)		/	/	/
GND		/	/	/
UART1 TX		3V3	UART1 TX	203
UART1 RX		3V3	UART1 RX	205
DEBUG UART				
UART2_TX		3V3	UART2_TX	236
GND		/	/	/
I2C				
5V(左)		5V	/	/
GND		/	/	/
SCL		3V3	I2C1 SCL	189
SDA		3V3	I2C1 SDA	190
GPIO				
GPIO4(左)		3V3	GPIO13	228
GPIO3		3V3	GPIO12	218
GPIO2		3V3	GPIO09	211
GPIO1		3V3	GPIO07	206
FAN Connector				
GND(上)		5V	GPIO14	230
5V		5V	GPIO8	208
FAN TACH		5V	/	/
FAN PWM		/	/	/
RTC后备电源				
1.65V-5.5V(上)		1.65V-5.5V	PMIC_BBAT	235
GND		GND	/	/

