

FlashArray Installation: Changing Purity//FA Version on a New FlashArray

Generated on: 21 October 2025

Contents

- FlashArray Installation: Changing Purity//FA Version on a New FlashArray 3
 - FA Factory Image for MFG 3
 - Changing Purity//FA Version 5
 - Additional Information 9
 - Installing Purity on FA with Factory Image 9
- New Array Purity//FA Recommended Version 13
 - Purity 6.10.x Install Packages. 13
 - Purity 6.9.x Install Packages 14
 - Purity 6.8.x Install Packages 15
 - Purity 6.7.x Install Packages. 17

FlashArray Installation: Changing Purity//FA Version on a New FlashArray

Note:

This process is to **only** be used on freshly installed arrays (POC, NDU preparation, etc.) that have **no data** on the system. This process should not be used to downgrade any array.



Employee - Internal and Confidential Note

If you are upgrading a production array, use the Purity//FA [FA Upgrade Runbook - Software NDUs](#) instead. Downgrading; please see [Downgrading Purity//FA is Not Supported](#).

FA Factory Image for MFG

Background

Manufacturing schedules do not always align with release schedules and historically Manufacturing has needed to determine the Purity code to ship equipment with and spend a lot of time determining whether the release was new enough to support the hardware, but old enough to be a mature release and be upgraded to a Customer's desired version. It also meant that Purity downgrading in the field was not possible. By decoupling manufacturing releases from mainstream Purity releases. Any new field install is forced to upgrade to GA Purity. This prevents scenarios of incompatible Purity for any DFM, HBAs, etc. It also encourages the field to adopt the latest GA versions before deploying systems

Impact

- The Factory image is unable to start purity and does not support `puresetup` or `pureadm start` (you will receive the following error: `Purity is in manufacturing mode`)
- The desired version of Purity must be deployed in the field during Installation
- It is now safe to install any supported release

Highlight that differentiates Factory image from GA Purity

- Factory image can't start purity and does not support `puresetup`

It's required to install GA Purity in the field to meet the minimum requirements of components installed in the system

Examples

- Message shown when Factory image bootup:

```
Welcome root. This is Pure Storage FactoryImage-FA Version 1.0.2 on Flash
Array hw-co-p2a-04
*****
WARNING: This controller is running the Pure Storage FactoryImage-FA
        A Purity package (ppkg) must be installed to run Purity
*****
*****
WARNING: The user pureuser is still configured with the default password.
        Please change the password now: pureadmin setattr pureuser --pas
sword
*****
http://www.purestorage.com/
```

- Factory image version:

```
~# pureversion -a
Product Version: 1.0.2
Middleware NDU Compatibility: 6.8.1
Operating Environment: factoryimage-fa
Version: 202411212347+8cff3559c78d-68x
Driver Version: 1837654073
Crypto Lib Version: FA-1.5
```

- `pureadm start` fails with Factory image

```
~# pureadm start
Error: Purity is in manufacturing mode.
```

- `puresetup` fails with Factory image

```
~# puresetup --help
PURESETUP_ERROR: [{'code': 120, 'context': '', 'message': 'Error: Purity
is in manufacturing mode. This controller is running the Pure Storage Fac
```

```
toryImage-FA. A Purity package (ppkg) must be installed to run puresetu  
p' }]  
CONFIG_TASK_COMPLETED:CONFIG_TASK_PURESETUP_EXITED
```

Resolution to solve the above failures

The unit needs to be installed (pureinstall) with a GA release Purity and then boot into it, purity can start, and `puresetup` can work as normal after that

Supported Platforms

- //X //C or //E with Chassis Gen 2
- //XLR5

Contact Support

Please contact Support if further assistance is needed.

Additional Information

For more information on the install process, see [Installing Purity on FA with Factory Image](#).

Changing Purity//FA Version

When a new array is received on-site, the Purity//FA version may not match the version that we want to run on the customer site. This procedure is performed **after** the array has been powered on, but **before** `pureinstall` or `puresetup` have been executed. If Purity//FA has already been started, you will not be able to move to a Purity//FA version lower than the one that is currently running, and you will need to contact Support.

Note:

This procedure is used during implementation time only, and it is not available or applicable on GA production arrays.



Partner - Partner Note



Please open a case with Support to obtain the PPKG and SHA1 files for the desired Purity version.



Employee - Internal and Confidential Note

Support and SE's, always check the [Version Recommendation Guide](#) (you may need to login to Skyline first, before accessing link) for the current recommended POC Release. If the links below are not in sync with the latest recommendation you can obtain it on Archive (https://archive.dev.purestorage.com/flasharray/purity/customer_shipped_releases/).

On a Linux based PC, for USB formatted EXT2, EXT3, EXT4, change the access permission of USB and all the ppkg files copied to that USB by running the command `sudo chmod 777 -R /media/USB`. Otherwise, if the user was to mount the USB to /mnt on the controller without doing this step, they may hit into a access permission error.

While the following procedure uses pureuser, employees can log in as root.

```
User: puresetup
Password (including spaces):
embind anecdota praiser obelize
```

1. Use the following command to find your disk in the list. The USB should appear as the last option, probably `/dev/sdb1` or `/dev/sdb2`.



Employee - Internal and Confidential Note

Note that `sda#` are internal partitions.

```
ls /dev/sd* -lrt
```



Note:

Another way to find your USB device is to give it a label when you format it, and then check `/dev/disk/by-label` to find it. You can then mount it using that path.

1. Obtain the recommended POC Release, from [Pure Storage Support](#).

- a. You may want to take advantage of the situation to show the customer the upgrade process and to receive the benefits of what the upgrade script does automatically. If so, install a lower version of Purity than what was intended to be the final version the customer will use. If that is the case, contact Pure Support to schedule the upgrade. If not, skip this step.
2. Copy the files to a USB Drive. Ensure the USB is formatted as NTFS.

 **Note:** New Purity releases require more than 4 GB, and do not fit on a USB device using fat32. Newer Purity releases support NTFS file systems on USB drives.

3. Insert the USB with the Purity//FA code on it in any slot on **CT0**.
4. If the array is running 4.8.0 or later, log in using the following credentials:

```
User: puresetup
Password (including spaces):
embind anecdota praiser obelize
```

5. Use the following command to find your disk in the list. The USB should appear as the last option, probably `/dev/sdb1` or `/dev/sdb2`

 Employee - Internal and Confidential Note

Note: Note that `sda#` are internal partitions.

```
ls /dev/sd* -lrt
```

 **Note:** Another way to find your USB device is to give it a label when you format it, and then check `/dev/disk/by-label` to find it. You can then mount it using that path.

6. Mount the USB. The following is an example and will change based on the device address from the previous step:

```
mount /dev/sdb1 /mnt
```

7. Confirm that the USB with Purity//FA code is mounted:

```
ls -l /mnt
```

8. Copy the `purity_<version>_<build>.ppkg` and `purity_<version>_<build>.ppkg.sha1` files in the `/home/puresetup` directory on the array:


```
pureboot reboot --offline
```

- b. Prior to 4.0.18 you use:

```
reboot
```

15. Repeat steps 3-14 on **CT1**.
16. You can now continue the [Quick Install Guide](#), and proceed with `puresetup newarray` on CT0, and subsequently `puresetup secondary` on CT1.
17. Contact Pure Support to make sure that default tunables that are set by the upgrade script have been successfully set on the FlashArray and that the array has been successfully rebooted.

Additional Information



Partner - Partner Note

For related information, see also, [Doing a Health Check on a FlashArray](#) on a [Updating and Managing Tunables](#).

When a new FlashArray is received on-site, the Purity//FA version may not match the version that we want to run on the customer site. This procedure is performed after the FlashArray has been powered on, but before `pureinstall` or `puresetup` have been executed.

Installing Purity on FA with Factory Image

When a new array is received on-site, it should be running a factory image, instead of a mainstream release of Purity (or GA Purity). Factory images are unable to start Purity and do not support “`puresetup`” or “`pureadm start`”. The array has to be installed with a GA Purity and then boot into it, Purity can start, and “`puresetup`” can work as normal after that.

Confirm FA is on Factory Image

Reference: [FA Factory Image for MFG](#)

Message shown when factory image bootup:

```
Welcome root. This is Pure Storage FactoryImage-FA Version 1.0.2 on FlashArray h
w-co-p2a-04
```

```
*****
```

```
WARNING: This controller is running the Pure Storage FactoryImage-FA
A Purity package (ppkg) must be installed to run Purity
*****
*****
WARNING: The user pureuser is still configured with the default password.
Please change the password now: pureadmin setattr pureuser --password
*****
http://www.purestorage.com/
```

Factory image version:

```
~# pureversion -a
Product Version: 1.0.2
Middleware NDU Compatibility: 6.8.1
Operating Environment: factoryimage-fa
Version: 202411212347+8cff3559c78d-68x
Driver Version: 1837654073
Crypto Lib Version: FA-1.5
```

“pureadm start” fails with factory image:

```
~# pureadm start
Error: Purity is in manufacturing mode.
```

“puresetup” fails with factory image:

```
~# puresetup --help
PURESETUP_ERROR: [{'code': 120, 'context': '', 'message': 'Error: Purity is in m
manufacturing mode. This controller is running the Pure Storage FactoryImage-FA.
A Purity package (ppkg) must be installed to run puresetup'}]
CONFIG_TASK_COMPLETED:CONFIG_TASK_PURESETUP_EXITED
```

Please contact Pure support if the new array is not on a factory image.

Select Purity Version

Please refer to the "[New Array Purity //FA Recommended Version](#)" for version recommendation.

The installation process requires 4 files: the PPKG file itself (with the extension .ppkg); the PPKG's signature file (with the extension .ppkg.sig); the PPKG's SHA1 checksum file (with the extension .ppkg.sha1) and the SHA1 checksum's signature file (with the extension .ppkg.sha1.sig).

For example, in Purity 6.8.4's case, the 4 required files are:

purity_6.8.4_202503070950+b2137b3b95a1.ppkg

purity_6.8.4_202503070950+b2137b3b95a1.ppkg.sig

purity_6.8.4_202503070950+b2137b3b95a1.ppkg.sha1

purity_6.8.4_202503070950+b2137b3b95a1.ppkg.sha1.sig

The files would be available for download on <https://releases.purestorage.com/flasharray/purity>.

Install PPKG

Reference: [Changing Purity//FA Version](#)

1. Copy the files that got downloaded in the “Obtain PPKG Files” section to a USB drive. Ensure the USB drive is formatted as NTFS.
2. Insert the USB drive with the PPKG files on it in any slot on CT0.
3. Log in using the following credentials:

```
User: puresetup  
Password (including spaces):  
embind anecdota praiser obelize
```

4. Use the following command to find your USB drive in the list, it should appear as the last option, probably `/dev/sdb1` or `/dev/sdb2`:

```
ls /dev/sd* -lrt
```

5. Mount the USB drive, the following is an example and will change based on the device address from the previous step:

```
mount /dev/sdb1 /mnt
```

or you may need to use `sudo` and then it would be:

```
sudo mount /dev/sdb1 /mnt
```

6. Confirm that the USB drive with the PPKG files is mounted:

```
ls -l /mnt
```

7. Copy the 4 PPKG files in the `/home/puresetup` directory on the array:

```
cp /mnt/purity_<version>* /home/puresetup
```

8. Confirm that the files have been moved:

```
ls -la /home/puresetup
```

9. Once the files have been moved, unmount the USB drive:

```
umount /mnt
```

10. Change directory to `"/home/puresetup"`:

```
cd /home/puresetup
```

11. Use the "pureinstall" command followed by the ".ppkg" file name to upgrade CT0:

```
puresetup@FlashArray-ct0:~# pureinstall purity_<version>_<build>.ppkg  
Verifying package...  
Installing on alternate partition labeled first  
Erasing alternate firmware image.  
WARNING: Do not interrupt this process!!  
Unpacking new firmware  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
. . . . .  
Finalizing installation. This may take several minutes.  
Purity installed  
Thank you, installation complete. New Purity will load at next reboot.
```

12. Verify the version that will be installed on the next Purity boot with the "pureboot" command:

```
pureboot list
```

- ### 13. Reboot CT0:

```
pureboot reboot --offline
```

14. Repeat steps 2 - 13 on CT1.

15. You can now continue the Quick Install Guide, and proceed with "puresetup newarray" on CT0, and subsequently "puresetup secondary" on CT1.
16. Contact Pure support to make sure that default tunables that are set by the upgrade script have been successfully set on the FlashArray and that the array has been successfully rebooted.

New Array Purity//FA Recommended Version

This section outlines recommended Purity versions for new array installations. Recommend a version that is compatible with their environment and consistent with customer requirements, balancing innovation with stability and known issues.

First, you must determine which **Release Type** to recommend, then you would generally select the most recent **Release Line** and **Version** that supports the hardware.

- **Feature Release (FR):** Recommended for new customers, demos, and POCs. Best for customers who want access to all of the latest features and capabilities.
- **Long-Life Release (LLR):** Recommended for existing customers who have standardized on a specific feature set and are looking for consistency across their fleet.

You can reference the [Purity//FA Release and End-of-Life Schedule](#) for a summary of the release lines, lifecycle dates, latest versions, and platforms supported. Follow the links from that page to explore the release notes for more detailed information on what is included and supported in each release.

If further assistance is needed with picking the recommended version please reach out to your account team or contact [Pure Storage Support](#).

Purity //FA Install Packages

Please utilize the links below to access the files needed for installation.

[6.9.x Packages](#)

[6.8.x Packages](#)

[6.7.x Packages](#)

Purity 6.10.x Install Packages

Purity 6.10.1 Install Packages

https://releases.purestorage.com/flasharray/purity/6.10.1/purity_6.10.1_202510062224%2B6f0f4c5898d7.ppkg

https://releases.purestorage.com/flasharray/purity/6.10.1/purity_6.10.1_202510062224%2B6f0f4c5898d7.ppkg.sig

https://releases.purestorage.com/flasharray/purity/6.10.1/purity_6.10.1_202510062224%2B6f0f4c5898d7.ppkg.sha1

https://releases.purestorage.com/flasharray/purity/6.10.1/purity_6.10.1_202510062224%2B6f0f4c5898d7.ppkg.sha1.sig

Purity 6.10.0 Install Packages

https://releases.purestorage.com/flasharray/purity/6.10.0/purity_6.10.0_202508230612%2Ba9ae8b3eee98.ppkg

https://releases.purestorage.com/flasharray/purity/6.10.0/purity_6.10.0_202508230612%2Ba9ae8b3eee98.ppkg.sig

https://releases.purestorage.com/flasharray/purity/6.10.0/purity_6.10.0_202508230612%2Ba9ae8b3eee98.ppkg.sha1

https://releases.purestorage.com/flasharray/purity/6.10.0/purity_6.10.0_202508230612%2Ba9ae8b3eee98.ppkg.sha1.sig

Purity 6.9.x Install Packages

Purity 6.9.2 Install Packages

https://releases.purestorage.com/flasharray/purity/6.9.2/purity_6.9.2_202510142333%2Baf11cde1386b.ppkg

https://releases.purestorage.com/flasharray/purity/6.9.2/purity_6.9.2_202510142333%2Baf11cde1386b.ppkg.sig

https://releases.purestorage.com/flasharray/purity/6.9.2/purity_6.9.2_202510142333%2Baf11cde1386b.ppkg.sha1

https://releases.purestorage.com/flasharray/purity/6.9.2/purity_6.9.2_202510142333%2Baf11cde1386b

Purity 6.9.1 Install Packages

https://releases.purestorage.com/flasharray/purity/6.9.1/purity_6.9.1_202508230347%2B3b6025474441.ppkg

<https://releases.purestorage.com/flasharray/purity/6.9.1/>

[purity_6.9.1_202508230347%2B3b6025474441.ppkg.sig](https://releases.purestorage.com/flasharray/purity/6.9.1/purity_6.9.1_202508230347%2B3b6025474441.ppkg.sig)

[https://releases.purestorage.com/flasharray/purity/6.9.1/
purity_6.9.1_202508230347%2B3b6025474441.ppkg.sha1](https://releases.purestorage.com/flasharray/purity/6.9.1/purity_6.9.1_202508230347%2B3b6025474441.ppkg.sha1)

[https://releases.purestorage.com/flasharray/purity/6.9.1/
purity_6.9.1_202508230347%2B3b6025474441.ppkg.sha1.sig](https://releases.purestorage.com/flasharray/purity/6.9.1/purity_6.9.1_202508230347%2B3b6025474441.ppkg.sha1.sig)

Purity 6.9.0 Install Packages

[https://releases.purestorage.com/flasharray/purity/6.9.0/
purity_6.9.0_202507150448%2Bdd9281824b54.ppkg](https://releases.purestorage.com/flasharray/purity/6.9.0/purity_6.9.0_202507150448%2Bdd9281824b54.ppkg)

[https://releases.purestorage.com/flasharray/purity/6.9.0/
purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sig](https://releases.purestorage.com/flasharray/purity/6.9.0/purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sig)

[https://releases.purestorage.com/flasharray/purity/6.9.0/
purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sha1](https://releases.purestorage.com/flasharray/purity/6.9.0/purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sha1)

[https://releases.purestorage.com/flasharray/purity/6.9.0/
purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sha1.sig](https://releases.purestorage.com/flasharray/purity/6.9.0/purity_6.9.0_202507150448%2Bdd9281824b54.ppkg.sha1.sig)

Purity 6.8.x Install Packages

Purity 6.8.8

[https://releases.purestorage.com/flasharray/purity/6.8.8/
purity_6.8.8_202506281541%2B042cdeab11ba.ppkg](https://releases.purestorage.com/flasharray/purity/6.8.8/purity_6.8.8_202506281541%2B042cdeab11ba.ppkg)

[https://releases.purestorage.com/flasharray/purity/6.8.8/
purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sig"](https://releases.purestorage.com/flasharray/purity/6.8.8/purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sig)

[https://releases.purestorage.com/flasharray/purity/6.8.8/
purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sha1](https://releases.purestorage.com/flasharray/purity/6.8.8/purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sha1)

[https://releases.purestorage.com/flasharray/purity/6.8.8/
purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sha1.sig](https://releases.purestorage.com/flasharray/purity/6.8.8/purity_6.8.8_202506281541%2B042cdeab11ba.ppkg.sha1.sig)

Purity 6.8.7

[https://releases.purestorage.com/flasharray/purity/6.8.7/
purity_6.8.7_202506052315%2B76a21ba50062.ppkg](https://releases.purestorage.com/flasharray/purity/6.8.7/purity_6.8.7_202506052315%2B76a21ba50062.ppkg)

<https://releases.purestorage.com/flasharray/purity/6.8.7/>

[purity_6.8.7_202506052315%2B76a21ba50062.ppkg.sha1](#)

https://releases.purestorage.com/flasharray/purity/6.8.7/purity_6.8.7_202506052315%2B76a21ba50062.ppkg.sha1.sig

https://releases.purestorage.com/flasharray/purity/6.8.7/purity_6.8.7_202506052315%2B76a21ba50062.ppkg.sig

Purity 6.8.6

https://releases.purestorage.com/flasharray/purity/6.8.6/purity_6.8.6_202505090007%2Be9d5a09780f3.ppkg

https://releases.purestorage.com/flasharray/purity/6.8.6/purity_6.8.6_202505090007%2Be9d5a09780f3.ppkg.sha1

https://releases.purestorage.com/flasharray/purity/6.8.6/purity_6.8.6_202505090007%2Be9d5a09780f3.ppkg.sha1.sig

https://releases.purestorage.com/flasharray/purity/6.8.6/purity_6.8.6_202505090007%2Be9d5a09780f3.ppkg.sig

Purity 6.8.5

https://releases.purestorage.com/flasharray/purity/6.8.5/purity_6.8.5_202504062042%2B65cf6ed3d144.ppkg

https://releases.purestorage.com/flasharray/purity/6.8.5/purity_6.8.5_202504062042%2B65cf6ed3d144.ppkg.sha1

https://releases.purestorage.com/flasharray/purity/6.8.5/purity_6.8.5_202504062042%2B65cf6ed3d144.ppkg.sha1.sig

https://releases.purestorage.com/flasharray/purity/6.8.5/purity_6.8.5_202504062042%2B65cf6ed3d144.ppkg.sig

Purity 6.8.4

https://releases.purestorage.com/flasharray/purity/6.8.4/purity_6.8.4_202503070950%2Bb2137b3b95a1.ppkg

https://releases.purestorage.com/flasharray/purity/6.8.4/purity_6.8.4_202503070950%2Bb2137b3b95a1.ppkg.sha1

<https://releases.purestorage.com/flasharray/purity/6.8.4/>

[purity_6.8.4_202503070950%2Bb2137b3b95a1.ppkg.sha1.sig](https://releases.purestorage.com/flasharray/purity/6.8.4/purity_6.8.4_202503070950%2Bb2137b3b95a1.ppkg.sha1.sig)

https://releases.purestorage.com/flasharray/purity/6.8.4/purity_6.8.4_202503070950%2Bb2137b3b95a1.ppkg.sig

Purity 6.7.x Install Packages

Purity 6.7.6

https://releases.purestorage.com/flasharray/purity/6.7.6/purity_6.7.6_202508150427%2B74e541490942.ppkg

Purity 6.7.5

https://releases.purestorage.com/flasharray/purity/6.7.5/purity_6.7.5_202507101114%2Bcee438d02700.ppkg

Purity 6.7.4

https://releases.purestorage.com/flasharray/purity/6.7.4/purity_6.7.4_202505261003%2B4520e960185e.ppkg
https://releases.purestorage.com/flasharray/purity/6.7.4/purity_6.7.4_202505261003%2B4520e960185e.ppkg.sig
https://releases.purestorage.com/flasharray/purity/6.7.4/purity_6.7.4_202505261003%2B4520e960185e.ppkg.sha1
https://releases.purestorage.com/flasharray/purity/6.7.4/purity_6.7.4_202505261003%2B4520e960185e.ppkg.sha1.sig

Purity 6.7.3

https://releases.purestorage.com/flasharray/purity/6.7.3/purity_6.7.3_202503241831%2B6aa78d215a66.ppkg
https://releases.purestorage.com/flasharray/purity/6.7.3/purity_6.7.3_202503241831%2B6aa78d215a66.ppkg.sig
https://releases.purestorage.com/flasharray/purity/6.7.3/purity_6.7.3_202503241831%2B6aa78d215a66.ppkg.sha1
https://releases.purestorage.com/flasharray/purity/6.7.3/purity_6.7.3_202503241831%2B6aa78d215a66.ppkg.sha1.sig

© 2015-2025 Pure Storage® ("Pure"), Portworx® and associated its trademarks can be found here as and its virtual patent marking program can be found here. Third party names may be trademarks of their respective owners. The Pure Storage products and programs described in this documentation are distributed under a license agreement restricting the use, copying, distribution, and decompilation/reverse engineering of the products. No part of this documentation may be reproduced in any form by any means without prior written authorization from Pure Storage, Inc. and its licensors, if any. Pure Storage may make improvements and/or changes in the Pure Storage products and/or the programs described in this documentation at any time without notice. This documentation is provided "as is" and all express or implied conditions, representations and warranties, including any implied warranty of merchantability, fitness for a particular purpose, or non-infringement, are disclaimed, except to the extent that such disclaimers are held to be legally invalid. Pure shall not be liable for incidental or consequential damages in connection with the furnishing, performance, or use of this documentation. The information contained in this documentation is subject to change without notice.
