Quantum Error Correction for Quantum Sensing: Gap Analysis and Research Proposals

Prepared 12 November 2026. Literature status as of that date.

0. Summary of conclusions

1. **The question is important and timely.** Decoherence reduces entanglement-enhanced sensors from the Heisenberg limit to the standard quantum limit; quantum error correction (QEC) is the only known general mechanism that restores the Heisenberg limit under Markovian noise. Logical qubits now exist in hardware, and in 2026 alone at least six papers moved the field from "does a suitable code exist?" to "how is a logical sensor operated?".
2. **Where the gap is.** Existing theory fixes the *code* and assumes ideal, instantaneous, complete recovery. What is still borrowed unchanged from quantum computing is the layer between the syndrome record and the estimate: the **decoder**, the **recovery policy**, and the **figures of merit**. No general theory states what a decoder must output for a sensing task, what an imperfect or slow decoder costs, or how a logical sensor should be benchmarked.
3. **Your first idea is correct, and can be sharpened.** A recovery never increases the information already acquired; its only function is to keep the future signal accumulating coherently. Consequently the object that must be *right* is the classical inference of a low-dimensional statistic of the error history, whereas the operation that is physically *applied* may be cheap, late, or wrong. Under stated assumptions I derive that the optimal decoder for local single-parameter sensing outputs **one real number per shot** (the posterior mean of the signed interrogation time), and that the loss of any other decoder equals one minus a squared correlation coefficient (Section 5.1).
4. **Your second idea addresses a real deficiency.** Logical fidelity is neither necessary nor sufficient for sensing performance (Section 5.2). Fragments of sensing-specific metrics exist; a unified operational definition does not.
5. **Parts of both ideas were published in 2026** (subsystem codes, partial QEC, fault-tolerant thresholds, syndrome-aware state estimation). The proposals below are positioned in what remains open.
6. **Seven proposals** are given in Section 6. I recommend P1 and P2 as the core, P3 as their framing, and P7 as the algorithmic continuation.

	Proposal	Type
P1	Metrological sufficiency: a statistical theory of decoders for sensing	theory
P2	Inference–action separation: frame tracking, decoder latency, two-tier decoding	theory and algorithm
P3	Figures of merit and benchmarking for logical sensors	theory and protocol
P4	Signals inside the Lindblad span: limits and optimal correlation-filter codes	theory
P5	Detection-theoretic logical sensing: Neyman–Pearson decoding, quickest detection	theory and algorithm
P6	Feature-sufficient subsystem codes with nuisance parameters	theory
P7	Learned decoder–estimators for continuous-QEC sensing	algorithm

1. Technical background

This section defines the terms used later. Readers familiar with them may skip to Section 2.

1.1 Parameter estimation and Fisher information

A sensor prepares a state ρ_0, lets it evolve under a Hamiltonian $H_\theta = \theta G$ containing an unknown real parameter θ (the *signal*; G is the *generator*), and measures. The outcome x has distribution $p_\theta(x)$.

- **Classical Fisher information (FI):** $F_C(\theta) = \sum_x p_\theta(x)\,[\partial_\theta \ln p_\theta(x)]^2$.
- **Cramér–Rao bound:** every unbiased estimator $\hat\theta$ built from ν independent repetitions satisfies $\mathrm{Var}(\hat\theta) \geq 1/(\nu F_C)$.
- **Quantum Fisher information (QFI):** $F_Q[\rho_\theta] = \max_{\text{measurements}} F_C$. For a pure state evolving for time t under θG, $F_Q = 4t^2\ \mathrm{Var}_\psi(G) \leq t^2\,(g_{\max} - g_{\min})^2$, where $g_{\max}, g_{\min}$ are the extreme eigenvalues of G.
- **Data-processing inequality:** for every parameter-independent quantum channel $\mathcal{R}$, $F_Q[\mathcal{R}(\rho_\theta)] \leq F_Q[\rho_\theta]$. Information about θ cannot be created by post-processing.
- **Standard quantum limit (SQL)** and **Heisenberg limit (HL):** with total resource N (number of probes, or total time T), the SQL is $F \propto N$, hence $\delta\theta \propto N^{-1/2}$; the HL is $F \propto N^2$, hence $\delta\theta \propto N^{-1}$.
- **Sensitivity:** $\eta = \min_t \sqrt{t/F(t)}$, the smallest signal resolvable in unit total time.

1.2 Noise

Markovian noise is described by the **Lindblad master equation**

$$\dot\rho = -i[\theta G, \rho] + \sum_k \Big(L_k \rho L_k^\dagger - \tfrac{1}{2}\{L_k^\dagger L_k, \rho\} \Big),$$

where the L_k are *jump operators*. The **Lindblad span** is the real linear space

$$\mathcal{S} = \mathrm{span}_{\mathbb{R}}\{I,\ L_k^{\mathrm{H}},\ iL_k^{\mathrm{AH}},\ (L_k^\dagger L_j)^{\mathrm{H}},\ i(L_k^\dagger L_j)^{\mathrm{AH}}\}_{j,k},$$

with H and AH denoting Hermitian and anti-Hermitian parts.

1.3 Quantum error correction

- A **code** is a subspace $\mathcal{C}$ with projector Π. It corrects an error set $\{E_a\}$ if and only if the **Knill–Laflamme conditions** hold: $\Pi E_a^\dagger E_b \Pi = c_{ab}\Pi$.
- A **stabilizer code** $[[n, k, d]]$ is the joint $+1$ eigenspace of a commuting group S of Pauli operators on n qubits; it encodes k logical qubits. Measuring the generators of S gives the **syndrome** s. **Logical operators** are the Paulis that commute with S but are not in it (the set $N(\mathsf{S}) \setminus \mathsf{S}$); the **distance** d is their minimum weight.
- A **decoder** is the classical algorithm mapping the syndrome record to a guess of the error class. A **recovery** is the physical operation applied as a result. A **logical error** occurs when error times recovery is a nontrivial logical operator.
- **Pauli-frame tracking:** in computation with Clifford gates, Pauli corrections need not be applied physically; they are recorded in software and applied to the final measurement outcomes.
- A **subsystem code** decomposes $\mathcal{C} = \mathcal{H}_L \otimes \mathcal{H}_G$ into a logical and a *gauge* factor; errors acting only on $\mathcal{H}_G$ need not be corrected.
- **Continuous QEC** replaces discrete projective syndrome measurements by weak continuous monitoring, producing noisy analogue records (Convy et al. 2022).

1.4 QEC for sensing: the established theory

A sensing code must protect against noise while remaining sensitive to the signal. The conditions are

$$\Pi L_k \Pi = \lambda_k \Pi, \qquad \Pi L_k^\dagger L_j \Pi = \mu_{kj}\Pi, \qquad \Pi G \Pi \not\propto \Pi.$$

Theorem (HNLS; Zhou, Zhang, Preskill, Jiang 2018; Demkowicz-Dobrzański, Czajkowski, Sekatski 2017). With noiseless ancillas and arbitrarily fast, perfect control, the HL in T is attainable if and only if $G \notin \mathcal{S}$ ("Hamiltonian not in Lindblad span"). The optimal QFI is $F(T) = 4T^2 \min_{S\in\mathcal{S}} \|G - S\|^2$ (operator norm), and the optimal code is found by a semidefinite program. If $G \in \mathcal{S}$, then $F(T) = O(T)$ for every protocol.

The other papers you supplied extend this result:

Paper	Contribution	Assumptions retained
Zhou, Layden et al. 2019 (SPIE review)	HNLS; ancilla-free codes for commuting noise; approximate HNLS gives HL up to $T \sim 1/\epsilon$; the logical sensor is described by a signal gain A and a dephasing factor B	ideal recovery
Górecki et al. 2020	multi-parameter HNLS: HL for all parameters iff the projections $(G_i)_\perp$ onto $\mathcal{S}^\perp$ are linearly independent; optimal code by SDP using the Holevo bound	ideal recovery; cost matrix $W > 0$
Convy et al. 2022	recurrent neural network decoding of continuous, non-ideal syndrome records; notes that an undiagnosed error causes "spurious Hamiltonian evolution" in the error subspace	objective is state fidelity, not sensing
Ott et al. 2026	signal *inside* the Lindblad span but pulsed and collective; syndrome extraction converts a kick ϵ into a logical phase $O(\epsilon^3)$ and extends coherence; advantage when noise rate $\gamma \gg$ event rate R	perfect syndrome extraction; only the mean logical phase is used

---

2. Why the question is important

1. **A fundamental obstruction.** For generic local noise, entanglement gives only a constant-factor gain over the SQL (Huelga et al. 1997; Escher et al. 2011; Demkowicz-Dobrzański et al. 2012). QEC is the only known general construction that restores HL scaling, and HNLS states exactly when.
2. **The premises have become experimental.** Repeated syndrome extraction on logical qubits, including operation below the surface-code threshold, has been demonstrated (see references 28–33 of Ott et al.). The limiting assumptions of the 2018 theory (noiseless ancillas, instantaneous exact recovery) are therefore the practically relevant ones to remove.
3. **The field is moving in this direction.** In 2026: fault-tolerant thresholds for HL sensing (Sahu, Xu, Zhou; Conlon et al.), subsystem and Floquet sensing codes (Liu, Zhou), partial QEC (Chen, Wang, Zhou), a protection–sensitivity trade-off $d \cdot F = O(n^2)$ (Chen et al.), rare-event logical sensing (Ott et al.), and QEC-inspired dark-matter searches (Fukuda et al.). Each treats one component; none treats the decoder–estimator layer in general.
4. **A structural difference from computing.** In computation the code must make every logical operation invisible to the environment. In sensing the signal is itself an unknown, continuous, non-Clifford logical rotation $e^{-i\theta G t}$ that must *not* be corrected, while errors that fail to commute with G change how the signal accumulates. Decoding objectives, latency requirements and metrics designed for computation are therefore not automatically the right ones.
5. **Consequence if solved.** A decoder theory specific to sensing determines hardware requirements (feedback speed, classical processing) for logical sensors, and tells experimenters which quantity to report.

---

3. State of the art, and what each work leaves open

Work	What it settles	What it leaves open (relevant here)
Zhou et al. 2018; Górecki et al. 2020	existence and optimal codes under ideal recovery	decoder, latency, noisy syndromes, metrics
Rojkov et al. 2022	finite-rate recovery biases the estimate; correctable in post-processing	general estimator theory using the syndrome record
Shettell et al. 2021	noisy ancilla and finite QEC rate limit the gain	optimal use of the record; general codes
Niroula et al. 2024	heralded (erasure) errors hurt sensing less than unheralded ones	theory for general syndrome information
Sahu, Xu, Zhou 2026 (arXiv:2601.05457)	threshold for HL in n; repetition code; circuit-level bit-flip noise	signal is instantaneous; estimator ignores syndromes; one code, one decoder
Conlon et al. 2026 (arXiv:2608.00171)	HL in T up to $T \propto p^{-(N+1)/2}$; repetition code; sign of the accumulated phase tracked classically; syndrome-weighted estimator (read in summary only)	one code and noise model; no latency analysis; no general decoder statement
Chen, Luo et al. 2025–26 (arXiv:2512.20426)	trade-off $d \cdot F = O(n^2)$; asymmetric codes with distances d_{sig}, d_{comp}	no noise rates, decoders, or thresholds
Chen, Wang, Zhou 2026 (arXiv:2605.08341)	"partial QEC": measure and correct only one check type	QFI of corrected state only; perfect measurements
Liu, Zhou 2026 (arXiv:2606.19628)	subsystem sensing codes: noise may act arbitrarily on gauge qubits; syndrome-free protocols; Floquet codes for a time-dependent signal	single parameter; noiseless operations; estimator does not use syndromes
Tsubouchi et al. 2026 (arXiv:2603.05145)	syndrome-aware Fisher information for logical *state* (expectation-value) estimation; classical syndrome use improves the effective logical error rate by at most a factor 2	explicitly lists metrology (channel estimation) and hypothesis testing as open
Ott et al. 2026	QEC as a nonlinear filter for rare collective pulses	optimality; syndrome record unused; perfect syndrome extraction; estimation only

4. Design space

An error-corrected sensing protocol is specified by nine choices. The last column marks where published work is concentrated.

Axis	Options	Coverage
1. Task	single parameter; several parameters; a function of parameters; detection (hypothesis test); waveform	single parameter dominant; detection and functions open
2. Signal structure	static, AC, pulsed, stochastic; local or collective; outside or inside $\mathcal{S}$	static and outside $\mathcal{S}$ dominant; inside $\mathcal{S}$ only Ott et al.
3. Noise	perpendicular to G; commuting with G; parallel to G; correlated; gate-level	ideal-gate models dominant; gate-level only bit-flip
4. Code	stabilizer, subsystem, Floquet, bosonic; with or without ancilla; asymmetry	well explored

Axis	Options	Coverage
5. Syndrome extraction	discrete or continuous; period δt; noiseless or noisy	mostly noiseless, $\delta t \to 0$
6. Inference (decoder)	hard or soft output; real-time or offline; which classes are resolved	**essentially unexplored**
7. Action (recovery)	physical, virtual (tracked), or none; latency	**essentially unexplored**
8. Readout and estimator	syndrome-agnostic; syndrome-aware; adaptive	syndrome-agnostic dominant
9. Figure of merit	QFI scaling; sensitivity; bias; error exponents; a "logical-sensor" metric	QFI scaling dominant

The proposals address axes 6–9 (P1, P2, P3, P7), axis 2 (P4), and axis 1 (P5, P6).

---

5. Formal assessment of your two ideas

5.1 Idea 1: "not every error needs to be recovered; a wrong but cheap recovery may be good"

The following statements are derived for this report under explicit assumptions, and were checked by Monte Carlo simulation on toy models. They have not been independently verified and should be re-derived before being relied upon.

Assumptions (M). (i) Stabilizer code with projector Π and one logical qubit used for sensing. (ii) Signal $H = \theta G$ with $G = \sum_j \lambda_j Q_j$ a sum of Paulis, and $\Pi G \Pi = \frac{\lambda}{2}\bar{Z}$ on the code, $\lambda > 0$. (iii) Pauli errors; syndromes measured with period $\delta t \to 0$, possibly with noisy outcomes; s denotes the complete syndrome record, whose statistics do not depend on θ in this limit. (iv) Recoveries ("actions") are Pauli operators chosen as functions of the past record. (v) Probe $|\bar{+}\rangle$, final measurement of $\bar{Y}$ with outcome $x = \pm 1$, local estimation near $\theta = 0$.

Fact 1 (a recovery adds no information). By data processing, $F_Q[\mathcal{R}(\rho_\theta)] \le F_Q[\rho_\theta]$. Hence no recovery is ever required to preserve information already acquired, and the final recovery of any protocol is statistically superfluous. The value of a recovery lies only in its effect on the *subsequent* evolution.

Fact 2 (frame identity). For any unitary error E,

$$e^{-i\theta G t}\, E = E\, e^{-i\theta (E^\dagger G E) t}.$$

An error that is present but known does not destroy the signal; it replaces the generator G by $E^\dagger G E$. For a Pauli error, $E^\dagger Q_j E = \chi_j(E) Q_j$ with $\chi_j(E) = \pm 1$, so on the code

$$\Pi E^\dagger G E\, \Pi = \frac{\lambda}{2}\, g(E)\, \bar{Z}, \qquad g(E) = \frac{\sum_j \chi_j(E)\lambda_j}{\sum_j \lambda_j},$$

where the sums run over the Pauli terms of G that act as $\bar{Z}$ on the code. I call $g(E)$ the **gain** of the error frame E; it lies in $[-1, 1]$ when the λ_j have a common sign, and $g(I) = 1$.

Proposition A (sufficient statistic of the error history). Let $E(t)$ be the cumulative Pauli (errors and actions) at time t. Define the **signed interrogation time** $\tau = \int_0^T g(E(t))\, dt$ and the **readout sign** $r = \pm 1$ according to whether $E(T)$ commutes with the measured operator. Then

$$p_\theta(x \mid \text{history}) = \tfrac{1}{2}\big[1 + x\, r\, \sin(\lambda \theta \tau)\big].$$

The history enters only through the pair (r, τ): one bit and one real number.

Proposition B (optimal decoder output and the cost of any other decoder). Define the **posterior weight** $w(s) = \mathbb{E}[\, r\tau \mid s\,]$. Then, at $\theta = 0$:

$$F_{\text{aware}} = \lambda^2\, \mathbb{E}_s\big[w(s)^2\big], \qquad \hat{\theta} = \frac{\sum_i x_i\, w(s_i)}{\lambda \sum_i w(s_i)^2} \ \text{is locally efficient.}$$

For any other weight function $\hat{w}(s)$ (the output of any cheaper decoder), the weighted estimator attains

$$F_{\hat{w}} = \lambda^2 \frac{(\mathbb{E}[\hat{w}\, w])^2}{\mathbb{E}[\hat{w}^2]}, \qquad \frac{F_{\hat{w}}}{F_{\text{aware}}} = \frac{(\mathbb{E}[\hat{w}\, w])^2}{\mathbb{E}[\hat{w}^2]\ \mathbb{E}[w^2]} =: \operatorname{corr}^2(\hat{w}, w) \le 1.$$

A syndrome-agnostic estimator corresponds to constant $\hat{w}$ and gives $F_{\text{agn}} = \lambda^2(\mathbb{E}[r\tau])^2 \le F_{\text{aware}}$ (Jensen).

Derivation. From Proposition A, $p_\theta(x \mid s) = \frac{1}{2}[1 + x\, \mathbb{E}(r \sin \lambda\theta\tau \mid s)]$, whose score at $\theta = 0$ is $x\lambda w(s)$; the remaining claims follow from the Cauchy–Schwarz inequality.

Proposition C (inference–action separation; three classes of error). F_{aware} depends on the action policy only through the joint law of (r, τ, s), whereas $w(s)$ may be computed offline from the entire record. Therefore:

- **Class N** ($g(E) = g(I)$ and $r = +1$): neither inference nor action is needed. Stabilizers, gauge operators, and logical operators commuting with both G and the readout belong here.
- **Class P** ($g(E) = g(I)$, $r = -1$): only the parity at the final time matters. Inference may be done offline; no action is needed.
- **Class T** ($g(E) \neq g(I)$): the time interval during which the error is present matters. Action restores gain; inference of the timing is still sufficient for unbiased estimation.

Examples (E1–E5 are closed-form, with E3 and E4 confirmed by simulation; E6 is a simulation).

- **E1. Ideal QEC:** $w = T$, $F = \lambda^2 T^2$.
- **E2. Unidentified logical flips only** ($\tau = T$, posterior flip probability q_s): $F = \lambda^2 T^2\, \mathbb{E}_s[(1 - 2q_s)^2]$. This is the channel-estimation counterpart of the state-estimation formula of Tsubouchi et al.
- **E3. No recovery at all, only tracking** (errors of class T at rate Γ, perfect syndromes): $F_{\text{aware}} = \lambda^2\big[T/\Gamma - (1 - e^{-2\Gamma T})/(2\Gamma^2)\big]$, while $F_{\text{agn}} = \lambda^2\big[(1 - e^{-2\Gamma T})/(2\Gamma)\big]^2$, which saturates. The best Fisher-information rates are λ^2/Γ and $0.204\,\lambda^2/\Gamma$: a factor 4.9 from inference alone, with no physical correction.
- **E4. Recovery with latency τ_d:** the mean gain is $\bar{g} = (1 - \Gamma\tau_d)/(1 + \Gamma\tau_d)$ and $F \simeq \bar{g}^2 \lambda^2 T^2$ to first order in $\Gamma\tau_d$. HL scaling survives with a reduced prefactor. A syndrome-agnostic estimator is biased by the factor $\bar{g}$; this is the kind of bias identified by Rojkov et al.
- **E5. Repetition code, $G = \frac{1}{2}\sum_i Z_i$, bit-flip pattern e:** $g = 1 - 2|e|/n$. Only the Hamming weight of the error matters, not its location.
- **E6. Hidden-Markov toy model** (tracking only, flip probability 0.03 per step, syndrome error 0.12, 40 steps): posterior weights give $F/T^2 = 0.505$; hard decisions lose 0.15%; the raw syndrome sum loses 2.5%; the syndrome-agnostic estimator retains only 29%.

Assessment. The idea is correct. Its precise form is: *what must be accurate is the inference of* (r, τ)*, and for local estimation only its posterior mean; what is physically applied affects only the gain.* A recovery that is "wrong" in the computing sense is harmless if it is of class N, costless in information if it is known (classes P and T), and costly only in gain while a class-T frame persists. Note the limit of the idea: for a single logical qubit without gauge freedom, all three nontrivial logical Paulis are sensing-relevant, so the number of classes is not reduced; the saving lies in *when* and *how accurately* each must be resolved.

Already published parts. Noise parked in gauge qubits (Liu, Zhou); only one check type measured (Chen, Wang, Zhou); "performing the syndrome measurements suffices" for dephasing (Ott et al., footnote 54); classical tracking of a sign and a syndrome-weighted estimator in one repetition-code model (Conlon et al.); syndrome-

aware Fisher information for states (Tsubouchi et al.). I found no general statement of Propositions A–C, of the corr^2 criterion, or of the latency law.

5.2 Idea 2: analogues of "logical qubit" and "logical fidelity" for sensing

Logical fidelity is not the right quantity. Let Λ_θ be the realised logical channel and $\mathcal{U}_\theta$ the ideal one.

- *Not sufficient.* If the code also detects the signal ($\Pi G \Pi \propto \Pi$), frequent QEC gives $\Lambda_\theta = \mathrm{id}$ for all θ: memory fidelity is 1 and the QFI is 0.
- *Not necessary.* If $\Lambda_\theta = \mathcal{V} \circ \mathcal{U}_{\bar{g}\theta}$ with a known unitary $\mathcal{V}$ and a known gain $\bar{g} \approx 1$, the fidelity to $\mathcal{U}_\theta$ can be arbitrarily small at large θT, yet the QFI is $\bar{g}^2$ times the ideal value.

Fidelity compares Λ_θ with $\mathcal{U}_\theta$ pointwise in θ. Sensing depends on how Λ_θ *varies* with θ, and is invariant under known post-processing.

Existing fragments. Signal gain A and dephasing B with $\eta = (\sqrt{B}/A)\sqrt{2e/T_2}$ (Zhou, Layden et al. 2019); renormalised signal and decoherence rates (Ott et al.); distances $d_{\mathrm{sig}}, d_{\mathrm{comp}}$ (Chen et al.); a Fisher-information-matched "effective logical error rate" for states (Tsubouchi et al.); thresholds (Sahu et al.; Conlon et al.).

Proposed definition. With $\lambda_0 = g_{\max} - g_{\min}$ the spread of the bare generator, define the **metrological fidelity** of a complete protocol (code, action policy, decoder $\hat{w}$) as

$$\mathcal{F}_{\mathrm{met}}(T) = \frac{F_{\hat{w}}(T)}{\lambda_0^2 T^2} = \underbrace{\left(\frac{\lambda}{\lambda_0}\right)^2}_{\text{code: signal retention}} \quad \underbrace{\frac{\mathbb{E}[w^2]}{T^2}}_{\text{noise and action}} \quad \underbrace{\mathrm{corr}^2(\hat{w}, w)}_{\text{inference}} \in [0, 1].$$

The three factors separate the contributions of the code (bounded by $\lambda \le 2 \min_{S \in \mathcal{S}} \|G - S\|$), of the recovery policy, and of the decoder. Section 6, P3 develops the remaining quantities.

---

6. Research proposals

Each proposal states the question, a formal formulation, the prior art with a novelty assessment, first steps, and the main risk.

P1. Metrological sufficiency: a statistical theory of decoders for sensing

Question. For a given code, noise model and sensing task, what is the minimal information a decoder must extract from the syndrome record, and what does any cheaper decoder cost?

Formulation. A decoder is a map $\mathsf{D} : s \mapsto \mathsf{D}(s)$. Together with the readout it defines a classical statistical experiment $\mathcal{E}_{\mathsf{D}} = \{p_\theta(\mathsf{D}(s), x)\}_\theta$. Order decoders by **statistical sufficiency** (the Blackwell order): $\mathsf{D} \succeq \mathsf{D}'$ if every decision problem is solved at least as well with $\mathcal{E}_{\mathsf{D}}$ as with $\mathcal{E}_{\mathsf{D}'}$. The **Le Cam deficiency** $\delta(\mathcal{E}_{\mathsf{D}}, \mathcal{E}_{\mathrm{id}})$ quantifies the worst-case loss over all tasks; $1 - \mathrm{corr}^2(\hat{w}, w)$ plays the role of its local, single-parameter counterpart. Call D *metrologically sufficient* if $\delta = 0$.

Programme.

1. Prove Propositions A–C with explicit error terms in δt and θ.
2. Remove assumptions (M): several logical and gauge qubits; non-commuting logical components of G (then τ becomes a time-ordered path); non-Pauli noise such as amplitude damping; finite δt, where the syndrome statistics themselves depend on θ and add a term $F_C[p_\theta(s)]$; global (Bayesian) estimation, where the sufficient statistic is the full posterior of (r, τ) and not only its mean.

3. Complexity of the **metrological decoding problem** "compute $w(s)$". It is a marginalisation problem, in general as hard as maximum-likelihood decoding (#P-hard), but exactly solvable by forward–backward smoothing for repetition-type codes and approximable by tensor networks, belief propagation, or soft-output matching. Seek approximation guarantees stated directly in corr^2.
4. Count sensing-relevant classes. For k logical qubits a computing decoder resolves 4^k classes. Characterise codes for which the sensing task requires strictly fewer (gauge qubits; CSS codes where only one error type is of class T).
5. Characterise the set of recoveries that yield equivalent experiments, which formalises "wrong but harmless".

Prior art and novelty. Quantum statistical comparison (Buscemi 2012; Jenčová 2016) and sufficiency via Fisher information (Gao, Li, Marvian, Rouzé 2023) exist as mathematics; I found no application to decoders in error-corrected sensing. Tsubouchi et al. treat states and name metrology as open. Conlon et al. use a syndrome-conditional weight in one model. Novelty: high for the general theory, with a real risk that parts of item 1 are implicit in Conlon et al.; their appendices should be read in full first.

First steps. Three-qubit and n-qubit repetition codes with noisy syndromes (exact posterior by forward–backward); then Bacon–Shor and small surface codes with a tensor-network posterior.

Risk. For one logical qubit without gauge freedom the class reduction is nil, so the benefit must be demonstrated through soft weights and offline inference. In toy model E6 the soft-over-hard gain is small; the aware-over-agnostic gain is large.

P2. Inference–action separation: frame tracking, decoder latency, and two-tier decoding

Question. Which corrections must be applied physically and in real time, and what is the exact sensitivity cost of decoder latency?

Formulation. An action policy π has latency τ_d and a probability p_{mis} of applying a wrong correction. The figure of merit is $F(\pi, \hat{w}) = \lambda^2 (\mathbb{E}_\pi[\hat{w} w])^2 / \mathbb{E}_\pi[\hat{w}^2]$.

Conjectures to prove.

1. *No-feedback theorem.* If every correctable error commutes with G (class P or N only; the commuting-noise setting of Layden et al. 2019), then F_{aware} is independent of the action policy as long as the accumulated error remains decodable. Syndrome *measurement* is required; real-time *feedback* is not.
2. *Latency law.* For class-T errors at rate Γ, $F = \bar{g}(\pi)^2 \lambda^2 T^2 + O(T)$ with $\bar{g} \simeq 1 - 2\Gamma(\tau_d + p_{\mathrm{mis}} \tau_{\mathrm{fix}})$, where τ_{fix} is the time until an offline pass detects the wrong action. Latency degrades the HL prefactor, not the scaling.
3. *Tracking-only law.* With no action at all, $F \to \lambda^2 T / \Gamma$: SQL scaling in T, but without exponential loss of contrast.

Algorithmic consequence: two-tier decoding. Use a fast, approximate real-time decoder to choose actions, and an accurate offline *smoother* (which also uses syndromes recorded after each event) to compute $w(s)$. Mistakes of the fast tier cost gain only. This differs from fault-tolerant computing, where a real-time decoding error before a non-Clifford gate is not recoverable.

Connection to continuous QEC. The "spurious Hamiltonian evolution" in the error subspace noted by Convy et al. and Atalaya et al. is, in sensing, proportional to the unknown θ and has known sign; it is therefore tracked by τ and need not be counted as a logical error.

Extensions. Noisy syndromes give timing uncertainty; at finite θ this produces dephasing of order $\theta^2 \operatorname{Var}(\tau \mid s)$, which fixes the admissible dynamic range.

Prior art and novelty. Pauli-frame tracking and latency are standard in computing. In sensing: bias from finite QEC rate (Rojkov et al.), finite-rate limits (Shettell et al.), sign tracking in one model (Conlon et al.). I found no latency law, no no-feedback theorem, and no two-tier proposal. Novelty: high.

Risk. The laws are first order in $\Gamma\tau_d$; a second error during the latency window produces genuine logical errors and must be bounded.

P3. Figures of merit and benchmarking for logical sensors

Question. What should replace "logical qubit" and "logical fidelity" when the encoded object is a sensor?

Definitions proposed.

- **Logical sensor response:** the pair of functions $\theta \mapsto \phi_L(\theta)$ (transfer function of the logical phase per unit time) and $\Gamma_L(\theta)$ (logical decoherence rate). This covers the linear case $\phi_L = \bar{g}\lambda\theta$, the bias of Rojkov et al., and the nonlinear case $\phi_L \propto \epsilon^3$ of Ott et al.
- **Metrological fidelity** $\mathcal{F}_{\mathrm{met}}(T)$ and its three-factor decomposition (Section 5.2).
- **Sensing-relevant logical error rate** Γ_L^{sens}: the rate of class-T or class-P logical events that remain unidentified after offline inference. It satisfies $\Gamma_L^{\mathrm{sens}} \leq \Gamma_L$, since class-N logical operators are harmless.
- **Coherent sensing horizon** $T^\star = \sup\{T : \mathcal{F}_{\mathrm{met}}(T) \geq \frac{1}{2}\}$, the time up to which HL scaling holds.
- **Logical sensitivity** $\eta_L = \min_T \sqrt{T/F(T)}$, and **metrological break-even:** $\eta_L < \eta_{\mathrm{phys}}$, the best sensitivity of the same n qubits without encoding under the same noise.

Questions.

1. Is there a threshold statement in these terms: a code family and a noise rate below which $T^\star \to \infty$, or below which $\mathcal{F}_{\mathrm{met}}$ stays bounded away from zero as $n \to \infty$? How does it relate to $d \cdot F = O(n^2)$ and to the thresholds of Sahu et al. and Conlon et al.?
2. A benchmarking protocol: inject a known calibration signal θ_{cal} through the physical generator, measure the slope (which gives $\bar{g}$) and the variance (which gives F). This plays the role that logical randomised benchmarking plays for gates, and requires no knowledge of the noise.
3. An extension to all tasks via the deficiency of P1, so that one number bounds the loss for estimation and detection alike.

Prior art and novelty. See the fragments listed in Section 5.2. No unified, decoder-inclusive, operational definition was found. Novelty: moderate to high; the contribution is conceptual unification, and its value depends on P1 and P2 supplying the theorems.

Risk. A definitional paper is persuasive only if the metric ranks real protocols differently from logical fidelity; the two counterexamples of Section 5.2 must be turned into quantitative case studies.

P4. Signals inside the Lindblad span: fundamental limits and optimal correlation-filter codes

Question. Ott et al. show that QEC can help even when $G \in \mathcal{S}$, provided signal and noise differ in spatio-temporal correlation structure. What is the ultimate limit for such signals, and which code, decoder and estimator attain it?

Formulation. The signal is a Poisson process of rate R of collective kicks $U_\epsilon = \prod_i (\cos\frac{\epsilon}{2} - i\sin\frac{\epsilon}{2}\, Z_i)$; the noise is local dephasing at rate γ. For a CSS code of odd Z-distance d, projection onto the trivial syndrome gives a logical rotation of angle

$$|\phi_+| = 2A_d\,(\epsilon/2)^d + O(\epsilon^{d+2}),$$

where A_d is the number of weight-d representatives of $\bar{Z}$. The logical signal is therefore governed by the **weight enumerator** of the logical coset. For $d = 3$, a syndrome pointing to qubit i gives a logical rotation of magnitude $|\phi_-^{(i)}| = \nu_i \epsilon$ with sign opposite to ϕ_+, where ν_i is the number of weight-3 logical operators containing qubit i.

Observation (my derivation under the approximations of Ott et al.; it reproduces their Steane-code values ϕ_+, ϕ_- and their constant 7). Define the signal-to-self-noise ratio $\rho(\mathcal{C}) = \lim_{\epsilon\to 0}(\partial_\epsilon \bar{\phi})^2/\sigma_\phi^2$, so that the total Fisher information in the limit $\delta t \to 0$ is $\rho(\mathcal{C})\, RT/e$. For distance-3 CSS codes with Z-stabilizer weight at least 4,

$$\rho(\mathcal{C}) = \frac{(\sum_i \nu_i)^2}{\sum_i \nu_i^2} \le n,$$

with equality if and only if the ν_i are uniform. Hence, with syndrome-agnostic processing, no distance-3 code improves on nRT/e; the Steane constant 7 is simply n.

Programme.

1. Compute the channel-QFI upper bound (Zhou, Jiang 2021) for the averaged generator $\gamma\mathcal{D} + R(\mathcal{U}_\epsilon - \mathrm{id})$ and compare it with nRT/e (logical), $nR^2T/(4e\gamma)$ (Ramsey), and $n^4 RT\epsilon^2/16$ (error detection). Determine whether the logical protocol is optimal, including constants, and map the regime boundaries.
2. Syndrome-aware processing. The self-noise Γ_R arises from averaging over syndrome outcomes. My estimate is that conditioning removes it only when $\gamma \lesssim R\epsilon^2$, because noise-triggered and signal-triggered syndromes are otherwise indistinguishable; this should be established rigorously, together with hybrid protocols for $d \ge 5$ in which weight-2 syndrome patterns carry error-detection information.
3. A *graded* HNLS criterion: classify signal–noise pairs that coincide at first order (so $G \in \mathcal{S}$) but differ in higher-order correlations, and state when QEC yields an advantage and of what size.
4. Gate-level noise and finite δt.

Prior art and novelty. Ott et al. (published 30 October 2026) treat the Steane and repetition codes with syndrome-agnostic estimation and perfect extraction. Fukuda et al. use a related projection idea for wave-like dark matter. I found no follow-up. Novelty: high; competition is likely to be rapid.

Risk. Item 1 may show the existing protocol is already optimal up to constants, which would be a useful but negative result.

P5. Detection-theoretic logical sensing: Neyman–Pearson decoding and quickest detection

Question. Many target applications (dark matter, transients) are detection problems, not estimation problems. What is the correct decoder and figure of merit when the task is to decide whether a signal is present?

Formulation. Test $H_0 : \theta = 0$ against $H_1 : \theta = \theta_1$ from the data $D = (s, x)$ of many shots. The false-alarm probability α and miss probability β replace the variance; the **Chernoff** and **Stein** exponents (asymptotic decay rates of the error probabilities) replace the Fisher information.

Statements to establish.

1. *Weak signals.* The log-likelihood ratio per shot is $\ln[1 + x\lambda\theta_1 w(s)]$, so the locally most powerful test uses the same posterior weight as P1, and the Kullback–Leibler rate is $\frac{1}{2}\theta_1^2 F_{\mathrm{aware}}$. The decoder theory of P1 therefore transfers.
2. *Detection-time scaling.* If HNLS holds, the encoded evolution is unitary and the two hypotheses become perfectly distinguishable after $T_\perp = \pi/(\lambda\theta_1)$; if it fails, QFI bounds imply $T_{\mathrm{detect}} = \Omega(\theta_1^{-2})$. This is the detection analogue of HL versus SQL. It follows from known bounds, so its novelty is modest, but I did not find it stated for error-corrected sensors.

3. *Strong, rare events.* Here the alternative is not local. An unidentified logical error is a **dark count**. The optimal statistic is the posterior odds of "signal" against all noise classes, which is a different objective from maximum-likelihood decoding: it calls for a decoder with asymmetric costs (**Neyman–Pearson decoding**) and for weighting or post-selecting shots by decoder confidence. Derive the receiver operating characteristic of a logical sensor as a function of code and decoder.
4. *Unknown arrival time.* Apply a sequential test (CUSUM) to the stream of syndrome-aware log-likelihood ratios. The detection delay at false-alarm rate α is $\ln(1/\alpha)/D$, with D the relative-entropy rate between the two data streams; compare with the quantum limit for change-point detection (Fanizza, Hirche, Calsamiglia 2023).

Prior art and novelty. Quantum hypothesis testing and change-point theory exist for states; Tsubouchi et al. list hypothesis testing with syndromes as open; dark-matter proposals use sensitivity estimates, not decoders designed for detection. Novelty: high for items 3 and 4.

Risk. Results in the rare-event regime depend strongly on the noise model; analytical progress may be limited to small codes.

P6. Feature-sufficient subsystem codes with nuisance parameters

Question. Suppose $H = \sum_\mu \theta_\mu G_\mu$ but only a feature $f = w^\mathsf{T}\theta$ is wanted (a gradient, one spatial mode, one spectral component). Which errors and which unknown Hamiltonian terms can be left uncorrected?

Formulation. Seek a subsystem code $\mathcal{C} = \mathcal{H}_L \otimes \mathcal{H}_G$ such that

$$\Pi E_a^\dagger E_b \Pi = I_L \otimes g_{ab}, \qquad \Pi(v\cdot G)\Pi = I_L \otimes n_v \ \ \forall v \perp w, \qquad \Pi(w\cdot G)\Pi = h_L \otimes I_G + I_L \otimes n_w, \ \ h_L \not\propto I.$$

The first condition is the subsystem Knill–Laflamme condition of Liu and Zhou. The second lets the nuisance generators act arbitrarily on the gauge factor. Then the reduced logical state depends on θ only through f, with no need to detect, freeze, or estimate the nuisance parameters.

Programme.

1. Existence. A corollary of the necessity argument of Górecki et al. is that f is HL-estimable if and only if $w \in \mathrm{range}(M^\mathsf{T})$, where $M : \theta \mapsto \sum_\mu \theta_\mu (G_\mu)_\perp$. Verify, and determine when the gauge relaxation above is achievable.
2. Optimality. Górecki et al. construct separate codes by placing the other generators in the Lindblad span, which freezes them ($\Pi G_j \Pi \propto \Pi$). The gauge condition is weaker, so the attainable QFI for f is at least as large. Characterise when it is strictly larger, and formulate the optimisation for the singular cost matrix $W = ww^\mathsf{T}$, which their SDP (stated for $W > 0$) does not cover directly.
3. Large or drifting nuisance parameters, where local estimation of the nuisance is not possible.

Prior art and novelty. Multi-parameter HNLS (Górecki et al.); nuisance parameters in quantum estimation (Suzuki, Yang, Hayashi 2020); spatial noise filtering and decoherence-free subspaces for distributed sensing (Layden, Cappellaro 2018; Sekatski, Wölk, Dür 2020); subsystem sensing codes for one parameter (Liu, Zhou 2026). The combination appears open. Novelty: moderate, because the asymptotic condition is a corollary of known results; the new content is the gauge relaxation and the finite-resource optimum.

Risk. The gauge relaxation may give no strict improvement in the examples of practical interest.

P7. Learned decoder–estimators for continuous-QEC sensing

Question. Can a neural network trained on realistic, non-ideal syndrome records serve as the optimal decoder for sensing, and can it be trained on hardware without knowing the noise?

Formulation. By Proposition B the optimal decoder output is $w(D) = \mathbb{E}[r\tau \mid D]$, with D the measurement record. A conditional expectation is the minimiser of a squared loss:

$$w = \arg\min_{\hat{w}} \ \mathbb{E}\big[(\hat{w}(D) - r\tau)^2\big].$$

Sensing decoding is therefore a **scalar regression** problem, and the excess training loss controls the metrological loss $1 - \mathrm{corr}^2(\hat{w}, w)$. No labels of individual error configurations are needed.

Programme.

1. Train recurrent or attention-based networks on simulated continuous records exhibiting the three non-idealities identified by Convy et al. (autocorrelation, transients after each flip, drift), with target $r\tau$. Compare with threshold filters, the Bayesian filter, and the exact smoother.
2. **Calibration-signal training on hardware.** For a small known θ_{cal}, $\mathbb{E}[x \mid D] = \lambda\theta_{\mathrm{cal}}\, w(D)$. Regressing the readout x on the record D therefore learns w up to a known scale from experimental data alone, without a noise model and without ground-truth errors.
3. Two-tier deployment (P2): a small, low-latency network for actions; a large offline network for w.
4. Robustness: drift of the syndrome baseline is itself a slow signal; study its separation from θ and the resulting bias.

Prior art and novelty. Neural decoders for QEC are numerous, including Convy et al. for continuous QEC; neural parameter estimation from continuous measurement exists without QEC (arXiv:2404.05526). I found no neural decoder trained for a sensing objective. Novelty: high; feasibility: high, since simulators for small codes are standard.

Risk. The regression formulation rests on assumptions (M); beyond them the target must be redefined (P1, item 2).

---

7. Comparison and recommended order

	Novelty (my confidence)	Difficulty	Depends on	First concrete result
P1	high (medium–high)	medium	—	rigorous Prop. A–C; corr^2 for repetition and Bacon–Shor codes
P2	high (high)	low–medium	P1	latency law and no-feedback theorem with simulation
P3	moderate–high (medium)	low	P1, P2	case studies where $\mathcal{F}_{\mathrm{met}}$ and logical fidelity disagree
P4	high (high), fast-moving	medium–high	—	channel-QFI bound versus nRT/e
P5	high for items 3–4 (medium)	medium	P1	ROC of a repetition-code sensor with dark counts
P6	moderate (medium)	medium	—	an example with strict gain from the gauge relaxation
P7	high (high)	low–medium	P1	network matching the exact smoother on a 3-qubit code

Recommendation. Begin with P2 on the repetition code (bit-flip noise, Z signal, noisy syndromes), because every quantity is computable exactly and the results (latency law, tracking-only law, bias removal) are immediately checkable. Formalise them as P1. Use P3 to frame the paper. P7 is the natural algorithmic sequel and gives an experimental collaboration path. P4 and P5 form a second line on rare events; P4 item 1 is the most valuable single calculation there. P6 is the lowest priority.

---

8. Limits of this novelty check

1. The search was conducted with web search on 12 November 2026 and is not exhaustive; arXiv listings of the last few weeks and work under review cannot be excluded.
2. Five 2026 preprints (arXiv:2601.05457, 2603.05145, 2605.08341, 2606.19628, 2608.00171) and arXiv:2512.20426 were read only in part: abstract and main sections verbatim, later sections and appendices through automatically extracted summaries. In particular, the statement that Conlon et al. weight their estimator by a syndrome-conditional statistic comes from such a summary. **Their appendices should be read in full before claiming priority for P1 or P2.**
3. Propositions A–C, the examples E3–E6, and the bound $\rho(\mathcal{C}) \leq n$ are my own derivations. They were checked numerically on toy models and against the published Steane-code constants, but not proved with error bounds and not reviewed.
4. Supplemental material of Ott et al. was not available to me.

References

Supplied papers

- S. Zhou, M. Zhang, J. Preskill, L. Jiang, *Achieving the Heisenberg limit in quantum metrology using quantum error correction*, Nat. Commun. 9, 78 (2018). arXiv:1706.02445
- S. Zhou, D. Layden, M. Zhang, J. Preskill, P. Cappellaro, L. Jiang, *Error-corrected quantum sensing*, Proc. SPIE 10934 (2019).
- W. Górecki, S. Zhou, L. Jiang, R. Demkowicz-Dobrzański, *Optimal probes and error-correction schemes in multi-parameter quantum metrology*, Quantum 4, 288 (2020). arXiv:1901.00896
- I. Convy et al., *Machine learning for continuous quantum error correction on superconducting qubits*, New J. Phys. 24, 063019 (2022).
- R. Ott, T. V. Zache, S. Choi, A. M. Kaufman, H. Pichler, *Rare-event quantum sensing using logical qubits*, Phys. Rev. Lett. 137, 180802 (2026). arXiv:2601.04313

Recent work found in the search

- H. Sahu, Q. Xu, S. Zhou, *Achieving the Heisenberg limit using fault-tolerant quantum error correction*. arXiv:2601.05457
- L. O. Conlon, Y.-X. Wang, E. Abbasgholinejad, V. V. Albert, M. J. Gullans, A. V. Gorshkov, *Fault-tolerant Heisenberg-limited quantum sensing*. arXiv:2608.00171
- J. Chen, R. Luo, Z. Du, Y. Yan, Y. Zhou, X. Ma, *Bypassing the protection–sensitivity incompatibility in quantum-error-corrected metrology via asymmetric codes*. arXiv:2512.20426
- Y. Chen, Z. Wang, S. Zhou, *Quantum metrology via partial quantum error correction*. arXiv:2605.08341
- Q. Liu, S. Zhou, *Subsystem quantum error correction for noisy quantum metrology*. arXiv:2606.19628
- K. Tsubouchi, H. Kwon, L. Jiang, N. Yoshioka, *Quantum advantages for syndrome-aware noisy logical observable estimation*. arXiv:2603.05145
- H. Fukuda, T. Moroi, T. Sichanugrist, *Quantum-error-correction-inspired noise mitigation for wavelike dark matter searches with quantum sensors*. arXiv:2511.03253
- *Encoded quantum signal processing for Heisenberg-limited metrology* (authors not verified). arXiv:2603.22798
- R. R. Allen, F. Machado, I. L. Chuang, H.-Y. Huang, S. Choi, *Quantum computing enhanced sensing*. arXiv:2501.07625

- arXiv:2404.05526: machine-learning parameter estimation from continuous qubit measurement records (title and authors not verified).

Earlier foundations

- S. F. Huelga et al., Phys. Rev. Lett. 79, 3865 (1997); B. M. Escher, R. L. de Matos Filho, L. Davidovich, Nat. Phys. 7, 406 (2011); R. Demkowicz-Dobrzański, J. Kołodyński, M. Guţă, Nat. Commun. 3, 1063 (2012).
- R. Demkowicz-Dobrzański, J. Czajkowski, P. Sekatski, Phys. Rev. X 7, 041009 (2017).
- D. Layden, S. Zhou, P. Cappellaro, L. Jiang, Phys. Rev. Lett. 122, 040502 (2019); D. Layden, P. Cappellaro, npj Quantum Inf. 4, 30 (2018).
- S. Zhou, L. Jiang, *Asymptotic theory of quantum channel estimation*, PRX Quantum 2, 010343 (2021). arXiv:2003.10559
- I. Rojkov, D. Layden, P. Cappellaro, J. Home, F. Reiter, *Bias in error-corrected quantum sensing*, Phys. Rev. Lett. 128, 140503 (2022). arXiv:2101.05817
- N. Shettell, W. J. Munro, D. Markham, K. Nemoto, *Practical limits of error correction for quantum metrology*, New J. Phys. 23, 043038 (2021).
- P. Niroula et al., *Quantum sensing with erasure qubits*, Phys. Rev. Lett. 133, 080801 (2024). arXiv:2310.01512
- J. Atalaya et al., *Continuous quantum error correction for evolution under time-dependent Hamiltonians*, Phys. Rev. A 103, 042406 (2021).
- P. Sekatski, S. Wölk, W. Dür, Phys. Rev. Research 2, 023052 (2020); J. Suzuki, Y. Yang, M. Hayashi, J. Phys. A 53, 453001 (2020).
- F. Buscemi, Commun. Math. Phys. 310, 625 (2012); A. Jenčová, *Comparison of quantum channels and statistical experiments*, arXiv:1512.07016; L. Gao, H. Li, I. Marvian, C. Rouzé, *Sufficient statistic and recoverability via quantum Fisher information*, arXiv:2302.02341.
- M. Fanizza, C. Hirche, J. Calsamiglia, *Ultimate limits for quickest quantum change-point detection*, Phys. Rev. Lett. 131, 020602 (2023). arXiv:2208.03265