

About this release

V5.72.0 added support for Qu-5/6/7.

Previous releases

V4.86.0 WDM input device for Qu-16/24/32/Pac/SB changed to stereo for improved compatibility.

V4.67.0 security update for Windows 10.

V3.34.0 adds support of Qu-SB and extended WDM support.

V3.20.0 added support of Windows 10.

V2.20.53 added support of Qu-Pac.

V2.20.52 changed routing of stereo Windows WDM audio to ST3 on Qu-16 and Qu-24, Ch31-32 on Qu-32.

V2.20.4 added a Control Panel and a driver tray icon.

Features

ASIO™ Features

- ASIO™ 2.2 compliant
- Supports both 32-bit and 64-bit ASIO™ host applications
- Multi-client support (multiple ASIO™ applications in parallel)
- Playback mix (simultaneous ASIO™ and WDM playback)

WDM/DirectX Features

- Supports standard Windows interfaces: MME, DirectSound, WASAPI
- Volume and mute control through Windows Mixer
- All models – Mono/Stereo/Quad/5.1 surround/7.1 surround WDM device
- **Qu-16/24/32/Pac/SB** – 1x Stereo Input Device presented (from Qu Stereo USB Audio Out 17&18)
- **Qu-16/24** - 3x Stereo Output Devices presented (to Qu USB inputs ST1, ST2, ST3)
- **Qu-32/Pac/SB** – 3x Stereo Output Devices presented (to Qu USB inputs 27&28, 29&30, 31&32)
- **Qu-5/6/7** – 4x Stereo Input Devices presented (from Qu USB Output sockets 1&2, 3&4, 5&6, 7&8)
- **Qu-5/6/7** – 4x Stereo Output Devices presented (to Qu USB Input sockets 1&2, 3&4, 5&6, 7&8)

MIDI Features

- Windows compliant MIDI input and output ports

System requirements

The Qu Windows driver supports these Windows operating systems:

- Windows 10
- Windows 11

Note A driver is not required for Mac computers.

Installation

1. Download the installation file.
2. Power the mixer and connect the rear panel USB-B (Qu-16/24/32/Pac/SB) or USB-C (Qu-5/6/7) port to the PC with a high-speed USB cable.
3. Run the installer and follow the instructions on screen.
4. Turn on your mixer.
5. Your mixer will show up as an audio device in Windows, and as a WDM / ASIO™ device in any software which supports it.

Control Panel

Click on the driver tray icon to access the Qu USB Control Panel and set the following configuration options:

Preferred ASIO™ Buffer Size

Defines the buffer depth between the driver and the DAW or other application.

Can be set to 8, 16, 32, 64, 128, 256, 512, 1024, 2048 samples at 48kHz or 16, 32, 64, 128, 256, 512, 1024, 2048, 4096 samples at 96kHz.

If your application requires low latency, try reducing the Buffer Size gradually and test for reliable streaming. Should you experience any audio dropout, revert to a higher buffer setting.

Some ASIO™ compatible applications have direct control of buffer size and this will take priority over the preferred buffer size.

Safe Mode

Safe Mode adjusts the buffer to provide more reliable streaming, though will also increase output latency. It is recommended that this is left on.

Known issues

- Pro Tools will report an unsupported buffer size when the driver is set to 2048 samples.
- The Qu mixer serial number is not displayed correctly in the driver Control Panel.
- Dynamic map of Windows WDM outputs is not supported.



*ASIO™ is a trademark and software of Steinberg Media Technologies GmbH