Translate (by hand) the following assembly program to Control Section object code. Which contains H record, T record, and E record.

Please solve this section:

LC LOCCTR	Symbol PROGC	Ins Start	Ref 0000	Object Code
		EXTDEF	LISTC, ENDC	
		EXTREF	LISTB, ENDB, LISTA, ENDA	
		.		
		.		
		.		
0018	REF1	+LDA	LISTA	03100000
	REF2	+LDT	LISTB+4	77100004
	REF3	+LDX	#ENDA-LISTA	05100000
		.		
		.		
		.		
0030	LISTC	EQU	*	no obj code
		.		
		.		
0042	ENDC	EQU	*	no obj code
	REF4	WORD	ENDA-LISTA+LISTC 4	000030
	REF5	WORD	ENDC-LISTC-10 5	000008
	REF6	WORD	ENDC-LISTC+LISTA-1 6	000011
	REF7	WORD	ENDA-LISTA-(ENDB-LISTB) 7	000000
	REF8	WORD	LISTB-LISTA 8	000000
		END		No obj code

H. PROGC X. 000000. 000051

D. LISTC. 000030. ENDC. 000042

R. LISTB. ENDB. LISTA. ENDA

T. 000018. 0C. 03100000. 77100004. 05100000

T. 000042. 0F. 000030. 000008. 000011. 000000. 000000

M. 000019. 05. +LISTA

M. 00001D. 05. +LISTB

M. 000021. 05. +ENDA

M. 000021. 05. -LIST

M. 000042. 06. +ENDA

M. 000042. 06. -LISTA

M. 000048. 06. +LISTA

M. 00004B. 06. +ENDA

M. 00004B. 06. -LISTA

M. 00004B. 06. -ENB

M. 00004B. 06. +LISTB

M. 00004E. 06. +LISTB

M. 00004E. 06. -LISTA

E. 000000

+LDA LISTA

1) opcode: 0000 (0) | n i x b p e: 00 1 1 0 0 0 1 (3, 1) | Address: 00000

2) +LDT LISTB+4

opcode: 0111 (7) | n i x b p e: 01 1 1 0 0 0 1 (7, 1) | Address: 00000+4 → 77100004

3) +LDX #...

04

opcode: 0000 (0) | n i x b p e: 01 01 0 0 0 1 (5) | Address: 00000

4) WORD ENDA - LISTA + LISTC

0000 - 0000 + 0030 = 000030

5) WORD: 0042 - 0030 - A = 000008

6) WORD: 0042 - 0030 + 0000 - 1 = 000011

7) WORD: 0000 - 0000 - 0030 + 0000 = 000000

8) WORD: 0000 - 0000 = 000000