



GGT-30B Geophysical Transmitter

High Power - Fast Turn-off



FEATURES

- Constant current supply
- Used for time/frequency domain IP, CR, TEM, FEM, CSAMT
- Broad-band: DC to 8 kHz
- Fast turn-off time: 125 μ s (300 · 300 m² loop)
- Drives a loop or grounded dipole
- Efficient, modular design
- Rugged design reliable in all climates

SPECIFICATIONS FOR THE GGT-30B TRANSMITTER

General

Description: Broadband, constant-current, time and frequency domain, high-power geophysical transmitter

Enclosure: Anodized blue aluminum case

Size: 56 x 40.8 x 43.2 cm

Weight: 71.4 kg

Operating temperature: -40° to +55°C (-40° to +130°F)

Operating humidity: 0 to 90%, non-condensing

Electrical Characteristics

Drives a loop or grounded dipole

Turnoff time: Under 10 μ s for a resistive load; 125 μ s for a 300 x 300 m² loop (16 ohms resistance, full current)

Maximum input: 30KVA @ 30°C

Output voltage range: 50 to 1000V

Output current range: 0.2 to 45A

Current stability: $\pm 0.2\%$

Frequency range: DC to 8 kHz

Switching Control

Switching controlled by external device

Recommended transmitter controller: Zonge XMT, GDP or ZEN

Waveform type: Capable of virtually any type of pulse waveform, limited by external controller device

Controls

Power ON / OFF

Transmit / Reset switch

Current adjust pot, continuously adjustable, locking

Voltage range TAP switch

50-250V

200-500V

450-750V

700-1000V

Displays

Analog input voltage meter, 0-150 V

Analog output voltage meter, 0-1000 V

Power On / Off LED

Transmit LED

Output LED

3 $\frac{1}{2}$ Digit Operating Information Display

Output current

Loop turnoff time (μ seconds)

Transformer temperature (°C)

Input power (KW)

Indicator LEDs: power on, transmit on, transmit polarity

Fault indicator LEDs: output and input overcurrent, output and input overvoltage, end of regulation, generator overvoltage, open circuit, phase error

Output Jacks

Isolated Output Current (10mV/A)

Isolated Output Voltage (10mV/V) Optional

Power

Three-phase, 120 VAC, 400 Hz \pm 15 Hz

Recommended motor generator set: Zonge ZMG.

Power connector: Hubbell, 4-Pole, 5-Wire.

Options

IGBT spare module

SCR spare module

ZCM-10 Isolated Output Voltage (10mV/V)

current monitor isolation amplifier module

LB6000 Resistor load bank

ETS-9 Switch box for rapid switching of dipole pairs

Zonge International Offices:

Arizona, Alaska, Nevada

Headquarters:

3475 N. Dodge Blv., Tucson, AZ 85716, USA (800) 523-9913

Tel: (520) 327-5501 Email: zonge@zonge.com

Fax: (520) 325-1588 Web: <http://www.zonge.com>

Specifications subject to change without notice

© Copyright 2022, Zonge International, Inc.

TRUSTED GEOPHYSICS™