

Electromagnetic Helix Reactor (EHR): A Multi-Physics Plasma Control Architecture for Advanced Plasma Processing

Zachary Auerbach

July 4, 2026

Abstract

This paper proposes the Electromagnetic Helix Reactor (EHR), a multi-physics plasma source architecture that integrates a tunable helical magnetic field, helicon-wave excitation with resonance-matched coupling, and acoustic standing-wave modulation of the neutral gas. The design aims to provide new degrees of spatial control in low-temperature plasmas relevant to semiconductor processing. The baseline operating regime is the magnetized-electron, unmagnetized-ion regime characteristic of helicon sources. Three falsifiable experimental predictions are outlined to test the core elements of the proposed architecture.

1 Introduction

Low-temperature plasmas are fundamental to semiconductor manufacturing, thin-film deposition, and surface modification. Conventional sources such as inductively coupled plasmas (ICP) and electron cyclotron resonance (ECR) sources typically operate with fixed magnetic geometries and single-mode excitation. Helicon sources have demonstrated high efficiency through whistler-wave coupling, while acoustic radiation forces are well established for structuring fluids and dusty plasmas.

The EHR integrates three elements into a single architecture:

- A divergence-free helical magnetic field whose pitch can be tuned via coil currents,
- Helicon-mode wave drive with resonance-matched power coupling, and
- Acoustic standing-wave modulation of the neutral gas as an independent mesoscale control channel.

The central motivation is to move beyond fixed-geometry sources toward a reactor in which key control variables — field-line pitch and acoustic mode structure — can be adjusted in a physically consistent manner. This paper outlines the underlying physical principles, defines a consistent operating regime, and proposes a clear experimental validation path.

2 System Architecture

The EHR consists of a cylindrical vacuum chamber, a multi-coil electromagnet producing a helical static field, an RF antenna for $m = 1$ helicon excitation, wall-mounted piezoelectric acoustic transducers, and an electrostatic wafer chuck with independent RF bias.




Figure 1: Schematic cross-section of the proposed EHR showing the helical field coils, helicon antenna, acoustic transducers, and wafer stage.

3 Electromagnetic Field Architecture

The static magnetic field combines axial and azimuthal components in cylindrical coordinates:

$$\mathbf{B}(r) = B_z(r) \hat{\mathbf{z}} + B_\theta(r) \hat{\boldsymbol{\theta}}, \quad B_r = 0. \quad (1)$$

The local field-line pitch is given by

$$L_p(r) = \frac{2\pi r B_z(r)}{B_\theta(r)}. \quad (2)$$

This pitch constitutes a programmable control variable. A force-free realization is provided by the constant- α Beltrami field:

$$B_z(r) = B_0 J_0(\alpha r), \quad B_\theta(r) = B_0 J_1(\alpha r). \quad (3)$$

The dynamic electromagnetic drive is realized through a helicon $m = 1$ mode:

$$\tilde{\mathbf{B}}(r, \theta, z, t) \propto f(r) \exp[i(\theta + kz - \omega t)]. \quad (4)$$

4 Magnetization Regime

The proposed baseline operating point uses argon at 10 mTorr with an axial field of 100 G. At this condition, electrons are strongly magnetized while ions remain unmagnetized. This regime is consistent with conventional helicon sources. As the magnetic field is increased toward approximately 1 kG, ions begin to magnetize, providing a clear physical regime boundary that can be explored experimentally.

5 Resonance-Matched Power Coupling

Efficient power deposition is achieved by coupling to the helicon mode, whose resonance condition links drive frequency, wavenumber, plasma density, and magnetic field through the helicon dispersion relation.




Figure 2: Illustrative helical field lines. The local pitch varies with the ratio B_z/B_θ according to Eq. (2).

6 Governing Equations

Single-particle motion obeys the Lorentz force. The fluid momentum equation includes an additional body-force term representing momentum transfer from the acoustically modulated neutral background.

7 Acoustic Standing-Wave Modulation

Acoustic standing waves are proposed as an independent control channel acting on the neutral gas. At 10 mTorr, acoustic radiation forces are weak and damping is strong. The EHR is therefore positioned as a research platform to explore neutral-to-plasma coupling at the centimeter scale. Sustaining well-defined standing waves would require resonant drive or operation at moderately higher pressure.




Figure 3: Illustrative acoustic standing-wave modes. Red lines indicate pressure nodes.

8 Applications

The architecture targets improved across-wafer uniformity in processes such as tungsten metallization and SiC etching. Magnetic field management near the wafer remains important to minimize non-uniformity and charging damage. The device is also proposed as a flexible platform for fundamental studies of helicon-acoustic coupling and dusty plasma dynamics under controlled conditions.

9 Proposed Experimental Validation

Three falsifiable predictions are defined at the baseline operating point of Section 4:

1. The $m = 1$ helicon mode can be directly measured with a phase-resolved B-dot probe array and shown to satisfy the helicon dispersion relation.
2. Scanning the drive frequency or magnetic field strength through the helicon resonance condition produces a measurable peak in plasma density.
3. Acoustic standing-wave drive imprints measurable centimeter-scale periodic modulation on both the neutral gas density and the plasma density.

Failure of the third prediction would indicate that acoustic modulation does not couple effectively to the plasma under the proposed conditions. Failure of pitch-dependent effects at constant $|B|$ and power would indicate that the tunable helical geometry does not provide meaningful additional control.

10 Dusty Plasma Dynamics and Ion Drag

When micron-sized particles are introduced into the plasma, they acquire substantial negative charge and experience several forces. The ion drag force, arising from both direct ion collection and Coulomb scattering, is often dominant in low-pressure discharges and governs dust transport, void formation, and dust-acoustic waves.

The EHR architecture offers experimental handles that are not readily available in conventional dusty plasma devices. The tunable helical magnetic field allows controlled modification of ion flow patterns through changes in field-line pitch at constant $|B|$. Acoustic standing-wave modulation provides an external means to influence the neutral gas background, which, through ion-neutral collisions, can affect local ion trajectories and the resulting ion drag.

11 Plasma Crystal Formation

Micron-sized dust particles in a plasma acquire large negative charges and interact via a screened (Yukawa) repulsive potential. When the coupling parameter

$$\Gamma = \frac{Q_d^2}{4\pi\epsilon_0 a k_B T_d} \exp\left(-\frac{a}{\lambda_D}\right) \quad (5)$$

becomes sufficiently large, the particles can self-organize into ordered crystalline structures known as plasma crystals. In two-dimensional laboratory systems, strong ordering is typically observed for $\Gamma \gtrsim 130$ –150 [13]. In three-dimensional Yukawa systems, the melting transition generally occurs at higher values, typically $\Gamma \gtrsim 170$ –200 for moderate screening, with the exact threshold depending on the screening parameter $\kappa = a/\lambda_D$ [14].

The EHR architecture offers experimental capabilities well suited to studying these strongly coupled regimes. The tunable helical magnetic field enables controlled modification of ion flow and ion wake structures, while acoustic modulation provides a means to externally influence dust kinetic temperature or drive the system across the crystallization threshold.

12 Magnetized Ion Wake Dynamics

In a flowing dusty plasma, ions streaming past negatively charged dust particles create localized regions of positive space charge known as ion wakes. These wakes make the effective dust–dust interaction non-reciprocal. A representative form of the electrostatic potential combines the screened Coulomb contribution with an oscillatory wake term:

$$\phi(r_{\perp}, z) \approx \frac{Q_d}{4\pi\epsilon_0} \left[\frac{\exp(-r/\lambda_D)}{r} + A \frac{\exp(-|z|/\ell_w)}{r} \sin(k_z|z|) \right], \quad (6)$$

where $z < 0$ is the downstream direction.

When ions become magnetized, their trajectories transition from straight lines to helical motion. This modifies the wake structure, making the screening anisotropic and altering both the amplitude and spatial form of the wake-mediated interaction. The EHR architecture is designed to allow controlled investigation of this transition. At the baseline field of 100 G, ions remain unmagnetized. As the field is increased toward ~ 1 kG, ions begin to magnetize. The tunable helical geometry further enables variation of the angle between $\mathbf{B}$ and the ion flow at fixed field strength.

13 Discussion

The EHR combines established physical elements — helical magnetic fields, helicon wave coupling, and acoustic modulation — into a single device with two programmable control variables. The primary technical challenges include efficient acoustic coupling at low pressure, thermal management of transducers, and careful management of magnetic fields near the wafer. Quantitative modeling of expected performance gains remains a subject for future work.

14 Conclusion

The Electromagnetic Helix Reactor proposes an integrated architecture in which a tunable helical magnetic field, helicon drive, and acoustic modulation operate within a physically consistent regime. A three-prediction experimental program provides clear criteria for validation or falsification. If successful, the concept offers a path toward improved spatial control in low-temperature plasma processing and a versatile platform for fundamental studies of wave-driven and dusty plasmas under controlled ion flow conditions.

Authorship Statement

This work was developed and authored solely by Zachary Auerbach with no external funding or collaborators.

References

- [1] M. A. Lieberman and A. J. Lichtenberg, *Principles of Plasma Discharges and Materials Processing*, 2nd ed., Wiley, 2005.
- [2] P. Chabert and N. Braithwaite, *Physics of Radio-Frequency Plasmas*, Cambridge University Press, 2011.

- [3] G. S. Oehrlein and S. Hamaguchi, “Foundations of low-temperature plasma enhanced materials synthesis and etching,” *Plasma Sources Sci. Technol.* **27**, 023001 (2018).
- [4] R. W. Boswell, *Plasma Phys. Control. Fusion* **26**, 1147 (1984).
- [5] F. F. Chen, *Plasma Sources Sci. Technol.* **24**, 014001 (2015).
- [6] F. F. Chen and D. Arnush, *Phys. Plasmas* **4**, 3411 (1997).
- [7] J. Asmussen, *J. Vac. Sci. Technol. A* **7**, 883 (1989).
- [8] L. P. Gor’kov, *Sov. Phys. Dokl.* **6**, 773 (1962).
- [9] H. Bruus, *Lab Chip* **12**, 1014 (2012).
- [10] J. Goree *et al.*, *Phys. Plasmas* **27**, 123701 (2020).
- [11] I. H. Hutchinson, *Principles of Plasma Diagnostics*, 2nd ed., Cambridge University Press, 2002.
- [12] J. P. Freidberg, *Ideal MHD*, Cambridge University Press, 2014.
- [13] A. Melzer, A. Homann, and A. Piel, *Phys. Rev. E* **53**, 2757 (1996).
- [14] S. Hamaguchi, R. T. Farouki, and D. H. E. Dubin, *Phys. Rev. E* **56**, 4671 (1997).