

Setting up Integrated Circuit Layout Design Software

IIC_OSIC_TOOLS first setup and launch

IIC tools git is available under this [link](#). The whole setup process comes down to one-line tool setup and installing Docker.

1. If you don't have curl, install it.

```
sudo apt install curl
```

2. Then install IIC tools, the one-line setup is:

```
curl -fsSL https://osic.tools/install.sh | bash
```

3. Add new user to docker.

```
sudo usermod -aG docker $USER
```

4. Apply changes to your current terminal session.

```
newgrp docker
```

5. If you don't want to repeat this step each time you login, you should reboot the system.

```
sudo reboot
```

6. Then follow the Docker installation process described on their [site](#)

7. There are few ways to launch the tool. firstly go to the iic-osic-tools folder in your home directory. then you can launch the environment by using commands:

`./start_x.sh` - launches the GUI using your local X11 server window.

`./start_vnc.sh` - launches a remote desktop session inside a VNC server, accessible via your web browser or a VNC viewer. After running the command go to <http://localhost> and use default password `abc123`. More about it [here](#).

`./start_shell.sh` - launches a text-only command-line interface (CLI) directly in your current terminal.

Just keep in mind that first launch might take a few minutes before the program launches.

(Optional) Quick launch for IIC-OSIC-TOOLS with chosen PDK

Inside `scripts/iic_tools_launch_scripts` there is a file `run_iic_tools.sh` - this is a new .sh file, not available with iic-osic-tools install. If you want to use it, copy it into `~/iic-osic-tools/` folder. You can still launch it same as the previously mentioned - by entering command `./run_iic_tools.sh`. For this instance we wanted quick and easy access to tool without bothering about our location so we created alias, which I highly recommend.

To create permanent aliases you have to edit .bashrc file:

```
micro ~/.bashrc
```

And then add at the end of the file:

```
alias run_iic='~/iic-osic-tools/run_iic_tools.sh'
```

(Optional) I also added some for general use and git:

```
alias c='clear'
alias update='sudo apt update && sudo apt upgrade'
alias gs='git status'
alias gc='git commit -m'
alias gp='git push origin main'
```

Then you refresh this config file:

```
source ~/.bashrc
```

Everything is set up correctly now, you can launch tools by typing `run_iic` in the terminal.

Script `run_iic_tools.sh` is basically `./start_x.sh` but with addition of automatic PDK launch so you won't have to type `sak-pdk [PDK]` each time you run iic tools. If viewed with notepad/vim you can search near the file's end two variables for config:

SELECT_PDK - set flag to 'True' to choose PDK on each launch. Currently set as 'False'.

USER_PDK - Default PDK that will be chosen if **SELECT_PDK** is False or user doesn't input anything when prompted for PDK. Since I will be working on Sky130A, that's currently default. When launched it always outputs default PDK and which PDK is used for launch.

Introduction IIC-OSIC-TOOLS and sky130A PDK

This guide will follow the local environment started up with `./start_x.sh` or `./run_iic_tools.sh`. It should launch a terminal.

1. With command `sak-pdk` you can switch between different PDKs, type this command to see the usage.
In this tool, there are 4 available by default PDKs with them being:
 - `sky130A` - SkyWater Technologies, 180-130nm hybrid 1.8-3.3V
 - `gf180mcuD` - Global Foundries, 180nm 3.3-6V
 - `ihp-sg13g2` - IHP Microelectronics
 - `ihp-sg13cmos51` - IHP Microelectronics
2. This instruction will get you familiar with sky130A PDK so use `sak-pdk sky130A` or the `./run`. If this command is not input before starting your work, you will be using default PDK, which is `ihp-sg13g2`. You can check current PDK with `echo $PDK` after launch. This step is not necessary if launched using `run_iic_tools.sh` or `run_iic` alias that was optionally set up.
3. Then you can launch schematic capture and netlisting EDA tool - Xschem - with command:

```
xschem # or `xschem [filename].sch` to launch specific file from your designs
```

4. Feel free to explore Menu Bar, especially the `Help -> Keys/Keybindings` that has many useful shortcuts and `Help -> About XSCHEM` from which can check program's git or [Xschem Manual](#).
5. If PDK is already chosen as sky130A and you use just `xschem` command Xschem will launch with `top.sch` that has: all available components in this PDK and some useful informations about them; Links to sky130A instructions, documentation, github; test cells for different simulations; digital standard cells.