
PAC-Bayesian Bounds for Learning Partially Observed Stochastic Linear Time-Invariant State-Space Systems with Inputs and Sub-Gaussian Noise

Mihaly Petreczky

CRIStAL, Centrale Lille, Université de Lille, France, mihaly.petreczky@centraledelille.fr

Mohamad Al Ahdab

Department of Electronic Systems, Aalborg University, Denmark, maah@es.aau.dk

John Leth

Department of Electronic Systems, Aalborg University, Denmark, jjl@es.aau.dk

Abstract

In this paper we derive a Probably Approximately Correct (PAC)-Bayesian error bound for partially observed linear time-invariant (LTI) stochastic dynamical systems in state-space form with inputs. Such bounds are widespread in machine learning, and they are useful for characterizing the predictive power of models learned from finitely many data points. The bound derived in this paper relates the expectation of prediction errors with the prediction error generated by the model on the data used for learning. In addition, we show that it can also be used to derive bounds for the parameter estimation error. In turn, this allows us to provide finite-sample error bounds for the prediction error and parameter estimation error for a wide class of system identification algorithms. Furthermore, as LTI systems are a sub-class of recurrent neural networks (RNNs), these error bounds could be a first step towards PAC-Bayesian bounds for RNNs.

1 Introduction

PAC and PAC-Bayesian bounds are fundamental tools for analyzing learning algorithms. They provide generalization guarantees that relate the *true error* (performance on unseen data) to the *empirical error* (performance on training data), by bounding the *generalization gap*, the difference between true and empirical error, in a way that is independent of the specific learning algorithm. In this framework, learning is viewed as selecting a model from a data-dependent posterior distribution over hypotheses, which is a modification of a prior based on the observed data. Different learning algorithms correspond to different choices of priors, posteriors, and selection mechanisms (e.g., sampling, averaging, or maximizing the posterior). PAC-Bayesian bounds then provide a uniform upper bound on the average generalization gap with respect to any posterior, thus offering generalization guarantees for a broad class of learning and model selection methods.

This generality makes PAC-Bayesian approaches especially useful for analyzing complex models, including neural networks, where they can yield non-vacuous generalization bounds [7]. Although PAC and PAC-Bayesian theory is well developed for i.i.d. settings [36, 2, 17], there are comparatively few results for dynamical systems.

Contribution: In this paper, we derive PAC-Bayesian error bounds for learning discrete-time stochastic LTI state-space systems with sub-Gaussian noise and partial observations (the full states

is not observed). Following standard practice in system identification, we view LTI systems as predictors that generate predictions for the current output based on past inputs and outputs. Our main contribution is a PAC-Bayesian bound showing that, with high probability (at least $1 - \delta$), for any posterior distribution over predictors, the average generalization gap is $O(\frac{(\ln N)^r}{\sqrt{N}})$, where N is the sample size, $r = 0$ for bounded noise, $r = 1$ for Lipschitz loss, and $r = 3/2$ for quadratic loss. The bound depends on the Kullback–Leibler (KL) divergence between prior and posterior distributions and on $\ln(1/\delta)$. We subsequently derive generalization gap and parameter estimation error bounds for concrete learning algorithms (e.g., maximum likelihood, regularized prediction-error methods (PEM), and Bayesian methods).

Related work: PAC and PAC-Bayesian bounds for autoregressive models with bounded signals or Lipschitz loss have been studied in [5, 44, 3, 1, 27, 29]. In contrast, our results address state-space models with partially observed states and with inputs, which are more general than autoregressive models, and we allow for unbounded (sub-Gaussian) noise, and handle quadratic loss. We also build on techniques from [3, 1].

In contrast to the literature on finite-sample parameter estimation bounds for specific least-squares based learning algorithms for LTI systems, e.g., [38, 37, 32, 24, 14, 19, 42, 20, 35], this paper presents bounds on both the parameter estimation and the generalization gap for a wide-range of algorithms, see Remark D.12, Appendix D.5 for a detailed comparison.

PAC bounds for recurrent neural networks, of which LTI state-space representations are a subclass, have been developed using VC dimension [23, 41], Rademacher complexity [23, 41, 6], and PAC-Bayesian approaches [7]. However, existing results assume noiseless models, fixed prediction horizons, i.i.d. training data samples, and bounded signals. In contrast, this paper considers noisy models, infinite-horizon prediction errors, a single observed time series, and unbounded signals with sub-Gaussian noise.

In [12], bounds based on Rényi divergence were proposed, but the resulting probabilistic guarantees scale as $O(1/\delta)$ with the confidence level, rather than the standard $O(\ln(1/\delta))$, and it applies only to quadratic losses as opposed to general Lipschitz losses, and it provides parameter estimation bounds only in terms of the empirical error. In contrast, the bound of this paper depends on the confidence level $O(\ln(1/\delta))$ and it provides an absolute bound on the parameter estimation error. The works [11, 8] provide PAC-Bayesian generalization gap bounds for RNNs and LTI systems with bounded noise, respectively. In contrast, the present paper addresses unbounded (sub-Gaussian) noise and also derives parameter estimation error bounds. Even for bounded signals, our results refine the constants used in [11, 8] (see Remark D.11, Appendix D.5). PAC-Bayesian bounds for autonomous LTI systems without inputs were considered in [9] but those bounds did not converge to zero as $N \rightarrow \infty$.

Paper Outline: We start by defining the problem formulation in Section 2, followed by the main results in Section 3 and discussion of the bounds in Section 4. The technical proofs are presented in the appendices.

2 Problem formulation

2.1 Notation and terminology

We occasionally use $\triangleq$ to denote "defined by". Let $\mathcal{F}$ denote a σ -algebra on the set Ω and $\mathbf{P}$ be a probability measure on $\mathcal{F}$. Unless otherwise stated, all probabilistic considerations will be with respect to the probability space $(\Omega, \mathcal{F}, \mathbf{P})$, and we let $\mathbf{E}[\mathbf{z}]$ denote expectation of the stochastic variable $\mathbf{z}$. We use bold face letters to indicate stochastic variables/processes relative to $(\Omega, \mathcal{F}, \mathbf{P})$. Each euclidean space is associated with the topology generated by the 2-norm $\|\cdot\|_2$, and the Borel σ -algebra generated by the open sets. The induced matrix 2-norm is also denoted $\|\cdot\|_2$.

Let B_Θ be the σ -algebra of Lebesgue-measurable subsets of $\Theta \subset \mathbb{R}^{n_\theta}$, and m the Lebesgue measure. For a probability density ρ on (Θ, B_Θ, m) and a measurable, integrable function $g : \Theta \rightarrow \mathbb{R}$, define $E_{\theta \sim \rho}[g(\theta)] \triangleq \int_\Theta \rho(\theta)g(\theta)dm(\theta)$ as the expectation of g under ρ . For a density π on Θ , let $\mathcal{M}_\pi$ denote the set of all densities on Θ whose probability measure is absolutely continuous w.r.t. the probability measure of π .

Let $\text{vol}(A) = \int_A dm(\theta)$ denote the Lebesgue measure of $A \subseteq \mathbb{R}^{n_\theta}$. The uniform distribution on a measurable set $A \in \mathcal{B}_\Theta$ is $\rho(\theta) = \frac{\chi_A(\theta)}{\text{vol}(A)}$, where χ_A is the indicator function. For $A = \Theta$, this is the uniform distribution on Θ .

The phrase *probability over data* refers to probability under $\mathbf{P}$ on $(\Omega, \mathcal{F})$. Specifically, for measurable functions $\{X_i, Y_i\}_{i \in I}$ and a binary relation $\diamond$, we say $\forall i \in I : X_i \diamond Y_i$ holds with probability at least $1 - \delta$ over data if the set $F = \{\omega \in \Omega : \forall i \in I, X_i(\omega) \diamond Y_i(\omega)\}$ satisfies $\mathbf{P}(F) \geq 1 - \delta$.

2.2 Problem formulation

The problem formulation follows [11, 8, 12].

Let us fix stationary stochastic processes $\mathbf{y}(t) \in \mathbb{R}^{n_y}$, and $\mathbf{u}(t) \in \mathbb{R}^{n_u}$, that share a time axis $t \in \mathbb{Z}$, that is, for any $t \in \mathbb{Z}$, $\mathbf{y}(t) : \Omega \rightarrow \mathbb{R}^{n_y}; \omega \mapsto \mathbf{y}(t)(\omega)$, and $\mathbf{u}(t) : \Omega \rightarrow \mathbb{R}^{n_u}; \omega \mapsto \mathbf{u}(t)(\omega)$ are random vectors on $(\Omega, \mathcal{F}, \mathbf{P})$: $\mathbf{y}$ represents outputs (labels), and $\mathbf{u}$ represents inputs (features). The goal is to learn models from the finite sample $\mathcal{D} = \{\mathbf{y}(t)(\omega), \mathbf{u}(t)(\omega)\}_{t=0}^{N-1}, \omega \in \Omega$, such that the learned model predicts $\mathbf{y}$ from past measurements of $(\mathbf{y}, \mathbf{u})$ sufficiently well.

Predictor class: To simplify notation, let us define a stochastic process $\mathbf{w}(t) \in \mathbb{R}^{n_w}$ by

$$\begin{aligned} \mathbf{w}(t) &= [\mathbf{y}^T(t), \mathbf{u}^T(t)]^T \text{ when } n_w = n_y + n_u \text{ and both past } \mathbf{y} \text{ and } \mathbf{u} \text{ are used for prediction,} \\ \mathbf{w}(t) &= \mathbf{u}(t) \text{ when } n_w = n_u, \text{ when only past } \mathbf{u} \text{ is used for prediction.} \end{aligned}$$

Note that with a trivial extension of the results of this paper one can define $\mathbf{w}(t)$ to consist of only some of the components of $\mathbf{y}(t)$, extending the results to not only prediction but also filtering.

Assumption 2.1 (Predictors). *The class of predictors is the class of LTI systems parametrized by $\theta \in \Theta \subseteq \mathbb{R}^{n_\theta}$ which generate predictions $\hat{\mathbf{y}}_\theta(t|t_0)$ of $\mathbf{y}(t)$ based on $\{\mathbf{w}(s)\}_{s=t_0}^t$*

$$\hat{\mathbf{x}}(t+1) = \hat{A}_\theta \hat{\mathbf{x}}(t) + \hat{B}_\theta \mathbf{w}(t), \quad \hat{\mathbf{x}}(t_0) = 0, \quad \hat{\mathbf{y}}_\theta(t|t_0) = \hat{C}_\theta \hat{\mathbf{x}}(t) + \hat{D}_\theta \mathbf{w}(t), \quad t \geq t_0, \quad (1)$$

where $\hat{A}_\theta, \hat{B}_\theta, \hat{C}_\theta, \hat{D}_\theta$ are $\hat{n} \times \hat{n}$, $\hat{n} \times n_w$, $n_y \times \hat{n}$ and $n_y \times n_w$ matrices respectively, they are continuous in θ , and $\hat{A}_\theta$ is Schur (all its eigenvalues are inside the unit disk). Moreover, if $\mathbf{w}(t) = [\mathbf{y}^T(t) \mathbf{u}^T(t)]^T$, then $\hat{D}_\theta = [0 \hat{D}_{u,\theta}]$ for some $n_y \times n_u$ matrix $\hat{D}_{u,\theta}$.¹ Moreover, there exist constants $M, C > 0, \gamma \in (0, 1)$ such that for all $\theta \in \Theta$, $\|\hat{A}_\theta\|_2 \leq M\gamma^k$, $\max\{\|\hat{B}_\theta\|_2, \|\hat{C}_\theta\|_2, \|\hat{D}_\theta\|_2\} \leq C$.

Intuitively, our assumption expresses that the predictors are stable LTIs and we have a uniform upper bound on the matrices and on the spectral radius of $\hat{A}_\theta$. These assumptions are standard in system identification, see Remark A.3, Appendix A. Note that the predictors are started at the zero initial state at initial time t_0 . The latter represents the time instant at which the predictor was applied to generate predictions, or when learning started. Most of the time, we will set $t_0 = 0$ to simplify notation.

Data generator: Intuitively, we would like the data $\mathbf{y}$ to be generated by an LTI system

$$\hat{\mathbf{s}}_g(t+1) = A_0 \hat{\mathbf{s}}_g(t) + B_0 \mathbf{u}(t) + K_0 \mathbf{e}^s(t), \quad \mathbf{y}(t) = C_0 \hat{\mathbf{s}}_g(t) + D_0 \mathbf{u}(t) + \mathbf{e}^s(t), \quad t \in \mathbb{Z}, \quad (2)$$

where A_0, B_0, K_0, C_0, D_0 are matrices of suitable dimension, A_0 and $A_0 - K_0 C_0$ are both Schur, and $\mathbf{e}^s(t)$ is a zero-mean i.i.d. sub-Gaussian process. The Schur conditions ensure stationarity of $\mathbf{x}$ and that $\mathbf{e}^s(t)$ is the innovation process (see [26, Chapter 4, p. 87]), i.e., the difference between $\mathbf{y}(t)$ and its best linear predictor based on past inputs and outputs. Thus, (2) is in steady-state Kalman filter form. Unlike predictors, the data generator (2) is assumed to operate in steady state, i.e., it has run for infinite time prior to prediction. This standard assumption in system identification (e.g., [26]) reflects that the physical system has been subject to noise and inputs long before learning begins. This subtle difference has significant theoretical implications.

Assuming the data is generated by a system of the same form as the predictors is a realizability assumption, as (2) yields the optimal predictor.

$$\hat{\mathbf{s}}_g(t+1 | t_0) = \hat{A}_0 \hat{\mathbf{s}}_g(t) + \hat{B}_0 \mathbf{w}(t), \quad \hat{\mathbf{s}}_g(t_0 | t_0) = 0, \quad \hat{\mathbf{y}}(t | t_0) = \hat{C}_0 \hat{\mathbf{s}}_g(t | t_0) + \hat{D}_0 \mathbf{w}(t), \quad (3)$$

¹The latter assumption is necessary, as it guarantees that $\hat{D}_\theta \mathbf{w}(t)$ depends only on $\mathbf{u}(t)$ and hence it does not depend on $\mathbf{y}(t)$, since otherwise we would be using $\mathbf{y}(t)$ to predict $\mathbf{y}(t)$, which is not meaningful.

where $t \geq t_0$, $\hat{A}_0 = A_0$, $\hat{B}_0 = B_0$, $\hat{C}_0 = C_0$, $\hat{D}_0 = D_0$ if $n_w = n_u$ and $\hat{A}_0 = A_0 - K_0 C_0$, $\hat{B}_0 = [K_0 \ B_0 - K_0 D_0]$, $\hat{C}_0 = C_0$, $\hat{D}_0 = [0 \ D_0]$ if $n_w = n_u + n_y$. When $\mathbf{w}(s) = [\mathbf{y}^T(s), \mathbf{u}^T(s)]^T$, the predictor (3) corresponds to stationary Kalman-filter and it is an optimal predictor of $\mathbf{y}(t)$ in the mean square error sense. Formally, instead of assuming the existence of (2), for the data generator we use the following assumption, which is essentially equivalent to the existence of (2).

Assumption 2.2. Let $\mathbf{y}(t)$ and $\mathbf{u}(t)$ be generated by an autonomous stochastic LTI system

$$\mathbf{x}(t+1) = A_g \mathbf{x}(t) + K_g \mathbf{e}_g(t), \quad \begin{bmatrix} \mathbf{y}(t) \\ \mathbf{u}(t) \end{bmatrix} = C_g \mathbf{x}(t) + \mathbf{e}_g(t) \quad (4)$$

with $A_g \in \mathbb{R}^{n \times n}$, $K_g \in \mathbb{R}^{n \times n_e}$, $C_g \in \mathbb{R}^{n_e \times n}$, for some $n > 0$, and $n_e = n_y + n_u \geq 2$, A_g and $A_g - K_g C_g$ are Schur. Moreover, $\mathbf{x}(t)$ has finite variance, $\mathbf{e}_g(t)$ is independent of $\mathbf{x}(t)$ for all $t \in \mathbb{Z}$, and $\mathbf{e}_g$ is square integrable, i.i.d process, $\|\mathbf{e}_g(t)\|_2$ is sub-Gaussian and the sub-Gaussian norm of $\|\mathbf{e}_g(t)\|_2$ [43, Definition 2.6.4] is denoted by $\|\mathbf{e}_g\|_{\psi_2}$.

If $\mathbf{e}_g(t)$ is sub-Gaussian, then $\|\mathbf{e}_g(t)\|_2$ is also sub-Gaussian, see [21, Lemma 1]. Under Assumption 2.2, $\mathbf{y}$ and $\mathbf{u}$ are jointly stationary and square integrable processes [4]. Under mild conditions, Assumption 2.2 is equivalent to the existence of an LTI system (2), see Remark A.2 in Appendix A. Assumption 2.2 is more convenient, and it is often used in system identification [22, Chapter 9].

Measure of prediction accuracy: Following standard practice in system identification [26], we measure the predictive accuracy using a *loss function* $\ell : \mathbb{R}^{n_y} \times \mathbb{R}^{n_y} \rightarrow [0, \infty)$ which is continuous and satisfies $\ell(y, y) = 0$. Typical choices are $\ell(y, \hat{y}) = \|y - \hat{y}\|_2$, to which we refer to as ℓ_2 loss, and $\ell(y, \hat{y}) = \|y - \hat{y}\|_2^2$ to which we refer to as the *quadratic loss*.

Assumption 2.3 (Quadratic or Lipschitz loss functions). *The loss function ℓ is either quadratic or it is L_ℓ -Lipschitz, i.e., for all $y_1, y_2, \hat{y}_1, \hat{y}_2 \in \mathbb{R}^{n_y}$, $|\ell(y_1, \hat{y}_1) - \ell(y_2, \hat{y}_2)| \leq L_\ell(\|y_1 - y_2\|_2 + \|\hat{y}_1 - \hat{y}_2\|_2)$.*

We define the *true error* as the limit

$$\mathcal{L}(\theta) \triangleq \lim_{t_0 \rightarrow -\infty} \mathbf{E}[\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t | t_0))]. \quad (5)$$

The true error captures the long-term, steady-state prediction error obtained during the deployment of the predictor on an increasing number of past inputs.

Lemma 2.4. *Let Assumptions 2.2, 2.1, and 2.3 hold. Then the limits $\hat{\mathbf{y}}_\theta(t) = \lim_{t_0 \rightarrow -\infty} \hat{\mathbf{y}}_\theta(t | t_0)$ and $\lim_{t \rightarrow \infty} (\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t | 0)) = 0$ exist in the mean-square sense for all t and θ , the process $\hat{\mathbf{y}}_\theta(t)$ is stationary, and $\mathcal{L}(\theta) = \mathbf{E}[\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t))] = \lim_{t \rightarrow \infty} \mathbf{E}[\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t | 0))]$.*

The proof of Lemma 2.4 is presented in Appendix A. Intuitively, $\hat{\mathbf{y}}_\theta(t)$ is the output predicted by the LTI system corresponding to θ , if the latter is started from zero at $-\infty$, and as t grows, $\hat{\mathbf{y}}_\theta(t)$ and $\hat{\mathbf{y}}_\theta(t | 0)$ converge to each other.

The Learning Problem is to find a parameter θ_* from sampled data $\mathcal{D}$ of the sequence of random variables $\{\mathbf{y}(t), \mathbf{u}(t)\}_{t=0}^{N-1}$ which minimizes the true error, i.e., $\theta_* \in \arg \min \mathcal{L}(\theta)$. Note that we do not assume the knowledge of the matrices A_g, K_g, C_g and noise process $\mathbf{e}_g$ when learning.

Since the true error is unknown, a standard practice is to use the *empirical error*

$$\hat{\mathcal{L}}_N(\theta) = \frac{1}{N} \sum_{t=0}^{N-1} \ell(\mathbf{y}(t)(\omega), \hat{\mathbf{y}}_\theta(t|0)(\omega)) \quad (6)$$

as a proxy for the true error, and try to find a model $\hat{\theta}$ for which the empirical error $\hat{\mathcal{L}}_N(\hat{\theta})$ is small. While doing so, we would like to keep the *generalization gap* $\mathcal{L}(\theta) - \hat{\mathcal{L}}_N(\theta)$, i.e., the difference between a model's performance on the training data (empirical error) and its expected performance (true error) on unseen test data, small. The PAC-Bayesian approach provides a framework to derive such guarantees.

2.3 Constants used in PAC-bounds

In order to present the main result, we will need several constants, many of which have an interesting system-theoretic interpretation.

Definition 2.5 (Convolution and ℓ_1 norm). Let $\alpha = \{\alpha(k)\}_{k=0}^{\infty}$ be a sequence of matrices. Define the ℓ_1 norm $\|\alpha\|_{\ell_1}$ and the weakly dependent mixing coefficient (WDMC) $\theta_{\infty}(\alpha)$ of α as

$$\|\alpha\|_{\ell_1} = \sum_{k=0}^{\infty} \|\alpha(k)\|_2, \quad \theta_{\infty}(\alpha) = \sum_{k=0}^{\infty} k \|\alpha(k)\|_2.$$

If $\|\alpha\|_{\ell_1} < \infty$ and $\mathbf{r}$ is a stationary square integrable stochastic process, then define the convolution $(\alpha \star \mathbf{r})$ of α with $\mathbf{r}$ as the stochastic process $(\alpha \star \mathbf{r})(t) = \sum_{k=0}^{\infty} \alpha(k) \mathbf{r}(t-k)$. By [4, Theorem 1.1], $(\alpha \star \mathbf{r})$ is well-defined and stationary.

Intuitively, the ℓ_1 norm of a sequence is the extension of the standard norm on the space of absolutely summable scalar sequences to the case of matrix valued ones. The convolution $(\alpha \star \mathbf{r})$ represents the response of a linear filter with impulse response α to the noise $\mathbf{r}$, and $\|\alpha\|_{\ell_1}$ represents the ℓ_1 norm of the filter. If $\mathbf{r}$ is bounded, i.e., $\|\mathbf{r}(t)\|_2 < C$, then the convolution $(\alpha \star \mathbf{r})(t)$ is bounded, i.e., $\|(\alpha \star \mathbf{r})\|_2 < \|\alpha\|_{\ell_1} C$, and it is a weakly dependent process, in the sense of [3], whose mixing coefficients $\{\theta_{\infty,n}(1)\}_{n=1}^{\infty}$ are bounded by $2\theta_{\infty}(\alpha)C$, [3, Proposition 4.12]. Intuitively, the smaller $\theta_{\infty}(\alpha)$ is, the closer $(\alpha \star \mathbf{r})(t)$ is to being i.i.d., if $\mathbf{r}$ is i.i.d. If α is the sequence of Markov parameters of a stable LTI system, then both $\|\alpha\|_{\ell_1}$ and $\theta_{\infty}(\alpha)$ are finite and can be upper bounded in terms of bounds on the norms of the system matrices and the spectral radius of the system matrix A , see Remark B.1.

Definition 2.6 (Auxiliary definitions). Let us consider the Markov-parameters α_g and α_{θ} of the data generator (4) and predictor (1) corresponding to $\theta \in \Theta$ respectively:

$$\alpha_g(k) = \begin{cases} C_g A_g^{k-1} K_g & k > 0 \\ I & k = 0 \end{cases}, \quad \alpha_{\theta}(k) = \begin{cases} \hat{C}_{\theta} \hat{A}_{\theta}^{k-1} \hat{B}_{\theta} & k > 0 \\ \hat{D}_{\theta} & k = 0 \end{cases} \quad (7)$$

Let $\bar{\alpha}(k) = \sup_{\theta \in \Theta} \|\alpha_{\theta}(k)\|_2$. With notation as above

$$\begin{aligned} G_e(\theta) &\triangleq (1 + \|\alpha_{\theta}\|_{\ell_1}) \|\alpha_g\|_{\ell_1}, & G_{e,1}(\theta) &\triangleq \theta_{\infty}(\alpha_{\theta}) \|\alpha\|_{\ell_1} + \theta_{\infty}(\alpha_g) (\|\alpha_{\theta}\|_{\ell_1} + 1) \\ G_e &\triangleq (1 + \|\bar{\alpha}\|_{\ell_1}) \|\alpha_g\|_{\ell_1}, & G_{e,1} &\triangleq \theta_{\infty}(\bar{\alpha}) \|\alpha_g\|_{\ell_1} + \theta_{\infty}(\alpha_g) (\|\bar{\alpha}\|_{\ell_1} + 1) \end{aligned}$$

For the definition of the upcoming bounds, we are going to use the quantities $\|\alpha\|_{\ell_1}$, $\theta_{\infty}(\alpha)$ for $\alpha \in \{\alpha_g, \bar{\alpha}\} \cup \{\alpha_{\theta} \mid \theta \in \Theta\}$ and the constants $G_e(\theta)$, $G_{e,1}(\theta)$, G_e , $G_{e,1}$ defined above. Note that all these quantities are well-defined, see Lemma B.2. In addition, they are related to the true outputs $\mathbf{y}(t)$ and predicted outputs $\hat{\mathbf{y}}_{\theta}(t)$, $\hat{\mathbf{y}}_{\theta}(t \mid t_0)$ as follows: $[\mathbf{y}^T(t) \quad \mathbf{u}^T(t)]^T = (\alpha_g \star \mathbf{e}_g)(t)$, $\hat{\mathbf{y}}_{\theta}(t) = (\alpha_{\theta} \star \mathbf{w})(t)$, $\hat{\mathbf{y}}_{\theta}(t \mid t_0) = (\alpha_{\theta, t-t_0} \star \mathbf{w})(t)$. The formal relationship between the constants is provided in Lemma B.3, Appendix B. The interpretation of the various terms appearing in Definition 2.6 is as follows

- $\|\alpha_g\|_{\ell_1}$, $\theta_{\infty}(\alpha_g)$ are the ℓ_1 norm and the mixing coefficients of Markov-parameters of the data generator: both quantities decrease with stability of the data generator, see Remark B.1.
- $\|\alpha_{\theta}\|_{\ell_1}$ is the ℓ_1 norm of the predictor (1). This term decreases with the spectral radius of the predictor, see Remark B.1.
- $\theta_{\infty}(\alpha_{\theta})$ describes the mixing properties of the output generated by the predictor, and it also bounds the sum of differences between the infinite and finite past prediction $\sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_{\theta}(t) - \hat{\mathbf{y}}_{\theta}(t \mid 0)\|$. Intuitively, the smaller $\theta_{\infty}(\alpha_{\theta})$ is, the closer $\hat{\mathbf{y}}_{\theta}(t \mid 0)$ is to $\hat{\mathbf{y}}_{\theta}(t)$. This quantity decreases with the spectral radius of the predictor by Remark B.1.
- $G_{e,1}(\theta)$ characterizes mixing properties (short memory condition [1]) of the prediction error $\mathbf{y}(t) - \hat{\mathbf{y}}_{\theta}(t)$. Intuitively, the smaller $G_{e,1}(\theta)$ is, the more the prediction error behaves like an i.i.d process. This constant is related to stability of the generator and the predictor, the smaller the spectral radius of those systems are, the smaller this constant is.
- $\|\bar{\alpha}\|_{\ell_1}$, $\theta_{\infty}(\bar{\alpha})$, G_e , $G_{e,1}$ are uniform upper bounds on $\|\alpha_{\theta}\|_{\ell_1}$, $\theta_{\infty}(\alpha_{\theta})$, $G_e(\theta)$, $G_{e,1}(\theta)$ respectively.

3 Main result

We start by presenting the main result of the paper, which is the following theorem.

Theorem 3.1 (Main result). *Let Assumptions 2.2, 2.3 and 2.1 hold. For any a prior distribution π over Θ , confidence level $\delta \in (0, 0.5)$, integer $\epsilon \in \{-1, 1\}$, and $N \geq K_\delta$, the inequality*

$$\forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) \leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\text{KL}(\rho \| \pi) + \ln \frac{C_\delta}{\delta} + \frac{1}{2} \sum_{i=1}^2 \ln E_{\theta \sim \pi} \exp(C_i(2\lambda, \theta, N, \delta, \epsilon)) \right) \quad (8)$$

holds with probability at least $1 - 2\delta$ over data, with $\text{KL}(\rho \| \pi) = E_{\theta \sim \rho} \ln \frac{\rho(\theta)}{\pi(\theta)}$ the Kullback–Leibler divergence and the constants K_δ , $C_i(\lambda, \theta, N, \delta, \epsilon)$, $i = 1, 2$ and C_δ are defined as follows:

Bounded noise: *If $\|\mathbf{e}_g(t)\|_\infty \leq c_e$, then $C_\delta = 1$, $K_\delta = 2$, $\lambda > 0$, and*

$$\begin{aligned} C_i(\lambda, \theta, N, \delta, \epsilon) &\triangleq C_{b,i}(\lambda, \theta, L(\theta), c_e, N) \triangleq \frac{C_{m,b,i}(\lambda, \alpha_\theta, G_e(\theta) + 2G_{e,1}(\theta), L(\theta), c_e)}{N} \\ L(\theta) &\triangleq \begin{cases} 2G_e(\theta)c_e\sqrt{n_e} & \ell \text{ is quadratic loss} \\ L_\ell & \ell \text{ is } L_\ell\text{-Lipschitz} \end{cases} \\ C_{m,b,i}(\lambda, \alpha, X, L, c_e) &\triangleq \begin{cases} \lambda L c_e \sqrt{n_e} \theta_\infty(\alpha) \|\alpha_g\|_{\ell_1} & i = 1 \\ \lambda^2 \frac{L^2}{2} X(\sqrt{n_e} c_e)^2 & i = 2 \end{cases} \end{aligned}$$

Lipschitz loss: *If ℓ is L_ℓ -Lipschitz, then $C_\delta = 1$, $K_\delta = 2$, $0 < \lambda < \frac{N}{16L_\ell}$, and*

$$\begin{aligned} C_i(\lambda, \theta, N, \delta, \epsilon) &\triangleq C_{ub,i}(\lambda, \theta, L(\theta), N) \triangleq \frac{1}{2} C_{b,i} \left(2\lambda, \theta, L(\theta), \frac{2 \ln(N)}{\|\alpha_g\|_{\ell_1} K}, N \right) + \bar{C}_{ub}(\lambda, L(\theta), N) \\ \bar{C}_{ub}(\lambda, L(\theta), N) &\triangleq \frac{\lambda^2 32 L(\theta)^2 C_{u,1}}{N} + \frac{4\lambda L(\theta) C_{u,2} \ln(N)}{N} = \frac{\lambda^2 32 L_\ell^2 C_{u,1}}{N} + \frac{4\lambda L_\ell C_{u,2} \ln(N)}{N} \end{aligned}$$

where the constants, $K, C_{u,j}$, $j = 1, 2$ are defined as follows:

$$\begin{aligned} C_{u,1} &\triangleq \bar{\Psi}_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) + \bar{\Psi}_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}), \quad \bar{\Psi}_{\mathbf{e}_g}(s) = e^{14^2 s^2 \|\mathbf{e}_g\|_{\psi_2}^2 + 3s \|\mathbf{e}_g\|_{\psi_2}} \\ C_{u,2} &\triangleq \bar{\Psi}_{\mathbf{e}}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) \frac{\|\bar{\alpha}\|_{\ell_1}^2 \|\alpha_g\|_{\ell_1}}{K} + \bar{\Psi}_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \frac{\|\alpha_g\|_{\ell_1}}{K}, \quad K = \min\{1, \|\bar{\alpha}\|_{\ell_1}\} \end{aligned} \quad (9)$$

Quadratic loss: *if ℓ is the quadratic loss, then $C_\delta = \frac{2}{3}$, $K_\delta = 3$, $0 < \lambda < \frac{N}{16L_{qd}}$,*

$$C_i(\lambda, \theta, N, \delta, \epsilon) \triangleq \frac{\lambda L_{qd}^2 \max\{0, \epsilon\}}{2N} + C_{ub,i}(\lambda, \theta, L_{qd}, N), \quad L_{qd} = 12G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln \left(\frac{3N^2}{2\delta} \right)}$$

For $\epsilon = 1$, (8) bounds the average generalization gap $E_{\theta \sim \rho}(\mathcal{L}(\theta) - \hat{\mathcal{L}}_N(\theta))$; for $\epsilon = -1$, it bounds $E_{\theta \sim \rho}(\hat{\mathcal{L}}_N(\theta) - \mathcal{L}(\theta))$. The latter is useful for deriving oracle inequalities. By applying the union bound to both cases, we obtain a bound on $|E_{\theta \sim \rho}(\mathcal{L}(\theta) - \hat{\mathcal{L}}_N(\theta))|$. Note that except for the quadratic loss case with potentially unbounded data, $C_i(\lambda, \theta, N, \delta, \epsilon)$ is independent of δ and ϵ .

Intuition behind the proof: The proof of Theorem 3.1 is in Appendix C. The key idea is to decompose the generalization gap using an auxiliary empirical error $V_N(\theta) = \frac{1}{N} \sum_{t=0}^{N-1} \ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t))$ where the predictor has run for infinite time (started at $t_0 = -\infty$). Since $\mathbf{E}[V_N(\theta)] = \mathcal{L}(\theta)$, we have $\epsilon(\mathcal{L}(\theta) - \hat{\mathcal{L}}_N(\theta)) = \epsilon(\mathcal{L}(\theta) - V_N(\theta)) + \epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))$. The constants $\exp(C_1)$ and $\exp(C_2)$ bound the moment generating functions of these two differences. The PAC-Bayesian bound then follows by standard concentration arguments [2, Chapter 2].

Bounded case: C_1 is obtained by direct calculation, and C_2 via Rios's concentration inequality for weakly-dependent processes [1, Prop. 4.2], improving upon constants in [11, 8].

Unbounded case: We employ a truncation approach [3]. Define truncated data $\bar{\mathbf{y}}(t), \bar{\mathbf{u}}(t)$ generated from truncated noise $\bar{\mathbf{e}}_g(t) = \mathbf{e}_g(t) \chi(\|\mathbf{e}_g(t)\| \leq C)$ with $C = \frac{2 \ln(N)}{K \|\alpha_g\|_{\ell_1}}$, where $K = \min\{1, \|\bar{\alpha}\|_{\ell_1}\}$.

We bound the moment generating functions of the differences $\sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|$ and

$\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|$ by $\exp(\bar{\mathcal{C}}_{ub}(\lambda, L_\ell, N))$. Combining with the bounded-case bounds yields PAC-Bayesian guarantees for unbounded data.

Quadratic case: We show that with probability at least $1 - \frac{2\delta}{3}$ over data, the prediction errors satisfy $\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2 \leq C$ and $\|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2 \leq C$ for $C = 6G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln(\frac{3N^2}{2\delta})}$. The empirical quadratic loss then coincides with the empirical error for the truncated Lipschitz loss $\ell_C(y, y') = \min\{\|y - y'\|_2^2, C^2\}$. The result follows by union bound and the Lipschitz case, noting that the true error difference between the quadratic loss and the truncated loss is $O(C^2/N)$.

Interpretation and $O(\frac{\ln(N)^r}{N})$ rates: The interpretation of Theorem 3.1 is similar to other PAC-Bayesian bounds [2]: we view learning algorithms as choices of parameters from a data-dependent probability density on model parameters, referred to as *posterior* $\rho^{\mathcal{D}}$, for which the right-hand side of (8) is small for $\epsilon = 1$. One option is to choose $\rho^{\mathcal{D}}$ as the *Gibbs posterior* which minimizes the right-hand side of (8) and which is given by [2, Definition 2.1]:

$$\rho_{\text{Gibbs}} \triangleq \operatorname{argmin}_{\rho \in \mathcal{M}_\pi} \left(E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho \parallel \pi) \right), \quad \rho_{\text{Gibbs}}(\theta) = \frac{\pi(\theta) \exp(-\lambda \hat{\mathcal{L}}_N(\theta))}{E_{\theta \sim \pi} \exp(-\lambda \hat{\mathcal{L}}_N(\theta))},$$

Once a posterior $\rho^{\mathcal{D}}$ is obtained, the learned model θ_* can be chosen as follows:

Mean posterior (MEP): as the mean of the posterior $\rho^{\mathcal{D}}$, i.e. $\theta_* = E_{\theta \sim \rho^{\mathcal{D}}} \theta$,

Single draw: draw θ_* randomly from $\rho^{\mathcal{D}}$, and

Maximum posterior (MAP): choose θ_* as $\theta_* = \operatorname{argmax}_{\theta} \rho^{\mathcal{D}}(\theta)$. For $\rho^{\mathcal{D}} = \rho_{\text{Gibbs}}$, it minimizes the empirical error regularized using the prior, i.e., $\theta_* = \operatorname{argmin}_{\theta \in \Theta} \left(\hat{\mathcal{L}}_N(\theta) - \frac{1}{\lambda} \ln \pi(\theta) \right)$,

These choices represent well-known classes of system identification algorithms, such as regularized PEM, maximum likelihood estimation for state-space models, and Bayesian methods, see Remarks D.8, D.5, and D.6 in Appendix D.5.

Theorem 3.1 bounds the average generalization gap $E_{\theta \sim \rho} (\mathcal{L}(\theta) - \hat{\mathcal{L}}_N(\theta))$ by a sum of two terms: the KL divergence $\frac{1}{\lambda} \text{KL}(\rho \parallel \pi)$ between the posterior and the prior, and a complexity term $\mathcal{C}_i(2\lambda, \theta, N, \delta, \epsilon)$ that depends on the data and the prior. For bounded noise, $\mathcal{C}_i = O(1/N)$; for Lipschitz loss, $\mathcal{C}_i = O(\frac{\ln N}{N})$; and for quadratic loss, $\mathcal{C}_i = O(\frac{(\ln N)^3}{N})$. By choosing $\lambda = \frac{\sqrt{N}}{L(\ln N)^r}$ with appropriately selected L and r , and thus forcing $\frac{1}{\lambda} \text{KL}(\rho \parallel \pi)$ to tend to zero as $N \rightarrow \infty$, we obtain an $O\left(\frac{(\ln N)^r}{\sqrt{N}}\right)$:

Corollary 3.2 ($O((\ln(N))^r / \sqrt{N})$ bound). *With the notation and assumptions of Theorem 3.1,*

$$\forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) \leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho \parallel \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \quad (10)$$

holds with probability at least $1 - 2\delta$ over data, for any prior π , $\delta \in (0, 0.5)$, and for any $\epsilon \in \{-1, 1\}$, and $N \geq K_\delta$, where $\mathcal{C}(\delta, \epsilon)$, L , r are defined as follows.

Bounded noise: If $\|e_g(t)\|_\infty \leq c_e$, then $r \triangleq 0$, $L \triangleq 1$, and

$$\mathcal{C}(\delta, \epsilon) \triangleq \frac{1}{2} \sum_{i=1}^2 \mathcal{C}_{m,b,i}(2, \bar{\alpha}, G_e + 2G_{e,1}, L_b, c_e), \quad L_b \triangleq \begin{cases} 2G_e c_e \sqrt{n_e} & \ell \text{ is the quadratic loss} \\ L_\ell & \ell \text{ is } L_\ell\text{-Lipschitz} \end{cases}$$

Lipschitz loss: If ℓ is L_ℓ -Lipschitz, then $r \triangleq 1$, $L \triangleq 16L_\ell$, and

$$\mathcal{C}(\delta, \epsilon) \triangleq \bar{\mathcal{C}}_{ub} = \left(C_{u,1} + C_{u,2} + \frac{1}{2} \sum_{i=1}^2 \mathcal{C}_{m,b,i} \left(\frac{1}{4}, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K} \right) \right),$$

Quadratic loss: If ℓ is quadratic, then $L \triangleq 192G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{2} \sqrt{1 + \ln(\frac{3}{2\delta})}$, $r \triangleq 3/2$,

$$\mathcal{C}(\delta, \epsilon) \triangleq \frac{L \max\{0, \epsilon\}}{128} + C_{u,1} + C_{u,2} + \frac{1}{2} \sum_{i=1}^2 \mathcal{C}_{m,b,i} \left(\frac{1}{4}, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K} \right)$$

The proof of Corollary 3.2 follows by substituting $\lambda = \frac{\sqrt{N}}{L(\ln N)^r}$ into Theorem 3.1 and simplifying the resulting bounds (see Appendix C.4 for the proof). Note that while Corollary 3.2 makes the $O\left(\frac{(\ln N)^r}{\sqrt{N}}\right)$ rates explicit, Theorem 3.1 may give a tighter bound even for $\lambda = \frac{\sqrt{N}}{L(\ln N)^r}$ [2].

The previous results bound the average generalization gap with respect to a posterior $\rho^{\mathcal{D}}$. For practical learning, however, we are interested in the generalization gap for a specific choice of θ_* (e.g., MEP, MAP, or a single draw from $\rho^{\mathcal{D}}$). Below, we provide such bounds when $\rho^{\mathcal{D}}$ is the Gibbs posterior with $\lambda = \frac{\sqrt{N}}{L(\ln N)^r}$, where L, r are as in Corollary 3.2. This yields a generalization gap for θ_* of order $O\left(\frac{(\ln N)^{r+1}}{\sqrt{N}}\right)$. We now introduce the necessary assumptions for these results.

Assumption 3.3. *The following conditions are used in the sequel.*

(Opt) *An optimal model $\theta_{true} = \arg \min_{\theta \in \Theta} \mathcal{L}(\theta)$ exists.*

(LipModel) *The map $\theta \mapsto \alpha_\theta$ is L_α -Lipschitz w.r.t. to the $\|\cdot\|_{\ell_1}$ norm, i.e.,*

$$\|\alpha_{\theta_1} - \alpha_{\theta_2}\|_{\ell_1} \leq L_\alpha \|\theta_1 - \theta_2\|_2, \quad \forall \theta_1, \theta_2 \in \Theta.$$

(Gauss) $\Theta = \mathbb{R}^{n_\theta}$ and π is Gaussian $\mathcal{N}(\theta_m, P)$.

(Uni) Θ is compact and π is the uniform density on Θ .

(SConv) *The true error $\mathcal{L}(\theta)$ is smooth and strongly convex in θ and its Hessian is bounded from below $m_\Theta I \preceq \nabla_\theta^2 \mathcal{L}(\theta)$ for all $\theta \in \Theta$.*

(Real) *The predictor $\Sigma(\theta_{true})$ equals the predictor (3) corresponding to the data generator.*

(PE) *The spectral density $\Phi_{\mathbf{w}}$ of $\mathbf{w}$ satisfies $\Phi_{\mathbf{w}}(iz) \geq m_{\mathbf{w}} I$ for all $z \in [-\pi, \pi]$.*

Corollary 3.4. *Assume the following*

(1) *Assumptions 2.2, 2.1, 2.3 and **(Opt)** and **(LipModel)** of Assumption 3.3 hold, and*

(2) *either **(Gauss)** or **(Uni)** of Assumption 3.3 holds, and*

(3) *θ_* be selected from ρ_{Gibbs} using MEP, MAP or a single draw, and ρ_{Gibbs} is computed using $\lambda = \lambda_N = \frac{\sqrt{N}}{2L(\ln(N))^r}$ with r, L, K_δ are as defined in Corollary 3.2.*

(4) *Furthermore, if θ_* is chosen using MEP, then assume that **(SConv)** of Assumption 3.3 holds.*

Consider the constants $\mathcal{C}_{em}(\delta, \sigma)$, $\mathcal{C}_{or}(\delta, \sigma)$, $r_{\text{Lip},1}$, $r_{\text{Lip},2}$ as in Table 1, and consider the inequalities

$$\textbf{Empirical bound:} \quad \mathcal{L}(\theta_*) - \hat{\mathcal{L}}_N(\theta_*) \leq \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \mathcal{C}_{em}(\theta_*, \delta) \quad (11)$$

$$\textbf{Oracle bound:} \quad \mathcal{L}(\theta_*) - \mathcal{L}(\theta_{true}) \leq \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \mathcal{C}_{or}(\delta, \sigma) \quad (12)$$

$$\textbf{Parameter estimation error:} \quad \|\theta_* - \theta_{true}\|_2^2 \leq \frac{L(\ln(N))^{r+1}}{\sqrt{N} m_\Theta} \mathcal{C}_{or}(\delta, \sigma), \quad (13)$$

$$\textbf{H}_2 \textbf{ error bound:} \quad \|H_{\theta_{true}} - H_{\theta_*}\|_{H_2}^2 \leq \frac{L(\ln(N))^{r+1}}{m_{\mathbf{w}} \sqrt{N}} \mathcal{C}_{or}(\delta, \sigma) \quad (14)$$

*Then the following holds: **(A)** (11) holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$,*

(B) *(12) holds with probability at least $1 - 2\delta$ for single draw and MEP, and with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ for MAP,*

(C) *(13) holds with probability at least $1 - 2\delta$ for single draw and MEP, and with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ for MAP, if **(SConv)** of Assumption 3.3 holds,*

(D) *(14) holds with probability at least $1 - 2\delta$ for single draw and MEP, and with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ for MAP, if **(Real)** and **(PE)** of Assumption 3.3 holds, ℓ is the quadratic loss, and H_θ the transfer function of the predictor corresponding to θ , and denote by $\|H\|_{H_2}$ the H_2 norm of the transfer function H .*

Here, the probability is taken over data for MEP and MAP, and over the data and over all samples θ_ drawn from ρ_{Gibbs} for the single draw.*²

²The precise meaning of probability over data and samples drawn from ρ_{Gibbs} is explained in Remark D.1

Table 1: Constants for learning bounds under different algorithm choices (Corollary 3.4)

Constant	MEP / Single Draw	MAP
$L_\Theta(\delta)$	$\frac{L_\alpha L_\ell \ \alpha_g\ _{\ell_1}}{16} \sqrt{n_e} \frac{1}{K}$	bounded noise Lipschitz/quadratic
$C(\theta)$	$\frac{1}{2}(\sigma^2 \text{trace}(P^{-1}) - n_\theta + (\theta_m - \theta)^T P^{-1}(\theta_m - \theta) + \ln \frac{\det(P)}{\sigma^{2n_\theta}} + n_\theta)$	(Gauss) $\ln \frac{\text{vol}(\Theta)}{(\sqrt{\pi} \sigma^{2n_\theta} \Gamma(n_\theta/2+1))} + \frac{n_\theta}{2}$ (Uni)
$r_{\text{Lip},1}, r_{\text{Lip},2}$	$r_{\text{Lip},1} = \begin{cases} 0 & \mathbf{e}_g \text{ is bounded} \\ 1 & \text{otherwise} \end{cases}$	$r_{\text{Lip},2} = \begin{cases} 2 & \ell \text{ is quadratic and } \mathbf{e}_g \text{ is unbounded} \\ 0 & \text{otherwise} \end{cases}$
$\mathcal{C}_{L,\text{emp}}$	$L_\Theta(\delta)\sigma + 2r_{\text{Lip},1}(C_{u,1} + C_{u,2})$	
$\mathcal{C}_{L,\text{true}}$	$\mathcal{C}_{L,\text{emp}} + 2r_{\text{Lip},2} \frac{L}{512}$	
$\mathcal{C}_L(\delta, \epsilon)$	$\ln\left(\frac{C_\delta}{\delta}\right) + \mathcal{C}_{L,\text{emp}} + C(\theta_\star) + C(\delta, \epsilon)$	
$C_{em}(\theta_\star, \delta)$	$\mathcal{C}_L(\delta, 1) + 2r_{\text{Lip},1} \ln\left(\frac{1}{\delta}\right)$	$\mathcal{C}_L(\delta, 1) + \mathcal{C}_{L,\text{true}} + 2r_{\text{Lip},1} \ln\left(\frac{1}{\delta}\right)$
$C(\theta_{\text{true}}, \theta_\star)$	$\mathcal{C}_{L,\text{true}} - 2\mathcal{C}_{L,\text{emp}}$	$2\mathcal{C}_{L,\text{true}} - C(\theta_{\text{true}}) + C(\theta_\star) + \ln\left(\frac{\pi(\theta_{\text{true}})}{\pi(\theta_\star)}\right)$
$\mathcal{C}_{or}(\delta, \sigma)$	$C(\theta_{\text{true}}, \theta_\star) + \mathcal{C}_L(\frac{\delta}{2}, 1) + \mathcal{C}_L(\frac{\delta}{2}, -1)$	

In summary, for any outcome $\theta_\star$ obtained via MAP, MEP, or a single draw from the Gibbs posterior, Corollary 3.4 yields $O\left(\frac{(\ln N)^{r+1}}{\sqrt{N}}\right)$ bounds on: **(1)** the generalization gap (11), **(2)** the excess true error over the optimal model (12), and **(3)** the parameter estimation error (13)–(14). The constants for the learning bounds, as given by Corollary 3.4, are in Table 1. The influence of system properties and convergence rates is discussed in Section 4.

Intuition behind the proof: The proof of Corollary 3.4 is in Appendix D. For MAP, (11)–(12) are derived from Corollary 3.2 by constructing suitable data-dependent posteriors and applying oracle inequality techniques from [2, Theorem 4.1]. For single draw and MEP, similar arguments apply using [2, Theorems 2.7 and Corollary 2.6] combined with the moment generating function bounds from the proof of Theorem 3.1. Finally, the parameter estimation bounds (13)–(14) follow from the oracle inequality (12) by relating the parameter error to the loss difference through strong convexity (for (13)) or persistence of excitation (for (14)).

4 Discussion on the bound and conclusions

In this paper, we derived PAC-Bayesian error bounds for stochastic LTI systems with inputs and sub-Gaussian noise.

The convergence rates are fastest for bounded noise, slower for Lipschitz losses, and slowest for quadratic losses with general sub-Gaussian noise (see Table 2). All bounds in Theorem 3.1, Corollary 3.2, and Corollary 3.4 improve with increased system stability, lower sub-Gaussian noise norm, and depend logarithmically on the confidence level δ via $\ln(1/\delta)$.

Specifically, the bounds increase monotonically with the sub-Gaussian norm $\|\mathbf{e}_g\|_{\psi_2}$ of the noise, and with the ℓ_1 norms and mixing coefficients of the Markov parameters of both the predictors and the data generator ($\|\alpha_\theta\|_{\ell_1}$, $\|\alpha_g\|_{\ell_1}$, $\theta_\infty(\alpha_\theta)$, $\theta_\infty(\alpha_g)$). Smaller ℓ_1 norms and mixing coefficients correspond to more stable systems and weaker dependence on past inputs, making learning easier. Similarly, a smaller sub-Gaussian norm (i.e., lower noise variance) yields tighter bounds.

In summary, the bounds are tighter for less noisy and more stable systems, aligning with intuition: learning is easier when the system is less noisy and more stable.

Additionally, if the goal is to bound not only the generalization gap but also the parameter estimation error (in terms of the H_2 distance between the true and learned systems (14), or the Euclidean distance between parameters (13)), the bounds also depend on the *persistence of excitation* of the input $\mathbf{w}$ ($m_{\mathbf{w}}$) and the *identifiability* constant (m_Θ). Larger values of $m_{\mathbf{w}}$ (richer input) and m_Θ (greater separation between models) yield tighter bounds. The bound (14) can also be used to bound the system matrices (up to similarity), see Remark D.10, Appendix D.5.

For parameter estimation error, our obtained rate $O((\ln N)^{r+1}/\sqrt{N})$ is more conservative than classical asymptotic theory [26, 4] (which yields $O(1/\sqrt{N})$ asymptotic consistency) and existing

Table 2: Summary of convergence rates for different noise and loss function types

Scenario	Empirical PAC-Bayesian Bound	PAC/Oracle/parameter est./ H_2 bounds
Bounded noise	$O\left(\frac{1}{\sqrt{N}}\right)$	$O\left(\frac{\ln(N)}{\sqrt{N}}\right)$
Lipschitz loss	$O\left(\frac{\ln(N)}{\sqrt{N}}\right)$	$O\left(\frac{(\ln(N))^2}{\sqrt{N}}\right)$
Quadratic loss	$O\left(\frac{(\ln(N))^{3/2}}{\sqrt{N}}\right)$	$O\left(\frac{(\ln(N))^{5/2}}{\sqrt{N}}\right)$

finite-sample bounds [32, 24, 39, 42](which achieve $O(\ln N/\sqrt{N})$). However, this is the expected price for generality: our bound applies to a broad class of learning algorithms, provides non-asymptotic guarantees with high probability, and simultaneously bounds the generalization gap (properties not offered by prior results). In addition, most existing finite-sample bounds are algorithm-specific (e.g., for least-squares only) and do not address the generalization gap.

References

- [1] P. Alquier, X Li, and O. Wintenberger. Prediction of time series by statistical learning: general losses and fast rates. *Dependence Modeling*, 1(2013):65–93, 2013.
- [2] Pierre Alquier. User-friendly introduction to PAC-bayes bounds. *arXiv:2110.11216*, 2021.
- [3] Pierre Alquier and Olivier Wintenberger. Model selection for weakly dependent time series forecasting. *Bernoulli*, 18(3):883 – 913, 2012.
- [4] P. E. Caines. *Linear Stochastic Systems*. John Wiley and Sons, 1988.
- [5] Marco C Campi and Erik Weyer. Finite sample properties of system identification methods. *IEEE Transactions on Automatic Control*, 47(8):1329–1334, 2002.
- [6] Minshuo Chen, Xingguo Li, and Tuo Zhao. On generalization bounds of a family of recurrent neural networks. In *Proceedings of AISTATS 2020*, volume 108 of *PMLR*, pages 1233–1243, 8 2020.
- [7] G. K. Dziugaite and D. M. Roy. Computing nonvacuous generalization bounds for deep (stochastic) neural networks with many more parameters than training data. In *UAI*. AUAI Press, 2017.
- [8] Deividas Eringis, John Leth, Zheng-Hua Tan, Rafael Wisniewski, and Mihaly Petreczky. PAC-bayesian bounds for learning lti-ss systems with input from empirical loss. *arXiv:2303.16816*, 2023.
- [9] Deividas Eringis, John Leth, Zheng-Hua Tan, Rafal Wisniewski, Alireza Fakhrizadeh Esfahani, and Mihaly Petreczky. PAC-Bayesian theory for stochastic LTI systems. In *2021 60th IEEE Conference on Decision and Control (CDC)*, pages 6626–6633, 2021.
- [10] Deividas Eringis, John Leth, Zheng Hua Tan, Rafal Wisniewski, and Mihaly Petreczky. Explicit construction of the minimum error variance estimator for stochastic LTI-ss systems. *Automatica*, 153, July 2023.
- [11] Deividas Eringis, John Leth, Zheng-Hua Tan, Rafal Wisniewski, and Mihaly Petreczky. PAC-Bayes Generalisation Bounds for Dynamical Systems Including Stable RNNs. In *Proceedings of the 38th AAAI Conference on Artificial Intelligence*, number 11, pages 11901–11909, March 2024.
- [12] Deividas Eringis, John Leth, Zheng-Hua Tan, Rafal Wisniewski, and Mihály Petreczky. PAC-Bayesian Error Bound, via Rényi Divergence, for a Class of Linear Time-Invariant State-Space Models. In *41st International Conference on Machine Learning*, volume 235, pages 12560–12587, Vienne, Austria, July 2024. PMLR.

- [13] Herbert Federer. *Geometric Measure Theory*. Classics in Mathematics. Springer Berlin Heidelberg, Berlin, Heidelberg, 1 edition, 1996. eBook ISBN: 978-3-642-62010-2. Originally published as volume 153 in the series Grundlehren der mathematischen Wissenschaften. IV, 677 pages. Springer-Verlag Berlin Heidelberg, 1996.
- [14] Dylan Foster and Max Simchowitz. Logarithmic regret for adversarial online control. In *Proceedings of the 37th ICML*, volume 119 of *PMLR*, page 3211–3221. PMLR, 7 2020.
- [15] P. Germain, F. Bach, A. Lacoste, and S. Lacoste-Julien. PAC-bayesian theory meets bayesian inference. In *NIPS*, pages 1876–1884, 2016.
- [16] I. I. Gikhman and A. V. Skorokhod. *Introduction to the Theory of Random Processes*. Dover, 1st edition, 1996.
- [17] B. Guedj. A Primer on PAC-Bayesian Learning. *arXiv:1901.05353*, 2019.
- [18] B. Hanzon. On the differentiable manifold of fixed order stable linear systems. *Systems & Control Letters*, 13(4):345–352, 1989.
- [19] Elad Hazan, Holden Lee, Karan Singh, Cyril Zhang, and Yi Zhang. Spectral filtering for general linear dynamical systems. In *Advances in Neural Information Processing Systems*, volume 31. Curran Associates, Inc., 2018.
- [20] Jiabao He, Ingvar Ziemann, Cristian R. Rojas, S. Joe Qin, and Håkan Hjalmarsson. Finite sample analysis of open-loop subspace identification methods. *IEEE Transactions on Automatic Control*, pages 1–16, 2026.
- [21] Chi Jin, Praneeth Netrapalli, Rong Ge, Sham M. Kakade, and Michael I. Jordan. A short note on concentration inequalities for random vectors with subgaussian norm, 2019.
- [22] Tohru Katayama. *Subspace methods for system identification*. Communications and control engineering. Springer, Berlin, London, 2005.
- [23] Pascal Koiran and Eduardo D. Sontag. Vapnik-chervonenkis dimension of recurrent neural networks. *Discrete Applied Mathematics*, 86(1):63–79, 1998.
- [24] Sahin Lale, Kamyar Azizzadenesheli, Babak Hassibi, and Anima Anandkumar. Logarithmic regret bound in partially observable linear dynamical systems. *Advances in Neural Information Processing Systems*, 33:20876–20888, 2020.
- [25] A. Lindquist and G. Picci. *Linear Stochastic Systems: A Geometric Approach to Modeling, Estimation and Identification*. Springer, 2015.
- [26] L. Ljung. *System Identification: Theory for the user (2nd Ed.)*. PTR Prentice Hall., Upper Saddle River, USA, 1999.
- [27] Louis Massucci, Fabien Lauer, and Marion Gilson. A statistical learning perspective on switched linear system identification. *Automatica*, 145:110532, 2022.
- [28] Tomas McKelvey, Anders Helmersson, and Thomas Ribarits. Data driven local coordinates for multivariable linear systems and their application to system identification. *Autom.*, 40(9):1629–1635, 2004.
- [29] Abdelkader Metakalard, Fabien Lauer, Kevin Colin, and Marion Gilson. Uniform error bounds for quantized dynamical models. *IFAC Journal of Systems and Control*, 35:100373, 2026.
- [30] Yurii Nesterov. *Introductory Lectures on Convex Optimization: A Basic Course*, volume 87. Springer Science & Business Media, 2004.
- [31] Brett Ninness and Soren Henriksen. Bayesian system identification via markov chain monte carlo techniques. *Automatica*, 46(1):40–51, 2010.
- [32] Samet Oymak and Necmiye Ozay. Revisiting ho–kalman-based system identification: Robustness and finite-sample analysis. *IEEE Transactions on Automatic Control*, 67(4):1914–1928, 4 2022.

- [33] R. L. M. Peeters. *System Identification Based on Riemannian Geometry: Theory and Algorithms*. PhD thesis, Free University, Amsterdam, 1994.
- [34] Gianluigi Pillonetto, Tianshi Chen, Alessandro Chiuso, Giuseppe De Nicolao, and Lennart Ljung. *Regularized system identification: Learning dynamic models from data*. Springer Nature, 2022.
- [35] Tuhin Sarkar, Alexander Rakhlin, and Munther A. Dahleh. Finite time LTI system identification. *J. Mach. Learn. Res.*, 22:26:1–26:61, 2021.
- [36] S. Shalev-Shwartz and S. Ben-David. *Understanding machine learning: From theory to algorithms*. Cambridge university press, 2014.
- [37] Max Simchowitz. *Statistical Complexity and Regret in Linear Control*. University of California, Berkeley, 2021.
- [38] Max Simchowitz, Ross Boczar, and Benjamin Recht. Learning linear dynamical systems with semi-parametric least squares. In *Conference on Learning Theory*, pages 2714–2802. PMLR, 2019.
- [39] Max Simchowitz and Dylan Foster. Naive exploration is optimal for online lqr. In *Proceedings of the 37th ICML*, volume 119 of *PMLR*, page 8937–8948. PMLR, 7 2020.
- [40] David J. Smith and Mavina K. Vamanamurthy. How small is a unit ball? *Mathematics Magazine*, 62(2):101–107, 1989.
- [41] Eduardo D Sontag. A learning result for continuous-time recurrent neural networks. *Systems & control letters*, 34(3):151–158, 1998.
- [42] A. Tsiamis, I. Ziemann, N. Matni, and G. J. Pappas. Statistical learning theory for control: A finite-sample perspective. *IEEE Control Systems Magazine*, 43(6):67–97, 2023.
- [43] Roman Vershynin. *High-Dimensional Probability: An Introduction with Applications in Data Science*. Cambridge University Press, 2 edition, 2026.
- [44] Mathukumalli Vidyasagar and Rajeeva L Karandikar. A learning theory approach to system identification and stochastic adaptive control. *Probabilistic and randomized methods for design under uncertainty*, pages 265–302, 2006.

A Proofs of Section 2

Remark A.1 (LTI in innovation form). *Let us assume that $\mathbf{e}_g$ has zero mean. It follows that $\mathbf{e}_g(t)$ is the innovation process of $[\mathbf{y}^T(t) \ \mathbf{u}^T(t)]^T$ and (4) is in the so called (forward) innovation form, see [22, Section 8.5.2]. Intuitively, it means that $\mathbf{e}_g$ is the difference between $[\mathbf{y}^T(t) \ \mathbf{u}^T(t)]^T$ and its best linear prediction based on its own past values.*

Remark A.2 (Equivalence of (4) and (2)). *Let us assume that $\mathbf{e}_g$ and $\mathbf{e}_s$ are both zero mean. More precisely, if there is no feedback from $\mathbf{y}$ to $\mathbf{u}$ according to Definition 17.1.1. of [25], then (2) holds and by [10] the matrices A_0, B_0, C_0, K_0, D_0 can be computed from the matrices A_g, K_g, C_g .*

Conversely, if (2) holds and $\mathbf{u}(t)$ is generated by an ARMA process, and there is no feedback from $\mathbf{y}(t)$ to $\mathbf{u}(t)$, then Assumption 2.2 holds and A_g, K_g, C_g can be computed from those of (2) and the ARMA representation of $\mathbf{u}(t)$, again by reversing the equations from [10]. As a passing remark, if there is a feedback from $\mathbf{y}(t)$ to $\mathbf{u}(t)$ and $\mathbf{u}(t)$ is generated by an LTI systems driven by $\mathbf{y}(t)$, i.e.,

$$\mathbf{s}_u(t+1) = A_u \mathbf{s}_u(t) + K_u \mathbf{y}(t), \quad \mathbf{u}(t) = C_u \mathbf{s}_u(t) \quad (15)$$

then again the generator described in Assumption 2.2 can be obtained by adding (15) to (2).

Remark A.3 (Methods for stable parametrisations). *The construction of [33, Section 3.2.3] relies on canonical forms based on structure indices, to which the diffeomorphism from [18] between general and stable parametrisations are applied. Intuitively, the latter transformation maps (A, B, C, D) to $(\frac{A}{\mu}, B, C, D)$, where μ is the maximum of moduli of the eigenvalues of A . The construction of [28, Section 4.6] uses Ober's balanced canonical forms, and it relies on fixing the observability and controllability Grammians to being equal and diagonal. That is, stability is assured by using diagonal quadratic Lyapunov functions. In this case, by fixing upper bounds on the diagonals of the Grammians and on the norms of the system matrices occurring in the parameterisation, we ensure existence of constants M, C, γ mentioned in Assumption 2.1.*

Proof of Lemma 2.4. We have $\mathbf{y}_\theta(t|t_0) = \sum_{k=t_0}^{t-1} H_\theta(t-1-k) \mathbf{w}(k) + D_\theta \mathbf{w}(t) = \sum_{k=0}^{t-1-t_0} H_\theta(k) \mathbf{w}(t-1-k) + D_\theta \mathbf{w}(t)$ with the impulse response $H_\theta(k) \triangleq C_\theta A_\theta^k B_\theta$ for $k \geq 0$. Because A_θ is Schur, there exist $M > 0$ and $\rho \in (0, 1)$ such that $\|A_\theta^k\|_2 \leq M \rho^k$, hence $\sum_{k=s}^\infty \|H_\theta(k)\|_2 \leq \|C_\theta\|_2 \|B_\theta\|_2 M \frac{\rho^s}{1-\rho} \rightarrow 0$ as $s \rightarrow \infty$. For $t_1 < t_2 \leq t$ we get, using stationarity of $\mathbf{w}$ ($\sigma_{\mathbf{w}}^2 = \mathbf{E}\|\mathbf{w}(s)\|_2^2$) and setting $\beta = \rho^2$, that

$$\mathbf{E}[\|\mathbf{y}_\theta(t|t_2) - \mathbf{y}_\theta(t|t_1)\|_2^2] = \mathbf{E}\left[\left\|\sum_{m=t-t_2}^{t-1-t_1} H_\theta(m) \mathbf{w}(t-1-m)\right\|_2^2\right] \quad (16a)$$

$$\leq (t_2 - t_1) \mathbf{E}\left[\sum_{m=t-t_2}^{t-1-t_1} \|H_\theta(m)\|_2^2 \|\mathbf{w}(t-1-m)\|_2^2\right] \quad (16b)$$

$$\leq \sigma_{\mathbf{w}}^2 (\|C_\theta\|_2 \|B_\theta\|_2 M)^2 (t_2 - t_1) \sum_{m=t-t_2}^{t-1-t_1} \beta^m \quad (16c)$$

$$= \sigma_{\mathbf{w}}^2 (\|C_\theta\|_2 \|B_\theta\|_2 M)^2 \frac{\beta^t}{1-\beta} (t_2 - t_1) (\beta^{-t_2} - \beta^{-t_1}) \quad (16d)$$

Therefore $\{\mathbf{y}_\theta(t|t_0)\}_{t_0 \leq t}$ is Cauchy and hence converges in mean square to $\mathbf{y}_\theta(t) = \sum_{k=-\infty}^{t-1} H_\theta(t-1-k) \mathbf{w}(k) + D_\theta \mathbf{w}(t) = \sum_{k=0}^\infty H_\theta(k) \mathbf{w}(t-1-k) + D_\theta \mathbf{w}(t)$. This representation shows that $\mathbf{y}_\theta$ is the output of a causal, time-invariant, stable LTI filter (with impulse response $\{H_\theta(k)\}$ and feed-through D_θ) driven by the stationary input $\mathbf{w}$. Hence $\mathbf{y}_\theta$ is stationary, since stable LTI filtering preserves stationarity. Moreover, it follows that

$$\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0) = \sum_{k=t-t_0}^\infty H_\theta(k) \mathbf{w}(t-1-k). \quad (17)$$

so $\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|0) \rightarrow 0$ in mean square as $t \rightarrow \infty$ by arguments as in (16).

Finally, consider

$$|\mathbf{E}[\ell(\mathbf{y}(t), \mathbf{y}_\theta(t))] - \mathbf{E}[\ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))]| \leq \mathbf{E}[|\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))|] \quad (18)$$

If ℓ is L_ℓ -Lipschitz, then the right hand side of (18) is bounded by $L_\ell \mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2]$, and hence, as $\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0) \rightarrow 0$ in mean square as $t \rightarrow \infty$ or as $t_0 \rightarrow -\infty$, the right hand side of (18) also tends to 0, i.e.,

$$\mathbf{E}[|\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))|] \rightarrow 0.$$

as $t \rightarrow \infty$ or $t_0 \rightarrow -\infty$.

If ℓ is quadratic, then

$$\begin{aligned} |\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))| &= \left| \|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2^2 - \|\mathbf{y}(t) - \mathbf{y}_\theta(t|t_0)\|_2^2 \right| = \\ &= |2\mathbf{y}^T(t)(-\mathbf{y}_\theta(t) + \mathbf{y}_\theta(t|t_0)) + (\|\mathbf{y}_\theta(t)\|_2^2 - \|\mathbf{y}_\theta(t|t_0)\|_2^2)| \leq \\ &= 2\|\mathbf{y}^T(t)\|_2\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2 + \left| \|\mathbf{y}_\theta(t)\|_2^2 - \|\mathbf{y}_\theta(t|t_0)\|_2^2 \right| (\|\mathbf{y}_\theta(t)\|_2 + \|\mathbf{y}_\theta(t|t_0)\|_2) \end{aligned}$$

Hence, using the Cauchy-Schwartz inequality

$$\begin{aligned} \mathbf{E}[|\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))|] &\leq \\ 2\mathbf{E}[\|\mathbf{y}^T(t)\|_2\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2] + \mathbf{E}[\left| \|\mathbf{y}_\theta(t)\|_2^2 - \|\mathbf{y}_\theta(t|t_0)\|_2^2 \right| (\|\mathbf{y}_\theta(t)\|_2 + \|\mathbf{y}_\theta(t|t_0)\|_2)] &\leq \\ 2\sqrt{\mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2^2]}\sqrt{\mathbf{E}[\|\mathbf{y}(t)\|_2^2]} + & \\ \sqrt{\mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2^2]}\sqrt{(\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + 2\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2\|\mathbf{y}_\theta(t|t_0)\|_2] + \mathbf{E}[\|\mathbf{y}_\theta(t|t_0)\|_2^2])} & \end{aligned}$$

Note that $\mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2^2] \rightarrow 0$ as $t_0 \rightarrow -\infty$ or $t \rightarrow \infty$, since $\mathbf{y}_\theta(t|t_0) - \mathbf{y}_\theta(t|t_0) \rightarrow 0$ in the mean-square sense as $t_0 \rightarrow -\infty$ or $t \rightarrow \infty$. Moreover,

$$2\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2\|\mathbf{y}_\theta(t|t_0)\|_2] \leq \mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + \mathbf{E}[\|\mathbf{y}_\theta(t|t_0)\|_2^2],$$

and $\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2]$ is constant due to stationarity of $\mathbf{y}_\theta(t)$. Now for sufficiently large $t > T_\epsilon$ or $-t_0 > T_\epsilon$, $\mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2^2] < \epsilon^2$, and it follows that

$$\begin{aligned} \mathbf{E}[\|\mathbf{y}_\theta(t|t_0)\|_2^2] &\leq \mathbf{E}[(\|\mathbf{y}_\theta(t)\|_2 + \|\mathbf{y}_\theta(t|t_0) - \mathbf{y}_\theta(t)\|_2)^2] \\ &\leq 2(\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + \mathbf{E}[\|\mathbf{y}_\theta(t) - \mathbf{y}_\theta(t|t_0)\|_2^2]) < 2\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + 2\epsilon^2 \end{aligned}$$

Hence, it follows that for $t > T_\epsilon$ or $-t_0 > T_\epsilon$,

$$\sqrt{(\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + 2\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2\|\mathbf{y}_\theta(t|t_0)\|_2] + \mathbf{E}[\|\mathbf{y}_\theta(t|t_0)\|_2^2])} \leq \sqrt{6\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + 4\epsilon^2}$$

and $\sqrt{6\mathbf{E}[\|\mathbf{y}_\theta(t)\|_2^2] + 4\epsilon^2} = C$ does not depend on t . Hence, if $t > T_\epsilon$ or $-t_0 > T_\epsilon$, then

$$\mathbf{E}[|\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))|] \leq \epsilon(2\mathbf{E}[\|\mathbf{y}(t)\|_2^2] + C)$$

from which it follows that $\mathbf{E}[|\ell(\mathbf{y}(t), \mathbf{y}_\theta(t)) - \ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))|] \rightarrow 0$ as either $t_0 \rightarrow -\infty$ or $t \rightarrow \infty$.

That is, in all cases,

$$\lim_{t \rightarrow \infty} \mathbf{E}[\ell(\mathbf{y}(t), \mathbf{y}_\theta(t|0))] = \mathbf{E}[\ell(\mathbf{y}(t), \mathbf{y}_\theta(t))] = \lim_{t_0 \rightarrow -\infty} \mathbf{E}[\ell(\mathbf{y}(t), \mathbf{y}_\theta(t|t_0))] \quad (19)$$

proving the lemma since $\mathcal{L}(\theta)$ is the right hand side of (19) by definition. $\square$

B Proofs of Section 2.3

Remark B.1 (α as Markov-parameters). *If α is the sequence of Markov parameters of a stable deterministic LTI system determined by matrices (A, B, C, D) , i.e., $\alpha(0) = D$, $\alpha(k) = CA^{k-1}B$, $k \geq 1$, then the ℓ_1 norm $\|\alpha\|_{\ell_1}$ and the WDMC $\theta_\infty(\alpha)$ are both finite. In this case, $\|\alpha\|_{\ell_1}$ is the classical ℓ_1 norm of the underlying LTI system. Moreover, if $M > 0$, $\gamma \in [0, 1)$ are such that $\|A^k\|_2 < M\gamma^k$, then $\|\alpha\|_{\ell_1} \leq \|D\|_2 + M\|B\|_2\|C\|_2/(1-\gamma)$ and $\theta_\infty(\alpha) \leq \|D\| + \gamma M\|B\|_2\|C\|_2/(1-\gamma)^2$. In turn, such M always exist if A is a Schur matrix, and γ can be chosen to be the spectral radius of A . In particular, $\|\alpha\|_{\ell_1}$, $\theta_\infty(\alpha)$ decrease as the spectral radius of A decreases.*

Finally, as promised before Lemma B.3, we can state that all the constants from Definition 2.6 are well-defined.

Lemma B.2. *If Assumption 2.2 and 2.1 hold, then the quantities $\|\alpha_\theta\|_{\ell_1}$ and $\theta_\infty(\alpha_\theta)$, $\|\bar{\alpha}\|_{\ell_1}$, $\theta_\infty(\bar{\alpha})$, $G_e(\theta)$, $G_{e,1}(\theta)$, G_e , $G_{e,1}$ are well defined real numbers.*

Proof. From Remark B.1 and the assumption that A_g is Schur it follows that $\|\alpha_g\|_{\ell_1}$ and $\theta_\infty(\alpha_g)$ are well-defined. By Assumption 2.1 there exists constants M, γ, C such that for all $\theta \in \Theta$, $\|A_\theta^k\|_2 \leq M\gamma^k$, $\|B_\theta\|_2 \leq C$, and $\|C_\theta\|_2 \leq C$. Therefore, $\bar{\alpha}(k) = \sup \|\alpha_\theta(k)\|_2 \leq M\gamma^k C^2$ and hence, by using the argument of Remark B.1, $\|\alpha_\theta\|_{\ell_1} \leq \sum_{k=0}^{\infty} \|\alpha\|_{\ell_1} \leq \sum_{k=0}^{\infty} \bar{\alpha}(k) = \|\bar{\alpha}\|_{\ell_1} \leq \frac{MC^2}{1-\gamma} < \infty$ and $\theta_\infty(\alpha_\theta) = \sum_{k=0}^{\infty} k \|\alpha_\theta(k)\|_2 \leq \sum_{k=0}^{\infty} k \bar{\alpha}(k) = \theta_\infty(\bar{\alpha}) \leq \frac{MC^2}{(1-\gamma)^2} < \infty$. Therefore, the quantities $\|\alpha_\theta\|_{\ell_1}$ and $\theta_\infty(\alpha_\theta)$, $\|\bar{\alpha}\|_{\ell_1}$, $\theta_\infty(\bar{\alpha})$ defining $G_e(\theta)$, $G_{e,1}(\theta)$, G_e , $G_{e,1}$ are well-defined, and hence so are $G_e(\theta)$, $G_{e,1}(\theta)$, G_e , $G_{e,1}$ $\square$

Lemma B.3. *Let $\alpha_{g,y}(k)$ and $\alpha_{g,w}(k)$ be the matrix formed by the first n_y and the last n_w rows of $\alpha_g(k)$ respectively, where n_w is the number of entries of $\mathbf{w}(t)$. Let $c_{\theta,s}(k) = \left(\sum_{l=0}^{\min\{k,s\}} \alpha_\theta(k) \alpha_{g,w}(k-l) \right)$ and $c_\theta(k) = \sum_{l=0}^k \alpha_\theta(k) \alpha_{g,w}(k-l)$.*

$$\begin{aligned} \begin{bmatrix} \mathbf{y}(t) \\ \hat{\mathbf{y}}_\theta(t) \end{bmatrix} &= \left(\begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \star \mathbf{e}_g \right)(t), \quad \begin{bmatrix} \mathbf{y}(t) \\ \hat{\mathbf{y}}_\theta(t | t_0) \end{bmatrix} = \left(\begin{bmatrix} \alpha_{g,y} \\ c_{\theta,t-t_0} \end{bmatrix} \star \mathbf{e}_g \right)(t), \\ \mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t) &= ((\alpha_{g,y} - c_\theta) \star \mathbf{e}_g)(t), \quad \mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t | t_0) = ((\alpha_{g,y} - c_{\theta,t-t_0}) \star \mathbf{e}_g)(t) \end{aligned} \quad (20)$$

Moreover, the constants from Definition 2.6 satisfy:

$$\max\{\|c_\theta\|_{\ell_1}, \|c_{\theta,s}\|_{\ell_1}\} \leq \|\alpha_\theta\|_{\ell_1} \|\alpha_g\|_{\ell_1}, \quad (21)$$

$$\max\left\{ \left\| \begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \right\|_{\ell_1}, \left\| \begin{bmatrix} \alpha_{g,y} \\ c_{\theta,t-t_0} \end{bmatrix} \right\|_{\ell_1}, \|\alpha_{g,y} - c_\theta\|_{\ell_1}, \|\alpha_{g,y} - c_{\theta,s}\|_{\ell_1} \right\} \leq G_e(\theta) \leq G_e \quad (22)$$

$$\max\left\{ \theta_\infty \left(\begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \right), \theta_\infty \left(\begin{bmatrix} \alpha_{g,y} \\ c_{\theta,t-t_0} \end{bmatrix} \right), \theta_\infty(\alpha_{g,y} - c_\theta), \theta_\infty(\alpha_{g,y} - c_{\theta,s}) \right\} \leq G_{e,1}(\theta) \quad (23)$$

$$\sum_{t=t_0}^{N+t_0} \|c_{\theta,t-t_0} - c_\theta\|_{\ell_1} \leq \theta_\infty(\alpha_\theta) \|\alpha_g\|_{\ell_1} \quad (24)$$

In particular, the two LTI filters in (20) are stationary.

Proof of Lemma B.3. Let C_w denote the matrix formed by the last n_w rows of C_g . From Assumption 2.2 and the proof of Lemma 2.4 we get that

$$\begin{aligned} \mathbf{w}(t) &= \sum_{k=1}^{\infty} C_w A_g^{k-1} K_g \mathbf{e}_g(t-k) + \mathbf{e}_g(t) = \sum_{k=0}^{\infty} \alpha_{g,w}(k) \mathbf{e}_g(t-k) = (\alpha_{g,w} \star \mathbf{e}_g)(t) \\ \mathbf{y}(t) &= \sum_{k=0}^{\infty} \alpha_{g,y}(k) \mathbf{e}_g(t-k) \\ \hat{\mathbf{y}}_\theta(t | t_0) &= \sum_{k=1}^{t-t_0} \hat{C}_\theta \hat{A}_\theta^{k-1} \hat{B}_\theta \mathbf{w}(t-k) + \hat{D}_\theta \mathbf{w}(t) = \sum_{k=0}^{t-t_0} \alpha_\theta(k) \mathbf{w}(t-k) \\ \hat{\mathbf{y}}_\theta(t) &= \lim_{t_0 \rightarrow -\infty} \hat{\mathbf{y}}_\theta(t | t_0) = \sum_{k=0}^{\infty} \alpha_\theta(k) \mathbf{w}(t-k) \end{aligned}$$

It then follows using the new index $n = k + j \geq 0$ and the standard argument involving Cauchy products of series,

$$\begin{aligned}\hat{\mathbf{y}}_\theta(t \mid t_0) &= \sum_{k=0}^{t-t_0} \alpha_\theta(k) \sum_{j=0}^{\infty} \alpha_{g,w}(j) \mathbf{e}_g(t-k-j) \\ &= \sum_{n=0}^{\infty} \left(\sum_{k=0}^{\min(n, t-t_0)} \alpha_\theta(k) \alpha_{g,w}(n-k) \right) \mathbf{e}_g(t-n) \\ &= \sum_{n=0}^{\infty} c_{\theta, t-t_0}(n) \mathbf{e}_g(t-n) = (c_{\theta, t-t_0} \star \mathbf{e}_g)(t)\end{aligned}$$

Notice that since A_g and A_θ are Schur, the series $\sum_{k=0}^{\infty} \alpha_\theta(k)$ and $\sum_{k=0}^{\infty} \alpha_{g,w}(k)$ are absolutely convergent. With a similar argument, using that absolutely convergent series can be rearranged, it follows that

$$\begin{aligned}\hat{\mathbf{y}}_\theta(t) &= \sum_{k=0}^{\infty} \alpha_\theta(k) \sum_{j=0}^{\infty} \alpha_{g,w}(j) \mathbf{e}_g(t-k-j) \\ &= \sum_{n=0}^{\infty} \left(\sum_{k=0}^n \alpha_\theta(k) \alpha_{g,w}(n-k) \right) \mathbf{e}_g(t-n) \\ &= \sum_{n=0}^{\infty} c_\theta(n) \mathbf{e}_g(t-n) = (c_\theta \star \mathbf{e}_g)(t)\end{aligned}$$

From this the first claim of the lemma, i.e., (20), follows. The first inequality of the second claim, i.e., (21), follows by first noticing that

$$\begin{aligned}\|c_\theta(k)\|_2 &\leq \sum_{i=0}^k \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2, \\ \|c_{\theta, t-t_0}(k)\|_2 &\leq \sum_{i=0}^{\min(k, t-t_0)} \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 \leq \sum_{i=0}^k \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2\end{aligned}$$

Since $\sum_{i=0}^k \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2$ is the k 'th coefficient of the Cauchy-product of $\sum_{k=0}^{\infty} \|\alpha_\theta(k)\|_2$ and $\sum_{k=0}^{\infty} \|\alpha_{g,w}(k)\|_2$, we obtain (21) by

$$\|c\|_{\ell_1} = \sum_{k=0}^{\infty} \|c(k)\|_2 \leq \sum_{i=0}^{\infty} \|\alpha_\theta(i)\|_2 \sum_{j=0}^{\infty} \|\alpha_{g,w}(j)\|_2 = \|\alpha_\theta\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1} \leq \|\alpha_\theta\|_{\ell_1} \|\alpha_g\|_{\ell_1} \quad (25)$$

with c denoting either c_θ or $c_{\theta, t-t_0}$. Concerning the second inequality (22), notice that

$$\left\| \begin{bmatrix} \alpha_{g,y}(k) \\ c_\theta(k) \end{bmatrix} \right\|_2 \leq \|\alpha_{g,y}(k)\|_2 + \|c_\theta(k)\|_2, \quad \|\alpha_{g,y}(k) - c_\theta(k)\|_2 \leq \|\alpha_{g,y}(k)\|_2 + \|c_\theta(k)\|_2 \quad (26a)$$

$$\left\| \begin{bmatrix} \alpha_{g,y}(k) \\ c_{\theta, t-t_0}(k) \end{bmatrix} \right\|_2 \leq \|\alpha_{g,y}(k)\|_2 + \|c_{\theta, t-t_0}(k)\|_2, \quad (26b)$$

$$\|\alpha_{g,y}(k) - c_{\theta, t-t_0}(k)\|_2 \leq \|\alpha_{g,y}(k)\|_2 + \|c_{\theta, t-t_0}(k)\|_2 \quad (26c)$$

and hence,

$$\max \left\{ \left\| \begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \right\|_{\ell_1}, \|\alpha_{g,y} - c_\theta\|_{\ell_1} \right\} \leq \|\alpha_{g,y}\|_{\ell_1} + \|c_\theta\|_{\ell_1} \quad (27a)$$

$$\max \left\{ \left\| \begin{bmatrix} \alpha_{g,y} \\ c_{\theta, t-t_0} \end{bmatrix} \right\|_{\ell_1}, \|\alpha_{g,y} - c_{\theta, t-t_0}\|_{\ell_1} \right\} \leq \|\alpha_{g,y}\|_{\ell_1} + \|c_{\theta, t-t_0}\|_{\ell_1} \quad (27b)$$

From (27) and (25), the inequality of (22) follows by using the definition of $G_e(\theta)$ and the fact that $\max\{\|\alpha_{g,y}\|_{\ell_1}, \|\alpha_{g,w}\|_{\ell_1}\} \leq \|\alpha_g\|_{\ell_1}$.

Concerning (23), notice that by definining $d_1(i) = i\|\alpha_\theta(i)\|_2$ and $d_2(i) = i\|\alpha_{g,w}(i)\|_2$,

$$\begin{aligned}
\theta_\infty(c_{\theta,t-t_0}) &= \sum_{k=0}^{\infty} k\|c_{\theta,t-t_0}(k)\|_2 \leq \sum_{k=0}^{\infty} k \sum_{i=0}^{\min(k,t-t_0)} \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 = \\
&\sum_{k=0}^{\infty} \sum_{i=0}^{\min(k,t-t_0)} i\|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 + \sum_{k=0}^{\infty} \sum_{i=0}^{\min(k,t-t_0)} (k-i)\|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 = \\
&\sum_{k=0}^{\infty} \sum_{i=0}^{\min(k,t-t_0)} d_1(i)\|\alpha_{g,w}(k-i)\|_2 + \sum_{k=0}^{\infty} \sum_{i=0}^{\min(k,t-t_0)} d_2(k-i)\|\alpha_\theta(i)\|_2 \leq \\
&\sum_{k=0}^{\infty} \sum_{i=0}^k d_1(i)\|\alpha_{g,w}(k-i)\|_2 + \sum_{k=0}^{\infty} \sum_{i=0}^k d_2(k-i)\|\alpha_\theta(i)\|_2
\end{aligned}$$

Similarly,

$$\begin{aligned}
\theta_\infty(c_\theta) &= \sum_{k=0}^{\infty} k\|c_\theta(k)\|_2 \leq \sum_{k=0}^{\infty} k \sum_{i=0}^k \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 = \\
&\sum_{k=0}^{\infty} \sum_{i=0}^k i\|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 + \sum_{k=0}^{\infty} \sum_{i=0}^k (k-i)\|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 = \\
&\sum_{k=0}^{\infty} \sum_{i=0}^k d_1(i)\|\alpha_{g,w}(k-i)\|_2 + \sum_{k=0}^{\infty} \sum_{i=0}^k d_2(k-i)\|\alpha_\theta(i)\|_2 \leq \\
&\left(\sum_{k=0}^{\infty} d_1(k)\right) \left(\sum_{k=0}^{\infty} \|\alpha_{g,w}(k)\|_2\right) + \left(\sum_{k=0}^{\infty} d_2(k)\right) \left(\sum_{k=0}^{\infty} \|\alpha_\theta(k)\|_2\right) = \\
&\theta_\infty(\alpha_\theta)\|\alpha_{g,w}\|_{\ell_1} + \theta_\infty(\alpha_{g,w})\|\alpha_\theta\|_{\ell_1} \leq \theta_\infty(\alpha_\theta)\|\alpha_g\|_{\ell_1} + \theta_\infty(\alpha_g)\|\alpha_\theta\|_{\ell_1}
\end{aligned}$$

In particular,

$$\max\{\theta_\infty(c_\theta), \theta_\infty(c_{\theta,t-t_0})\} \leq \theta_\infty(\alpha_\theta)\|\alpha_g\|_{\ell_1} + \theta_\infty(\alpha_g)\|\alpha_\theta\|_{\ell_1} \quad (28)$$

Moreover, using (26) it follows that

$$\begin{aligned}
&\max\left\{\theta_\infty\left(\begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix}\right), \theta_\infty\left(\begin{bmatrix} \alpha_{g,y} \\ c_{\theta,t-t_0} \end{bmatrix}\right), \theta_\infty(\alpha_{g,y} - c_\theta), \theta_\infty(\alpha_{g,y} - c_{\theta,t-t_0})\right\} \leq \\
&\theta_\infty(\alpha_{g,y}) + \max\{\theta_\infty(c_\theta), \theta_\infty(c_{\theta,t-t_0})\}
\end{aligned}$$

from which inequality (23) follows by using (28). Finally, notice that

$$c_\theta(k) - c_{\theta,t-t_0}(k) = \begin{cases} 0 & k \leq t - t_0 \\ \sum_{i=t-t_0+1}^k \alpha_\theta(i)\alpha_{g,w}(k-i) & k > t - t_0 \end{cases}$$

Hence, by setting $d_3(k) = \|\alpha_\theta(k+t-t_0+1)\|_2$

$$\begin{aligned}
\|c_\theta - c_{\theta,t-t_0}\|_{\ell_1} &= \sum_{k=t-t_0+1}^{\infty} \left\| \sum_{i=t-t_0+1}^k \alpha_\theta(i)\alpha_{g,w}(k-i) \right\|_2 \\
&\leq \sum_{k=t-t_0+1}^{\infty} \sum_{i=t-t_0}^k \|\alpha_\theta(i)\|_2 \|\alpha_{g,w}(k-i)\|_2 \\
&= \sum_{k=t-t_0+1}^{\infty} \sum_{i=0}^{k-(t-t_0+1)} d_3(i)\|\alpha_{g,w}(k-i-(t-t_0+1))\|_2 \\
&= \sum_{k=0}^{\infty} \sum_{i=0}^k d_3(i)\|\alpha_{g,w}(k-i)\|_2 = \left(\sum_{k=t-t_0+1}^{\infty} \|\alpha_\theta(k)\|_2\right) \cdot \|\alpha_{g,w}\|_{\ell_1}
\end{aligned}$$

By noticing that

$$\sum_{t=t_0}^{N+t_0} \sum_{k=t-t_0+1}^{\infty} \|\alpha_{\theta}(k)\|_2 \leq \sum_{k=1}^{\infty} \min\{k, N\} \|\alpha_{\theta}(k)\|_2 \leq \sum_{k=1}^{\infty} k \|\alpha_{\theta}(k)\|_2 = \theta_{\infty}(\alpha_{\theta})$$

the last inequality (24) follows. Finally, the stationarity of the two LTI filters is a consequence of the standard result that stable LTI filters maps stationary process to stationary process, see e.g., [16, Section 5.6]. $\square$

C Proof of Theorem 3.1

The proof of Theorem 3.1 is organized as follows. First, we define an auxiliary quantity called *the infinite past empirical error*

$$V_N(\theta) = \frac{1}{N} \sum_{t=0}^{N-1} \ell(\mathbf{y}(t), \hat{\mathbf{y}}_{\theta}(t))$$

It follows that $V_N(\theta)$ is an unbiased estimate of $\mathcal{L}(\theta)$, i.e., $\mathbf{E}[V_N(\theta)] = \mathcal{L}(\theta)$.

As the first step, we show the following general theorem.

Theorem C.1. *Given a parameter set Θ , a prior distribution π over Θ , $\delta \in [0, 0.5)$, $\lambda > 0$ and $\epsilon \in \{-1, 1\}$. Then with probability at least $1 - 2\delta$, the following holds*

$$\forall \rho \in \mathcal{M}_{\pi} : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) \leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \tilde{\mathbb{B}}_N(\rho, \pi, \lambda, \epsilon) \quad (29)$$

$$\tilde{\mathbb{B}}_N(\rho, \pi, \lambda, \epsilon) \triangleq \frac{1}{\lambda} \left(\text{KL}(\rho \parallel \pi) + \ln \frac{1}{\delta} + \Psi(\lambda, \pi, N, \epsilon) \right) \quad (30)$$

$$\begin{aligned} \Psi(\lambda, \pi, N, \epsilon) \triangleq & \frac{1}{2} \left(\ln E_{\theta \sim \pi} \mathbf{E}[e^{2\epsilon\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] \right. \\ & \left. + \ln E_{\theta \sim \pi} \mathbf{E}[e^{2\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}] \right), \end{aligned} \quad (31)$$

with $\text{KL}(\rho \parallel \pi) = E_{\theta \sim \rho} \ln \frac{\rho(\theta)}{\pi(\theta)}$ the Kullback–Leibler divergence.

In the theorem above, the moment generating functions $\mathbf{E}[e^{2\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}]$ and $\mathbf{E}[e^{2\epsilon\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ in the right-hand side are interpreted as ∞ whenever $2\epsilon\lambda$ falls outside of their domain of definition. In this case, $\Psi(\lambda, \pi, N, \epsilon)$ is taken to mean ∞ and the bounds are trivially true.

Proof of Theorem C.1. By [15, Theorem 3], for any measurable functions $X(\theta, \omega), Y(\theta, \omega)$, $\tilde{\lambda} > 0$, and $\epsilon \in \{-1, 1\}$, with probability at least $1 - \delta$ we have:

$$\forall \rho \in \mathcal{M}_{\pi} : E_{\theta \sim \rho} X(\theta, \omega) \leq E_{\theta \sim \rho} Y(\theta, \omega) + \frac{1}{\tilde{\lambda}} \left(\text{KL}(\rho \parallel \pi) + \ln \frac{1}{\delta} + \Psi_{X,Y}(\tilde{\lambda}) \right), \quad (32)$$

with $\Psi_{X,Y}(\tilde{\lambda}) = \ln E_{\theta \sim \pi} \mathbf{E}[e^{\tilde{\lambda}(X(\theta, \omega) - Y(\theta, \omega))}]$. Now apply the above theorem for $X = \epsilon \mathcal{L}(\theta)$, $Y = \epsilon V_N(\theta)$, and $X = \epsilon V_N(\theta)$, $Y = \epsilon \hat{\mathcal{L}}_N(\theta)$. Then by applying a union bound on the two obtained probabilistic inequalities, we obtain with probability at least $1 - 2\delta$

$$\begin{aligned} \forall \rho \in \mathcal{M}_{\pi} : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) & \leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) \\ & + \frac{1}{\tilde{\lambda}} \left(2\text{KL}(\rho \parallel \pi) + 2\ln \frac{1}{\delta} + \Psi_{\epsilon V_N, \epsilon \hat{\mathcal{L}}_N}(\tilde{\lambda}) + \Psi_{\epsilon \mathcal{L}, \epsilon V_N}(\tilde{\lambda}) \right) \end{aligned}$$

With some algebraic manipulation and $\tilde{\lambda} = 2\lambda$, we obtain the statement of the theorem. $\square$

For the case of bounded innovation noise or Lipschitz loss function, we then show that $\mathbf{E}[e^{2\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ and $\mathbf{E}[e^{2\lambda(\mathcal{L}(\theta) - V_N(\theta))}]$ can be both upper bounded by $\mathcal{C}_i(\theta, \lambda, N, \delta, \epsilon)$, from which the statement of the theorem follows. For the case of quadratic loss function, we will show that it can be reduced to the case of Lipschitz loss function with probability $\delta/3$ and then we apply the result for Lipschitz loss with $\delta/3$ instead of δ .

C.1 Proof of Theorem 3.1: bounded case

For the sake of readability, we repeat below the basic assumptions for the case of bounded data.

Assumption C.2 (Bounded noise and Lipschitz loss). *The innovation noise $\mathbf{e}_g(t)$ from (4) is essentially bounded, i.e.,*

$$\|\mathbf{e}_g(t)\|_\infty \leq c_e, \quad \forall t \in \mathbb{Z} \quad (33)$$

and the loss function ℓ is either L_ℓ -Lipschitz or quadratic.

The following Lemma is obvious in the L_ℓ -Lipschitz case, and follow by applying Cauchy-Schwarz in the quadratic case.

Lemma C.3. *Let $B = \{(z, z') \in \mathbb{R}^{n_y} \times \mathbb{R}^{n_y} \mid \|z - z'\|_2 \leq G_e(\theta)\sqrt{n_e}c_e\}$. Then $(\mathbf{y}(t), \mathbf{y}_\theta(t)), (\mathbf{y}(t), \mathbf{y}_\theta(t \mid 0)) \in B$ for all $t, t_0 \leq t$, and for all $(z_1, z_2), (z_3, z_4) \in B$,*

$$\ell(z_1, z_2) - \ell(z_3, z_4) \leq L(\theta) (\|z_1 - z_3\|_2 + \|z_2 - z_4\|_2)$$

where $L(\theta)$ is as in Theorem 3.1, i.e., $L(\theta) = 2G_e(\theta)\sqrt{n_e}c_e$ if ℓ -quadratic, and $L(\theta) = L_\ell$ if ℓ is L_ℓ -Lipschitz.

Remark C.4 (Norm loss L_ℓ -Lipschitz). *Note that if the loss ℓ is the p norm of the difference, i.e., $\ell(y, \hat{y}) = \|y - \hat{y}\|_p$, then $\ell(y, \hat{y}) \leq C_p \|y - \hat{y}\|_2$ with $C_p = \sqrt{n_y}$ if $p = 1$, and $C_p = 1$ if $p = \infty$ or $p = 2$.*

Lemma C.5. *Let assumptions 2.2, 2.1 and C.2 hold. Then*

$$\mathbf{E}[e^{(\epsilon\lambda|V_N(\theta) - \hat{\mathcal{L}}_N(\theta)|)}] \leq e^{(\frac{L(\theta)\lambda}{N}\theta_\infty(\alpha_\theta)\|\alpha_g\|_{\ell_1}(c_e\sqrt{n_e}))} = e^{C_{b,1}(\lambda, \theta, L(\theta), c_e, N)}$$

Proof C.5. Using the Lipschitz property of the loss function it follows that

$$\begin{aligned} \epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta)) &\leq |V_N(\theta) - \hat{\mathcal{L}}_N(\theta)| \leq \frac{1}{N} \sum_{t=0}^{N-1} |\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t)) - \ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t \mid 0))| \leq \\ &\frac{L(\theta)}{N} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t \mid 0)\|_2 \end{aligned} \quad (34)$$

From Lemma B.3 it follows that

$$\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t \mid 0) = ((c_\theta - c_{\theta,t}) \star \mathbf{e}_g)(t) = \sum_{k=0}^{\infty} (c_\theta - c_{\theta,t})(k) \mathbf{e}_g(t - k)$$

and hence

$$\sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t \mid 0)\|_2 \leq \sum_{t=0}^{N-1} \sum_{k=0}^{\infty} \|(c_\theta - c_{\theta,t})(k)\|_2 \|\mathbf{e}_g(t - k)\|_2 \leq \sum_{t=0}^{N-1} \|c_\theta - c_{\theta,t}\|_{\ell_1} \sqrt{n_e} c_e$$

From (24) it follows that

$$\sum_{t=0}^{N-1} \|c_\theta - c_{\theta,t}\|_{\ell_1} \leq \theta_\infty(\alpha_\theta) \|\alpha_g\|_{\ell_1}$$

and hence,

$$\sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t \mid 0)\|_2 \leq \theta_\infty(\alpha_\theta) \|\alpha_g\|_{\ell_1} \sqrt{n_e} c_e$$

from which the statement of the lemma follows using the definition of $\mathcal{C}_{b,1}(\lambda, \theta, L(\theta), c_e, N)$. $\square$

Lemma C.6. *Let assumptions 2.2, 2.1 and C.2 hold. Then*

$$\mathbf{E}[e^{\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}] \leq e^{\frac{(L(\theta))^2\lambda^2}{2N}(G_e(\theta) + 2G_{e,1}(\theta))(c_e\sqrt{n_e})^2} = e^{\mathcal{C}_{b,2}(\lambda, \theta, L(\theta), c_e, N)} \quad (35)$$

Proof of Lemma C.6. For each $\Sigma(\theta) \in \mathcal{F}$, consider $\mathbf{z}_t = [\mathbf{y}^T(t) \hat{\mathbf{y}}_\theta^T(t)]^T$. Then by Lemma B.3, $\mathbf{z}_t = \left(\begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \star \mathbf{e}_g \right)(t)$ and $\mathbf{z}_t$ is stationary. Moreover, as $\left\| \begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \right\|_{\ell_1} \leq G_e(\theta) < \infty$ and $\theta_\infty \left(\begin{bmatrix} \alpha_{g,y} \\ c_\theta \end{bmatrix} \right) \leq G_{e,1}(\theta) < \infty$, it follows that $\mathbf{z}_t$ is a Bernoulli-shift. In particular, $\|\mathbf{z}_t\|_\infty \leq G_e(\theta) c_e \sqrt{n_e}$, and by [1, Proposition 4.2] $\mathbf{z}_t$ is a weakly dependent process in the terminology of [1], with $\|\mathbf{z}_0\|_\infty \leq G_e(\theta) c_e \sqrt{n_e}$, and the mixing coefficient $\theta_{\infty,N}(1)$ of $\mathbf{z}_t$ satisfies $\theta_{\infty,N}(1) < 2G_{e,1}(\theta) c_e \sqrt{n_e}$.

If ℓ is L_ℓ -Lipschitz, then let $B = \mathbb{R}^{n_y} \times \mathbb{R}^{n_y}$. If ℓ is quadratic, then consider the set B from Lemma C.3. Define the function $h(z_0, z'_0, \dots, z_{N-1}, z'_{N-1}) = \epsilon \frac{1}{L(\theta)} \sum_{i=0}^{N-1} \ell(z_i, z'_i)$, $z_0, \dots, z_{N-1}, z'_0, \dots, z'_{N-1} \in \mathbb{R}^{n_y}$ on B^N . We claim that h has Lipschitz constant 1 in the following sense:

$$|h(z_0, z'_0, \dots, z_{N-1}, z'_{N-1}) - h(\tilde{z}_0, \tilde{z}'_0, \dots, \tilde{z}_{N-1}, \tilde{z}'_{N-1})| \leq \sum_{i=0}^{N-1} \|z_i - \tilde{z}_i\|_2 + \|z'_i - \tilde{z}'_i\|_2$$

Indeed, using Lemma C.3,

$$\begin{aligned} |h(z_0, z'_0, \dots, z_{N-1}, z'_{N-1}) - h(\tilde{z}_0, \tilde{z}'_0, \dots, \tilde{z}_{N-1}, \tilde{z}'_{N-1})| &= \left| \frac{\epsilon}{L(\theta)} \sum_{i=0}^{N-1} \ell(z_i, z'_i) - \ell(\tilde{z}_i, \tilde{z}'_i) \right| \\ &\leq \frac{1}{L(\theta)} \sum_{i=0}^{N-1} L(\theta) (\|z_i - \tilde{z}_i\|_2 + \|z'_i - \tilde{z}'_i\|_2) = \sum_{i=0}^{N-1} \|z_i - \tilde{z}_i\|_2 + \|z'_i - \tilde{z}'_i\|_2 \end{aligned}$$

If ℓ is L_ℓ -Lipschitz, then h is already defined on $(\mathbb{R}^{n_y} \times \mathbb{R}^{n_y})^N$. If ℓ is quadratic, we can use Kirszbraun's theorem for scalar valued functions [13, 2.10.44, page 202], from which it then follows that h can be extended to a 1-Lipschitz map on $(\mathbb{R}^{n_y} \times \mathbb{R}^{n_y})^N$ without changing its values on B^N . In fact, such an extension can be defined as $h_{ext}(z) = \inf_{x \in B^N} \{h(x) + \|z - x\|_2\}$. By abuse of notation this extension will be denote by h too. Notice that by Lemma C.3, $(\mathbf{y}(t), \mathbf{y}_\theta(t)) \in B$ for all t , hence $h(\mathbf{y}(0), \mathbf{y}_\theta(0), \dots, \mathbf{y}(N-1), \mathbf{y}_\theta(N-1)) = \frac{\epsilon}{L(\theta)} \sum_{i=0}^{N-1} \ell(\mathbf{y}(i), \mathbf{y}_\theta(i)) = \frac{\epsilon}{L(\theta)} NV_N(\theta)$.

Notice that,

$$\epsilon \lambda(\mathbf{E}[V_N(\theta)] - V_N(\theta)) = \frac{\lambda L(\theta)}{N} (\mathbf{E}[h] - h).$$

Now we can apply [1, Theorem 6.6], from which it follows that for any $q \geq 0$

$$\mathbf{E}[e^{q(\mathbf{E}[h] - h)}] \leq e^{\frac{q^2 N}{2} (\|\mathbf{z}_t\|_\infty + \theta_{\infty,N}(1))^2} \quad (36)$$

By choosing $q = \frac{\lambda L(\theta)}{N}$ and using the definition of $\mathcal{C}_{b,2}(\lambda, \theta, L(\theta), c_e, N)$, we obtain the statement of the lemma. $\square$

Proof of Theorem 3.1: bounded processes. The statement of the theorem follows from Theorem C.1 by replacing $\mathbf{E}[e^{2\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ and $\mathbf{E}[e^{2\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))}]$ with their upper bound from Lemma C.5 and Lemma C.6 respectively. $\square$

C.2 Proof of Theorem 3.1: unbounded processes and Lipschitz loss functions

Recall that according to our assumptions, the 2-norm of the noise process $\mathbf{e}_g$ is subgaussian. Bounded processes have this property, however, in this section we will not assume that the process $\mathbf{e}_g$ is bounded.

Recall that we also consider Lipschitz losses.

Assumption C.7 (Lipschitz loss). *We assume that the loss function ℓ is L_ℓ -Lipschitz, i.e., for all $y, \hat{y}, y', \hat{y}' \in \mathbb{R}^{n_y}$, $|\ell(y, \hat{y}) - \ell(y', \hat{y}')| \leq L_\ell(\|y - y'\|_2 + \|\hat{y} - \hat{y}'\|_2)$.*

The main idea is to use Theorem C.1 and to derive bounds for moment generating functions of $\mathbf{E}[2\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))]$ and $\mathbf{E}[2\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))]$. In order to achieve this, we will reduce the problem of bounding $\mathbf{E}[2\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))]$ and $\mathbf{E}[2\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))]$ to the same problem for bounded noises, by truncating the unbounded noise $\mathbf{e}_g$ which drives the data generator. This problem was solved in Lemma C.5 and Lemma C.6, which thus can be re-used.

To this end, let $C > 0$ be any constant and let $\bar{\mathbf{e}}_g(t)$ be the truncated version of $\mathbf{e}_g(t)$, i.e.,

$$\bar{\mathbf{e}}_g(t) = \mathbf{e}_g(t)\chi_{\{\|\mathbf{e}_g(t)\| < C\}}(t) := \mathbf{e}_g(t)\chi(\|\mathbf{e}_g(t)\| < C). \quad (37)$$

Let $\bar{\mathbf{w}}(t) = \begin{bmatrix} \bar{\mathbf{y}}^T(t) \\ \bar{\mathbf{u}}^T(t) \end{bmatrix}$ be the output of the data generator, if $\mathbf{e}_g(t)$ is replaced by $\bar{\mathbf{e}}_g(t)$, and let $\hat{\mathbf{y}}_\theta(t | t_0)$ be the output of the predictor (1) parametrized by θ with $\mathbf{w}$ replaced by $\bar{\mathbf{w}}$, and let $\hat{\mathbf{y}}_\theta(t)$ be the limit $\lim_{t_0 \rightarrow -\infty} \hat{\mathbf{y}}_\theta(t | t_0)$. Note that Lemma 2.4 applies, as $\bar{\mathbf{e}}_g(t)$ satisfies all the assumptions of Assumption 2.2. Let $\bar{V}_N(\theta) = \frac{1}{N}\ell(\bar{\mathbf{y}}(t), \hat{\mathbf{y}}_\theta(t))$ be the corresponding infinite past empirical error, $\hat{\mathcal{L}}_N(\theta) = \frac{1}{N}\sum_{t=0}^{N-1}\ell(\bar{\mathbf{y}}(t), \hat{\mathbf{y}}_\theta(t | 0))$ the finite past empirical error, and $\bar{\mathcal{L}}(\theta) = \mathbf{E}[\ell(\bar{\mathbf{y}}(t), \hat{\mathbf{y}}_\theta(t))]$ the true error for the model corresponding to $\theta \in \Theta$, if it is fed with the truncated signal $\bar{\mathbf{w}}$ instead of $\mathbf{w}$.

It turns out that we can bound the difference between these quantities and their non-truncated counterparts. The basic steps are as follows: First, using Lipschitz properties of the loss function, we bound the moment generating functions of the differences $\sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)|$, $\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|$ by the corresponding quantity for the ℓ_2 loss, i.e.; by the moment generating functions of $\sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2$ and $\sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2$.

Lemma C.8.

$$\mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)|}] \leq \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2)}]} \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t|0) - \hat{\mathbf{y}}_\theta(t|t_0)\|_2}]} \quad (38)$$

$$\mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|}] \leq \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2)}]} \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2}]} \quad (39)$$

Then, using the technique of [3] we bound the moment generating functions of the truncation errors $\sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2$ and $\sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2$. To this end, we use the following bound on the moment generating function of $\|\mathbf{e}_g(t)\|_2$.

Lemma C.9 (Subgaussian noise). *If $\|\mathbf{e}_g(t)\|_2$ is sub-Gaussian then $\Psi_{\mathbf{e}_g}(\lambda) = \mathbf{E}[e^{\lambda \|\mathbf{e}_g(0)\|_2}]$ is well-defined for all $\lambda > 0$. In fact,*

$$\Psi_{\mathbf{e}_g}(\lambda) \leq \bar{\Psi}_{\mathbf{e}_g}(\lambda) = e^{(\lambda^2 14^2 \|\mathbf{e}_g\|_{\psi_2}^2 + 3\lambda \|\mathbf{e}_g\|_{\psi_2})}$$

Using this bound, the moment generating function of the truncation error can be bounded as follows:

Lemma C.10. *For any $\lambda < 0.5N$*

$$\begin{aligned} \mathbf{E}[e^{\frac{\lambda}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2}] &\leq e^{\mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, \lambda, N, C)} \\ \mathbf{E}[e^{\frac{\lambda}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2}] &\leq e^{\mathcal{C}(\|\alpha_{g,w}\|_{\ell_1}, \lambda, N, C)} \\ \mathbf{E}[e^{\frac{\lambda}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t|0) - \hat{\mathbf{y}}_\theta(t|0)\|_2}] &\leq e^{\mathcal{C}(\|\alpha_{g,w}\|_{\ell_1}, \lambda, N, C)} \end{aligned}$$

where

$$\mathcal{C}(s, \lambda, N, C) = \lambda \frac{\bar{\Psi}_{\mathbf{e}_g}(s) s^2 C}{(e^{sC} - 1)} + \frac{\lambda^2}{N} 2\bar{\Psi}_{\mathbf{e}_g}(s) \quad (40)$$

From this we derive

Lemma C.11. *For any $\lambda < N/4L_\ell$*

$$\begin{aligned} \max\{\mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)|}], \mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|}], e^{\lambda \sup_{\theta \in \Theta} |\mathcal{L}(\theta) - \bar{\mathcal{L}}(\theta)|}\} &\leq \\ e^{\frac{1}{2}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}, \|\alpha_{g,w}\|_{\ell_1}, 2L_\ell \lambda, N) + \mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 2L_\ell \lambda, N))} & \end{aligned}$$

In order to go back to bounding the moment generating functions of $\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))$ and $\epsilon(\mathcal{L}(\theta) - V_N(\theta))$, we use the previous lemma, and the following inequality which we derive using the Cauchy-Schwartz inequality:

Lemma C.12. For $\epsilon = \{-1, 1\}$

$$\mathbf{E}[e^{\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))}] \leq \sqrt{\mathbf{E}[e^{2\lambda\epsilon(\bar{\mathcal{L}}(\theta) - \bar{V}_N(\theta))}]} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|}]} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\bar{\mathcal{L}}(\theta) - \mathcal{L}(\theta)|}]} \quad (41)$$

$$\mathbf{E}[e^{\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] \leq \sqrt{\mathbf{E}[e^{2\lambda\epsilon(\bar{V}_N(\theta) - \hat{\bar{\mathcal{L}}}_N(\theta))}]} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|}]} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\hat{\bar{\mathcal{L}}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}]} \quad (42)$$

If we apply Lemma C.11 to the right-hand sides of the latter inequalities, then we obtain.

Lemma C.13. For $\epsilon \in \{1, -1\}$, for $\lambda < \frac{N}{16L_\ell}$,

$$\begin{aligned} \mathbf{E}[e^{\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] &\leq e^{\frac{1}{4}(C(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 8L_\ell\lambda, N, C) + C(\|\alpha_{g,y}\|_{\ell_1}, 8L_\ell\lambda, N, C))} \sqrt{\mathbf{E}[e^{2\lambda\epsilon(\bar{V}_N(\theta) - \hat{\bar{\mathcal{L}}}_N(\theta))}]} \\ \mathbf{E}[e^{\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))}] &\leq e^{\frac{1}{4}(C(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 8L_\ell\lambda, N, C) + C(\|\alpha_{g,y}\|_{\ell_1}, 8L_\ell\lambda, N, C))} \sqrt{\mathbf{E}[e^{2\lambda\epsilon(\hat{\bar{\mathcal{L}}}_N(\theta) - \bar{V}_N(\theta))}]} \end{aligned}$$

Finally, Lemma C.5 and Lemma C.6 derived for the bounded case can be applied to the moment generating functions of $\epsilon(\hat{\bar{\mathcal{L}}}_N(\theta) - \bar{V}_N(\theta))$ and $\epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta))$, for a suitable choice of C . The detailed proof is presented below.

Proof of Theorem 3.1: unbounded noise and Lipschitz loss. Let $C = \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}$ where $K = \min\{1, \|\bar{\alpha}\|_{\ell_1}\}$. Then

$$C\|\alpha_g\|_{\ell_1} \geq 2\ln(N), \quad C\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1} \geq 2\ln(N)$$

and hence for $N \geq 2$,

$$e^{C\|\alpha_g\|_{\ell_1}} - 1 \geq e^{2\ln(N)} - 1 = N^2 - 1 \geq N, \quad e^{C\|\alpha_g\|_{\ell_1} \|\bar{\alpha}\|_{\ell_1}} - 1 \geq e^{2\ln(N)} - 1 = N^2 - 1 \geq N$$

and therefore

$$\frac{1}{e^{C\|\alpha_g\|_{\ell_1}} - 1} \leq \frac{1}{N}, \quad \frac{1}{e^{C\|\alpha_g\|_{\ell_1} \|\bar{\alpha}\|_{\ell_1}} - 1} \leq \frac{1}{N}$$

Therefore, as $C\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1} = 2\ln(N) \max\{1, \|\bar{\alpha}\|_{\ell_1}\}$,

$$\begin{aligned} C(\|\alpha_g\|_{\ell_1}, 8L_\ell\lambda, N, C) &\leq \frac{8L_\ell\lambda}{N} \Psi_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \|\alpha_g\|_{\ell_1}^2 \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}} + \frac{(8L_\ell\lambda)^2}{N} 2\Psi_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \leq \\ &\frac{8L_\ell\lambda}{N} \Psi_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \frac{\|\alpha_g\|_{\ell_1}}{\min\{1, \|\bar{\alpha}\|_{\ell_1}\}} 2\ln(N) + \frac{128L_\ell^2\lambda^2}{N} \Psi_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \\ C(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}, 8L_\ell\lambda, N, C) &\leq \\ &\frac{8L_\ell\lambda}{N} \Psi_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) (\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1})^2 C + \frac{(8L_\ell\lambda)^2}{N} 2\Psi_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) = \\ &\frac{8L_\ell\lambda}{N} \Psi_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) \|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1} 2\ln(N) \max\{1, \|\bar{\alpha}\|_{\ell_1}\} + \frac{128L_\ell^2\lambda^2}{N} \Psi_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1}) \end{aligned}$$

Hence,

$$\begin{aligned}
& \frac{1}{4}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 8L_\ell\lambda, N, C) + \mathcal{C}(\|\alpha_g\|_{\ell_1}, 8L_\ell\lambda, N, C)) \leq \\
& \frac{4\lambda\ln(N)L_\ell}{N} \left(\underbrace{\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1})\|\bar{\alpha}\|_{\ell_1} \max\{1, \|\bar{\alpha}\|_{\ell_1}\}\|\alpha_g\|_{\ell_1} + \bar{\Psi}_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}) \frac{\|\alpha_g\|_{\ell_1}}{\min\{1, \|\bar{\alpha}\|_{\ell_1}\}}}_{C_{u,2}} \right) \\
& + \frac{32\lambda^2 L_\ell^2}{N} \underbrace{(\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}) + \bar{\Psi}_{\mathbf{e}_g}(\|\alpha_g\|_{\ell_1}))}_{C_{u,1}} = \bar{\mathcal{C}}_{ub}(\lambda, L_\ell, N)
\end{aligned} \tag{43}$$

From Lemma C.5 and Lemma C.6 applied to $\bar{V}_N(\theta)$, $\bar{\mathcal{L}}(\theta)$, $\hat{\mathcal{L}}_N(\theta)$, with $c_e = C = \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}$ and $L(\theta) = L_\ell$, it follows that

$$\begin{aligned}
\sqrt{\mathbf{E}[e^{2\lambda\epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]} & \leq \sqrt{e^{C_{b,1}(2\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)}} = e^{\frac{1}{2}C_{b,1}(2\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)} \\
\sqrt{\mathbf{E}[e^{2\lambda\epsilon(\bar{\mathcal{L}}(\theta) - \bar{V}_N(\theta))}]} & \leq \sqrt{e^{C_{b,2}(2\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)}} = e^{\frac{1}{2}C_{b,2}(2\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)}
\end{aligned}$$

Using Lemma C.13 with $\|\alpha_{g,y}\|_{\ell_1}$ and $\|\alpha_{g,w}\|_{\ell_1}$ replaced by their upper bound $\|\alpha_g\|_{\ell_1}$ it follows that for any $\lambda < L_\ell/16N$,

$$\begin{aligned}
\mathbf{E}[e^{2\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] & \leq e^{\bar{\mathcal{C}}_{ub}(2\lambda, L_\ell, N) + \frac{1}{2}C_{b,1}(4\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)} = e^{C_1(2\lambda, \theta, N, \delta, \epsilon)} \\
\mathbf{E}[e^{2\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))}] & \leq e^{\bar{\mathcal{C}}_{ub}(2\lambda, L_\ell, N) + \frac{1}{2}C_{b,2}(4\lambda, \theta, L_\ell, \frac{2\ln(N)}{K\|\alpha_g\|_{\ell_1}}, N)} = e^{C_2(2\lambda, \theta, N, \delta, \epsilon)}
\end{aligned} \tag{44}$$

The statement of the theorem follows from Theorem C.1 by replacing $\mathbf{E}[e^{2\lambda\epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ and $\mathbf{E}[e^{2\lambda\epsilon(\mathcal{L}(\theta) - V_N(\theta))}]$ with their upper bound from (44). □

The rest of the section is devoted to the proof of the lemmas used above.

First, we prove Lemma C.9

Proof of Lemma C.9. First note that $\mathbf{z}(t) := \|\mathbf{e}_g(t)\|_2 - \mathbf{E}[\|\mathbf{e}_g(t)\|_2]$ is zero mean sub-Gaussian, and using sub-additivity of the sub-Gaussian norm we get $\|\mathbf{z}(t)\|_{\psi_2} \leq \|\|\mathbf{e}_g(t)\|_2\|_{\psi_2} + \|\mathbf{E}[\|\mathbf{e}_g(t)\|_2]\|_{\psi_2} = \|\mathbf{e}_g\|_{\psi_2} + \|\mathbf{E}[\|\mathbf{e}_g(t)\|_2]\|_{\psi_2}$. Now from the proof of [43, Proposition 2.6.1] it follows that $\mathbf{E}[\|\mathbf{e}_g(t)\|_2] \leq 3\|\mathbf{e}_g\|_{\psi_2}$, and by [43, Exercise 2.24], $\|\mathbf{E}[\|\mathbf{e}_g(t)\|_2]\|_{\psi_2} \leq \mathbf{E}[\|\mathbf{e}_g(t)\|_2]/\sqrt{\ln 2} \leq 2\mathbf{E}[\|\mathbf{e}_g(t)\|_2]$. Hence $\|\mathbf{z}(t)\|_{\psi_2} \leq 7\|\mathbf{e}_g\|_{\psi_2}$.

Then from the proof of [43, Proposition 2.6.1] it follows that $\mathbf{E}[e^{\lambda(\|\mathbf{e}_g(t)\|_2 - \mathbf{E}[\|\mathbf{e}_g(t)\|_2])}] \leq e^{\lambda^2 K^2}$ and $K = \sqrt{\frac{3}{2}}\|\mathbf{z}(t)\|_{\psi_2} \leq 14\|\mathbf{e}_g\|_{\psi_2}$. It then follows that $\Psi_e(\lambda) \leq e^{(\lambda^2 K^2 + \lambda \mathbf{E}[\|\mathbf{e}_g(t)\|_2])}$ and the statement of the lemma follows. □

In order to present the proof of Lemma C.8-C.13, we need the following sequence of results.

Lemma C.14. *Let $\mathbf{z}$ be positive valued random variable such that for all $s \leq \bar{\lambda}$ its moment generating function is well-defined. Then for any $C > 0$,*

$$\mathbf{E}[\mathbf{z}\chi(\mathbf{z} > C)] \leq \frac{C\mathbf{E}[e^{\bar{\lambda}\mathbf{z}}]}{e^{\bar{\lambda}C} - 1}$$

Note that, as in (37), we use $\chi(\mathbf{z} > C)$ as a shorthand for the indicator function $\chi_{\{\mathbf{z} > C\}}(\mathbf{z})$. This practices will be used in the sequel.

Proof of Lemma C.14. Let us consider $\phi(x) = \frac{e^x - 1}{x}$. It then follows that ϕ is a monotonically increasing function of x for $x > 0$. Hence,

$$\frac{\phi(\bar{\lambda}\mathbf{z})}{\phi(\bar{\lambda}C)} \geq \chi(\mathbf{z} > C).$$

Indeed, if $\mathbf{z} > C$, then $\frac{\phi(\bar{\lambda}\mathbf{z})}{\phi(\bar{\lambda}C)} \geq 1 = \chi(\mathbf{z} > C)$. If $\mathbf{z} \leq C$, then $1 > \frac{\phi(\bar{\lambda}\mathbf{z})}{\phi(\bar{\lambda}C)} \geq 0 = \chi(\mathbf{z} > C)$. It then follows that

$$\mathbf{z} \frac{\phi(\bar{\lambda}\mathbf{z})}{\phi(\bar{\lambda}C)} \geq \mathbf{z}\chi(\mathbf{z} > C)$$

and by taking expectations it follows that

$$\mathbf{E}[\mathbf{z}\chi(\mathbf{z} > C)] \leq \frac{1}{\phi(\bar{\lambda}C)} \mathbf{E}[\mathbf{z}\phi(\bar{\lambda}\mathbf{z})]$$

Note that

$$\mathbf{z}\phi(\bar{\lambda}\mathbf{z}) = \frac{e^{\bar{\lambda}\mathbf{z}} - 1}{\bar{\lambda}}$$

and hence by using the inequality $e^x - 1 \leq e^x$ for $x \geq 0$ it follows that

$$\mathbf{E}[\mathbf{z}\phi(\bar{\lambda}\mathbf{z})] = \frac{\mathbf{E}[e^{\bar{\lambda}\mathbf{z}}] - 1}{\bar{\lambda}} \leq \frac{\mathbf{E}[e^{\bar{\lambda}\mathbf{z}}]}{\bar{\lambda}}$$

By noticing that

$$\bar{\lambda}\phi(\bar{\lambda}C) = \frac{e^{\bar{\lambda}C} - 1}{C}$$

the statement of the lemma follows. $\square$

Lemma C.15.

$$\mathbf{E}[e^{s\|\mathbf{e}_g(t)\|_2 \chi(\|\mathbf{e}_g(t)\|_2 > C)}] \leq \left(1 + s \frac{\bar{\Psi}_{\mathbf{e}_g}(\bar{\lambda})C}{e^{\bar{\lambda}C} - 1} + s^2 \frac{2\bar{\Psi}_{\mathbf{e}_g}(\bar{\lambda})}{\bar{\lambda}^2}\right) := \Psi_{\mathbf{e}_g}(s, \bar{\lambda}, C)$$

for all $s \in [0, 0.5\bar{\lambda})$.

Proof Lemma C.15. First note that

$$\begin{aligned} \mathbf{E}[e^{s\|\mathbf{e}_g(t)\|_2 \chi(\|\mathbf{e}_g(t)\|_2 > C)}] &= 1 + s\mathbf{E}[\|\mathbf{e}_g(t)\|_2 \chi(\|\mathbf{e}_g(t)\|_2 > C)] + \\ &\sum_{k=2}^{\infty} \frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k \chi(\|\mathbf{e}_g(t)\|_2 > C)] s^k}{k!}. \end{aligned} \quad (45)$$

and $\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k \chi(\|\mathbf{e}_g(t)\|_2 > C)] \leq \mathbf{E}[\|\mathbf{e}_g(t)\|_2^k]$.

As in Lemma C.9 let $\Psi_{\mathbf{e}_g}(\bar{\lambda}) = \mathbf{E}[e^{\bar{\lambda}\|\mathbf{e}_g(t)\|_2}] = \mathbf{E}[e^{\bar{\lambda}\|\mathbf{e}_g(t)\|_2}]$ be the moment generating function for $\|\mathbf{e}_g(t)\|_2$. Then

$$\Psi_{\mathbf{e}_g}(\bar{\lambda}) = \sum_{k=0}^{\infty} \frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k]}{k!} \bar{\lambda}^k$$

and we get

$$\frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k]}{k!} \leq \frac{\Psi_{\mathbf{e}_g}(\bar{\lambda})}{\bar{\lambda}^k}.$$

It follows that for all $k \geq 2$,

$$\frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k \chi(\|\mathbf{e}_g(t)\|_2 > C)] s^k}{k!} \leq \frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k] s^k}{k!} \leq \Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^k}{\bar{\lambda}^k}.$$

Therefore, for all $s \in [0, 0.5\bar{\lambda})$,

$$\begin{aligned} \sum_{k=2}^{\infty} \frac{\mathbf{E}[\|\mathbf{e}_g(t)\|_2^k \chi(\|\mathbf{e}_g(t)\|_2 > C)] s^k}{k!} &\leq \sum_{k=2}^{\infty} \Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^k}{\bar{\lambda}^k} = \Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^2}{\bar{\lambda}^2} \frac{1}{1 - \frac{s}{\bar{\lambda}}} = \\ \Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^2}{\bar{\lambda}(\bar{\lambda} - s)} &\leq \Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^2}{0.5\bar{\lambda}^2} = 2\Psi_{\mathbf{e}_g}(\bar{\lambda}) \frac{s^2}{\bar{\lambda}^2} \end{aligned} \quad (46)$$

where in the last inequality we used that as $s < 0.5\bar{\lambda}$, $\bar{\lambda} - s \geq 0.5\bar{\lambda}$. Finally, use Lemma C.14 with $\mathbf{z} = \|\mathbf{e}_g(t)\|_2$ to obtain

$$\mathbb{E}[\|\mathbf{e}_g(t)\|_2 \chi(\|\mathbf{e}_g(t)\|_2 > C)] \leq \frac{\Psi_{\mathbf{e}_g}(\bar{\lambda})C}{e^{\bar{\lambda}C} - 1} \quad (47)$$

The result now follows by combining (45), (46) and (47), and then use Lemma C.9. $\square$

We will also need the following technical lemma

Lemma C.16. *Let $a_k \geq 0$ be a sequence of positive numbers such that the series $\sum_{k=0}^{\infty} a_k$ is convergent. For any N , define $c_{k,N} = \sum_{l=\max\{0, k-N+1\}}^k a_l$. Then $\sum_{k=0}^L c_{k,N} \leq N \sum_{k=0}^L a_k$, the series $\sum_{k=0}^{\infty} c_{k,N}$ is convergent, and $\sum_{k=0}^{\infty} c_{k,N} \leq N \sum_{k=0}^{\infty} a_k$.*

Proof of Lemma C.16. We will prove by induction on $L \geq N - 1$ that

$$\sum_{k=0}^L c_{k,N} = \sum_{k=0}^{L-N+1} N a_k + \sum_{k=L-N+2}^L (L - k + 1) a_k \quad (48)$$

For $L = N - 1$, by induction on N , it can be shown that

$$\sum_{k=0}^{N-1} c_{k,N} = \sum_{k=0}^{N-1} \sum_{l=0}^k a_l = \sum_{k=0}^{N-1} (N - k) a_k.$$

which yield (48) for $L = N - 1$. Assume (48) holds for $N - 1 \leq L' \leq L$. Notice that $c_{L+1,N} = \sum_{l=L-N+2}^L a_l$ and hence

$$\begin{aligned} \sum_{k=0}^{L+1} c_{k,N} &= \sum_{k=0}^L c_{k,N} + c_{L+1,N} = \sum_{k=0}^{L-N+1} N a_k + \sum_{k=L-N+2}^L (L - k + 1) a_k + \sum_{l=L-N+2}^L a_l = \\ &= \sum_{k=0}^{L-N+1} N a_k + \sum_{k=L-N+2}^L (L - k + 2) a_k = \sum_{k=0}^{L-N+1} N a_k + (L - (L - N + 2) + 2) a_{L-N+2} + \\ &= \sum_{k=L-N+3}^L ((L + 1) - k + 1) a_k = \sum_{k=0}^{L-N+2} N a_k + \sum_{k=L-N+3}^L ((L + 1) - k + 1) a_k \end{aligned}$$

The last expression is the right-hand side of (48) for L being replaced by $L + 1$, thus proving (48). Note that for $k = L - N + 2, \dots, L$ we have $L - k + 1 \leq N$, and hence (48) implies that $\sum_{k=0}^L c_{k,N} \leq N \sum_{k=0}^L a_k$. Since a_k and c_k are nonnegative, and $\sum_{k=0}^{\infty} a_k$ is convergent, the rest of the lemma follows. $\square$

Lemma C.17. *Let $\mathbf{I}$ be an index set, and $\{\beta_{i,t}(k)\}_{k=0}^{\infty}$, $i \in \mathbf{I}$, be a sequence of matrices such that $\|\bar{\beta}\|_{\ell_1} < \infty$, where $\bar{\beta}(k) = \sup_{i \in \mathbf{I}, t \in \mathbb{Z}} \|\beta_{i,t}(k)\|_2$. Let $\mathbf{z}_i(t) = (\beta_{i,t} \star \mathbf{e}_g)(t)$ and $\bar{\mathbf{z}}_i(t) = (\bar{\beta}_{i,t} \star \bar{\mathbf{e}}_g)(t)$. Then for $\lambda < 0.5N$*

$$\begin{aligned} \mathbb{E}[e^{\frac{\lambda}{N} \sup_{i \in \mathbf{I}} \sum_{t=0}^{N-1} \|\mathbf{z}(t) - \bar{\mathbf{z}}_i(t)\|_2}] &\leq \prod_{k=0}^{\infty} \bar{\Psi}_{\mathbf{e}_g} \left(\frac{c(k)\lambda}{N}, \|\bar{\beta}\|_{\ell_1}, C \right) \leq e^{\mathcal{C}(\|\bar{\beta}\|_{\ell_1}, \lambda, N, C)} \\ \mathcal{C}(s, \lambda, N, C) &= \lambda \frac{\bar{\Psi}_{\mathbf{e}_g}(s) s^2 C}{(e^{sC} - 1)} + \frac{\lambda^2}{N} 2 \bar{\Psi}_{\mathbf{e}_g}(s) \end{aligned}$$

where $c(k) = \sum_{l=\max\{0, k-N+1\}}^k \|\bar{\beta}(l)\|_2$ and the infinite product on the right-hand side is well-defined.

Proof of Lemma C.17. Note that

$$c(k) \leq \|\bar{\beta}\|_{\ell_1} \quad (49)$$

and by Lemma C.16

$$\sum_{k=0}^{\infty} c(k) \leq N \sum_{k=0}^{\infty} \|\bar{\beta}(k)\|_2 = N \|\bar{\beta}\|_{\ell_1} \quad (50)$$

Note now that

$$\begin{aligned} & \sum_{t=0}^{N-1} \|\mathbf{z}_{i,t}(t) - \bar{\mathbf{z}}_{i,t}(t)\|_2 \\ & \leq \sum_{t=0}^{N-1} \sum_{k=0}^{\infty} \|\beta_{i,t}(k)\|_2 \|\mathbf{e}_g(t-k) - \bar{\mathbf{e}}_g(t-k)\|_2 \\ & \leq \sum_{t=0}^{N-1} \sum_{k=0}^{\infty} \|\bar{\beta}(k)\|_2 \|\mathbf{e}_g(t-k)\|_2 \chi(\|\mathbf{e}_g(t-k)\|_2 > C) \\ & = \sum_{k=0}^{\infty} c(k) \|\mathbf{e}_g(N-k-1)\|_2 \chi(\|\mathbf{e}_g(N-k-1)\|_2 > C) \end{aligned}$$

Hence,

$$\begin{aligned} & \mathbf{E}[e^{\frac{\lambda}{N} \sup_{i \in \mathbf{I}, t \in \mathbb{Z}} \sum_{t=1}^N \|\mathbf{z}_{i,t}(t) - \bar{\mathbf{z}}_{i,t}(t)\|_2}] \leq \\ & \leq \mathbf{E}[e^{\frac{\lambda}{N} \sum_{k=0}^{\infty} c(k) \|\mathbf{e}_g(N-k-1)\|_2 \chi(\|\mathbf{e}_g(N-k-1)\|_2 > C)}] \\ & = \lim_{L \rightarrow \infty} \prod_{k=0}^L \bar{\Psi}_{\mathbf{e}_g} \left(\frac{c(k)\lambda}{N}, \|\bar{\beta}\|_{\ell_1}, C \right) \end{aligned}$$

where we applied Lemma C.15 to $\mathbf{E}[e^{\frac{\lambda}{N} c(k) \|\mathbf{e}_g(N-k-1)\|_2 \chi(\|\mathbf{e}_g(N-k-1)\|_2 > C)}]$ with $\bar{\lambda} = \|\bar{\beta}\|_{\ell_1}$ and $s = \frac{c(k)\lambda}{N} < 0.5\|\bar{\beta}\|_{\ell_1}$ since $\lambda < 0.5N$ by assumption.

Note that

$$\begin{aligned} d_L &= \ln \left(\prod_{k=0}^L \bar{\Psi}_{\mathbf{e}_g} \left(\frac{c(k)\lambda}{N}, \|\bar{\beta}\|_{\ell_1}, C \right) \right) = \sum_{k=0}^L r_k \\ r_k &:= \ln \left(1 + \frac{c(k)\lambda}{N} \frac{\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1}) \|\bar{\beta}\|_{\ell_1} C}{e^{\|\bar{\beta}\|_{\ell_1} C} - 1} + \left(\frac{c(k)\lambda}{N} \right)^2 \frac{2\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1})}{\|\bar{\beta}\|_{\ell_1}^2} \right) \geq 0 \end{aligned}$$

We show that the series $\sum_{k=0}^{\infty} r_k$ is bounded, more precisely,

$$\sum_{k=0}^L r_k \leq \|\bar{\beta}\|_{\ell_1} \lambda \frac{\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1}) \|\bar{\beta}\|_{\ell_1} C}{e^{\|\bar{\beta}\|_{\ell_1} C} - 1} + \frac{\lambda^2}{N} (\|\bar{\beta}\|_{\ell_1})^2 \frac{2\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1})}{\|\bar{\beta}\|_{\ell_1}^2} = \mathcal{C}(\|\bar{\beta}\|_{\ell_1}, \lambda, N, C)$$

From this it follows that d_L is convergent, and from

$$\prod_{k=0}^L \bar{\Psi}_{\mathbf{e}_g} \left(\frac{c(k)\lambda}{N}, \|\bar{\beta}\|_{\ell_1}, C \right) = e^{d_L}$$

it follows that

$$\lim_{L \rightarrow \infty} \prod_{k=0}^L \bar{\Psi}_{\mathbf{e}_g} \left(\frac{c(k)\lambda}{N}, \|\bar{\beta}\|_{\ell_1}, C \right) \leq e^{\mathcal{C}(\|\bar{\beta}\|_{\ell_1}, \lambda, N, C)} \quad (51)$$

i.e., the infinite product is well-defined, and the statement of the lemma holds.

In order to show (51), note that using $\ln(1+x) \leq x$, it follows that

$$r_k \leq \frac{c(k)\lambda}{N} \frac{\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1}) \|\bar{\beta}\|_{\ell_1} C}{e^{\|\bar{\beta}\|_{\ell_1} C} - 1} + \left(\frac{c(k)\lambda}{N} \right)^2 \frac{2\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1})}{\|\bar{\beta}\|_{\ell_1}^2}$$

Hence,

$$\sum_{k=0}^L r_k \leq \frac{\lambda \sum_{k=0}^L c(k)}{N} \frac{\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1}) \|\bar{\beta}\|_{\ell_1} C}{e^{\|\bar{\beta}\|_{\ell_1} C} - 1} + \left(\frac{\sum_{k=0}^L (c(k))^2}{N^2} \right) \frac{2\bar{\Psi}_{\mathbf{e}_g}(\|\bar{\beta}\|_{\ell_1})}{\|\bar{\beta}\|_{\ell_1}^2}$$

From (49) it follows that $c(k) \leq \|\bar{\beta}\|_{\ell_1}$. Hence

$$\left(\frac{1}{N} c(k) \right)^2 \leq \frac{1}{N^2} c(k) \|\bar{\beta}\|_{\ell_1}$$

and as from (50) it follows that $\sum_{k=0}^L c(k) \leq N \|\bar{\beta}\|_{\ell_1}$, we get that

$$\sum_{k=0}^L \left(\frac{1}{N} c(k) \right)^2 \leq \frac{1}{N^2} \sum_{k=0}^L c(k) \|\bar{\beta}\|_{\ell_1} \leq \frac{1}{N} \|\bar{\beta}\|_{\ell_1}^2$$

This completes the proof. $\square$

Lemma C.17 provides the basis for several technical results.

Proof of Lemma C.10. From Lemma B.3 it follows that $\mathbf{y}(t) = (\alpha_{g,y} \star \mathbf{e}_g)(t)$ and $\bar{\mathbf{y}}(t) = (\alpha_{g,y} \star \bar{\mathbf{e}}_g)(t)$. By setting $I = \{g\}$, $\beta_{i,t} = \alpha_{g,y}$, $i = g$ and using Lemma C.17, the first inequality follows.

Similar, from Lemma B.3 it follows that $\hat{\mathbf{y}}(t) = (c_\theta \star \mathbf{e}_g)(t)$ and $\hat{\bar{\mathbf{y}}}(t) = (c_\theta \star \bar{\mathbf{e}}_g)(t)$. By setting $I = \Theta$, $\beta_{i,t} = c_\theta$, $i = \theta \in \Theta$, it follows that

$$\mathbf{E}[e^{\frac{\lambda}{N} \sup_{\theta \in \Theta} \sum_{t=0}^N \|\hat{\mathbf{y}}(t) - \hat{\bar{\mathbf{y}}}(t)\|_2}] \leq e^{\mathcal{C}(\|\bar{c}\|_{\ell_1}, \lambda, N, C)}$$

where $\bar{c}(k) = \sup_{\theta \in \Theta} \|c_\theta(k)\|_2$. Note that by definition $c_\theta(k) = \sum_{l=0}^k \alpha_\theta(l) \alpha_{g,w}(k-l)$ and hence

$$\|c_\theta(k)\|_2 \leq \sum_{l=0}^k \|\alpha_\theta(l)\|_2 \|\alpha_{g,w}(k-l)\|_2 \leq \sum_{l=0}^k \|\bar{\alpha}(l)\|_2 \|\alpha_{g,w}(k-l)\|_2$$

In particular,

$$\bar{c}(k) \leq \sum_{l=0}^k \|\bar{\alpha}(l)\|_2 \|\alpha_{g,w}(k-l)\|_2$$

from which by the well-known property of Cauchy products of series (the infinite sum of the Cauchy product of two absolutely convergent series is equal to the product of their infinite sums) it follows that

$$\|\bar{c}\|_{\ell_1} \leq \|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}.$$

By noticing that $\mathcal{C}(\beta, \lambda, N, C)$ is increasing in β , it follows that $\mathcal{C}(\|\bar{c}\|_{\ell_1}, \lambda, N, C) \leq \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, \lambda, N, C)$, from which the second inequality follows.

Finally, the proof of the third inequality is similar to the second one. By Lemma B.3 it follows that $\hat{\mathbf{y}}(t | 0) = (c_{\theta,t} \star \mathbf{e}_g)(t)$ and $\hat{\bar{\mathbf{y}}}(t | 0) = (c_{\theta,t} \star \bar{\mathbf{e}}_g)(t)$. By applying lemma C.17 to $I = \Theta$, $\beta_{i,t} = c_{\theta,t}$ it follows that

$$\mathbf{E}[e^{\frac{\lambda}{N} \sup_{\theta \in \Theta} \sum_{t=0}^N \|\hat{\mathbf{y}}(t|0) - \hat{\bar{\mathbf{y}}}(t|0)\|_2}] \leq e^{\mathcal{C}(\|\bar{c}\|_{\ell_1}, \lambda, N, C)}$$

where $\bar{c}(k) = \sup_{\theta \in \Theta, t \geq 0} \|c_{\theta,t}(k)\|_2$. By noticing that

$$\begin{aligned} \|c_{\theta,t}(k)\|_2 &= \left\| \sum_{l=0}^{\min\{k,t\}} \alpha_\theta(k) \alpha_{g,w}(k-l) \right\|_2 \leq \sum_{l=0}^{\min\{k,t\}} \|\alpha_\theta(k)\|_2 \|\alpha_{g,w}(k-l)\|_2 \\ &\leq \sum_{l=0}^k \|\bar{\alpha}(k)\|_2 \|\alpha_{g,w}(k-l)\|_2 \leq \sum_{l=0}^k \|\bar{\alpha}(k)\|_2 \|\alpha_{g,w}(k-l)\|_2, \end{aligned}$$

from which it follows that

$$\|\bar{c}\|_{\ell_1} \leq \|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}$$

From the monotonicity of $\mathcal{C}(s, \lambda, N, C)$ in s , it follows that

$$\mathcal{C}(\|\bar{c}\|_{\ell_1}, \lambda, N, C) \leq \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, \lambda, N, C),$$

which completes the proof. $\square$

Proof of Lemma C.8. Notice that

$$\begin{aligned} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)| &\leq \frac{1}{N} \sum_{t=0}^{N-1} |\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t | 0)) - \ell(\bar{\mathbf{y}}(t), \hat{\mathbf{y}}_\theta(t | 0))| \leq \\ &\frac{L_\ell}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2 + \frac{L_\ell}{N} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2 \end{aligned}$$

and hence

$$\sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)| \leq \frac{L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2 + \frac{L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2)$$

Then

$$\begin{aligned} \mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}] &\leq \mathbf{E}[e^{\frac{\lambda L_\ell}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2} e^{\frac{\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2}] \leq \\ &\sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2)}]} \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2}]} \end{aligned}$$

from which (38) follows. Similarly,

$$\begin{aligned} |V_N(\theta) - \bar{V}_N(\theta)| &\leq \frac{1}{N} \sum_{t=0}^{N-1} |\ell(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t)) - \ell(\bar{\mathbf{y}}(t), \hat{\mathbf{y}}_\theta(t))| \leq \\ &\frac{L_\ell}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2 + \frac{L_\ell}{N} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \end{aligned}$$

and hence

$$\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)| \leq \frac{L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2 + \frac{L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2)$$

so that

$$\begin{aligned} \mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|}] &\leq \mathbf{E}[e^{\frac{\lambda L_\ell}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2} e^{\frac{\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2}] \leq \\ &\sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sum_{t=0}^{N-1} (\|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2)}]} \sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2}]} \end{aligned}$$

from which (39) follows. $\square$

Proof of Lemma C.11. From Lemma C.10 it follows that

$$\sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sum_{t=0}^{N-1} \|\mathbf{y}(t) - \bar{\mathbf{y}}(t)\|_2}]} \leq e^{\frac{1}{2} \mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 2L_\ell \lambda, N, C)} \quad (52)$$

and

$$\sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t | 0) - \hat{\mathbf{y}}_\theta(t | t_0)\|_2}]} \leq e^{\frac{1}{2} \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 2L_\ell \lambda, N, C)} \quad (53)$$

from which by using (38) it follows that

$$\mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}] \leq e^{\frac{1}{2} (\mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 2L_\ell \lambda, N, C) + \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 2L_\ell \lambda, N, C))}$$

Likewise, from Lemma C.10 it follows that

$$\sqrt{\mathbf{E}[e^{\frac{2\lambda L_\ell}{N} \sup_{\theta \in \Theta} \sum_{t=0}^{N-1} \|\hat{\mathbf{y}}_\theta(t) - \hat{\mathbf{y}}_\theta(t)\|_2}]} \leq e^{\frac{1}{2} \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,y}\|_{\ell_1}, 2L_\ell \lambda, N, C)}$$

By combining this with (52), it follows by (39) that

$$\mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|}] \leq e^{\frac{1}{2} (\mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 2L_\ell \lambda, N, C) + \mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 2L_\ell \lambda, N, C))} \quad (54)$$

Finally, as $\mathcal{L}(\theta) = \mathbf{E}[V_N(\theta)]$ and $\bar{\mathcal{L}}(\theta) = \mathbf{E}[\bar{V}_N(\theta)]$, it follows that

$$\begin{aligned} \sup_{\theta \in \Theta} |\mathcal{L}(\theta) - \bar{\mathcal{L}}(\theta)| &= \sup_{\theta \in \Theta} |\mathbf{E}[V_N(\theta) - \bar{V}_N(\theta)]| \\ &\leq \sup_{\theta \in \Theta} \mathbf{E}[|V_N(\theta) - \bar{V}_N(\theta)|] \leq \mathbf{E}[\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|] \end{aligned}$$

and hence

$$e^{\lambda \sup_{\theta \in \Theta} |\mathcal{L}(\theta) - \bar{\mathcal{L}}(\theta)|} \leq e^{\lambda \mathbf{E}[\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|]} \quad (55)$$

As the function $\phi : x \mapsto e^{\lambda x}$ is convex, by Jensen's inequality it follows that

$$\begin{aligned} e^{\lambda \mathbf{E}[\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|]} &= \phi(\mathbf{E}[\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|]) \leq \\ &= \mathbf{E}[\phi(\sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|)] = \mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |V_N(\theta) - \bar{V}_N(\theta)|}] \end{aligned}$$

and then the statement of the lemma follows from (54) and (55). $\square$

Proof of Lemma C.12. Note that

$$\begin{aligned} \epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta)) &= \epsilon(\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)) + \epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta)) + \epsilon(V_N(\theta) - \bar{V}_N(\theta)) \\ &\leq \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)| + \epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta)) + \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)| \end{aligned}$$

Hence, by using monotonicity of $x \mapsto e^x$ and Cauchy-Schwartz inequality for expectations,

$$\begin{aligned} \mathbf{E}[e^{\lambda \epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] &\leq \mathbf{E}[e^{\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|} e^{\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|} e^{\lambda \epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] \\ &\leq \sqrt{\mathbf{E}[e^{2\lambda \epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]} \sqrt{\mathbf{E}[e^{2\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|} e^{2\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}]} \\ &\leq \sqrt{\mathbf{E}[e^{2\lambda \epsilon(\bar{V}_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]} \sqrt{\sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|}]} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}]} \end{aligned}$$

proving (42). A similar argument proves (41). $\square$

Proof of Lemma C.13. From Lemma C.11 it follows that

$$\begin{aligned} \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\bar{V}_N(\theta) - V_N(\theta)|}]} &\leq e^{\frac{1}{4}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 8L_\ell \lambda, N, C) + \mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 8L_\ell \lambda, N, C))} \\ \sqrt{\mathbf{E}[e^{4\lambda \sup_{\theta \in \Theta} |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}]} &\leq e^{\frac{1}{4}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 8L_\ell \lambda, N, C) + \mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 8L_\ell \lambda, N, C))} \end{aligned}$$

and hence

$$\begin{aligned} \sqrt{\sqrt{\mathbf{E}[e^{4\lambda |\bar{V}_N(\theta) - V_N(\theta)|}]} \sqrt{\mathbf{E}[e^{4\lambda |\hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta)|}]} \\ \leq e^{\frac{1}{4}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1} \|\alpha_{g,w}\|_{\ell_1}, 8L_\ell \lambda, N, C) + \mathcal{C}(\|\alpha_{g,y}\|_{\ell_1}, 8L_\ell \lambda, N, C))} \end{aligned}$$

By using (42) the first statement of the lemma follows. The proof of the second claim is similar. $\square$

C.3 Proof of Theorem 3.1: quadratic loss

The core of the proof is to show that the prediction errors $\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2$ and $\|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2$ are sub-Gaussian and hence they are bounded with high probability as follows.

Lemma C.18. For $N \geq 1$ and $\delta \in (0, 0.5)$

$\mathbf{P}(\forall \theta \in \Theta, \forall t = 0, \dots, N-1 :$

$$\max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2\} \leq 6G_e(\|\mathbf{e}_g\|_{\psi_2}) \sqrt{\ln\left(\frac{3N^2}{2\delta}\right)} \geq 1 - \frac{2\delta}{3} \quad (56)$$

and

$$\mathbf{E}[\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2^2 > (6G_e\|\mathbf{e}_g\|_{\psi_2})^2 \ln\left(\frac{3N^2}{2\delta}\right))] \leq \frac{2 \cdot 6^2 G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} \quad (57)$$

We then replace the quadratic loss with a loss which is Lipschitz for the case when $\|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2$ are bounded. More precisely, let us define the loss function ℓ_C as follows:

$$\ell_C(y, \hat{y}) = \min\{\|y - \hat{y}\|_2^2, C^2\}$$

Lemma C.19. For any $C > 0$, ℓ_C is $2C$ -Lipschitz.

The proof then reduces the quadratic case to the case of Lipschitz loss ℓ_C for a suitable C and it goes as follows.

Proof of Theorem 3.1:quadratic case. Let us set $C = 6G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln(\frac{3N^2}{2\delta})}$ and let us consider the true and empirical errors for the loss function ℓ_C :

$${}^C\hat{\mathcal{L}}_N(\theta) = \frac{1}{N} \sum_{t=0}^{N-1} \ell_C(y(t), \hat{y}_\theta(t | 0)), \quad {}^C\mathcal{L}(\theta) = \mathbf{E}[\ell_C(y(t), \hat{y}_\theta(t))]$$
 (58)

By applying Theorem 3.1 for the case of Lipschitz loss function ℓ_C and with $\frac{2\delta}{3}$ instead of δ , it follows that for all $\epsilon \in \{-1, 1\}$, for all $0 < \lambda < \frac{N}{16 \cdot 2C}$

$$\begin{aligned} \forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} {}^C\mathcal{L}(\theta) &\leq \epsilon E_{\theta \sim \rho} {}^C\hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\text{KL}(\rho \| \pi) + \ln \frac{3}{2\delta} + \right. \\ &\left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right) \end{aligned}$$
 (59)

holds with probability at least $1 - \frac{4\delta}{3}$, where for $i = 1, 2$.

$$\bar{\mathcal{C}}_i(\lambda, \theta, N, \delta, \epsilon) = \mathcal{C}_{ub,i}(\lambda, \theta, 12G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln(\frac{3N^2}{2\delta})}, N)$$
 (60)

By using Lemma C.18, (59) and the union bound, it follows that

$$\begin{aligned} \forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} {}^C\mathcal{L}(\theta) &\leq \epsilon E_{\theta \sim \rho} {}^C\hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\text{KL}(\rho \| \pi) + \ln \frac{3}{2\delta} + \right. \\ &\left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right) \end{aligned}$$
 (61)

and

$$\forall \theta \in \Theta, \forall t = 0, \dots, N-1 : \quad \|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \leq C, \|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t | 0)\|_2 \leq C$$

holds with probability at least $1 - (\frac{4\delta}{3} + \frac{2\delta}{3}) = 1 - 2\delta$ over data.

Notice that if $\omega \in \Omega$ is such that

$$\forall \theta \in \Theta, t = 0, \dots, N-1 : \quad \|\mathbf{y}(t)(\omega) - \hat{\mathbf{y}}_\theta(t)(\omega)\|_2 \leq C, \|\mathbf{y}(t)(\omega) - \hat{\mathbf{y}}_\theta(t | 0)(\omega)\|_2 \leq C$$

then $\ell_C(\mathbf{y}(t)(\omega), \hat{\mathbf{y}}_\theta(t | 0)(\omega)) = \|\mathbf{y}(t)(\omega) - \hat{\mathbf{y}}_\theta(t | 0)(\omega)\|_2^2$ and hence

$$\hat{\mathcal{L}}_N(\theta)(\omega) = {}^C\hat{\mathcal{L}}_N(\theta)(\omega)$$

Therefore, the event defined by (61) equals the event defined by

$$\begin{aligned} \forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} {}^C\mathcal{L}(\theta) &\leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\text{KL}(\rho \| \pi) + \ln \frac{3}{2\delta} + \right. \\ &\left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right) \end{aligned}$$
 (62)

and

$$\forall \theta \in \Theta, \forall t = 0, \dots, N-1 : \quad \|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \leq C, \|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t | 0)\|_2 \leq C$$

For $\epsilon = -1$ we will show (62) implies

$$\begin{aligned} \forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) &\leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\text{KL}(\rho \| \pi) + \ln \frac{3}{2\delta} + \right. \\ &\left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right) \end{aligned}$$
 (63)

and as (62) holds with probability at least $1 - 2\delta$, it follows that (63) also holds with probability at least $1 - 2\delta$. To this end, notice that

$$\begin{aligned}\mathcal{L}(\theta) &= \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2] = \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \leq C)] + \\ &\quad \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)]\end{aligned}\quad (64)$$

and that $\mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)] \geq C^2 \mathbf{P}(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)$. Hence

$$\begin{aligned}\mathcal{L}(\theta) &\geq \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \leq C)] + C^2 \mathbf{P}(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C) \\ &= \mathbf{E}[\ell_C(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t))] = {}^C \mathcal{L}(\theta)\end{aligned}\quad (65)$$

i.e., $\epsilon \mathcal{L}(\theta) \leq \epsilon^C \mathcal{L}(\theta)$ for $\epsilon = -1$, from which it follows that (62) implies (63).

For $\epsilon = 1$, we will show that (62) implies

$$\begin{aligned}\forall \rho \in \mathcal{M}_\pi : \epsilon E_{\theta \sim \rho} \mathcal{L}(\theta) &\leq \epsilon E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} + \frac{1}{\lambda} \left(\text{KL}(\rho \|\pi) + \ln \frac{3}{2\delta} + \right. \\ &\quad \left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right)\end{aligned}\quad (66)$$

First note that

$$\frac{72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} = \frac{1}{\lambda} \ln \left(\exp \left(\lambda \frac{72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} \right) \right)$$

and hence after algebraic manipulations

$$\begin{aligned}&\frac{72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} + \frac{1}{\lambda} \left(\text{KL}(\rho \|\pi) + \ln \frac{3}{2\delta} + \right. \\ &\quad \left. \frac{1}{2} \left(\ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_1(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\bar{\mathcal{C}}_2(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)) \right) \right) = \\ &\quad \frac{1}{\lambda} \left(\text{KL}(\rho \|\pi) + \ln \frac{3}{2\delta} + \frac{1}{2} (\ln E_{\theta \sim \pi} \exp(\mathcal{C}_1(2\lambda, \theta, N, \delta, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\mathcal{C}_2(2\lambda, \theta, N, \delta, \epsilon))) \right)\end{aligned}$$

where for $i = 1, 2$,

$$\mathcal{C}_i(\lambda, \theta, N, \delta, \epsilon) = \lambda \frac{72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \ln\left(\frac{3N^2}{2\delta}\right)}{N} + \mathcal{C}_{ub,i}(\lambda, \theta, 12G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln\left(\frac{3N^2}{2\delta}\right)}, N)$$

To show that (62) implies (66), notice that

$$\begin{aligned}\mathcal{L}(\theta) &= \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2] = \\ &\mathbf{E}[\ell_C(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t)) \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 \leq C)] + \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)] \leq \\ &\mathbf{E}[\ell_C(\mathbf{y}(t), \hat{\mathbf{y}}_\theta(t))] + \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)] \\ &= {}^C \mathcal{L}(\theta) + \mathbf{E}[\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2^2 \chi(\|\mathbf{y}(t) - \hat{\mathbf{y}}_\theta(t)\|_2 > C)]\end{aligned}\quad (67)$$

Using (57) it follows that

$$\mathcal{L}(\theta) \leq {}^C \mathcal{L}(\theta) + 72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln\left(\frac{3N^2}{2\delta}\right)}{N}\quad (68)$$

Hence, by adding $72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln\left(\frac{3N^2}{2\delta}\right)}{N}$ to both sides of the inequality (62), it follows that (66) is implied by (62). Combining the two case it follows that for quadratic loss and $\epsilon \in \{-1, 1\}$, the inequality (8) also holds with probability at least $1 - 2\delta$ over data. $\square$

We will conclude by presenting the proof of Lemma C.18-C.19. To this end, we need the following technical result.

Lemma C.20. *Let $\mathbf{I}$ be an index set, $\{\beta_{i,t}(k)\}_{k=0}^\infty$, $i \in \mathbf{I}$, be a sequence of matrices such that $\|\bar{\beta}\|_{\ell_1} < \infty$, where $\bar{\beta}(k) = \sup_{i \in \mathbf{I}, t \in \mathbb{Z}} \|\beta_{i,t}(k)\|_2$, and let $\mathbf{z}_i(t) = (\beta_{i,t} \star \mathbf{e}_g)(t)$. Then $\|\mathbf{z}_i(t)\|_2$, $i \in \mathbf{I}$ and $\mathbf{z}(t) = \sup_{i \in \mathbf{I}} \|\mathbf{z}_i(t)\|_2$ are sub-Gaussian with sub-Gaussian norm*

$$\|\mathbf{z}_i(t)\|_2 \|_{\psi_2} \leq \|\mathbf{z}(t)\|_{\psi_2} \leq 6 \|\bar{\beta}\|_{\ell_1} \|\mathbf{e}_g\|_{\psi_2} \quad (69)$$

and the moments and the moment generating function of $\mathbf{z}^2(t) = \sup_{i \in \mathbf{I}} \|\mathbf{z}_i(t)\|_2^2$ satisfy

$$\mathbf{E}[\mathbf{z}^{2r}(t)] \leq \|\bar{\beta}\|_{\ell_1}^{2r} (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} 2r! \quad (70)$$

$$\mathbf{E}[e^{\lambda \mathbf{z}^2(t)}] \leq \frac{1 + \lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2}{1 - \lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2}, \quad |\lambda| < \frac{1}{\|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2} \quad (71)$$

Moreover, for any $C > 0$,

$$\mathbf{E}[\|\mathbf{z}_i(t)\|_2^2 \chi(\|\mathbf{z}_i(t)\|_2^2 > C^2)] \leq \frac{2C^2}{e^{\frac{C^2}{(6 \|\bar{\beta}\|_{\ell_1} \|\mathbf{e}_g\|_{\psi_2})^2}} - 1} \quad (72)$$

Proof Lemma C.20. Notice that

$$\begin{aligned} \mathbf{z}(t) &= \sup_{i \in \mathbf{I}} \left\| \sum_{k=0}^{\infty} \beta_{i,t}(k) \mathbf{e}_g(t-k) \right\|_2 \\ &\leq \sup_{i \in \mathbf{I}} \sum_{k=0}^{\infty} \|\beta_{i,t}(k)\|_2 \|\mathbf{e}_g(t-k)\|_2 \leq \sum_{k=0}^{\infty} \|\bar{\beta}(k)\|_2 \|\mathbf{e}_g(t-k)\|_2 \end{aligned}$$

Hence, for any $r \geq 1$, by using the arithmetic-geometric mean inequality we get $a_1 \cdots a_k \leq \frac{1}{k} \sum_{i=1}^k a_i^k$, $a_1, \dots, a_k \geq 0$,

$$\begin{aligned} \mathbf{z}^{2r}(t) &\leq \left(\sum_{k=0}^{\infty} \|\bar{\beta}(k)\|_2 \|\mathbf{e}_g(t-k)\|_2 \right)^{2r} = \sum_{k_1, \dots, k_{2r}=0}^{\infty} \prod_{j=1}^{2r} \|\bar{\beta}(k_j)\|_2 \|\mathbf{e}_g(t-k_j)\|_2 \leq \\ &\sum_{k_1, \dots, k_{2r}=0}^{\infty} \frac{1}{2r} \left(\sum_{j=1}^{2r} \|\bar{\beta}(k_j)\|_2^{2r} \right) \frac{1}{2r} \sum_{j=1}^{2r} \|\mathbf{e}_g(t-k_j)\|_2^{2r} \end{aligned}$$

By taking expectations, using the fact that $\|\mathbf{e}_g(t)\|_2$ is sub-Gaussian, and the proof of [43, Proposition 2.6.1] we obtain

$$\mathbf{E}[\|\mathbf{e}_g(t-k_j)\|_2^{2r}] = \mathbf{E}[\|\mathbf{e}_g(t)\|_2^{2r}] \leq 2r(r-1)! (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} = 2r! (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} \quad (73)$$

it follows that

$$\begin{aligned} \mathbf{E}[\mathbf{z}^{2r}(t)] &\leq \sum_{k_1, \dots, k_{2r}=0}^{\infty} \left(\sum_{j=1}^{2r} \|\bar{\beta}(k_j)\|_2^{2r} \right) \frac{1}{2r} \sum_{j=1}^{2r} \mathbf{E}[\|\mathbf{e}_g(t-k_j)\|_2^{2r}] = \\ &\sum_{k_1, \dots, k_{2r}=0}^{\infty} \left(\sum_{j=1}^{2r} \|\bar{\beta}(k_j)\|_2^{2r} \right) \mathbf{E}[\|\mathbf{e}_g(t)\|_2^{2r}] \leq \sum_{k_1, \dots, k_{2r}=0}^{\infty} \left(\sum_{j=1}^{2r} \|\bar{\beta}(k_j)\|_2^{2r} \right) 2r! (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} = \\ &\left(\sum_{k=0}^{\infty} \|\bar{\beta}(k)\|_2 \right)^{2r} 2r! (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} = \|\bar{\beta}\|_{\ell_1}^{2r} 2r! (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} \end{aligned}$$

i.e., (70) holds. By noticing that

$$\begin{aligned} \mathbf{E}[e^{\lambda \mathbf{z}^2(t)}] &= 1 + \sum_{r=1}^{\infty} \frac{\lambda^r \mathbf{E}[\mathbf{z}^{2r}(t)]}{r!} \leq 1 + \sum_{r=1}^{\infty} \frac{\lambda^r \|\bar{\beta}\|_{\ell_1}^{2r} (3 \|\mathbf{e}_g\|_{\psi_2})^{2r} 2r!}{r!} = \\ &1 + 2\lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2 \sum_{r=0}^{\infty} (\lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2)^r = 1 + \frac{2\lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2}{1 - \lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2} = \\ &\frac{1 + \lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2}{1 - \lambda \|\bar{\beta}\|_{\ell_1}^2 (3 \|\mathbf{e}_g\|_{\psi_2})^2} \end{aligned}$$

it follows that (71) holds. Finally, for $\lambda = \frac{1}{4\|\bar{\beta}\|_{\ell_1}^2(3\|\mathbf{e}_g\|_{\psi_2})^2}$, the bound becomes

$$\mathbf{E}[e^{\lambda \mathbf{z}^2(t)}] \leq \frac{1 + \frac{1}{4}}{1 - \frac{1}{4}} = \frac{5/4}{3/4} = \frac{5}{3} \leq 2$$

from which by the definition of sub-Gaussian norm of $\mathbf{z}(t)$ it follows

$$\|\mathbf{z}(t)\|_{\psi_2} \leq \sqrt{\frac{1}{\lambda}} = 6\|\bar{\beta}\|_{\ell_1}\|\mathbf{e}_g\|_{\psi_2}$$

i.e., (69) holds. In particular, the sub-Gaussian norm of $\mathbf{z}(t)$ is bounded and hence by [43, Proposition 2.6.1] $\mathbf{z}(t)$ is sub-Gaussian. Moreover, as $\mathbf{z}^2(t) \geq \|\mathbf{z}_i(t)\|_2^2$, it follows that the sub-Gaussian norm of $\|\mathbf{z}_i(t)\|_2$ is also bounded and it is also sub-Gaussian.

Finally, from Lemma C.14 applied to $\|\mathbf{z}_i(t)\|_2$ it follows that

$$\mathbf{E}[\|\mathbf{z}_i(t)\|_2^2 \chi(\|\mathbf{z}_i(t)\|_2^2 > C^2)] \leq \frac{\mathbf{E}[e^{\bar{\lambda}\|\mathbf{z}_i(t)\|_2^2}]C^2}{e^{C^2\bar{\lambda}} - 1} \quad (74)$$

if $\bar{\lambda}$ is such that the moment generating function $\mathbf{E}[e^{s\|\mathbf{z}_i(t)\|_2^2}]$ is well-defined on $[0, \bar{\lambda}]$. Note that $\|\mathbf{z}_i(t)\|_2^2 \leq \mathbf{z}^2(t)$ and hence $\mathbf{E}[e^{s\|\mathbf{z}_i(t)\|_2^2}] \leq \mathbf{E}[e^{s\mathbf{z}^2(t)}]$. Now $\bar{\lambda}$ can be chosen as $\bar{\lambda} = \frac{1}{4\|\bar{\beta}\|_{\ell_1}^2(3\|\mathbf{e}_g\|_{\psi_2})^2}$ and hence $\mathbf{E}[e^{\bar{\lambda}\|\mathbf{z}_i(t)\|_2^2}] \leq \mathbf{E}[e^{\bar{\lambda}\mathbf{z}^2(t)}] \leq 2$. Combining (74) and the bound on $\mathbf{E}[e^{\bar{\lambda}\|\mathbf{z}_i(t)\|_2^2}]$, we obtain (72). $\square$

Proof of Lemma C.18. Let $\mathbb{I} = \Theta \times \{1, 2\}$, $\mathbf{z}_{(\theta,1)}(t) = \mathbf{y}(t) - \mathbf{y}_\theta(t)$, $\mathbf{z}_{(\theta,2)}(t) = \mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)$, $\beta_{(\theta,1),t} = \alpha_{g,y} - c_\theta$, and $\beta_{(\theta,2),t} = \alpha_{g,y} - c_{\theta,t}$. Note that from the proof of Lemma B.3 it follows that

$$\begin{aligned} \|(\alpha_{g,y} + c_\theta)(k)\|_2 &\leq \|\alpha_{g,y}(k)\|_2 + \sum_{l=0}^k \|\alpha_\theta(l)\|_2 \|\alpha_{g,w}(k-l)\|_2 \\ &\leq \|\alpha_{g,y}(k)\|_2 + \sum_{l=0}^k \bar{\alpha}(l) \|\alpha_{g,w}(k-l)\|_2 \\ \|(\alpha_{g,y} + c_{\theta,t})(k)\|_2 &\leq \|\alpha_{g,y}(k)\|_2 + \sum_{l=0}^{\min\{k,t\}} \|\alpha_\theta(l)\|_2 \|\alpha_{g,w}(k-l)\|_2 \\ &\leq \|\alpha_{g,y}(k)\|_2 + \sum_{l=0}^k \bar{\alpha}(l) \|\alpha_{g,w}(k-l)\|_2. \end{aligned}$$

Hence $\bar{\beta}(k) = \sup_{i \in \mathbb{I}} \|\beta_{i,t}(k)\|_2 \leq \|\alpha_{g,y}(k)\|_2 + \sum_{l=0}^k \bar{\alpha}(l) \|\alpha_{g,w}(k-l)\|_2$ and

$$\|\bar{\beta}\|_{\ell_1} \leq \sum_{k=0}^{\infty} \|\alpha_{g,y}(k)\|_2 + \sum_{k=0}^{\infty} \sum_{l=0}^k \bar{\alpha}(l) \|\alpha_{g,w}(k-l)\|_2 \leq \|\alpha_g\|_{\ell_1} + \|\bar{\alpha}\|_{\ell_1} \|\alpha_g\|_{\ell_1} = G_e$$

From this and Lemma C.20 and Lemma B.3 it follows that for any $t = 0, \dots, N-1$ $\sup_{\theta \in \Theta} \max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2\}$ are sub-Gaussian random variable whose sub-Gaussian norms are upper bounded by $6G_e\|\mathbf{e}_g\|_{\psi_2}$. Hence, using the sub-Gaussian tail bound (proof of (iii) $\implies$ (i) in [43, Proposition 2.6.1]), we obtain the desired result

$$\begin{aligned} \mathbf{P} \left(\sup_{\theta \in \Theta} \max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_2\} \geq 6G_e\|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln\left(\frac{3N^2}{2\delta}\right)} \right) &\leq \\ &= 2e^{-\ln\left(\frac{3N^2}{2\delta}\right)} = \frac{2}{N} \frac{2\delta}{3N} \leq \frac{2\delta}{3N} \end{aligned}$$

Therefore, by applying a union bound over $t = 0, \dots, N-1$, the first inequality (56) of the lemma follows.

In order to obtain the second inequality, we use (72), and notice that

$$\begin{aligned} \frac{2C^2}{e^{\frac{C^2}{(6G_e\|\mathbf{e}_g\|_{\psi_2})^2}} - 1} &= \frac{2(6G_e\|\mathbf{e}_g\|_{\psi_2})^2 \ln(\frac{3N^2}{2\delta})}{e^{\ln(\frac{3N^2}{2\delta})} - 1} = \frac{2(6G_e\|\mathbf{e}_g\|_{\psi_2})^2 \ln(\frac{3N^2}{2\delta})2\delta}{3N^2 - 2\delta} \\ &\leq 72G_e^2\|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln(\frac{3N^2}{2\delta})}{N} \end{aligned}$$

where we used that $2\delta \leq 1$, $3N^2 - 2\delta \geq N^2 \geq N$, i.e., (57). $\square$

Proof of Lemma C.19. Notice that

$$|\ell_C(y_1, \hat{y}_1) - \ell_C(y_2, \hat{y}_2)| = \begin{cases} \left| \|y_1 - \hat{y}_1\|_2^2 - \|y_2 - \hat{y}_2\|_2^2 \right| & \|y_1 - \hat{y}_1\|_2^2 \leq C^2, \quad \|y_2 - \hat{y}_2\|_2^2 \leq C^2 \\ \left| \|y_2 - \hat{y}_2\|_2^2 - C^2 \right| & \|y_1 - \hat{y}_1\|_2^2 > C^2, \quad \|y_2 - \hat{y}_2\|_2^2 \leq C^2 \\ \left| \|y_1 - \hat{y}_1\|_2^2 - C^2 \right| & \|y_2 - \hat{y}_2\|_2^2 > C^2, \quad \|y_1 - \hat{y}_1\|_2^2 \leq C^2 \\ 0 & \|y_1 - \hat{y}_1\|_2^2 > C^2, \quad \|y_2 - \hat{y}_2\|_2^2 > C^2 \end{cases} \quad (75)$$

For each of the cases above we will show that the right-hand side of (75) is bounded by $2C(\|y_1 - y_2\|_2 + \|\hat{y}_1 - \hat{y}_2\|_2)$.

First, consider the case when $\|y_1 - \hat{y}_1\|_2^2 \leq C^2$ and $\|y_2 - \hat{y}_2\|_2^2 \leq C^2$. Then by repeated use of the triangle inequality,

$$\begin{aligned} \left| \|y_1 - \hat{y}_1\|_2^2 - \|y_2 - \hat{y}_2\|_2^2 \right| &= \left| \|y_1 - \hat{y}_1\|_2 - \|y_2 - \hat{y}_2\|_2 \right| (\|y_1 - \hat{y}_1\|_2 + \|y_2 - \hat{y}_2\|_2) \\ &\leq \|(y_1 - y_2) - (\hat{y}_1 - \hat{y}_2)\|_2 (2C) \leq 2C(\|y_1 - y_2\|_2 + \|\hat{y}_1 - \hat{y}_2\|_2) \end{aligned}$$

Consider the case when $\|y_1 - \hat{y}_1\|_2^2 > C^2$, $\|y_2 - \hat{y}_2\|_2^2 \leq C^2$. Then by the definition of ℓ_C ,

$$\begin{aligned} |\ell_C(y_1, \hat{y}_1) - \ell_C(y_2, \hat{y}_2)| &= |C^2 - \|y_2 - \hat{y}_2\|_2^2| = \\ &= (C - \|y_2 - \hat{y}_2\|_2)(\|y_2 - \hat{y}_2\|_2 + C) \leq (C - \|y_2 - \hat{y}_2\|_2)2C \leq \\ &= 2C(\|y_1 - \hat{y}_1\|_2 - \|y_2 - \hat{y}_2\|_2) = 2C\|(y_2 - y_1) - (\hat{y}_2 - \hat{y}_1)\|_2 \leq 2C(\|y_1 - y_2\|_2 + \|\hat{y}_1 - \hat{y}_2\|_2) \end{aligned}$$

The case when $\|y_2 - \hat{y}_2\|_2^2 > C^2$, $\|y_1 - \hat{y}_1\|_2^2 \leq C^2$ is symmetric.

Finally, consider the case when $\|y_1 - \hat{y}_1\|_2^2 > C^2$, $\|y_2 - \hat{y}_2\|_2^2 > C^2$. Then by the definition of ℓ_C ,

$$|\ell_C(y_1, \hat{y}_1) - \ell_C(y_2, \hat{y}_2)| = |C^2 - C^2| = 0 \leq 2C(\|y_1 - y_2\|_2 + \|\hat{y}_1 - \hat{y}_2\|_2)$$

This completes the proof. $\square$

C.4 Proof of Corollary 3.2

The corollary follows from Theorem 3.1 by choosing λ as follows:

$$\lambda = \frac{\sqrt{N}}{L(\ln(N))^r} = \begin{cases} \frac{\sqrt{N}}{16L_\ell \ln(N)} & \mathbf{e}_g \text{ is bounded} \\ \frac{\sqrt{N}}{192G_e\|\mathbf{e}_g\|_{\psi_2}\sqrt{1+\ln(\frac{3}{2\delta})}(\ln(N))^{3/2}} & \ell \text{ is } L_\ell\text{-Lipschitz} \\ \frac{\sqrt{N}}{192G_e\|\mathbf{e}_g\|_{\psi_2}\sqrt{1+\ln(\frac{3}{2\delta})}(\ln(N))^{3/2}} & \ell \text{ is quadratic} \end{cases} \quad (76)$$

and upper bounding the right-hand side of (8), i.e., by showing that

$$\frac{1}{2} (\ln E_{\theta \sim \pi} \exp(C_1(\lambda, \theta, N, \delta, \epsilon)) + \ln E_{\theta \sim \pi} \exp(C_2(\lambda, \theta, N, \delta, \epsilon))) \leq \mathcal{C}(\delta, \epsilon) \quad (77)$$

To this end, note that from Lemma B.3

$$\|\alpha_\theta\|_{\ell_1} \leq \|\bar{\alpha}\|_{\ell_1}, \quad \theta_\infty(\alpha_\theta) \leq \theta_\infty(\bar{\alpha}), \quad G_e(\theta) \leq G_e, \quad G_{e,1}(\theta) \leq G_{e,1} \quad (78)$$

In addition, notice that the functions $\mathcal{C}_{m,b,i}(\lambda, \alpha, X, L, c)$ has the following property; if $\lambda \leq \bar{\lambda}\sqrt{N}$, $L_1 \leq L_2$, $X_1 \leq X_2$, $c_1 \leq c_2$, and $\|\alpha(k)\|_2 \leq \|\beta(k)\|_2$ for all $k \in \mathbb{N}$, then

$$\mathcal{C}_{m,b,i}(\lambda, \alpha, X_1, L_1, c_1) \leq N\mathcal{C}_{m,b,i}(\bar{\lambda}, \beta, X_2, L_2, c_2) \quad (79)$$

Bounded case Note that $L(\theta) \leq L_b$, any by using by using (78), it follows that $\|\alpha_\theta(k)\|_2 \leq \bar{\alpha}(k) = \|\bar{\alpha}(k)\|_2$, $G_e(\theta) \leq G_e$, $G_{e,1}(\theta) \leq G_{e,1}$, and hence, by using (79), it follows that for all $i = 1, 2$

$$\mathcal{C}_i(2\lambda, \theta, N, \delta, \epsilon) = \frac{\mathcal{C}_{m,b,i}(N, \alpha_\theta, G_e(\theta) + 2G_{e,1}(\theta), L(\theta), c_e)}{N} \leq \mathcal{C}_{m,b,i}(1, \bar{\alpha}, G_e + 2G_{e,1}, L_b, c_e)$$

Hence for $i = 1, 2$,

$$\begin{aligned} \ln E_{\theta \sim \pi} \exp(\mathcal{C}_i(2\lambda, \theta, N, \delta, \epsilon)) &\leq \ln E_{\theta \sim \pi} \exp(\mathcal{C}_{b,m,i}(2, \bar{\alpha}, G_e + 2G_{e,1}, L_b, c_e)) \\ &= \mathcal{C}_{b,m,i}(2, \bar{\alpha}, G_e + 2G_{e,1}, L_b, c_e) \end{aligned}$$

and hence (77).

Lipschitz loss case: First, notice that for $N \geq 2$, $\ln(N) \geq 1$ and hence

$$\begin{aligned} \bar{\mathcal{C}}_{ub}(2\lambda, L_\ell, N) &= \frac{1}{N} \left(\frac{2\sqrt{N}}{16L_\ell \ln(N)} \right)^2 (32L_\ell^2 C_{u,1}) + 4 \frac{1}{N} \frac{2\sqrt{N}}{16L_\ell \ln(N)} L_\ell C_{u,2} \ln(N) \\ &= \frac{1}{2\ln(N)^2} C_{u,1} + \frac{1}{2} C_{u,2} \frac{1}{\sqrt{N}} \leq C_{u,1} + C_{u,2} \end{aligned} \quad (80)$$

Moreover, using (79),

$$\begin{aligned} \mathcal{C}_{b,i}(2\lambda, \theta, L_\ell, \frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K}, N) &= \mathcal{C}_{b,i}(\frac{2\sqrt{N}}{16L_\ell \ln(N)}, \theta, L_\ell, \frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K}, N) \\ &= \frac{\mathcal{C}_{b,m,i}(\frac{2}{16L_\ell} \frac{\sqrt{N}}{\ln(N)}, \alpha_\theta, G_\theta + 2G_{e,1}(\theta), L_\ell, \frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K})}{N} \\ &\leq \mathcal{C}_{b,m,i}(\frac{1}{8L_\ell \ln(N)}, \bar{\alpha}, G_e + 2G_{e,1}, L_\ell, \frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K}) \\ &= \begin{cases} \frac{1}{8L_\ell \ln(N)} L_\ell \frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K} \sqrt{n_e} \theta_\infty(\bar{\alpha}) \|\alpha_g\|_{\ell_1} & i = 1 \\ \frac{1}{(8L_\ell \ln(N))^2} \frac{L_\ell^2}{2} (G_e + 2G_{e,1}) \left(\frac{2\ln(N)}{\|\alpha_g\|_{\ell_1} K} \right)^2 n_e & i = 2 \end{cases} \\ &= \begin{cases} \frac{1}{4K} \sqrt{n_e} \theta_\infty(\bar{\alpha}) & i = 1 \\ \frac{1}{16} \frac{(G_e + 2G_{e,1})}{2} \left(\frac{1}{\|\alpha_g\|_{\ell_1} K} \right)^2 n_e & i = 2 \end{cases} \\ &\leq \mathcal{C}_{b,m,i}(\frac{1}{4}, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K}) \end{aligned} \quad (81)$$

From this it then follows that

$$\mathcal{C}_{ub,i}(\frac{2}{16L_\ell} \frac{\sqrt{N}}{\ln(N)}, \theta, L_\ell, N) \leq C_{u,1} + C_{u,2} + \frac{1}{2} \mathcal{C}_{b,m,i}(\frac{1}{4}, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K}) \quad (82)$$

and hence

$$\begin{aligned} &\frac{1}{2} (\ln E_{\theta \sim \pi} \exp(\mathcal{C}_1(2\lambda, \theta, N, \delta, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\mathcal{C}_2(2\lambda, \theta, N, \delta, \epsilon))) \\ &\leq \frac{1}{2} \sum_{i=1}^2 \left(C_{u,1} + C_{u,2} + \frac{1}{2} \mathcal{C}_{b,m,i}(1/4, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K}) \right) = \mathcal{C}(\delta, \epsilon) \end{aligned}$$

so (77) holds.

Quadratic loss case: Notice that as $N^2 \geq 4$, it follows that $\ln(N^2) \geq 1$, and hence

$$\ln \left(\frac{3N^2}{2\delta} \right) = \left(\ln(N^2) + \ln \left(\frac{3}{2\delta} \right) \right) \leq \ln(N^2) \left(1 + \ln \left(\frac{3}{2\delta} \right) \right) \quad (83)$$

By using (83) and applying (82) with $L_\ell = \frac{L(\ln(N))^{1/2}}{16}$ and noticing that $\lambda = \frac{\sqrt{N}}{16L_\ell \ln(N)}$ it follows that

$$\begin{aligned} \mathcal{C}_{ub,i}(2\lambda, \theta, 12G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln\left(\frac{3N^2}{2\delta}\right)}, N) &\leq \mathcal{C}_{ub,i}(2\lambda, \theta, \frac{L(\ln(N))^{1/2}}{16}, N) \\ &\leq C_{u,1} + C_{u,2} + \frac{1}{2}\mathcal{C}_{b,m,i}\left(1/4, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_{\ell_1} K}\right) \end{aligned} \quad (84)$$

Moreover, from (83) and the fact that $\ln(N) \geq 1$ and $\ln\left(\frac{3N^2}{2\delta}\right) \geq 1$, it follows that

$$\begin{aligned} &2\lambda \frac{\ln\left(\frac{3N^2}{2\delta}\right)}{N} 72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \max\{0, \epsilon\} \\ &= \frac{2\sqrt{N}}{192G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{2\ln(N)} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{\ln(N)}} (72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \max\{0, \epsilon\}) \frac{\ln\left(\frac{3N^2}{2\delta}\right)}{N} \\ &\leq \frac{2\sqrt{N}}{192G_e \|\mathbf{e}_g\|_{\psi_2} \ln(N) \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{\ln(N^2)}} (72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \max\{0, \epsilon\}) \frac{(1 + \ln\left(\frac{3}{2\delta}\right)) \ln(N^2)}{N} \\ &= \frac{2 \cdot 72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \max\{0, \epsilon\} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{\ln(N^2)}}{192G_e \|\mathbf{e}_g\|_{\psi_2} \ln(N) \sqrt{N}} \\ &= \frac{6}{16} \frac{2G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{2(\ln(N))^{1/2}} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \max\{0, \epsilon\}}{\ln(N) \sqrt{N}} \\ &= \frac{6}{8 \cdot 192} \frac{L(\ln(N))^{1/2}}{\sqrt{N} \ln(N)} \max\{0, \epsilon\} \\ &= \frac{1}{128} \frac{L}{\sqrt{N}(\ln(N))^{1/2}} \max\{0, \epsilon\} \end{aligned} \quad (85)$$

Hence, for $i = 1, 2$,

$$\begin{aligned} \mathcal{C}_i(2\lambda, \theta, N, \delta, \epsilon) &\leq \frac{L}{128} \max\{0, \epsilon\} + \\ &\quad C_{u,1} + C_{u,2} + \frac{1}{2}\mathcal{C}_{b,m,i}\left(1/4, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_2 K}\right) \end{aligned}$$

and thus

$$\begin{aligned} &\frac{1}{2} (\ln E_{\theta \sim \pi} \exp(\mathcal{C}_1(\lambda, \theta, N, \delta, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\mathcal{C}_2(\lambda, \theta, N, \delta, \epsilon))) \\ &\leq \frac{L}{128} \max\{0, \epsilon\} + \frac{1}{2} \sum_{i=1}^2 \left(C_{u,1} + C_{u,2} + \frac{1}{2}\mathcal{C}_{b,m,i}\left(1/4, \bar{\alpha}, G_e + 2G_{e,1}, 1, \frac{1}{\|\alpha_g\|_2 K}\right) \right) \\ &= \mathcal{C}(\delta, \epsilon) \end{aligned}$$

which completes the proof.

C.5 Uniform bounds derived from Corollary 3.2

In order to present the uniform bounds, we need the following assumptions from Assumption 3.3: **(LipModel)** and either **(Gauss)** or **(Uni)**.

Corollary C.21 (Uniform [PAC bounds, Example 2.1,2.2 [2]]). *With the Assumption **(LipModel)** and either **(Gauss)** or **(Uni)** from Assumption 3.3 the following holds. Let $L_\Theta(\delta)$, $\mathcal{C}_{L,emp}$, $\mathcal{C}_{L,true}$, $C(\theta)$, $r_{Lip,1}$, $r_{Lip,2}$ be defined as in Table 1, and let L , C_δ , $\mathcal{C}(\delta, \epsilon)$, r be defined as in Corollary 3.2 For any*

$\delta \in (0, 0.5)$, $\lambda, \sigma > 0$, $N \geq 3$, $\epsilon \in \{-1, 1\}$,

$$\forall \theta \in \Theta : \epsilon \mathcal{L}(\theta) \leq \epsilon \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}_{L,emp} + \mathcal{C}_{L,true} + C(\theta) + \ln \left(\frac{C_\delta}{\delta^{2r_{Lip,1}+1}} \right) + \mathcal{C}(\delta, \epsilon) \right) \quad (86)$$

holds with probability at least $1 - (2 + r_{Lip,1})\delta$ over data.

The proof of Corollary C.21 is based on a number of technical lemmas, which will also be used for the proof of Corollary 3.4.

Lemma C.22 (KL divergence). *Assume that either **(Gauss)** or **(Uni)** holds. For every $\theta \in \Theta$, define the density ρ_θ as follows*

$$\rho_\theta = \begin{cases} \mathcal{N}(\theta, \frac{\sigma^2}{N}I) & \text{if **(Gauss)** holds} \\ \mathcal{U}(\theta, \frac{\sigma}{\sqrt{N}}I) & \text{if **(Uni)** holds} \end{cases}$$

where $\mathcal{N}(m, \sigma^2 I)$ denotes the Gaussian distribution with mean m and variance $\sigma^2 I$, and $\mathcal{U}(m, r)$ denotes the uniform distribution on the ball with center in m and radius r . Then for $N \geq 3$,

$$\text{KL}(\rho_\theta \mid \pi) \leq C(\theta) \ln(N)$$

Proof of Lemma C.22. If **(Gauss)** holds, then using KL divergence for Gaussian densities ([25, Lemma 11.3.4]) it follows that

$$\begin{aligned} \text{KL}(\rho_\theta \mid \pi) &= \frac{1}{2} \left(\text{trace} \left(\frac{\sigma^2}{N} P^{-1} \right) + (\theta_m - \theta)^T P^{-1} (\theta_m - \theta) - n_\theta + \ln \frac{\det(P) N^{n_\theta}}{\sigma^{2n_\theta}} \right) \\ &= \frac{1}{2} \left(\text{trace} \left(\frac{\sigma^2}{N} P^{-1} \right) + (\theta_m - \theta)^T P^{-1} (\theta_m - \theta) - n_\theta + \ln \frac{\det(P)}{\sigma^{2n_\theta}} + n_\theta \ln(N) \right) \\ &\leq \ln(N) C(\theta) \end{aligned}$$

where we used the fact that $\ln(N) \geq 1$ and $\frac{1}{N} \leq 1$ if $N \geq 3$. Likewise, if **(Uni)** holds, and we denote by C_2 the volume of the ball of radius $\frac{\sigma}{\sqrt{N}}$ centered at $\tilde{\theta}$, then

$$\begin{aligned} \text{KL}(\rho_\theta \mid \pi) &= \int_{\|\tilde{\theta} - \theta\|_2 \leq \frac{\sigma}{\sqrt{N}}} \ln \left(\frac{\rho_\theta(\tilde{\theta})}{\pi(\tilde{\theta})} \right) \frac{1}{C_2} dm(\tilde{\theta}) \\ &= \int_{\|\tilde{\theta} - \theta\|_2 \leq \frac{\sigma}{\sqrt{N}}} \frac{1}{C_2} \ln \left(\frac{\text{vol}(\Theta)}{C_2} \right) dm(\tilde{\theta}) = \ln \left(\frac{\text{vol}(\Theta)}{C_2} \right) \end{aligned}$$

From the formula for the volume of a high-dimensional ball [40] it follows that

$$C_2 = \frac{\pi^{n_\theta/2}}{\Gamma(n_\theta/2 + 1)} \left(\frac{\sigma}{\sqrt{N}} \right)^{n_\theta}$$

and hence

$$\begin{aligned} \text{KL}(\rho_\theta \mid \pi) &= \ln \left(\frac{\text{vol}(\Theta)}{C_2} \right) = \ln \left(\frac{\text{vol}(\Theta)}{\frac{\pi^{n_\theta/2}}{\Gamma(n_\theta/2 + 1)} \left(\frac{\sigma}{\sqrt{N}} \right)^{n_\theta}} \right) \\ &= \ln \left(\frac{\text{vol}(\Theta) \Gamma(n_\theta/2 + 1)}{\pi^{n_\theta/2} (\sigma)^{n_\theta}} \right) + \ln \left((\sqrt{N})^{n_\theta} \right) \\ &= \ln \left(\frac{\text{vol}(\Theta) \Gamma(n_\theta/2 + 1)}{\sqrt{\pi} \sigma^{n_\theta}} \right) + \frac{n_\theta}{2} \ln(N) \leq C(\theta) \ln(N) \end{aligned}$$

□

Another ingredient is the following:

Lemma C.23 (Lipschitz continuity of the true and empirical errors). *Using the constants defined in Corollary 3.2-C.21, the following inequality holds*

$$\begin{aligned} \forall \theta_1, \theta_2 \in \Theta : \\ |\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| \leq L_\Theta(\delta) L(\ln(N))^r \|\theta_1 - \theta_2\|_2 + \\ 2r_{Lip,1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right), \end{aligned} \quad (87)$$

with probability $1 - r_{Lip,1}\delta$ over data, where

$$r_{Lip,1} = \begin{cases} 0 & \mathbf{e}_g \text{ is bounded} \\ 1 & \text{otherwise} \end{cases}$$

and

$$\begin{aligned} \forall \theta_1, \theta_2 \in \Theta : \\ |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \leq L_\Theta(\delta) L(\ln(N))^r \|\theta_1 - \theta_2\|_2 + 2r_{Lip,1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + \\ 2r_{Lip,2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \end{aligned} \quad (88)$$

where

$$r_{Lip,2} = \begin{cases} 2 & \ell \text{ is quadratic and } \mathbf{e}_g \text{ is unbounded} \\ 0 & \text{otherwise} \end{cases}.$$

Moreover, the inequalities below

(10) from Corollary 3.2 holds, and

$$\begin{aligned} \forall \theta_1, \theta_2 \in \Theta : \\ |\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| \leq L_\Theta(\delta) L(\ln(N))^r \|\theta_1 - \theta_2\|_2 + \\ 2r_{Lip,1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right), \end{aligned} \quad (89)$$

and

$$\begin{aligned} \forall \theta_1, \theta_2 \in \Theta : \\ |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \leq L_\Theta(\delta) L(\ln(N))^r \|\theta_1 - \theta_2\|_2 + 2r_{Lip,1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + \\ 2r_{Lip,2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \end{aligned}$$

hold simultaneously with probability at least $1 - (2 + r_{Lip,1})\delta$.

Proof of Lemma C.23. Bounded noise case: If ℓ is L_ℓ -Lipschitz and $\mathbf{e}_g$ is bounded, then using **(LipModel)** and the argument of the proof from Lemma B.3, it follows that

$$\begin{aligned} |\ell(\mathbf{y}(t), \mathbf{y}_{\theta_1}(t)) - \ell(\mathbf{y}(t), \mathbf{y}_{\theta_2}(t))| &\leq L_\ell \|\mathbf{y}_{\theta_1}(t) - \mathbf{y}_{\theta_2}(t)\|_2 \\ &\leq L_\ell \sum_{k=0}^{\infty} \|c_{\theta_1}(k) - c_{\theta_2}(k)\|_2 \|\mathbf{e}_g(t-k)\|_2 \leq L_\ell \sum_{k=0}^{\infty} \sum_{l=0}^k \|\alpha_{\theta_1}(l) - \alpha_{\theta_2}(l)\|_2 \|\alpha_{g,w}(k-l)\|_2 c_{\mathbf{e}} \sqrt{n_{\mathbf{e}}} \\ &\leq L_\ell \|\alpha_{\theta_1} - \alpha_{\theta_2}\|_{\ell_1} \|\alpha_g\|_{\ell_1} c_{\mathbf{e}} \sqrt{n_{\mathbf{e}}} = \underbrace{L_\alpha L_\ell \|\alpha_g\|_{\ell_1} c_{\mathbf{e}} \sqrt{n_{\mathbf{e}}}}_{L_\Theta(\delta)} \|\theta_1 - \theta_2\|_2 \end{aligned}$$

From this it then follows that

$$|\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \leq L_\Theta(\delta) \|\theta_1 - \theta_2\| \quad \forall \theta_1, \theta_2 \in \Theta \quad (90)$$

$$|\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| \leq L_\Theta(\delta) \|\theta_1 - \theta_2\| \quad \forall \theta_1, \theta_2 \in \Theta \quad (91)$$

By noticing that $r = 0$ and $L = 1$ for the bounded case, the claim of the lemma follows.

Unbounded noise case: Assume that the noise is not necessarily bounded and ℓ is L_ℓ -Lipschitz. From Subsection C.2, recall the definition of truncated empirical and true errors $\hat{\mathcal{L}}_N(\theta)$ and $\bar{\mathcal{L}}(\theta)$, corresponding to the output $\hat{\mathbf{y}}(t)$ and $\bar{\mathbf{y}}_\theta(t)$ and $\bar{\mathbf{y}}_\theta(t \mid 0)$ generated for the truncated noise $\bar{\mathbf{e}}_g(t) = \mathbf{e}_g(t)\chi(\mathbf{e}_g(t) < C)$ for $C = \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}}$. Using Chernoff's inequality and Lemma C.11, it follows that

$$\mathbf{P}(\forall \theta \in \Theta : |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)| > c) \leq \frac{e^{\lambda \frac{1}{2}(\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \mathcal{C}(\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N))}}{e^{\lambda c}} \quad (92)$$

and hence

$$\begin{aligned} \mathbf{P}\left(\forall \theta \in \Theta : |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)| \leq \frac{1}{2\lambda} (\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \right. \\ \left. \mathcal{C}(\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \ln\left(\frac{1}{\delta}\right)\right) \geq 1 - \delta \end{aligned} \quad (93)$$

Similarly, from Lemma C.11 it follows that

$$\forall \theta \in \Theta : |\mathcal{L}(\theta) - \bar{\mathcal{L}}(\theta)| \leq \frac{1}{2\lambda} (\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \mathcal{C}(\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N)) \quad (94)$$

From (43) in Subsection C.2 for $C = \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}}$ it follows that

$$\frac{1}{2} (\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \mathcal{C}(\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N)) = 2\bar{C}_{ub}\left(\frac{\lambda}{8}, L_\ell, N\right)$$

and hence by setting $\lambda = \frac{\sqrt{N}}{16L_\ell \ln(N)}$ it follows that

$$\begin{aligned} \frac{1}{\lambda} \left(\frac{1}{2} (\mathcal{C}(\|\bar{\alpha}\|_{\ell_1}\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N) + \mathcal{C}(\|\alpha_g\|_{\ell_1}, 2L_\ell\lambda, N)) \right) \\ \leq \left(\frac{1}{2}C_{u,1} + \frac{1}{8}C_{u,2} \right) \frac{16L_\ell \ln(N)}{\sqrt{N}} \leq (C_{u,1} + C_{u,2}) \frac{16L_\ell \ln(N)}{\sqrt{N}} \end{aligned} \quad (95)$$

and hence, applying it to (93)-(94) and recalling that $L = 16L_\ell$ results in

$$\begin{aligned} \mathbf{P}\left(\forall \theta \in \Theta : |\hat{\mathcal{L}}_N(\theta) - \bar{\mathcal{L}}_N(\theta)| \leq (C_{u,1} + C_{u,2} + \ln\left(\frac{1}{\delta}\right)) \frac{16L_\ell \ln(N)}{\sqrt{N}}\right) \geq 1 - \delta \\ \forall \theta_1, \theta_2 \in \Theta : |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \leq (C_{u,1} + C_{u,2}) \frac{L \ln(N)}{\sqrt{N}} \end{aligned} \quad (96)$$

Note that (90)-(91) holds for $\bar{\mathcal{L}}_N(\theta)$ and $\hat{\mathcal{L}}_N(\theta)$ with $L_\Theta(\delta) = L_\alpha L_\ell \sqrt{n_\mathbf{e}} \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}}$ and hence by using (96) and the observation

$$\begin{aligned} |\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| &\leq |\hat{\mathcal{L}}_N(\theta_1) - \bar{\mathcal{L}}_N(\theta_1)| + |\bar{\mathcal{L}}_N(\theta_1) - \bar{\mathcal{L}}_N(\theta_2)| + |\bar{\mathcal{L}}_N(\theta_2) - \hat{\mathcal{L}}_N(\theta_2)| \\ |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| &\leq |\mathcal{L}(\theta_1) - \bar{\mathcal{L}}(\theta_1)| + |\bar{\mathcal{L}}(\theta_1) - \bar{\mathcal{L}}(\theta_2)| + |\bar{\mathcal{L}}(\theta_2) - \mathcal{L}(\theta_2)| \end{aligned}$$

it follows

$$\begin{aligned} \mathbf{P}\left(\forall \theta_1, \theta_2 \in \Theta : |\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| \leq 2(C_{u,1} + C_{u,2} + \ln\left(\frac{1}{\delta}\right)) \frac{16L_\ell \ln(N)}{\sqrt{N}} + \right. \\ \left. L_\alpha L_\ell \sqrt{n_\mathbf{e}} \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}} \|\theta_1 - \theta_2\|_2\right) \geq 1 - \delta \\ \forall \theta_1, \theta_2 \in \Theta : |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \\ \leq 2(C_{u,1} + C_{u,2} + \ln\left(\frac{1}{\delta}\right)) \frac{L \ln(N)}{\sqrt{N}} + L_\alpha L_\ell \sqrt{n_\mathbf{e}} \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}} \|\theta_1 - \theta_2\|_2 \end{aligned} \quad (97)$$

Since $L_\alpha L_\ell \sqrt{n_\mathbf{e}} \frac{\ln(N)}{K\|\alpha_g\|_{\ell_1}} = L_\Theta L \ln(N)$ with the definition of L_Θ as in Corollary C.21, (97) can be rewritten as

$$\begin{aligned} \mathbf{P}\left(\forall \theta_1, \theta_2 \in \Theta : |\hat{\mathcal{L}}_N(\theta_1) - \hat{\mathcal{L}}_N(\theta_2)| \leq 2(C_{u,1} + C_{u,2} + \ln\left(\frac{1}{\delta}\right)) \frac{L \ln(N)}{\sqrt{N}} + \right. \\ \left. L_\Theta(\delta) L \ln(N) \|\theta_1 - \theta_2\|_2\right) \geq 1 - \delta \\ \forall \theta_1, \theta_2 \in \Theta : |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \\ \leq 2(C_{u,1} + C_{u,2} + \ln\left(\frac{1}{\delta}\right)) \frac{L \ln(N)}{\sqrt{N}} + L_\Theta(\delta) L \ln(N) \|\theta_1 - \theta_2\|_2 \end{aligned} \quad (98)$$

hence (87)-(88). By using the union bound, and that (10) holds with probability $1 - 2\delta$, (89) follows.

Quadratic case Recall from (58), Subsection C.3 the definition of the loss function ℓ_C and the true and empirical errors ${}^C\mathcal{L}(\theta)$ and ${}^C\mathcal{L}_N(\theta)$. Recall that for $C = 6G_e\|\mathbf{e}_g\|_{\psi_2}\sqrt{\ln(\frac{3N^2}{2\delta})}$.

Recall that by Lemma C.18 that

$$\sup_{t=0,\dots,N-1,\theta\in\Theta} \max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t[0])\|_\infty\} \leq C \quad (99)$$

holds with probability at least $1 - \frac{\delta}{3}$. Also recall that ℓ_C is L_ℓ -Lipschitz with $L_\ell = 12G_e\|\mathbf{e}_g\|_{\psi_2}\sqrt{\ln(\frac{3N^2}{2\delta})}$.

By applying (98) to ${}^C\mathcal{L}_N(\theta)$ and ${}^C\mathcal{L}(\theta)$ and replacing δ with $\frac{2\delta}{3}$ and using the union bound, it follows that

$$\begin{aligned} & \sup_{t=0,\dots,N-1,\theta\in\Theta} \max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t[0])\|_\infty\} \leq 6G_e(\|\mathbf{e}_g\|_{\psi_2})\sqrt{\ln\left(\frac{3N^2}{2\delta}\right)} \\ & \sup_{\theta_1, \theta_2 \in \Theta} |{}^C\mathcal{L}_N(\theta_1) - {}^C\mathcal{L}_N(\theta_2)| \\ & \leq L_\alpha L_\ell \frac{\sqrt{n_e}}{K\|\alpha_g\|_{\ell_1}} \ln(N)\|\theta_1 - \theta_2\| + 2\frac{16L_\ell \ln(N)}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln\left(\frac{2}{3\delta}\right) \right), \end{aligned} \quad (100)$$

holds with probability at least $1 - \delta$, and

$$\begin{aligned} & \sup_{\theta_1, \theta_2 \in \Theta} |{}^C\mathcal{L}(\theta_1) - {}^C\mathcal{L}(\theta_2)| \\ & \leq L_\alpha L_\ell \frac{\sqrt{n_e}}{K\|\alpha_g\|_{\ell_1}} \ln(N)\|\theta_1 - \theta_2\| + 2\frac{16L_\ell \ln(N)}{\sqrt{N}} (C_{u,1} + C_{u,2}) \end{aligned} \quad (101)$$

where $L_\ell = 12G_e\|\mathbf{e}_g\|_{\psi_2}\sqrt{\ln(\frac{3N^2}{2\delta})}$. By using

$$\sqrt{\ln\left(\frac{3N^2}{2\delta}\right)} \leq \sqrt{2}(\ln(N))^{1/2} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)}$$

it follows that

$$L_\alpha L_\ell \frac{\sqrt{n_e}}{K} \ln(N) \leq 12L_\alpha G_e\|\mathbf{e}_g\|_{\psi_2} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{2} \frac{\sqrt{n_e}}{K} (\ln(N))^{3/2}$$

Recall from Subsection C.3, proof of Theorem 3.1 that if

$$\forall: t = 0, 1, \dots, N-1: \max\{\|\mathbf{y}(t) - \mathbf{y}_\theta(t)\|_2, \|\mathbf{y}(t) - \mathbf{y}_\theta(t \mid 0)\|_\infty\} \leq C$$

holds, then ${}^C\hat{\mathcal{L}}_N(\theta) = \hat{\mathcal{L}}_N(\theta)$. Moreover, recall (67)-(68) holds, and thus using (83), it follows that

$$\begin{aligned} |\mathcal{L}(\theta) - {}^C\mathcal{L}(\theta)| & \leq 72G_e^2\|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln\left(\frac{3N^2}{2\delta}\right)}{N} \leq 72\frac{L^2}{192^2} \frac{\ln(N)}{N} = \\ & \frac{6}{16 \cdot 192} L^2 \frac{\ln(N)}{N} \leq \frac{L}{512} \frac{L(\ln(N))^{\frac{3}{2}}}{\sqrt{N}} \end{aligned} \quad (102)$$

In then follows that

$$\begin{aligned} |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| & \leq |\mathcal{L}(\theta_1) - {}^C\mathcal{L}(\theta_1)| + |{}^C\mathcal{L}(\theta_1) - {}^C\mathcal{L}(\theta_2)| + |{}^C\mathcal{L}(\theta_2) - \mathcal{L}(\theta_2)| \\ & \leq \frac{\sqrt{n_e}}{K} L \ln(N)\|\theta_1 - \theta_2\| + 2\frac{16L_\ell \ln(N)}{\sqrt{N}} (C_{u,1} + C_{u,2}) + \frac{2L}{512} \frac{L(\ln(N))^{\frac{3}{2}}}{\sqrt{N}} \end{aligned} \quad (103)$$

By repeating the argument of the proof of Theorem 3.1 for the quadratic case, and using (103) and

$$\begin{aligned} & \frac{1}{L} 12L_\alpha G_e\|\mathbf{e}_g\|_{\psi_2} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{2} \frac{\sqrt{n_e}}{K} = \\ & \frac{12L_\alpha G_e\|\mathbf{e}_g\|_{\psi_2} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)} \sqrt{2} \frac{\sqrt{n_e}}{K}}{192G_e\|\mathbf{e}_g\|_{\psi_2} \sqrt{2} \sqrt{1 + \ln\left(\frac{3}{2\delta}\right)}} = L_\alpha \frac{\sqrt{n_e}}{16K} \end{aligned}$$

it then follows that (100) implies that

$$(99) \text{ holds} \quad (104)$$

$$\sup_{\theta_1, \theta_2 \in \Theta} |\mathcal{L}_N(\theta_1) - \mathcal{L}_N(\theta_2)| \quad (105)$$

$$\leq L_\Theta(\delta) L(\ln(N))^{3/2} \|\theta_1 - \theta_2\| + \frac{2L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{2}{3\delta} \right) \right) \quad (106)$$

which implies (87), and

$$\sup_{\theta_1, \theta_2 \in \Theta} |\mathcal{L}(\theta_1) - \mathcal{L}(\theta_2)| \quad (107)$$

$$\leq L_\Theta L(\ln(N))^{3/2} \|\theta_1 - \theta_2\| + \frac{2L \ln(N)^{3/2}}{\sqrt{N}} (C_{u,1} + C_{u,2}) + \quad (109)$$

$$+ 2 \frac{L}{512} \frac{L(\ln(N))^{3/2}}{\sqrt{N}} \quad (110)$$

which is equivalent to (88). Since (100) holds with probability at least $1 - \delta$, it then follows that (87) also holds with probability at least $1 - \delta$.

Finally, from Corollary 3.2 it follows that (10) holds with probability at least $1 - \delta$, and hence by the union bound (100) follows. $\square$

Proof of Corollary C.21. Consider the inequality (89) which holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$. If (89) holds, then for all $\theta \in \Theta$,

$$\epsilon(\mathcal{L}(\theta)) - (\mathcal{L}(\tilde{\theta})) \leq |\epsilon(\mathcal{L}(\theta) - \mathcal{L}(\tilde{\theta}))| = |\mathcal{L}(\theta) - \mathcal{L}(\tilde{\theta})|$$

and hence

$$\epsilon \mathcal{L}(\theta) \leq \epsilon \mathcal{L}(\tilde{\theta}) + L_\Theta(\delta) L(\ln(N))^r \|\theta - \tilde{\theta}\|_2 + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}}$$

Then $E_{\tilde{\theta} \sim \rho_\theta} \|\tilde{\theta} - \theta\|_2^2 \leq \frac{\sigma^2}{N}$ and hence

$$E_{\tilde{\theta} \sim \rho_\theta} \|\tilde{\theta} - \theta\|_2 \leq \sqrt{E_{\tilde{\theta} \sim \rho_\theta} \|\tilde{\theta} - \theta\|_2^2} \leq \frac{\sigma}{\sqrt{N}}$$

Therefore

$$\begin{aligned} \mathcal{L}(\theta) &\leq E_{\tilde{\theta} \sim \rho_\theta} \mathcal{L}(\tilde{\theta}) + L_\Theta(\delta) L(\ln(N))^r \|\theta - \tilde{\theta}\|_2 \\ &\quad + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\leq \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \end{aligned} \quad (111)$$

Similarly,

$$\epsilon \hat{\mathcal{L}}_N(\tilde{\theta}) \leq \epsilon \hat{\mathcal{L}}_N(\theta) + L_\Theta(\delta) L(\ln(N))^r \|\theta - \tilde{\theta}\|_2 + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right)$$

and hence

$$\begin{aligned} \epsilon E_{\tilde{\theta} \sim \rho_\theta} \hat{\mathcal{L}}_N(\tilde{\theta}) &\leq \epsilon \hat{\mathcal{L}}_N(\theta) + L_\Theta(\delta) L(\ln(N))^r E_{\tilde{\theta} \sim \rho_\theta} \|\theta - \tilde{\theta}\|_2 \\ &\quad + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right) \\ &\leq \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} \ln \left(\frac{1}{\delta} \right) \right) \end{aligned} \quad (112)$$

In addition, since (10) also holds, it follows that

$$\epsilon E_{\tilde{\theta} \sim \rho_\theta} \mathcal{L}(\tilde{\theta}) \leq \epsilon E_{\tilde{\theta} \sim \rho_\theta} \hat{\mathcal{L}}_N(\tilde{\theta}) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho_\theta \parallel \pi) + \ln \left(\frac{C_\delta}{\delta} + C(1, \delta) \right) \right) \quad (113)$$

By combining (111), (112), and (113), it follows that

$$\begin{aligned} \epsilon \mathcal{L}(\theta) &\leq \epsilon E_{\tilde{\theta} \sim \rho_\theta} \mathcal{L}(\tilde{\theta}) + \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) \\ &\quad + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\leq \epsilon E_{\tilde{\theta} \sim \rho_\theta} \hat{\mathcal{L}}_N(\tilde{\theta}) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho_\theta \parallel \pi) + \ln \left(\frac{C_\delta}{\delta} \right) + C(1, \delta) \right) + \\ &\quad + \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\leq \epsilon \hat{\mathcal{L}}_N(\theta) + \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right) \\ &\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho_\theta \parallel \pi) + \ln \left(\frac{C_\delta}{\delta} \right) + C(1, \delta) \right) + \\ &\quad + \frac{\sigma L_\Theta(\delta)}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &= \epsilon \hat{\mathcal{L}}_N(\theta) + \frac{2\sigma L_\Theta(\delta)}{\sqrt{N}} + 4r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(C(\theta) \ln(N) + \ln \left(\frac{C_\delta}{\delta^{2r_{\text{Lip},1}+1}} \right) + C(\epsilon, \delta) \right) \\ &\leq \epsilon \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} (2\sigma L_\Theta(\delta) + 4r_{\text{Lip},1} (C_{u,1} + C_{u,2})) \\ &\quad + 2r_{\text{Lip},2} \frac{L}{512} + \left(C(\theta) + \ln \left(\frac{C_\delta}{\delta^{2r_{\text{Lip},1}+1}} \right) + C(\epsilon, \delta) \right) \end{aligned}$$

where in the last step we used that $r \geq 0$ and $\ln(N) \geq 1$ for $N \geq 4$. $\square$

D Proof of Corollary 3.4

We start with the following remark explaining the notion of random models drawn from a data-dependent posterior.

Remark D.1 (Joint probability over data and parameters). *Let $\rho^\mathcal{D}$ be a function on $\Omega \times \Theta$ which is measurable w.r.t. the direct product $\mathcal{F} \times \mathcal{B}_\Theta$ of σ -algebras, and such that for any $\omega \in \Omega$, $\rho^\mathcal{D}(\omega) : \Theta \ni \theta \mapsto \rho^\mathcal{D}(\omega, \theta)$ is a probability density on Θ . We refer to $\rho^\mathcal{D}$ as a random density on Ω . Let B be a subset of $\mathcal{F} \times \mathcal{B}_\Theta$ and denote by $P_{\theta \sim \rho^\mathcal{D}}(B)$ the random variable $\omega \mapsto P_{\theta \sim \rho^\mathcal{D}(\omega)}(\{\theta \mid (\omega, \theta) \in B\})$, where $P_{\theta \sim \rho^\mathcal{D}(\omega)}$ is the probability measure induced by the density $\rho^\mathcal{D}(\omega)$. Define the probability measure $\mathbf{P} \times P_{\theta \sim \rho^\mathcal{D}}$ on $\mathcal{F} \times \mathcal{B}_\Theta$ as follows:*

$$(\mathbf{P} \times P_{\theta \sim \rho^\mathcal{D}})(B) \triangleq \mathbf{E}[P_{\theta \sim \rho^\mathcal{D}}(B)]$$

Similarly to the previous definition of relationship holding with probability over data, if $\diamond$ is a binary operator and $\{X_i, Y_i\}_{i \in I}$ is family of functions taking values in $\mathbb{R}$ and which are measurable w.r.t. $(\Omega \times \Theta, \mathcal{F} \times \mathcal{B}_\Theta)$, then we say that $\forall i \in I : X_i \diamond Y_i$, holds with probability at least $1 - \delta$ over data and over samples from $\rho^\mathcal{D}$, if the set $B = \{(\omega, \theta) \in \Omega \times \Theta \mid \forall i \in I : X_i(\omega, \theta) \diamond Y_i(\omega, \theta)\}$ is measurable in $(\Omega \times \Theta, \mathcal{F} \times \mathcal{B}_\Theta)$ and $(\mathbf{P} \times P_{\theta \sim \rho^\mathcal{D}})(B) \geq 1 - \delta$.

Note that if a relationship holds with a probability at least $1 - \delta$ over data, then it also holds with a probability at least $1 - \delta$ over data and sampled from $\rho^\mathcal{D}$: if F is an event from $\mathcal{F}$, then $(\mathbf{P} \times P_{\theta \sim \rho^\mathcal{D}})(F) = \mathbf{P}(F) \geq 1 - \delta$.

D.1 Proof of the (11) on empirical error

First, we present a useful property of Gibbs posteriors.

Lemma D.2 (Property of Gibbs distribution).

$$\begin{aligned}\hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \ln \left(\frac{\rho^{\text{Gibbs}}(\theta)}{\pi(\theta)} \right) &= -\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} \\ &= \inf_{\rho \in \mathcal{M}_\pi} \left(\mathbf{E}_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho \parallel \pi) \right)\end{aligned}\quad (114)$$

$$\begin{aligned}E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho^{\text{Gibbs}} \parallel \pi) &= -\frac{1}{\lambda} \ln \mathbf{E}_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} = \\ &= \inf_{\rho \in \mathcal{M}_\pi} \left(\mathbf{E}_{\theta \sim \rho} (\hat{\mathcal{L}}_N(\theta)) + \frac{1}{\lambda} \text{KL}(\rho \parallel \pi) \right)\end{aligned}\quad (115)$$

Proof of Lemma D.2. Using the definition of the Gibbs distribution $\rho^{\text{Gibbs}}(\theta) = \frac{\pi(\theta) e^{-\lambda \hat{\mathcal{L}}_N(\theta)}}{Z}$, $Z = E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)}$, it follows that

$$\ln \left(\frac{\rho^{\text{Gibbs}}(\theta)}{\pi(\theta)} \right) = -\lambda \hat{\mathcal{L}}_N(\theta) - \ln Z$$

and hence

$$\hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \ln \left(\frac{\rho^{\text{Gibbs}}(\theta)}{\pi(\theta)} \right) = \hat{\mathcal{L}}_N(\theta) - \hat{\mathcal{L}}_N(\theta) - \frac{1}{\lambda} \ln Z = -\frac{1}{\lambda} \ln Z$$

This gives the first equality of (114).

As to the first equality of (115), it follows directly from the first equality of (114) by taking the expectation with respect to $\theta \sim \rho^{\text{Gibbs}}$ and recalling that $\text{KL}(\rho^{\text{Gibbs}} \parallel \pi) = \mathbf{E}_{\theta \sim \rho^{\text{Gibbs}}} \left[\ln \frac{\rho^{\text{Gibbs}}(\theta)}{\pi(\theta)} \right]$.

The second equalities of (114)-(115) are Donsker-Varadhan's variational formula [2, Lemma 2.2]

□

Next, we present a version of Theorem 3.1 where the inequality holds not only over data but over data and any model randomly drawn from a data-dependent posterior.

Lemma D.3 (Single draw bound). *Let $\rho^{\mathcal{D}}$ be a data-dependent posterior. For any prior π , any $\delta \in (0, 0.5)$ with a probability at least $(1 - 2\delta)$ over the data and over all samples $\theta_\star$ drawn from $\rho_{\mathcal{D}}$, for any λ satisfying the condition of Theorem 3.1*

$$\epsilon \mathcal{L}(\theta_\star) \leq \epsilon \hat{\mathcal{L}}_N(\theta_\star) + \frac{1}{\lambda} \left(\ln \frac{\rho^{\mathcal{D}}(\theta_\star)}{\pi(\theta_\star)} + \ln \frac{C_\delta}{\delta} + \frac{1}{2} \sum_{i=1}^2 \ln \mathbf{E}_{\theta \sim \pi} \exp(2\lambda \mathcal{C}_i(2\lambda, \theta_\star, N, \delta, \epsilon)) \right) \quad (116)$$

In particular, with probability at least $(1 - 2\delta)$ over data and over all samples $\theta_\star$ drawn from $\rho_{\mathcal{D}}$,

$$\epsilon \mathcal{L}(\theta_\star) \leq \epsilon \hat{\mathcal{L}}_N(\theta_\star) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \left(\frac{\rho^{\mathcal{D}}(\theta_\star)}{\pi(\theta_\star)} \right) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \quad (117)$$

for all $N \geq K_\delta$, where the constants K_δ, C_δ, L, r are defined as in Corollary 3.2. Moreover, if $\epsilon = 1$ and $\rho^{\mathcal{D}} = \rho^{\text{Gibbs}}$, then with probability at least $(1 - 2\delta)$ over the data and over $\theta_\star$ sampled from ρ^{Gibbs} ,

$$\mathcal{L}(\theta_\star) \leq E_{\theta \sim \pi} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\ln \frac{C_\delta}{\delta} + \frac{1}{2} \sum_{i=1}^2 \ln \mathbf{E}_{\theta \sim \pi} \exp(\mathcal{C}_i(2\lambda, \theta, N, \delta, \epsilon)) \right) \quad (118)$$

In particular, if the Gibbs posterior ρ^{Gibbs} is defined for $\lambda = \lambda_N = \frac{\sqrt{N}}{L(\ln(N))^r}$ then for $N \geq K_\delta$

$$\mathcal{L}(\theta_\star) \leq -\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1) \right) \quad (119)$$

Proof of Lemma D.3. Following the argument of the proof of [2, Theorem 2.7], it follows that for any measurable function X on $\Omega \times \Theta$, $E_{\theta \sim \pi} e^{2\lambda X(\omega, \theta)} = E_{\theta \sim \rho^D} e^{2\lambda X(\omega, \theta) - \ln \frac{\rho^D(\omega, \theta)}{\pi(\theta)}}$ and hence $\mathbf{E} E_{\theta \sim \pi} e^{2\lambda X(\theta)} = \mathbf{E} E_{\theta \sim \rho^D} e^{2\lambda X(\theta) - \ln \frac{\rho^D(\theta)}{\pi(\theta)}}$ with the random variables $X(\theta) : \omega \ni \Omega \mapsto X(\omega, \theta)$. Notice that $\mathbf{E} E_{\theta \sim \rho^D}$ is the expectation operator corresponding to the probability measure $\mathbf{P} \times P_{\theta \sim \rho^D}$, and that $\mathbf{E}[E_{\theta \sim \pi} X] = E_{\theta \sim \pi} \mathbf{E}[X]$, and hence, by Chernoff's bound:

$$\begin{aligned} & \mathbf{P} \times P_{\theta \sim \rho^D} (X < \frac{1}{2\lambda} (\ln \frac{1}{\delta} + \ln \frac{\rho^D(\theta)}{\pi(\theta)} + \ln \mathbf{E} E_{\theta \sim \pi} e^{2\lambda X})) \\ &= \mathbf{P} \times P_{\theta \sim \rho^D} ((X - \frac{1}{2\lambda} \ln \frac{\rho^D(\theta)}{\pi(\theta)}) < \frac{1}{2\lambda} (\ln \frac{1}{\delta} + \ln \mathbf{E} E_{\theta \sim \pi} e^{2\lambda X})) \leq \frac{\mathbf{E} E_{\theta \sim \rho^D} e^{2\lambda X - \ln \frac{\rho^D(\theta)}{\pi(\theta)}}}{e^{\ln \frac{1}{\delta} + \ln \mathbf{E} E_{\theta \sim \pi} e^{2\lambda X}}} \\ &= \frac{\mathbf{E} E_{\theta \sim \pi} e^{2\lambda X}}{\frac{1}{\delta} \mathbf{E} E_{\theta \sim \pi} e^{2\lambda X}} = \delta \end{aligned}$$

Hence,

$$X \leq \frac{1}{2\lambda} (\ln \frac{1}{\delta} + \ln \frac{\rho^D(\theta)}{\pi(\theta)} + \ln E_{\theta \sim \pi} \mathbf{E} e^{2\lambda X(\theta)}) \quad (120)$$

with probability at least $1 - \delta$ over data and samples from ρ^D . Hence, by taking $X = \epsilon(\mathcal{L}(\theta) - V_N(\theta))$ and then $X = \epsilon(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))$, and by taking the union bound as in the proof of Theorem C.1, it follows that

$$\begin{aligned} \mathcal{L}(\theta) &\leq \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\ln \frac{1}{\delta} + \ln \frac{\rho^D(\theta)}{\pi(\theta)} \right. \\ &\quad \left. + \frac{1}{2} \left(\ln E_{\theta \sim \pi} \mathbf{E}[e^{2\epsilon\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}] + \ln E_{\theta \sim \pi} \mathbf{E}[e^{2\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}] \right) \right) \end{aligned} \quad (121)$$

Proof of (116) for bounded noise Let us apply the inequality (121) and use the bound on $\mathbf{E}[e^{2\epsilon\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ and $\mathbf{E}[e^{2\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}]$ from Lemma C.6-C.5, from which (116) follows.

Proof of (116) for Lipschitz loss Let us apply (44) from Subsection C.2 to bound the bound on $\mathbf{E}[e^{2\epsilon\lambda(V_N(\theta) - \hat{\mathcal{L}}_N(\theta))}]$ and $\mathbf{E}[e^{2\epsilon\lambda(\mathcal{L}(\theta) - V_N(\theta))}]$, from which (116) follows.

Proof of (116) quadratic loss Recall from Subsection C.3 the definition of the losses ${}^C\mathcal{L}(\theta)$, ${}^C\hat{\mathcal{L}}_N(\theta)$ corresponding to the loss ℓ_C . Note that by Lemma C.19 ℓ_C is $2C$ -Lipschitz. Notice that from the statement of the present lemma proven for the case of Lipschitz losses for $\lambda \leq \frac{\sqrt{N}}{16 \cdot 2C \ln(N)}$, with $C = 6G_e \|\mathbf{e}_g\|_{\psi_2} \sqrt{\ln(\frac{3N^2}{2\delta})}$ probability $1 - \frac{4}{3\delta}$ over data and parameters sampled from ρ^D , the following holds:

$$\begin{aligned} \epsilon {}^C\mathcal{L}(\theta) &\leq \epsilon {}^C\hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \left(\ln \left(\frac{\rho(\theta)}{\pi(\theta)} \right) + \ln \frac{3}{2\delta} + \right. \\ &\quad \left. \frac{1}{2} \sum_{i=1}^2 \ln \mathbf{E}_{\theta \sim \pi} \exp \left(\bar{C}_i(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon) \right) \right) \end{aligned} \quad (122)$$

where $\bar{C}_i(2\lambda, \theta, N, \frac{2\delta}{3}, \epsilon)$ satisfies (60). From Lemma C.18 it follows that (56) holds with probability at least $1 - \frac{2\delta}{3}$ over data and hence (C.18) holds with probability at least $1 - \frac{2\delta}{3}$ over data and parameters sampled from ρ^θ . Hence, by using the union bound, it follows that (122) and (56) hold simultaneously with probability at least $1 - 2\delta$ over data and parameters sampled from ρ^D .

Moreover, if (57) holds, then it holds that ${}^C\hat{\mathcal{L}}_N(\theta) = \hat{\mathcal{L}}_N(\theta)$ and by and (68) – (67)

$${}^C\mathcal{L}(\theta) \leq \mathcal{L}(\theta) \leq {}^C\mathcal{L}(\theta) + 72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln \left(\frac{3N^2}{2\delta} \right)}{N}$$

Hence,

$$\epsilon \mathcal{L}(\theta) \leq \epsilon {}^C\mathcal{L}(\theta) + 72G_e^2 \|\mathbf{e}_g\|_{\psi_2}^2 \frac{\ln \left(\frac{3N^2}{2\delta} \right)}{N} \max\{\epsilon, 0\} \quad (123)$$

Hence, by using (122) and ${}^C\hat{\mathcal{L}}_N(\theta) = \hat{\mathcal{L}}_N(\theta)$, it follows that if (123) and (56) both hold, then (116) holds. Since (123) and (56) holds with probability at least $1 - 2\delta$ over data and samples from $\rho^{\mathcal{D}}$, so does (116).

Proof of (116) implies (118) It follows by applying Lemma D.2.

Proof of (117) From the proof of Corollary 3.2 it follows that for $\lambda = \frac{\sqrt{N}}{L(\ln(N))^r}$ where r is as in Corollary 3.2,

$$\frac{1}{2\lambda} (\ln E_{\theta \sim \pi} \exp(\mathcal{C}_1(2\lambda, \theta, N, \delta, \epsilon)) + \ln E_{\theta \sim \pi} \exp(\mathcal{C}_2(2\lambda, \theta, N, \delta, \epsilon))) \leq \mathcal{C}(\delta, \epsilon)$$

Using this inequality, it follows that (116) implies (117). $\square$

Lemma D.4. *If $\mathcal{L}(\theta)$ is convex, ρ is a probability density over Θ , and $\theta_\star = E_{\theta \sim \rho} \theta$ is the mean of the density ρ , then*

$$\mathcal{L}(\theta_\star) \leq E_{\theta \sim \rho} [\mathcal{L}(\theta)]. \quad (124)$$

Proof of Lemma D.4. If $\mathcal{L}(\theta)$ is convex in θ , then $\mathcal{L}(\theta_\star) = \mathcal{L}(E_{\theta \sim \rho^{\mathcal{D}}} \theta) \leq E_{\theta \sim \rho^{\mathcal{D}}} \mathcal{L}(\theta)$ by Jensen's inequality. $\square$

Proof of (11). For the single draw case, from (118) of Lemma D.3, it follows that with probability at least $1 - 2\delta$ over data and samples from ρ^{Gibbs} ,

$$\mathcal{L}(\theta_\star) \leq -\ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \quad (125)$$

for $\lambda = \sqrt{N}/(L(\ln(N))^r)$. For the MEP case, using Lemma D.4 and Lemma D.2 and Corollary 3.2 it follows that with probability at least $1 - 2\delta$ over data, it holds that

$$\begin{aligned} \mathcal{L}(\theta_\star) &\leq E_{\theta \sim \rho^{\text{Gibbs}}} \mathcal{L}(\theta) \leq E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) + \underbrace{\frac{L(\ln(N))^r}{\sqrt{N}}}_{1/\lambda} \left(\text{KL}(\rho^{\text{Gibbs}} \mid \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\ &= \left(E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho^{\text{Gibbs}} \mid \pi) \right) + \underbrace{\frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right)}_{\mathcal{C}_{em}(\delta, \sigma)} \\ &= -\ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \mathcal{C}_{em}(\delta, \sigma) \end{aligned} \quad (126)$$

with $\lambda = \sqrt{N}/(L(\ln(N))^r)$. Using the second equality of (115), it follows that for any posterior $\rho \in \mathcal{M}_\pi$,

$$-\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} \leq E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho \parallel \pi) \quad (127)$$

Choose $\rho_{\theta_\star}$ as in Lemma C.22, i.e.,

$$\rho_{\theta_\star} = \begin{cases} \mathcal{N}(\theta_\star, \frac{\sigma^2}{N}) & \text{if (Gauss) holds} \\ \mathcal{U}(\theta_\star, \frac{\sigma}{\sqrt{N}}) & \text{if (Uni) holds} \end{cases}$$

From Lemma C.23 it follows that (87) holds with probability at least $1 - r_{\text{Lip},1} \delta$ over data, and hence over data and samples from ρ^{Gibbs} . In particular, as (87) implies

$$\begin{aligned} E_{\theta \sim \rho_{\theta_\star}} \hat{\mathcal{L}}_N(\theta) &\leq \hat{\mathcal{L}}_N(\theta_\star) + L_\Theta(\delta) L(\ln(N))^{r+1} \underbrace{E_{\theta \sim \rho_{\theta_\star}} \|\theta - \theta_\star\|_2}_{\leq \frac{\sigma}{\sqrt{N}}} + \\ &\quad 2r_{\text{Lip},1} \frac{L(\ln(N))^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right), \end{aligned} \quad (128)$$

It then follows that (128) holds with probability at least $1 - r_{\text{Lip},1}\delta$ over data and samples from ρ^{Gibbs} . Then using the union bound on (125), (128), and (127) and Lemma C.22 it follows that

$$\begin{aligned}
\mathcal{L}(\theta_*) &\leq E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) \leq -\ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\
&\leq E_{\theta \sim \rho_{\theta_*}} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho_{\theta_*} \parallel \pi) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\
&\leq \hat{\mathcal{L}}_N(\theta_*) + L_\Theta(\delta) L(\ln(N))^{r+1} \frac{\sigma}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right) \\
&\quad + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} C(\theta_*) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\
&\leq \hat{\mathcal{L}}_N(\theta_*) + \frac{L(\ln(N))^{r+1} \sigma}{\sqrt{N}} \underbrace{\left(L_\Theta(\delta) \sigma + 2r_{\text{Lip},1} (C_{u,1} + C_{u,2}) + C(\theta_*) \right)}_{\mathcal{C}_{L,emp}} \\
&\quad + \left(\ln \left(\frac{C_\delta}{\delta} \right) + 2r_{\text{Lin},1} \ln \left(\frac{1}{\sigma} \right) + C(\delta, \epsilon) \right) \leq \hat{\mathcal{L}}_N(\theta_*) + \frac{L(\ln(N))^{r+1} \sigma}{\sqrt{N}} \mathcal{C}_{em}(\delta, \sigma)
\end{aligned} \tag{129}$$

with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ over data and θ_* sampled from ρ^{Gibbs} . Similarly, by using that (126) holds with probability at least $1 - 2\delta$, the fact that (87) holds with probability at least $1 - r_{\text{Lip},1}\delta$ over data, and that (87) implies (127), it follows, using the union bound that for MEP,

$$\begin{aligned}
\mathcal{L}(\theta_*) &\leq E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) \leq -\ln e^{-\lambda E_{\theta \sim \pi} \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\
&\leq E_{\theta \sim \rho_{\theta_*}} \hat{\mathcal{L}}_N(\theta) + \frac{1}{\lambda} \text{KL}(\rho_{\theta_*} \parallel \pi) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \\
&\leq \hat{\mathcal{L}}_N(\theta_*) + L_\Theta(\delta) L(\ln(N))^{r+1} \frac{\sigma}{\sqrt{N}} + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} C(\theta_*) \\
&\quad + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} \left(C_{u,1} + C_{u,2} + \ln \left(\frac{1}{\delta} \right) \right) \\
&\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, \epsilon) \right) \leq \hat{\mathcal{L}}_N(\theta_*) + \frac{L(\ln(N))^{r+1} \sigma}{\sqrt{N}} \mathcal{C}_{em}(\delta, \sigma)
\end{aligned} \tag{130}$$

holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ over data.

Finally, the case of MAP follows from Lemma C.21 by applying it to the random model θ_* : as

$$\begin{aligned}
\forall \theta \in \Theta : \mathcal{L}(\theta) &\leq \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} (\sigma L_\Theta(\delta) + 2r_{\text{Lip},1} (C_{u,1} + C_{u,2}) \\
&\quad + 2r_{\text{Lip},2} \frac{L}{512} + C(\theta) + \ln \left(\frac{C_\delta}{\delta} \right) + 2r_{\text{Lip},1} \ln \left(\frac{1}{\delta} \right) + \mathcal{C}(\delta, \epsilon))
\end{aligned}$$

holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ over data, it then follows that for $\theta = \theta_*$,

$$\begin{aligned}
\mathcal{L}(\theta_*) &\leq \hat{\mathcal{L}}_N(\theta_*) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} (\sigma L_\Theta(\delta) + r_{\text{Lip},1} (C_{u,1} + C_{u,2}) \\
&\quad + 2r_{\text{Lip},2} \frac{L}{512} + C(\theta_*) + \ln \frac{C_\delta}{\delta^{2r_{\text{Lip},1}+1}} + \mathcal{C}(\delta, 1)) \\
&= \hat{\mathcal{L}}_N(\theta_*) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \mathcal{C}_{em}(\delta, \sigma)
\end{aligned}$$

□

D.2 Proof of (12)

From (10) it follows that each of the inequalities below hold with probability at least $1 - 2\delta$ over data

$$\forall \rho \in \mathcal{M}_\pi : E_{\theta \sim \rho} \mathcal{L}(\theta) \leq E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} (\text{KL}(\rho || \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1)) \quad (131)$$

$$\forall \rho \in \mathcal{M}_\pi : -E_{\theta \sim \rho} \mathcal{L}(\theta) \leq -E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} (\text{KL}(\rho || \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1)) \quad (132)$$

In particular, by using the union bound it follows that (131) and (132) hold simultaneously with probability at least $1 - 4\delta$. Using the fact that for any posterior $\rho \in \mathcal{M}_\pi$,

$$E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \text{KL}(\rho^{\text{Gibbs}} || \pi) \leq E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} (\text{KL}(\rho || \pi))$$

it then follows that with probability at least $1 - 4\delta$ over data

$$\begin{aligned} \forall \rho \in \mathcal{M}_\pi : E_{\theta \sim \rho^{\text{Gibbs}}} \mathcal{L}(\theta) &\leq E_{\theta \sim \rho^{\text{Gibbs}}} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} (\text{KL}(\rho^{\text{Gibbs}} || \pi) + \ln \left(\frac{C_\delta}{\delta} \right) + \mathcal{C}(\delta, 1)) \\ &\leq E_{\theta \sim \rho} \hat{\mathcal{L}}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \text{KL}(\rho || \pi) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \left(\frac{C_\delta}{\delta} \right) + \mathcal{C}(\delta, 1) \right) \\ &\leq E_{\theta \sim \rho} \mathcal{L}(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho || \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) \right) + \\ &\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho || \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1) \right) \\ &= E_{\theta \sim \rho} \mathcal{L}(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \left(2\text{KL}(\rho || \pi) + 2 \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) + \mathcal{C}(\delta, 1) \right) \end{aligned} \quad (133)$$

For the posterior $\rho_{\theta_{true}}$ from Lemma C.22, using (88) from Lemma C.23, it follows that

$$\begin{aligned} E_{\theta \sim \rho_{\theta_{true}}} \mathcal{L}(\theta) &\leq \mathcal{L}(\theta_{true}) \\ &\quad + L_\Theta(\delta) L(\ln(N))^r E_{\theta \sim \rho_{\theta_{true}}} \|\theta_1 - \theta_2\|_2 \\ &\quad + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\leq \mathcal{L}(\theta_{true}) + L_\Theta(\delta) \sigma \frac{L(\ln(N))^r}{\sqrt{N}} + 2r_{\text{Lip},1} \frac{L \ln(N)^r}{\sqrt{N}} (C_{u,1} + C_{u,2}) + 2r_{\text{Lip},2} \frac{L}{512} \frac{L(\ln(N))^r}{\sqrt{N}} \\ &\leq \mathcal{L}(\theta_{true}) + \frac{L \ln(N)^r}{\sqrt{N}} \mathcal{C}_{L,true} \end{aligned} \quad (134)$$

By applying (133) with $\rho = \rho_{\theta_{true}}$ and using that by Lemma C.22

$$\text{KL}(\rho_{\theta_{true}} || \pi) \leq \mathcal{C}(\theta_{true}) \ln(N)$$

and the fact that $\ln(N) \geq 1$ it follows that

$$\begin{aligned} E_{\theta \sim \rho^{\text{Gibbs}}} \mathcal{L}(\theta) &\leq \mathcal{L}(\theta_{true}) + \\ &\quad \frac{L \ln(N)^{r+1}}{\sqrt{N}} \left(\mathcal{C}_{L,true} + 2\mathcal{C}(\theta_{true}) + 2 \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) + \mathcal{C}(\delta, 1) \right) \end{aligned} \quad (135)$$

with probability at least $1 - 4\delta$. If θ_* is MEP, then by Lemma D.4 $\mathcal{L}(\theta_*) \leq E_{\theta \sim \rho^{\text{Gibbs}}} \mathcal{L}(\theta)$. Combining this with (135), (12) for MEP follows.

For single draw, from Lemma D.3, (119), it follows that with probability at least $1 - 2\delta$ over data and samples θ_* from ρ^{Gibbs} it holds that

$$\mathcal{L}(\theta_*) \leq -\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1) \right) \quad (136)$$

with $\lambda = \lambda_N = \frac{\sqrt{N}}{L(\ln N)^r}$. By using (114) from Lemma D.2, it follows that for $\rho_{\theta_{true}}$ from Lemma C.22

$$-\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} \leq E_{\theta \sim \rho_{\theta_{true}}} \mathcal{L}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \text{KL}(\rho_{\theta_{true}} \parallel \pi) \quad (137)$$

Using that 132 holds with probability at least $1 - 2\delta$ over data, and using (134), and $\ln(N) \geq 1$, it follows that

$$\begin{aligned} -\frac{1}{\lambda} \ln E_{\theta \sim \pi} e^{-\lambda \hat{\mathcal{L}}_N(\theta)} &\leq E_{\theta \sim \rho_{\theta_{true}}} \mathcal{L}_N(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \text{KL}(\rho_{\theta_{true}} \parallel \pi) \\ &\leq E_{\theta \sim \rho_{\theta_{true}}} \mathcal{L}(\theta) + \frac{L(\ln(N))^r}{\sqrt{N}} \text{KL}(\rho_{\theta_{true}} \parallel \pi) \\ &\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\text{KL}(\rho_{\theta_{true}} \parallel \pi) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) \right) \\ &\leq \mathcal{L}(\theta_{true}) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}_{L,true} + 2\mathcal{C}(\theta_{true}) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) \right) \end{aligned} \quad (138)$$

with probability at least $1 - 2\delta$ over data and hence over data and samples from ρ^{Gibbs} . By combining (136) and (138) using the union bounds, it follows that with probability $1 - 4\delta$ over data and samples $\theta_\star$ from ρ^{Gibbs} ,

$$\begin{aligned} \mathcal{L}(\theta_\star) &\leq \mathcal{L}(\theta_{true}) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}_{L,true} + 2\mathcal{C}(\theta_{true}) + \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, -1) \right) + \\ &\quad + \frac{L(\ln(N))^r}{\sqrt{N}} \left(\ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1) \right) \\ &\leq \mathcal{L}(\theta_{true}) + \frac{L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}_{L,true} + 2\mathcal{C}(\theta_{true}) + 2 \ln \frac{C_\delta}{\delta} + \mathcal{C}(\delta, 1) + \mathcal{C}(\delta, -1) \right) \end{aligned}$$

from which the statement of (12) for single draw follows, by replacing δ by $\frac{\delta}{2}$.

Finally, we consider the case of MAP. Since (11), i.e.,

$$\begin{aligned} \mathcal{L}(\theta_\star) &\leq \hat{\mathcal{L}}_N(\theta_\star) + \\ &\quad \frac{2L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}(\theta_\star) + \mathcal{C}_{L,true} + \mathcal{C}_{L,emp} + \ln \frac{C_\delta}{\delta^{2r_{\text{Lip},1}+1}} + \mathcal{C}(\delta, 1) \right) \end{aligned} \quad (139)$$

holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$. From (86) applied to $\theta = \theta_{true}$ and $\epsilon = 1$ it also follows that

$$\begin{aligned} \hat{\mathcal{L}}_N(\theta_{true}) &\leq \mathcal{L}(\theta_{true}) + \\ &\quad \frac{2L(\ln(N))^{r+1}}{\sqrt{N}} \left(\mathcal{C}(\theta_{true}) + \mathcal{C}_{L,true} + \mathcal{C}_{L,emp} + \ln \frac{C_\delta}{\delta^{2r_{\text{Lip},1}+1}} + \mathcal{C}(\delta, -1) \right) \end{aligned} \quad (140)$$

holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$ over data. If $\theta_\star$ is MAP, then $\theta_\star$ minimizes $\hat{\mathcal{L}}_N(\theta) - \frac{1}{\lambda} \ln \pi(\theta)$ and hence $\hat{\mathcal{L}}_N(\theta_\star) - \frac{1}{\lambda} \ln \pi(\theta_\star) \leq \hat{\mathcal{L}}_N(\theta_{true}) - \frac{1}{\lambda} \ln \pi(\theta_{true})$. Hence,

$$\hat{\mathcal{L}}_N(\theta_\star) \leq \hat{\mathcal{L}}_N(\theta_{true}) + \frac{1}{\lambda} \ln \left(\frac{\pi(\theta_\star)}{\pi(\theta_{true})} \right)$$

and then by using (139)-(140) and the fact that $\lambda = \frac{\sqrt{N}}{L(\ln(N))^r}$ and hence $\frac{1}{\lambda} \leq \frac{L(\ln(N))^{r+1}}{\sqrt{N}}$, it follows that with probability $1 - (4 + 2r_{\text{Lip},1})\delta$ over data,

$$\begin{aligned} \hat{\mathcal{L}}_N(\theta_\star) &\leq \mathcal{L}(\theta_{true}) \\ &\quad + \frac{2L(\ln(N))^{r+1}}{\sqrt{N}} \left(2\mathcal{C}(\theta_{true}) + 2\mathcal{C}_{L,true} + 2\mathcal{C}_{L,emp} + 2 \ln \frac{C_\delta}{\delta} \right. \\ &\quad \left. + \mathcal{C}(\delta, 1) + \mathcal{C}(\delta, -1) \right) + \frac{2L(\ln(N))^{r+1}}{\sqrt{N}} \ln \left(\frac{\pi(\theta_\star)}{\pi(\theta_{true})} \right) \end{aligned} \quad (141)$$

holds, hence, by replacing δ with $\delta/2$, it follows that (12) holds with probability at least $1 - (2 + r_{\text{Lip},1})\delta$.

D.3 Proof of (13)

If (SConv) holds, then by [30, Theorem 2.1.11, Theorem 2.1.8]

$$m_\Theta \|\theta_\star - \theta_{true}\|^2 \leq \mathcal{L}(\theta_\star) - \mathcal{L}(\theta_{true})$$

from which using (12) the inequality (13) follows.

D.4 Proof of (14)

From [26, Chapter 4, page 87] it follows that $\sigma_{\mathbf{e}^s}^2 = \mathcal{L}(\theta_{true}) = \inf_{\theta \in \Theta} \mathcal{L}(\theta)$, where $\sigma_{\mathbf{e}^s}^2 = \mathbf{E}[\|\mathbf{e}^s(t)\|_2^2]$, if ℓ is the quadratic loss function, i.e. the true system yields the best possible prediction in mean square sense.

$$\forall \theta \in \Theta : \sigma_{\mathbf{e}^s}^2 = \mathcal{L}(\theta_{true}) \leq \mathcal{L}(\theta) \quad (142)$$

where $\sigma_{\mathbf{e}^s}^2$ is the variance of $\mathbf{e}^s(t)$. That is, the parameter θ_{true} corresponding to the data generator results in the smallest possible generalisation loss for quadratic loss function. Let H_θ be the transfer function of the predictor parametrized by θ

It can be shown (see [12, Appendix, (82)] and [26, Chapter 4, page 87]) that

$$\|H_{\theta_{true}} - H_\theta\|_{H_2}^2 \leq \frac{1}{m_{\mathbf{w}}} (\mathcal{L}(\theta) - \mathcal{L}(\theta_{true})), \quad (143)$$

Then (14) follows from (12) and (143).

D.5 Remark on relationship with system identification and learning

Remark D.5 (Identification of FIR models). Consider the SISO case ($n_y = n_u = 1$), fix an integer T_0 and let $\Theta = \mathbb{R}^{T_0}$ and for any $\theta = (\theta_1, \dots, \theta_{T_0})^T \in \Theta$, let $D_\theta = \theta_1$,

$$A = \begin{bmatrix} 0 & 0 & \cdots & 0 & 0 \\ 1 & 0 & \cdots & 0 & 0 \\ \vdots & \vdots & \cdots & \vdots & \vdots \\ 0 & 0 & \cdots & 1 & 0 \end{bmatrix}, \quad B = \begin{bmatrix} 1 \\ 0 \\ \vdots \\ 0 \end{bmatrix}, \quad C_\theta = \begin{bmatrix} \theta_2 \\ \vdots \\ \theta_{T_0} \\ 1 \end{bmatrix}^T$$

Then $\hat{\mathbf{y}}_\theta(t) = u(t - T_0) + \sum_{i=0}^{T_0-1} \theta_{i+1} \mathbf{u}(t - i)$. Assume that there exists $\theta_{true} \in \Theta$, such that $\mathbf{y}(t) = \hat{\mathbf{y}}_{\theta_{true}}(t) + \mathbf{e}(t)$, where $\mathbf{e}(t)$ is i.i.d. with zero mean and variance σ^2 , and independent of $\mathbf{u}(s)$, $s \in \mathbb{Z}$. Let $\hat{\mathbf{u}}(t) = \mathbf{u}(t)$ for $t > 0$ and let $\hat{\mathbf{u}}(t) = 0$ for $t < 0$. Let Φ be the regressor matrix constructed from $\hat{\mathbf{u}}$ as in [34, (3.45), page 48] and let $Y = [\mathbf{y}(0) \ \cdots \ \mathbf{y}(N-1)]^T$. Then $\hat{\mathcal{L}}_N(\theta) = \frac{1}{N} \|Y - \Phi\theta\|_2^2$. Assume that the prior π is the Gaussian density $\mathcal{N}(\tilde{\theta}, P)$, $P = P^T > 0$. Then a lengthy but straightforward calculation reveal that the Gibbs posterior is the Gaussian density $\mathcal{N}(\tilde{\theta} + P\Phi^T(\Phi P\Phi^T + \frac{N}{2\lambda}I)^{-1}(Y - \Phi\tilde{\theta}), P - P\Phi^T(\Phi P\Phi^T + \frac{N}{2\lambda}I)^{-1}\Phi P)$, which is the conditional density of θ w.r.t. Y, Φ presented in [34, (4.6), page 101], if $Y = \Phi\theta + E$ is assumed with $E \sim \mathcal{N}(0, \frac{N}{2\lambda}I_{T_0})$. Then the MAP and MEP estimates are both $\theta_\star = \tilde{\theta} + P\Phi^T(\Phi P\Phi^T + \frac{N}{2\lambda}I)^{-1}(Y - \Phi\theta_{true})$ and they solve the regularized optimization problem $\arg \min_{\theta \in \Theta} \lambda \hat{\mathcal{L}}_N(\theta) + (\theta - \tilde{\theta})^T P^{-1}(\theta - \tilde{\theta})$. Moreover, they are also the maximum likelihood of the posterior $P(\theta | Y, \Phi)$.

Then Corollary 3.4 applies to $\theta_\star$, yielding a $O(\frac{(\ln(N))^r}{\sqrt{N}})$ bound on the generalization gap of $\theta_\star$ and a $O(\frac{(\ln(N))^{r+1}}{\sqrt{N}})$ bound on the square parameter estimation error $\|\theta_\star - \theta_{true}\|_2^2$.

Remark D.6. (Maximum likelihood estimates of state-space models). Consider the parametrization of LTI systems

$$\begin{aligned} \hat{\mathbf{x}}(t+1) &= (\hat{A}_\theta + \hat{L}_\theta \hat{C}_\theta) \hat{\mathbf{x}}(t) + (\hat{B}_\theta + L_\theta D_\theta) \mathbf{u}(t) + \hat{L}_\theta \mathbf{e}_\theta(t), \\ \mathbf{y}_\theta(t) &= \hat{C}_\theta \hat{\mathbf{x}}(t) + \hat{D}_\theta \mathbf{u}(t) + \mathbf{e}_\theta(t) \end{aligned} \quad (144)$$

where A_θ and $A_\theta + L_\theta C_\theta$ are Schur, $\mathbf{e}_\theta(t)$ is i.i.d., zero mean Gaussian with variance $\frac{1}{\lambda}$, $(\mathbf{u}, \mathbf{e}_\theta)$ is jointly Gaussian, $\mathbf{e}_\theta(t)$ is independent of $\mathbf{u}(s)$ for $s < t$. We can associate with (144) the predictor

$$\begin{aligned} \hat{\mathbf{x}}(t+1) &= \hat{A}_\theta \hat{\mathbf{x}}(t) + \hat{B}_\theta \mathbf{u}(t) + \hat{L}_\theta \mathbf{y}(t), \\ \hat{\mathbf{y}}_\theta(t | 0) &= \hat{C}_\theta \hat{\mathbf{x}}(t) + \hat{D}_\theta \mathbf{u}(t), \end{aligned} \quad (145)$$

Assume that $\mathbf{y}$ is generated by an LTI system of the form (144) which satisfies [4, (1), INP B, page 427].

In this case, by [4, (2.7), page 422, Chapter 7] the conditional likelihood function $p_\theta(\{y(t)\}_{t=-1}^{N-1} | \{u(t)\}_{t=0}^{N-1})$ w.r.t $\{\mathbf{u}(t)\}_{t=0}^{N-1}$, evaluated at $y(t) = \mathbf{y}(t)$ and $u(t) = \mathbf{u}(t)$, $t = -1, \dots, N-1$ equals $Z e^{-\frac{N\lambda}{2} \hat{\mathcal{L}}_N(\theta)}$ for a suitable constant Z , where the empirical error $\hat{\mathcal{L}}_N(\theta)$ is defined for the quadratic loss. That is, i.e., up to an additive constant, its logarithm equals $\ln \rho^{\text{Gibbs}}(\theta)$. In particular, the maximum likelihood estimate $\arg\max_{\theta \in \Theta} p_\theta(\{y(t)\}_{t=0}^{N-1} | \{u(t)\}_{t=0}^{N-1})$, see [4, Chapter 7, page 428] equals the MAP $\arg\max_{\theta \in \Theta} \rho^{\text{Gibbs}}(\theta)$ of the Gibbs posterior corresponding to the uniform distribution $\pi = \frac{1}{\text{vol}(\Theta)}$ as a prior. Here we assume that $\text{vol}(\Theta)$ is finite.

We can then use the bounds (11), (12), (13), (14), for the generalization gap, the gap between the true error of the learned model and the best true error and the parameter estimation error respectively.

Remark D.7 (Bayesian methods for estimating LTI systems). *The Bayesian method for system identification of LTI systems [31] corresponds to taking a single draw, MEP or MAP from the conditional distribution of the parameter given the past observations. If the parametrization is in innovation form, i.e., of the form (144) and all the signals are jointly Gaussian, then by Remark D.6 the joint density of $\{\mathbf{y}(t)\}_{t=-1}^{N-1}$ given $\{\mathbf{u}(t)\}_{t=0}^{N-1}$ and $\{\mathbf{y}(s), \mathbf{u}(s)\}_{s < 0}$ and a parameter θ is $Z e^{-N\lambda \hat{\mathcal{L}}_N(\theta)}$ for a suitable constant, and hence by [31, Section 3, eq. (12)] the conditional density of θ with respect to $\{\mathbf{y}(t), \mathbf{u}(t)\}_{t=0}^{N-1}$ is the Gibbs posterior $\frac{e^{-N\lambda \hat{\mathcal{L}}_N(\theta)} p_\theta(\mathbf{y}(-1)) \pi(\theta)}{\int_{\Theta} e^{-N\lambda \hat{\mathcal{L}}_N(\theta)} p_\theta(\mathbf{y}(-1)) \pi(\theta) d\theta}$ for the quadratic loss and a suitable prior, and hence Gibbs posterior for the predictors (145), and hence taking a random draw, MEP or MAP from this conditional density, as suggested by [31], corresponds to taking a random draw, MEP or MAP from the Gibbs posterior. In particular, the bounds (11), (12), (13), (14) apply.*

Remark D.8 (PEM methods). *To begin with if a PEM algorithm can be reduced to optimizing a cost function $\hat{\mathcal{L}}_N(\theta) + g(\theta)$, then the algorithm is equivalent to taking the MAP estimate of the Gibbs posterior with a prior π such that $-\frac{1}{\lambda} \ln \pi(\theta) = \frac{g(\theta)}{\lambda}$. In particular, (11)-(14) from Corollary 3.4 applies in this case. For example, the quadratic regularization term $g(\theta) = (\theta - \theta_m)^T P^{-1} (\theta - \theta_m)$ corresponds to $\pi \sim \mathcal{N}(\theta_m, P/\lambda)$. If π can be interpreted as a Gaussian density, then MAP is MEP and the corresponding sharper bounds can be used.*

Furthermore, many PEM algorithms rely on choosing randomly the initial parameter estimate. The outcomes of such algorithms can be viewed as drawing a sample from a suitable posterior distribution. More precisely, consider an algorithm A_N . For every initial value $\theta_0 \in \Theta$ and data $\mathcal{D}$, the algorithm generates an estimate $A_N(\theta_0, \mathcal{D})$. Most optimization algorithms used for PEM methods (Gradient, Gauss-Newton), etc. are of this form, if we fix the number of steps. Assume that the initial parameter values θ_{init} are i.i.d., samples from a prior density π . Then the resulting parameter values $A_N(\theta_{\text{init}}, \mathcal{D})$ are i.i.d. samples from a distribution $P_{A_N}(B) = \int_{A_N^{-1}(B, \mathcal{D})} \pi(\theta) d\mu(\theta)$ for any $B \in \mathcal{B}_\Theta$. Assume that the latter distribution has a density $\hat{\rho}$ which is in $\mathcal{M}_\pi$. Then Lemma D.3 provides an error bound for the true error of such an algorithm, when applied to an initial parameter value randomly sampled from π .

Remark D.9 (Strong convexity of the true error). *Strong convexity implies that there is a unique minimizer of the true error, which is the true system. It can be seen as an identifiability and persistence of excitation assumption, as it implies that there is no parameter value which gives the same input-output behavior as the true system (otherwise their true errors would be the same), and $\mathbf{w}$ is rich enough (the average response to $\mathbf{w}$ allows us to find the true system). In fact, strong convexity of the true error (at least locally), is a standard assumption for studying the asymptotic distribution of the parameter estimation error [26, Theorem 9.1].*

Remark D.10 (Bounds on the difference between system matrices). *Assuming that the LTI systems $\Sigma(\theta)$ are all minimal, we can use (14) and [32, Theorem V.2] to derive an error bound (in high-probability) on the difference between the matrices of the learned and true system. Alternatively, if we consider parametrizations based on structure indices [33, Chapter 3] we could use the fact that H_2 norms can be used to approximate locally the Riemannian distance between parameter values [33, Chapter 4, page 129].*

Remark D.11 (Relationship with [11, 8]). *For the case of bounded noise in the data generator, Theorem 3.1 provides a PAC-Bayesian bound on the generalization gap which is similar to [11,*

Theorem 2, Corollary 1] and [8, Theorem 5.2]. However, [11] considers RNNs, and the corresponding constants $L_v(\theta)$, $L_{g,s}(\theta)$, $L_{g,v}$ correspond to $\|\hat{B}_\theta\|_2$, $\|\hat{C}_\theta\|_2$, and $\|\hat{D}_\theta\|_2$, respectively, and $\tau(\theta)$ corresponds to an upper bound on the spectrum of $\hat{A}_\theta$ and $C(\theta)$ is such that $\|\hat{A}_\theta^k\|_2 \leq \tau(\theta)^k C(\theta)$. In our setting, $L_v(\theta)$, $L_{g,s}(\theta)$, $L_{g,v}$ can be taken to be C from Assumption 2.1, $C(\theta)$ can be taken to be M and $\tau(\theta)$ can be taken to be γ from Assumption 2.1. Then the constants G_θ , H_θ from [11] are upper bounds on $\|\alpha_\theta\|_{\ell_1}$ and $\theta_\infty(\alpha_\theta)$ respectively. Hence the term $\hat{\Psi}_\pi(\lambda, N)$ of [11, Theorem 2, Corollary 1] is an upper bound on the term $\frac{1}{2} \sum_{i=1}^2 \ln E_{\theta \sim \pi} \exp(C_i(2\lambda, \theta, N, \delta, \epsilon))$ from (8), i.e., the bound of [11, Theorem 2, Corollary 1] is more conservative than the one of this paper.

As to [8, Theorem 5.2], it uses $\|\alpha_{g,y} - c_\theta\|_{\ell_1} \leq G_e(\theta)$ and $\theta_\infty(\alpha_{g,y} - c_\theta) \leq G_{e,1}(\theta)$ in the bounds, where c_θ and $\alpha_{g,y}$ are defined in Lemma B.3. While this may appear less conservative, the use of c_θ makes the bound difficult to evaluate in practice, as c_θ depends on the parameters of the unknown data generator. In contrast, our bound uses only $\|\alpha_g\|_{\ell_1}$ and $\theta_\infty(\alpha_g)$, which, although they also depend on the data generator, are easier to estimate or upper bound in practice.

Note that [11, 8] do not address the case of unbounded signals or parameter estimation errors. They also do not provide generalization bounds for single draw, MEP, or MAP estimators.

Remark D.12 (Relationship with finite-sample bounds [32, 24, 39, 42, 20]). Recent works such as [32, 24, 39, 42, 20] provide finite-sample parameter estimation bounds for specific algorithms (e.g., least-squares for ARX models, subspace methods), typically assuming the data generator starts from a deterministic initial state and often neglecting the stochastic component. However, assuming a deterministic initial state can be problematic, since process noise generally drives the system to a random initial state determined by past disturbances.

In contrast, our results: (1) apply to a broad class of learning algorithms (including PEM, maximum likelihood, Bayesian, and regularized FIR methods), (2) assume the data generator is in a stationary regime, (3) explicitly account for both deterministic and stochastic components, and (4) provide generalization gap bounds. The trade-off is that our bound on the square of the parameter estimation error is $O\left(\frac{(\ln N)^{r+1}}{\sqrt{N}}\right)$, which is more conservative than the $O\left(\frac{\ln N}{N}\right)$ rates in the cited works.