AMK

3586 'System diagnostics: Special software message'

● CAN bus: Error during initialization			
Device	FSE		
Description			
Class	Error		
Drive behaviour	System run-up aborted		
Device behaviour			
Additional information (Info AMK service)			
	Info1	0	Invalid CAN configuration mode (ID34091-2)
		1	Configured index (ID) not found
		2	Invalid signal type
		3	Length of the configuration does not match the selected messages and signals
		4	Invalid transmission rate
		5	CAN module error
Error removal	● Restart device ● AMK service		
● Error messages of CAN communication			
Device	MCE		
Description			
Class	Error		
Drive behaviour	Drive coasts down		
Device behaviour			
Additional information (Info AMK service)			
	Info1	0	Memory error
		1	Module command error
		2	Invalid value in ID34028 'BUS output rate'
		3	Invalid value in ID34024 'BUS transmit rate'
		4	Error during access CAN
		5	Error in message configuration (ID34036 'CCB-File')
Error removal	● Check parameters ● Restart device		
● Fault BUS			
Device	ZWR		
Description	Fieldbus interruption		
Class	Error		
Device Behaviour	Automatic error reset and switch back on		
Additional Error Information (AMK Service)			
Error Removal	● Check bus wiring ● Check inverter -U1 ● Check control unit -A1		

© AMK Arnold Müller GmbH & Co. KG, Gaußstraße 37-39, D-73230 Kirchheim/Teck