

THESIS APPROVED BY

Date

Michael G. Nichols, Ph.D.

Jonathan P. Wrubel, Ph.D.

Brian Hill, MS.

A. Barron Breland, D.M.
Dean, Graduate School

MAGNETICALLY INDUCED FORCES ON
EPICARDIAL LEADS
EXPERIMENTAL DEVICE DEVELOPMENT AND CLINICAL TESTING

by

DANIEL JUAREZ LUNA

A THESIS

Submitted to the faculty of the Graduate School of Creighton
University in Partial Fulfillment of the Requirements for the degree of
Master of Science in Medical Physics in the Department of Physics

Omaha, NE
November 2, 2025

Abstract

The abstract is a maximum 350 word, double-spaced summary of your work. The word count limit is important for upload to the Creighton Digital Repository.

This project can be found as a template on the Overleaf.com Latex-writing website.

Acknowledgments

Thank your research team, advisor, committee, family and friends, etc. See previous theses for examples.

I would like to thank Kian for introducing me to Latex, Kyle and Bong for troubleshooting help, and Dr. Nichols for his help with thesis creation.

For Dr. Nichols

Contents

Abstract	iii
Acknowledgments	iv
Dedication	v
1 Introduction	1
1.1 Literature Review	4
1.2 Scope of Research	8
1.3 Summary	10
2 Theoretical Background	12
2.1 Magnetic Resonance Imaging	12
2.1.1 Scanner Design and Subsystems	17
2.1.2 The Static Field	19
2.1.3 Translational Forces induced by the Static Field	25
2.1.4 Torque induced by the Static Field and Torque Transfer	27
2.2 Epicardial Leads	27
2.3 Concluding Remarks	32
3 Materials and Methods	33
3.1 Magnetic Field Generation and mapping	34

3.1.1	Magnetic Field and Gradient Mapping Platform	35
3.2	Translational Force Measurement via Angular Deflection	37
3.2.1	Measurement Device	38
3.3	Torque Measurement via Counter-torque	41
3.3.1	Torque Measurement Apparatus	41
4	Results	51
4.1	Magnetic Field Mapping	51
4.2	Translational	51
4.3	Torque	51
5	Discussion and Conclusion	52
A	Engineering Drawings	53
Appendix A1:	Pole drawing	53
Appendix A2:	Frame drawing	55
B	Calibration Logs	56
C	Copyright permissions	61
	Glossary	61
	References	63

List of Tables

2.1	Magnetic susceptibility of epicardial lead materials	31
3.1	Characteristics of the rods used in experiments.	43

List of Figures

2.1	Proton alignment in a magnetic field	14
2.2	Illustration of proton precession under a static magnetic field B_0 compared to that of a spinning top under gravity. Adapted from Pooley, R. A., <i>Fundamental physics of MR imaging</i> , (2005) [1].	15
2.3	Comparison between T1- and T2-weighted brain MRI images.	16
2.4	Design schematic and example of a clinical MRI scanner	17
2.5	. Adapted from [2].	20
2.6	Expected 1D axial magnetic field B_z for an ideal solenoid, mimicking an MRI scanner.	21
2.7	3D rendering of the axial magnetic field of a 3 T MRI solenoid.	22
2.8	Spectrum of magnetic susceptibilities. The upper diagram uses a logarithmic scale to indicate the full range of observed magnetic susceptibility values: it extends from -1.0 for superconductors to 100,000 for soft ferromagnetic materials. The bottom diagram uses a linear scale (in ppm) to indicate the properties of some materials with 20 ppm. The susceptibilities of most human tissues are in the range from 7.0 to 11.0 ppm. Adapted from Schenck [16].	23
2.9	Free-body diagram of device in magnetic field (adapted from ASTM F2052-15 [20], Appendix X2).	25

2.10	Comparison of transvenous vs epicardial lead placement in pacemakers (adapted from [3]).	28
2.11	Comparison of unipolar and bipolar epicardial pacing leads	29
2.12	Lead fixation and body design variations in pacing leads	30
3.1	PVC-based magnetic field mapping platform	36
3.2	Flowchart of the Gaussmeter VI data acquisition algorithm.	47
3.3	CAD render of the pendulum apparatus created using CATIA.	48
3.4	3D render of the design on lead holder	48
3.5	In-lab experimental setup for MRI translational force assessment. La- beled components include the solenoid, pendulum fixture, measure- ment tools, and control equipment.	49
3.6	Experimental equipment and corresponding list.	49
3.7	Main device close up and corresponding list.	50
B.1	Displacement as a function of current through the solenoid.	56
B.2	Measured angle α versus magnetic field intensity B_0	57
B.3	Computed translational force F_m as a function of B_0	57
B.4	Residuals from linear fit of $\tan(\alpha)$ vs. $B_0 \cdot \frac{dB_0}{dz}$. Error bars indicate propagated uncertainties.	58
B.5	Propagation of measurement uncertainty through magnetic field anal- ysis. Top: Measured field B_0 with standard deviation and SEM. Mid- dle: Gradient dB/dz with propagated error. Bottom: Final product $B_0 \cdot dB/dz$ with multiple uncertainty estimations (standard, fractional, SEM). This term was used as the independent variable in the suscep- tibility fit.	59

B.6	Calibration curves for two aluminum (AL) rods in three different orientations. Linear fits show consistent response across orientations, confirming the reliability of the lab-built sensor (see Methods Section for details).	60
B.7	Mean voltage response of the sensor as a function of height for different distances from the center (50–100 mm). A small and relatively flat voltage is observed across all radii, while at larger heights (farther from the bridge) the measurements diverge, showing higher sensitivity near the center (50 mm). See Methods Section for details on torque transfer and distance selection.	60

Chapter 1

Introduction

Medical diagnostics heavily rely on imaging tools such as Magnetic Resonance Imaging (MRI), a powerful and evolving application capable of showing high contrast sensitivity to soft tissue while not depending on ionizing radiation. However, safety concerns may arise during cardiac MRI procedures, electrocardiogram (ECG) leads are generally cataloged as MRI unsafe because of the strong magnetic field and radiofrequency (RF) pulses that may interact with these leads.

More than 300,000 individuals are receiving new cardiac implantable electronic device (CIED) implants every year in the U.S. alone, reported the Heart Rhythm Society (HRS) in 2024 [4]. Some of these patients will eventually require device explantation or revision, necessitating surgery [5]. For this reason, a well established protocol to monitor cardiac rhythm exists, it involves the use of temporary epicardial leads, however there is a recognized practice when these leads are removed (only if significant resistance is encountered) to cut the wire flush with the skin, intentionally leaving a small segment inside the patient to prevent immediate complications [6, 7, 8].

Temporary epicardial pacing leads are frequently utilized as part of postoperative cardiac rhythm control procedures, for example, leads are frequently placed during open-heart surgery to regulate cardiac rhythm postoperatively, then are typically cut

at the skin surface leaving behind a short length of wire embedded in the tissue [9]. When the surgical danger of removing these leads is too high, they are left in place to prevent further complications. These cases introduce long-term repercussions, most notably the loss of access to MRI scanners.

According to ASTM F2503, a device labeled as MRI safe is expected to be non-conductive, non-electrical, non-magnetic, and to present no known hazards in the MRI environment [10]. However, this classification does not apply to all epicardial leads, as they are rarely physically characterized after removal, nor properly labeled by vendors. By the time they are cut, these leads have fulfilled their clinical purpose, and systematic safety evaluations are seldom performed.

Although retained leads are nonfunctional and relatively short, that of about 8 to 20 cm, they are frequently classified as MRI unsafe due to concerns over RF heating, magnetically induced translational forces and torques, or inadvertent cardiac stimulation [11, 12, 13]. Effectively preventing patients with CIED or cardiac surgery history, who are most likely to need a MRI scan during their lifetime, to not be able to enter MRI room.

There is still a dearth of focused studies evaluating the precise dangers associated with retained epicardial leads, despite the frequent use of such leads and their repercussions. Existing clinical recommendations tend to be too cautious and frequently disqualify these individuals from MRI eligibility even when there is little evidence to support it. Recent studies regarding this problem have shown both no image quality degradation and, most importantly, no serious safety events such as, device malfunction, myocardial injury or arrhythmias, associated with MRI examinations in patients with CIEDs abandoned leads, including epicardial leads [14, 15]. While these studies have evaluated (to some extent) the resulting consequences of RF-induced heating, mechanical forces and conductivity, additional detail is needed.

Therefore, the primary safety concerns regarding retained cardiac leads during MRI arise from three main interaction mechanisms. First, the strong magnetic field and its spatial gradient can exert translational forces and torques on the lead, resulting in mechanical displacement along the direction of the magnetic field. Second, the lead can absorb energy from the MRI's (RF) field, potentially causing localized heating that poses a thermal risk to the patient. Third, the RF field may induce alternating currents within the lead, which can electrically stimulate nearby cardiac tissue, potentially leading to dangerous physiological effects [16]. Being the main topic of this document, translational motion and torque. Which remains under-characterized and that most of the research done in this subject shows the importance of translational forces in safety about common hospital objects that could potentially become projectiles while disregarding smaller. These are developed in Chapter 2.

In this document an explanation of the current state of research on this matter, the main elements involved in the interaction of temporary epicardial leads and MRI, especially in relation to mechanical interactions like translational force and torque are given. Current research, safety recommendations and methodologies to assess the magnetically induced forces involved between an MRI system and epicardial leads were explored. And the development of a in-lab methodology capable of testing these micro-Newton forces with precision later carried into clinical work was documented. All these, in order to clarify whether the static magnetic field in MRI poses a real risk to patients with retained leads.

To properly situate this work, the following section reviews pertinent literature on MRI QA devices, MRI safety principles, and previous studies to establish current state of the art regarding epicardial leads on MRI environment.

1.1 Literature Review

A large observational study by Schaller et al. [17] evaluated 200 MRI examinations in 139 patients with a total of 243 abandoned leads. Their objective was to assess the safety of 1.5-T MRI in patients with at least one abandoned CIED lead and to evaluate any potentially harmful effects on the active CIED leads. The research found a low rate of adverse events (3%), with no serious complications such as sustained arrhythmias or device resets. The observed events were primarily transient, non-life-threatening changes in lead sensing parameters that resolved spontaneously. Notably, this safety profile held for thoracic and cardiac MRIs, where the theoretical risk is highest.

Complementing this, a retrospective study by Vuorinen et al. [14] focused on 26 MRIs in 17 patients with epicardial leads. The study's key finding was that MRIs performed on patients with "modern" epicardial leads (implanted in 2000 or later) had no detectable adverse events. However, one definite and one possible adverse event were noted in patients with "old" leads (implanted before 2000), suggesting that lead age and technology may be a factor in the risk profile.

From a safety standpoint, the static magnetic field (B_0) represents the main source of hazard and must be shielded properly. A huge number of diagnostic clinical scans are daily completed without incidents indicating that magnetic interactions with normal tissues are within the bounds of safety up to the highest fields now in use for MRI [16]. However, there had been incidents associated with ferromagnetic objects either implanted in the patient or located in the fringing field of the magnets [18, 19].

ASTM F2052-21 [20] offers a standardized technique for assessing magnetically induced displacement force on medical equipment in order to set safety standards for such situations. The methodology includes a non-magnetic pendulum apparatus with a protractor that allows for the a suspended subject to be pulled by the magnetic field. The characterization of the static magnetic field and its spacial gradient is required.

For this purpose, Ferreira et al. [21], developed a custom-designed fixture with an AlphaLab Gaussmeter probe to map the spatial gradients inside a Siemens Magnetom Trio 3T MRI scanner. Measurements of the magnetic field vector components (X, Y, and Z) were collected along the Z-axis in 5cm increments, correctly capturing the static magnetic field and ensuring repeatability and showing a steady spatial gradient.

Furthermore, Woods et al. [22], conducted a similar experiment, to assess the magnetically induced displacement force on eleven metal alloys commonly used in medical implants. For deflection force testing, nine specimens (in three nominal mass categories: 2, 20, and 200 g) of each alloy were tested in a Siemens MAGNETOM Trio 3T MR system. The main results regarding magnetically induced deflection force showed that for seven of the eleven tested alloys, the magnetic force was found to be less than the device weight in any current clinical 1.5 T, 3.0 T, and 7.0 T MR system. These safe alloys included various grades of CP titanium, Ti-6Al-7Nb, Ti-6Al-4V ELI, Ti-15Mo, Biodur 108, and Co-28Cr-6M. However, for the other alloys, including 316L stainless steel and 22Cr-13Ni-5Mn, the magnetically induced force was calculated to be greater than the device weight in certain high-field systems, such as 3.0 T and 7.0 T clinical scanners.

In terms of torque measurements, Woods et al. [22] claimed that for medical instruments made from their list of alloys the magnetically induced torque will always be less than the worst case torque produced by gravity in a 3.0 T or less static magnetic field. And emphasized that *“No movement was observed for any of the magnetically induced torque specimens at 3.0 T.”* This, was probably measured using ASTM F2213-17 [23] Low Friction Surface Method methodology which estimates magnetically induced torque by placing the device on a low-friction, non-metallic, non-conductive surface near the MRI isocenter. The device is rotated stepwise, and any spontaneous alignment or rotation toward the static magnetic field is observed.

If no movement occurs, the maximum possible torque is estimated from the device’s weight and the surface’s friction coefficient outside the MR environment.

ASTM F2213-17 states that, if rotation is observed, more precise tests (such as the Torsional Spring or Pulley Method) should be used instead which means this method relies on macroscopic motion and may not be able to detect μ Newton forces.

Another study by Seo et al. [24], utilized the “Pulley Method” for the safety assessment of magnetically induced torques on active implantable medical devices (AIMD)s in 1.5 T and 3.0 T magnetic resonance imaging (MRI) environments. The apparatus, has a cylindrical shape and was fabricated entirely from acrylic (including the bearings) to minimize magnetic field resistance.

This methodology determines the maximum magnetically induced torque by fixing the AIMD onto a rotating plate placed at the MRI isocenter. A thread attached to the plate is connected to a force gauge located far enough to avoid interference with the magnetic field. As the plate rotates to align with field, the thread tension is measured. The torque is then calculated by multiplying the plate’s radius (at the AIMD’s position) by the measured force, after subtracting the plate’s frictional resistance.

The main results showed that the bone conduction implant consistently exhibited the highest average torque (9.460 Ncm at 1.5 T and 14.618 Ncm at 3.0 T), while the pacemaker showed the lowest (0.255 Ncm at 1.5 T and 0.668 Ncm at 3.0 T). AIMDs containing magnets (cochlear and bone conduction implants) generally showed significantly higher torques than devices without magnets (ICD and pacemaker).

Similarly, Stoianovici et al. [25] showcases a variation of the ASTM F2213 Torsional Spring measurement technique, referred as the 2-string method. This method address the difficulty of measuring very low magnetically induced torques on lightweight, slender medical devices, such as needles. This approach utilizes two strings to suspend the device by its ends and creates a torsional spring mechanism that is frictionless.

The needle rotates due to magnetic torque, the torque is calculated analytically based on the measured rotation angle and compared to the weight of the object. The main results showed that the method successfully measured torques between 0.0001 Nm and 0.0018 Nm in the MRI environment. the maximum magnetically induced deflection angle remained below the 25° limit required by the ASTM F2213.

In contrast, the gradient and RF fields are primarily associated with peripheral nerve stimulation and tissue heating, respectively. These effects are relevant for patients with conductive leads or elongated implants that may act as antennas or current loops. Previous studies of Aboyewa, et al. [6], seek to illustrate the interaction of leads with the RF field in terms of energy absorbed and heat produced.

The experiment was performed on a 3 T MRI scanner using a turbo spin echo pulse sequence. The pulse sequence was set to produce a whole-body Specific Absorption Rate (SAR) of approximately 2 W/kg and fluoroptic probes were used to measure the temperature rise. Several factors on induced heating were tested, including lead length (such as 6.33 cm, 12.65 cm, and 18.98 cm), lead type (bipolar vs. unipolar), orientation, and shape

It showed that lead length, type, and orientation significantly influence heating behavior. This study found that short leads (< 13 cm) posed no significant thermal hazard during MRI at a specific absorption rate (SAR) of 2 W/kg but the maximum temperature rise observed at the lead tips. For both lead types investigated, the amount of heat induced increased with increasing lead length. Notably, bipolar leads showed slightly higher heating than unipolar leads and the straight lead configuration produced the highest maximum temperature rise.

Stoianovici et al. [25] solves the technical challenge of measuring very low magnetically induced torques on slender, lightweight medical devices, such as needles, where conventional ASTM F2213 methods often become unreliable due to friction bias with their new methodology variant (The-2-string-method). Similarly, Seo et al.

[24] validates the pulley methodology for AIMDs. The modeling of clinically relevant allows done by Woods et al. [22] shows experimental basis to rely on the listed alloys but requires further testing in terms of torque. While the modeling of the static magnetic field done by Ferreira et al. [21] provided a practical way to accurately map the magnetic field and calculate its spacial gradient.

Finally, MRI safety protocols are grounded in a system of absolute and relative contraindications. Absolute contraindications include non-MR-conditional cardiac implantable electronic devices (CIEDs), metallic intraocular, and foreign bodies, among others. Relative contraindications consider implants such as stents, surgical clips, and programmable shunts that may be scanned under controlled conditions [26]. The safety classification of each device is guided by testing standards and certification data, with CIEDs representing a critical category due to their susceptibility to electromagnetic interactions [16, 27].

The American College of Radiology (ACR) Manual on MR Safety (2024) [28] outlines the current regulatory and procedural framework for MRI safety. Recommendations include structured zoned access control and interprofessional collaboration through clearly defined positions (MR Medical Director, MR Safety Officer, and MR Safety Expert) to avoid unscreened individuals or ferromagnetic objects from inadvertently entering the magnet room. Pre-scan screening, implant model and status verification, and continuous patient monitoring are still necessary for this safety infrastructure [26].

1.2 Scope of Research

The primary objective of this study is to experimentally characterize torque and translational magnetic forces acting on retained epicardial pacing leads near and inside the MRI bore, and to map how those forces evolve with distance from the isocenter.

The wider research question is: Do retained epicardial pacing leads experience torque or translational magnetic forces within an MRI environment that are clinically significant enough to justify current safety restrictions? A particular research question then follows: How to implement current methodologies to measure micro-Newtons on a clinic environment?

A lab methodology was first developed, working towards clinical environment and rigor addressing potential issues. Thus, this document aims to provide experimental evidence and addressing a gap in the literature. In the lab, investigation used a Polyvinyl Chloride (PVC) pendulum-based measurement setup following ASTM F2052 [20] for the displacement angle and a custom-made solenoid simulating a magnetic field similar to that found on a MRI scanner bore entrance at scale. Displacement in millimeters of a metallic rod exposed to the field were recorded to ultimately estimate the translational force.

A second setup for torque measurements was developed. A set of neodymium magnets would create the static field while a metallic rod would be fixed in a position perpendicular to the field with an attachment and be allowed to rotate, counter forces would then be measured out the attachment with a circuit and sensor of our own fabrication. A second iteration of this setup would include a Helmholtz coil to test on field variation.

These methods allow for high sensitivity in detecting small magnetic forces in a controlled environment, without the complications of patient variability or direct MRI scanner use. The pendulum approach provides a clear physical model that isolates translational force components for precise characterization. The torque model allows to independently assess strength of force exerted.

In the following chapter, a thorough description of the experimental setup will be given. This includes the caveats found and their respective solutions with detailed documentation on the artifacts and tools created for the investigation.

The thesis consistently engages with the first of three interaction modes of concern between MRI and retained leads: mechanical forces, RF-induced heating, and induced currents. Particularly, the study cares about translational and rotational displacement due to static field gradients to clarify whether or not the movement involve signifies a risk to patients with temporal epicardial leads when an MRI scan is needed.

Measurements are interpreted in the context of magnetic susceptibility theory and compared to relevant thresholds from the literature [29, 20]. These techniques will help with more thorough evaluations of MRI safety in patients with retained temporary epicardial leads and set the stage for a future clinical adaptation of the protocol employing a 3T MRI scanner.

1.3 Summary

Epicardial leads have the problem of being broadly labeled MRI-unsafe under ASTM F2503. This classification origins from theoretical concerns over static magnetic field interactions (translational force and torque), RF-induced heating, and inadvertent electrical stimulation, yet it restricts MRI access for cardiac patients most in need of diagnostic imaging.

Hundreds of MRI tests using abandoned leads, including contemporary epicardial types, have shown no significant adverse events, indicating good safety profiles in large observational studies. There is still a significant gap in the accurate, micro-Newton-scale characterization of mechanical forces on thin, lightweight epicardial leads, despite the fact that standardized testing (ASTM F2052, F2213 [20],[23]) and earlier research on implant alloys confirm low magnetic interactions in many materials. The methodology on this project follows that of the literature reviewed in this chapter. Featuring a static field mapping fixture, a pendulum for deflection an-

gle determination, and a newly developed torque device that somewhat resembles a suspension method but uses a low friction bearing to enable rotation and a highly sensitive sensor to measure μ Newton forces, which is further described in Chapter ??.

Building on this foundation, Chapter 2 will provide essential background on the underlying physics of MRI scanners. It includes the generation and spatial distribution of static field, along with a broad introduction to gradient, and RF fields. Alongside physics, a detailed description of epicardial lead design, material composition, and implantation configurations is provided. Key concepts from electromagnetism (magnetic susceptibility, force, and torque on conductive elements) and mechanics (deflection, rotation, and tissue anchoring) will form the thematic backbone, enabling a rigorous analysis of lead-MRI interactions and informing the interpretation of experimental results in subsequent chapters.

Chapter 2

Theoretical Background

This chapter provides a review of the most important topics to know to fully understand the findings of this current work. It includes an introduction to MRI scanners, the physics behind them and, more importantly, the possible interactions of the system with matter. Moreover, an emphasis on the static magnetic field of a MRI scanner and mechanical interactions with epicardial leads is included. A brief discussion on epicardial leads design is included followed by implications for the clinic and the lab setting.

Most of this chapter content is based on physics and imaging from well known textbooks, including Griffith's Introduction to Electrodynamics [30], and Bushberg's Physics of Medical Imaging [2].

2.1 Magnetic Resonance Imaging

MRI or Magnetic Resonance Imaging is a medical imaging modality that uses magnetic fields and radiofrequency (RF) energy to produce images, rather than ionizing radiation like X-rays making it inherent safe. Moreover, MRI machines are capable of achieving high contrast sensitivity to soft tissue differences because of the reliance

on micromagnetic properties of the tissue and its inherent differences leveraging on Proton Density (PD) and the relaxation phenomena.

MRI, as the name suggests, leverages the magnetic properties of matter (its atoms) to capture information by applying RF energy at the resonance frequency and detects the re-emitted signals to ultimately create an image. In fact, MRI was originally named Nuclear Magnetic Resonance (NMR), because it involves the spectroscopic study of the magnetic properties of the nucleus of the atom as it resonates and aligns to the magnetic field changes.

It is important, then, to understand these properties and how they are characterized. On the scale of elementary particles, these effects involve interactions with protons and neutrons within the atomic nucleus due to their nuclear spin and charge distribution. Hydrogen (specifically its proton, 1H) is the most utilized element in clinical MRI because it has the largest magnetic moment and is highly abundant in biological tissues, primarily in water and fat.

Normally, these unbound hydrogen atoms have a random orientation of their nuclear magnetic moments (protons) due to thermal energy. When placed in a strong static magnetic field (B_0), these nuclear magnetic moments align in parallel (same direction of B_0 , low-energy state) and antiparallel (opposite direction of B_0 , high-energy state) directions. This is illustrated in Figure 2.1, notice that the distribution of protons into these two states is influenced by thermal energy and a slight majority align in the low-energy, parallel direction, resulting in an observable net magnetic moment (red arrow) usually denoted as equilibrium magnetization (M_0).

In addition to aligning with B_0 , the protons also experience precession, much like the Earth's rotation around its tilted axis or a spinning top under gravity. Depicted in Figure 2.2, the motion happens around the axis of the applied magnetic field due to the perpendicular torque they experience. This precession occurs at an angular




Figure 2.1: Schematic illustration of how hydrogen protons (^1H) behave in the presence of a strong static magnetic field (B_0). A: In the absence of a field, proton magnetic moments are randomly oriented, producing no net magnetization. B: When exposed to B_0 , protons align either parallel or antiparallel to the field. From Bushberg, J.T., *The Essential Physics of Medical Imaging* (2011) [2].

frequency (ω_0) known as the Larmor frequency, which is directly proportional to the magnetic field strength (B_0), as described by the Larmor equation (2.1):

$$\omega_0 = \gamma B_0. \quad (2.1)$$

An RF energy pulse (B_1) is then applied, synchronized to the Larmor frequency of protons (about 42.58 MHz per tesla), magnetizing the protons and tipping the net magnetization (M) away from the longitudinal direction (M_z). This pulse provides just enough energy for some protons to move into a higher energy state, also called RF excitation. In doing so, it also causes the magnetic moments of many protons to become synchronized, or phase-coherent. They start to precess together in the transverse plane, creating what is called transverse magnetization (M_{xy}).

The instant the RF pulse is turned off, the relaxation process starts, these precessing protons start to lose that synchronization due to slight variations in their local magnetic environments. This causes the transverse magnetization signal to gradually fade over time. The oscillations of this signal are detected by the same RF coils that




Figure 2.2: Illustration of proton precession under a static magnetic field B_0 compared to that of a spinning top under gravity. Adapted from Pooley, R. A., *Fundamental physics of MR imaging*, (2005) [1].

sent them. The strength and rate of decay of this signal are dependent on the tissue type and are characterized by two time constants: $T1$ and $T2$.

First, the signal in the transverse plane, (M_{xy}) , decreases as the protons desynchronize, this is described by $T2$ (Transverse Relaxation). And the process by which the system regains equilibrium is described by $T1$ (Longitudinal Relaxation). The longitudinal magnetization (M_z) returns, and the particles realign with the main magnetic field (B_0) . The final MRI image's depiction of a tissue's brightness or darkness is determined by these relaxation processes taken together. For instance, on $T1$ -weighted images, tissues with short $T1$ times (such as fat) seem bright, whereas on $T2$ -weighted images, tissues with longer $T2$ periods (such as cerebrospinal fluid) appear bright, see Figure 2.3.

However, this covers one a single signal from a particular spot. To make an image rather, the MRI system must know where each signal is coming from. This is achieved using small, precisely controlled variations in the magnetic field known as




Figure 2.3: Comparison between T1- and T2-weighted brain MRI images of the same subject. The left image shows a T2-weighted scan, where cerebrospinal fluid (CSF) appears bright, and the right image shows a T1-weighted scan, where fat and white matter appear bright. Adapted from [31].


gradient fields. These gradient coils, superimposed on B_0 , make the magnetic field slightly stronger or weaker depending on position, causing the Larmor frequency of the protons to vary with location.

Three gradient systems work together to map space. First, Slice Select Gradient (SSG) is applied during excitation so that only protons in a particular “slice” of the body resonate at the RF pulse frequency. This defines the plane of imaging. Then, Phase Encoding Gradient (PEG), briefly changes the precession speed of protons in one direction, giving each row of tissue a unique phase “signature”. Finally, Frequency Encoding Gradient (FEG) is applied during signal readout so that protons along another axis precess at slightly different frequencies.

The resulting signals are stored in a matrix called k-space. Each line in k-space represents one measurement with a specific gradient configuration. When all necessary lines are filled, the Fourier Transform reconstructs the data into an image, where each pixel corresponds to a small volume element (voxel) of tissue.

So far we have highlighted three of the five main components in the image formation process. That is, Static Field, RF pulses and Field gradients. Figure 2.4(a)

shows all these components and Figure 2.4(b) provides an example of a actual, clinically relevant MRI scanner like the one used at CHI Health Creighton University Medical Center - Bergan Mercy. Each of these pieces are accompanied by interaction complications if a foreign object lays around the test space. For example, as explained in section 1.1 heat and electrical interactions are a concern of RF fields or Gradient Coils [6, 17]. For mechanical interactions, the interest falls under the mechanisms in which the static magnetic field could possibly interact with wire or thin cylinder like devices. In the next section a review of an MRI scanner components is given, followed by a complete explanation on the main magnet as it is the focus of this document.



(a) Diagram illustrating the main five components of an MRI scanner.

(b) Siemens 3T Magnetom Trio clinical MRI system.

Figure 2.4: MRI scanner schematic and a clinical MRI system. (a) Simplified MRI scanner design highlighting the main magnet, gradient coils, and RF system, Control electronics, and Console. Adapted from Prince [32]. (b) Siemens Magnetom Trio 3T system, like at CUMC Bergan Mercy Hospital. As a modern whole-body MRI scanners, adapted from [33].

2.1.1 Scanner Design and Subsystems

As mentioned above, after the main static field (B_0) has been established and shimmed to high homogeneity the gradient coils introduce controlled spatial variation

in the magnetic field for encoding localizing signals generated during MR. Gradient coils, are wire conductors located within the main bore of the magnet with typical strength values from 1 to 50 mT/m and correspond to the logical coordinate axes: x, y, and z which relate to SSG, PEG, and FEG. They operate by adding to or subtracting from the magnitude of the main field (B_0), but they do not change the direction of the magnetic field [2].

These gradients must switch rapidly and with large current flows, typical slew rate ranges from 5 to 250 mT/m/ms, with currents on the order of 100–200 A [2, 32], to accomplish encoding. For this reason, they introduce hazard mechanisms beyond magnetic fields. For example, when the gradient currents are repeatedly turned on and off, large forces (Lorentz forces) are applied to the coils in the strong magnetic field, leading to significant vibration. That, is the source of the loud "knocking" sounds during MR scans. Noise levels in modern MRI systems can easily exceed 130 dB and temporary hearing loss was reported in early studies [34]. Consequently, hearing protection is now considered mandatory during MRI procedures.

Moreover, the rapid temporal variation of MRI gradient fields induces electric fields within conductive tissues via Faraday's law. Although these fields are much weaker than those associated with RF transmission in terms of tissue heating the time-varying electric potentials can depolarize excitable membranes, producing peripheral nerve stimulation (PNS) or, in extreme cases, involuntary muscle twitching [34, 35]. The effect scales with both the rate of change of the magnetic field and the spatial extent of the conductive path through tissue, so even though the absolute magnetic field perturbation from gradients (10–60 mT/m, or less than 1% of B_0) is small, the rapid temporal ramping can induce voltages large enough to reach neural activation thresholds [?]. Typical clinical systems, limited by FDA guidelines to ~ 40 T/s, remain below the threshold for cardiac excitation, but research systems capable

of 300 mT/m gradients and higher slew rates approach that regime, posing theoretical cardiac stimulation risks [2, 32, 34].

RF coils and heating

The control and computing subsystems coordinate every stage of image acquisition and reconstruction. The host computer and operator console provide the interface through which the technologist selects and supervises scanning protocols, while the pulse programming and measurement control systems synchronize gradient and RF activity [2]. Supporting units such as the digitizer, image processor, and compute engine translate the raw analog signals into interpretable digital images through Fourier-based reconstruction algorithms [32]; Finally, the dedicated power supplies, patient table mechanics, and electromagnetic shielding ensure stable operation, patient positioning, and noise minimization.

2.1.2 The Static Field

Magnets are at the core of MR systems, and their performance is judged by field strength, temporal stability, and homogeneity. The strength of a magnetic field, also known as magnetic flux density (B), is measured in Tesla (T). An older, alternative unit is the gauss (G), where $1 \text{ T} = 10,000 \text{ G}$. For perspective, Earth’s magnetic field is significantly weaker, around 0.00005 T (0.05 mT or 0.5-1.0 G).

Magnetic fields can be induced by moving charges in a wire, where the direction depends on the charge’s sign and direction, described by the ”right-hand rule”. Coiling a current-carrying wire, creating a solenoid or electromagnet, superimposes these magnetic fields, significantly augmenting the field strength inside the coil and causing a rapid falloff outside. Equation 2.2 shows how the amplitude of the current and the number of coil turns determine the overall magnitude of the magnetic field strength for an ideal solenoid and the shape of such field is depicted in figure 2.5.

$$B = \mu_0 nI. \quad (2.2)$$

Where B is the magnetic field, μ_0 is the vacuum permeability, n is the number of turns and I is the current. Common MRI are typically made of superconducting wire-wrapped cylinders. These wires are made from niobium-titanium alloys and show no resistance to electric current when maintained at extremely low temperatures. Notice that on Figure 2.5 produced magnetic field is parallel to the cylinder's long axis, usually horizontal (along the patient's cranial-caudal axis in clinical systems).




Figure 2.5: . Adapted from [2].

A more accurate depiction of the magnetic field can be obtained by modeling a finite solenoid of length L and radius R using a formula derived from Biot–Savart law with $B = 3\text{T}$ from equation 2.2 as follows:

$$B(z) = \frac{\mu_0 n I}{2} \left[\frac{z + \frac{L}{2}}{\sqrt{R^2 + \left(z + \frac{L}{2}\right)^2}} - \frac{z - \frac{L}{2}}{\sqrt{R^2 + \left(z - \frac{L}{2}\right)^2}} \right]. \quad (2.3)$$

where μ_0 is the permeability of free space. The first term in the brackets represents the contribution from the far end of the solenoid, and the second term represents the contribution from the near end.

This formula provides the axial field along the solenoid, with the maximum occurring at the center ($z = 0$) and decreasing smoothly toward the ends. Then, calculating the gradient and finding its maximum value, the bore entrance can be located [20, 21]. Figure 2.6 showcases this model, it features the magnetic field (B_0) along the z-axis, the origin $z = 0$ corresponds to the entrance of the bore. The field is normalized to a maximum of $B_0 = 3$ T, with no shielding or distortion applied.




Figure 2.6: Expected 1D axial magnetic field B_z for an ideal solenoid, mimicking an MRI scanner.

From the same model a 3D render with slices of the field can also be constructed. Figure 2.7 is the resulting plot with a reference cylinder superimposed to indicate the bore space.

Let us then follow the physics of a static magnetic field and its interaction with matter with electromagnetism theory. Any material placed in a magnetic field develops a magnetization, $\mathbf{M}$, defined as the net magnetic dipole moment per unit volume:

$$\mathbf{M} \equiv \frac{\boldsymbol{\mu}}{V}. \quad (2.4)$$

where $\boldsymbol{\mu}$ is the sum of the microscopic magnetic dipoles within the volume V [30]. In practice, the microscopic magnetic field inside a material fluctuates rapidly due to




Figure 2.7: 3D rendering of the axial magnetic field of a 3 T MRI solenoid.

atomic and electronic motion. To describe macroscopic behavior, we use an average field over many atoms, and $\mathbf{M}$ represents this “smoothed” magnetization.

To simplify the analysis of materials in magnetic fields, physicists define the auxiliary magnetic field $\mathbf{H}$:

$$\mathbf{H} \equiv \frac{1}{\mu_0} \mathbf{B} - \mathbf{M}. \quad (2.5)$$

where $\mathbf{B}$ is the macroscopic magnetic flux density and μ_0 is the permeability of free space. $\mathbf{H}$ accounts for the part of the magnetic field produced by free currents, separating it from the bound currents induced by magnetization [30]. This distinction becomes useful when analyzing mechanical effects on magnetic dipoles.

Different materials respond differently to an applied field. As magnetization is also directly proportional to the field strength $\mathbf{H}$:

$$\mathbf{M} = \chi_m \mathbf{H}. \quad (2.6)$$

The degree to which a material becomes magnetized is quantified by its magnetic susceptibility, χ , which is typically small in biological tissues ($|\Delta\chi| < 0.01$). Diamagnetic materials, such as water, calcium, and most organic compounds, develop a magnetization opposite to the applied B-field due to paired electrons. Paramagnetic substances, like molecular oxygen, deoxyhemoglobin, or gadolinium-based MRI contrast agents, align weakly with the field, enhancing the local magnetic flux. Ferromagnetic materials, by contrast, exhibit strong self-sustained magnetization but are generally avoided in MRI due to safety hazards. Figure 2.8 shows a spectrum of magnetic susceptibilities with a zoom in for the MRI compatibility obscure section.




Figure 2.8: Spectrum of magnetic susceptibilities. The upper diagram uses a logarithmic scale to indicate the full range of observed magnetic susceptibility values: it extends from -1.0 for superconductors to 100,000 for soft ferromagnetic materials. The bottom diagram uses a linear scale (in ppm) to indicate the properties of some materials with 20 ppm. The susceptibilities of most human tissues are in the range from 7.0 to 11.0 ppm. Adapted from Schenck [16].

For materials that obey Eq. 2.6, called *linear media*, the magnetic flux density can be expressed as

$$\mathbf{B} = \mu_0(1 + \chi_m)\mathbf{H}, \quad (2.7a)$$

$$\mathbf{B} \approx \mu_0\mathbf{H}, \quad (|\chi_m| \ll 1). \quad (2.7b)$$

where χ_m is the magnetic susceptibility of the material. We can define the *permeability* of the material as $\mu \equiv \mu_0(1 + \chi_m)$, so that the relationship between $\mathbf{B}$ and $\mathbf{H}$ simplifies to $\mathbf{B} = \mu\mathbf{H}$. Moreover for paramagnetic materials which susceptibility is tiny ($|\chi_m| \ll 1$) $\mathbf{B}$ can approximate to $\mathbf{B} \approx \mu_0\mathbf{H}$.

This formulation shows that in linear media, the magnetic flux density is directly proportional to the applied field strength, statement that will come in handy when calculating for forces and torque in the next section. In the particular case of magnetic dipoles $\boldsymbol{\mu}$, mechanical interactions with a magnetic field such as forces and torques the following expressions are the foundation from general physics.

$$\mathbf{F} = (\boldsymbol{\mu} \cdot \nabla)\mathbf{B}. \quad (2.8)$$

and a torque:

$$\boldsymbol{\tau} = \boldsymbol{\mu} \times \mathbf{B}. \quad (2.9)$$

where $\boldsymbol{\mu}$ is the magnetic dipole moment and B is the magnetic field. From these two equations we can solve for more specific physical setups. For translational force the equation (2.8) is developed following ASTM F2052-15, as same methodology was employed. While equation (2.9) for torque is dependent to the particular procedure

used on the lab, and will be developed in more detail based on our own experimental setup.

2.1.3 Translational Forces induced by the Static Field

Consider a simple pendulum, free to swing along the z-axis of an MRI (for simplicity, left to right), along with a magnet that produce a static magnetic field along that same axis. The pendulum is then pulled towards the magnet with a force F_m until it reaches equilibrium with its weight mg . Figure 2.9 shows a complete free body diagram, a simpler version excludes Θ and assumes point particle at the end of the pendulum.




FIG. X2.1 Free Body Diagram of Device in Magnetic Field

Figure 2.9: Free-body diagram of device in magnetic field (adapted from ASTM F2052-15 [20], Appendix X2).

The magnetic force F_m is described from equation (2.8) and using equation (2.4) and (2.6) we can write:

$$\begin{aligned} F_m &= MV\nabla B, \\ &= \chi_m HV\nabla B. \end{aligned}$$

Finally, with equation (2.7b) the magnetic force in a single dimension is given by:

$$F_m = \frac{\chi_m V}{\mu_0} B \nabla B \quad \Rightarrow \quad F_m = \frac{\chi_m}{\mu_0} B_0 \frac{dB_0}{dz}. \quad (2.10)$$

Then following ASTM F2052-15, the translational force exerted on a device due to a static magnetic field spatial gradient can be evaluated through angular deflection. In the pendulum, test subject is suspended in equilibrium, and the balance of forces leads to

$$\frac{F_m}{mg} = \tan \alpha. \quad (2.11)$$

where α is the deflection angle from vertical, F_m is the magnetically induced translational force, m is the mass of the object, and g is the gravitational acceleration.

This is also derived from Newtonian force balancing (see Fig 2.9), and is valid even in cases when the magnetic force does not operate exactly at the center of mass. As a result, the approach is reliable for evaluating a variety of devices.

The formulation of equation (2.11) explains why the measured deflection angle α (and thus F_m) depends not on χ or B_0 independently, but on their product. Practically, this insight justifies the lab methodology. Although magnets in our lab, a solenoid or neodymium magnets, generate small magnetic fields (only about 20 to 300 Gauss), we used a highly ferromagnetic sample (assuming large χ), allowing us to replicate clinically relevant force-to-weight ratios (F_m/mg).

According to ASTM F2052 [20], a deflection below 45° corresponds to $F_m/(mg) < 1$, meaning the magnetic force is less than the object's weight, a conservative reference point for safety, though not a strict acceptance criterion [22]. In contrast, a nonmagnetic stainless steel wire ($\chi \approx 10^{-4}$) might show $F_m/(mg) \approx 0.3$, whereas ferromagnetic metals like nickel can exceed $F_m/(mg) > 2 \times 10^4$. That is more than enough to become dangerous projectiles unless restrained [6, 22, 34].

In our lab, we aimed to determine the magnetic susceptibility χ_m of the test sample. Using Eqs. (2.10) and (2.11), it can be expressed as

$$\chi = \frac{\mu_0 m g \tan \alpha}{V B_0 \frac{dB_0}{dz}} \quad (2.12)$$

this provides a direct estimation of magnetic susceptibility from angular deflection measurements, provided the field and its gradient are known. For experimental purposes, a plot of the deflection angle versus the product of field strength and field gradient allows one to extract χ_m from the slope of a linear fit, following

$$\tan \alpha = \frac{\chi_m V}{\rho \mu_0 g} \cdot B_0 \frac{dB_0}{dz} \quad (2.13)$$

In general, these forces are described as a function of the static field strength (B_0), its spatial gradient (∇B_0), and the material properties such as magnetic susceptibility (χ) and density (ρ). The expectation is then, magnetic pull on high susceptibility materials toward regions of higher field strength, like near the bore entrance of the scanner where the spatial gradient is highest [2, 6, 34].

2.1.4 Torque induced by the Static Field and Torque Transfer

2.2 Epicardial Leads

CIED systems refer to cardiac implantable electronic devices, including pacemakers, implantable cardioverter-defibrillators (ICD)s, cardiac resynchronization therapy (CRT) devices, and implanted rhythm monitors. These are advanced medical devices used to monitor and regulate heart rhythm disorders and leads are a component of CIED systems.

In practice, leads are a type of very thin, ~ 4 to 5 F (French gauge, meaning 1.3 to 1.7 mm), electrical wire that connects a pulse generator to the heart. Figure 2.10 shows the two types of leads that are used, epicardial leads; which are implanted directly on the epicardium (the outer surface of the heart) and Transvenous leads, inserted through the veins and positioned inside the heart's chambers, making contact with the endocardium (the inner lining of the heart). All these are prone to complications like fracture, infection, venous obstruction (transvenous only), and require complex extraction procedures [36, 37].





Figure 2.10: Comparison of transvenous vs epicardial lead placement in pacemakers (adapted from [3]).

The position of leads is an important distinction. Clinically, these leads are indicated for different populations and diagnostics therefore carry a variety of management decisions (leaving vs extracting) and different complications (percutaneous lead extraction or transvenous lead extraction). [15, 38] Physically, different contact with tissue means mechanic interaction, an example is that transvenous leads may be cooled by blood affecting its overall heating capacity. Or that any MRI-induced displacement force or vibration translates directly to mechanical stress for epicardial leads, being sutured directly to the epicardial tissue. While tension on transvenous ones may be somewhat dampened by surrounding blood and vessel walls.

Within epicardial leads, design may vary, examples are from lead polarity and body structure. On unipolar leads, a single conductor and one electrode (the cathode) are in contact with the heart, while bipolar leads contain two conductors that connect to two electrodes on the lead itself, a tip electrode (cathode) and a ring electrode (anode). In figure 2.11 the comparison of these types is shown, on the left side (2.11(a)) depicts the current flow for each case while the right side (2.11(b)) shows from outside the position of the anode relative to the heart.




(a) Unipolar vs. bipolar epicardial lead configuration.


(b) Relative electrode positioning of unipolar and bipolar epicardial leads.

Figure 2.11: Comparison of unipolar and bipolar epicardial pacing leads. (a) Illustrates the distinction in current flow pathways using a schematic of the heart, adapted from [39, 40]. (b) Depicts the relative anode and cathode positions in unipolar and bipolar epicardial leads, adapted from [41, 40].

Bipolar leads then, have a body structure design variation. As shown in Fig. 2.12, coaxial design features an inner coil conductor nested within an outer coil conductor, with each wrapped in a separate layer of insulation while coradial design consists of a single coil containing two parallel, intertwined conductor strands, each individually insulated [40]. Furthermore, epicardial leads, when abandoned, encompass this diversity in design and composition as all components of the leads have different materials.



(a) Lead fixation mechanisms.



(b) Coaxial and coradial lead body design.

Figure 2.12: Lead fixation and body design variations in pacing leads. (a) Passive-fixation leads rely on flexible tines that anchor within myocardial trabeculae, while active-fixation leads employ a retractable helix that screws into the myocardium. (b) Coaxial designs use two nested coil conductors with separate insulation layers, whereas coradial designs incorporate parallel, intertwined conductors within a shared lumen. Adapted from [40].

The several components of an epicardial lead are made of different materials chosen for their biocompatibility, durability, and electrical properties. Electrodes are made from inert materials to minimize corrosion and inflammatory reactions over the long term. These include titanium, platinum-iridium alloys, Elgiloy (an alloy of cobalt, iron, chromium, and other metals), and vitreous carbon. Similarly, conductors which carry the electrical signals between the pulse generator and the electrode are commonly made out of MP-35N (alloy of nickel, cobalt, chromium, and molybdenum.) Then, insulation, a protective outer coating of the lead that prevents short-circuiting made of different polymers like Silicone Rubber (Polysiloxane), Polyurethane, Fluoropolymers.

Finally, epicardial leads are affixed directly to the heart's outer surface during a surgical procedure in mainly two ways, as shown in figure 2.12(b). Suturing and Screwing, meaning the electrode is designed to be sutured directly onto the epicardium. While screwing refers to an active-fixation helix (screw), typically made of a platinum-iridium alloy or a similar metal, screwed directly into the myocardium [40]

From figure 2.12 one can see some of the challenges when retracting the epicardial lead, for this practical reason they are commonly abandoned after its purpose has been fulfilled. An abandoned epicardial lead could measure full-length or fragments after being left behind. Some fragments are described as long as 5cm, being 2cm an average length. Further, longer leads are reported up to 30 cm or couple fragments adding to about 21 cm. In diameter size may be compared to standard transvenous pacing leads, that of about half a millimeter to 1.5 mm. And are typically narrower than standard transvenous leads ($\sim 5F$, $\simeq 1.7$ mm outer diameter), often measuring between 0.5 mm and 1.5 mm.”

The physical length of the wire can impact the resulting interactions with the magnetic field, as more of the material in the human body more of it can interact. Table 2.1 summarizes the materials found on a epicardial lead and relates to its magnetic susceptibility.

Table 2.1: Qualitative magnetic susceptibility of common epicardial lead materials and their relevance for MRI safety. [10, 42, 43, 44]

Component	Material	Magnetic susceptibility	Relevance for MRI safety
Electrode	Titanium	Paramagnetic	Low; minimal torque/force in MRI
Electrode	Platinum-Iridium alloy	Paramagnetic	Low; generally MRI safe
Electrode	Elgiloy (Co-Cr-Fe-Ni alloy)	Paramagnetic	Moderate; may experience slight translational force
Electrode	Vitreous carbon	Diamagnetic	Minimal; very low MRI interaction
Conductor	MP-35N	Weakly paramagnetic	Low; minimal contribution to MRI forces
Insulation	Silicone rubber (polysiloxane)	Diamagnetic	Negligible; non-conductive and non-magnetic
Insulation	Polyurethane	Diamagnetic	Negligible; non-magnetic
Insulation	Fluoropolymer (PTFE)	Diamagnetic	Negligible; MRI inert

Current institutional recommendations regarding MRI in patients with retained epicardial leads remain conservative despite evolving evidence. Major guideline bodies, including the Heart Rhythm Society (HRS), the European Society of Cardiology (ESC), and the Centers for Medicare & Medicaid Services (CMS), allow MRI in patients with MRI-conditional or certain legacy cardiac implantable electronic devices (CIEDs), but continue to restrict or discourage imaging in patients with abandoned or epicardial leads.

Specifically, at the time of the HRS 2017 consensus and the 2021 ESC pacing guidelines noted that there was insufficient data to comment on the safety of MRI with an abandoned cardiac lead. And that if a patient had an MRI-conditional system along with an abandoned lead, lead extender, lead remnants, fractured lead(s), or surgically implanted epicardial leads, the system was considered non-MRI-conditional. Leading to a Case-by-Case consideration for whether to image or not and in which modality. CMS similarly excludes abandoned or epicardial leads from coverage due to perceived insufficient safety data, even though large observational studies indicate that modern epicardial leads (implanted after 2000) may undergo MRI safely under carefully monitored conditions [14, 17].

This cautious stance of institution remark the need for experimental characterization of mechanical interactions between retained epicardial leads and MRI fields. Thus, providing a rationale for the present study. By quantifying these forces under controlled laboratory conditions, the work shown in this document directly addresses whether current institutional restrictions are justified and lays the groundwork for evidence-based updates to clinical safety policies.

2.3 Concluding Remarks

Chapter 3

Materials and Methods

The objective of this study was to measure and quantify MRI-induce translational forces and torque experienced by post-surgical epicardial pacing lead when exposed to the static magnetic field. With safety limits for MRI magnetic fields established and described in Chapter 1, based on ASTM F-series guidelines, we constructed 3 non-magnetic test apparatus specifically designed to measure these forces with the precision required for clinical applications.

However, given the challenges associated with clinical access for experimental testing, as MRI scanner time is typically associated with long scheduling delays and short available measurement periods, a secondary objective of this work was to improve the quality of our experimental setup in order to maximize the efficiency of data acquisition during these limited observation windows. In this chapter, a layout of the experiments conducted is documented.

Previous students have developed the laboratory-scale instruments and associated software necessary to evaluate magnetic forces in a controlled environment. This was achieved by generating a smaller but reproducible magnetic field in the laboratory, enabling characterization of materials with relatively high magnetic susceptibility. While this laboratory-generated field was not sufficient to directly measure or char-

acterize the epicardial lead itself, it allowed for evaluation of the accuracy and measurement capacity of each instrument, as well as for the observation of the physical phenomena described above. Furthermore, given the proportional nature of the magnetic effects on a material, it was expected that, when tested in the much stronger (3 T) magnetic field and field gradient of a clinical MRI system, the small magnetic susceptibility of the epicardial lead would not present a significant limitation in terms of measurement accuracy.

Refer to equations and scaling thing on chapter 2. Once is done

Three distinct experimental setups were involved in this study: (1) a spatial field mapping platform to characterize B_0 and ∇B_0 , (2) a pendulum-based deflection apparatus to assess translational force through angular displacement, and (3) a torque measurement system for rotational force assessments. In this chapter we will explain our setup and rationale, as well as the proven modifications to the instruments in order to provide a reproducible map of action to test our instruments.

3.1 Magnetic Field Generation and mapping

Magnetic fields were generated in multiple ways, seeking to archive the most reliable or similar situation as one would encounter on a clinic. The most intuitive way to accomplish this in a lab setting was to use neodymium magnets with the only problem being static or step-wise change of its magnetic flux, but proving to be quite effective and strong.

Another approach included using a custom-built air-core solenoid, approximately 15 cm in length and 10 cm in outer diameter. The solenoid was densely wound with copper wire (~ 1 mm diameter), forming an inner core of approximately 5 cm. A Pasco Scientific SF-9584 DC power supply was used to deliver currents in the range of 0–4 A, corresponding to magnetic field strengths from 1 to 18.9 Gauss for this

solenoid. Finally, in line to mimic that of a static but increasingly stronger magnetic field inside an MRI we used a set of educational Helmholtz coils

Further describe this coils, size, number of turns, pasco, series so on


Around our torque contraption allowing us to see changes with its strength in real time using the same Pasco Scientific SF-9584 DC power supply.

3.1.1 Magnetic Field and Gradient Mapping Platform


Magnetic field strength (B_0) and gradient (∇B_0) measurements were performed using a commercial Gaussmeter (Model GM2, AlphaLab Inc., Salt Lake City, UT). The GM2 operates on the Hall effect principle, wherein a voltage is generated across a probe when exposed to a perpendicular magnetic field. This voltage is proportional to the local magnetic flux density, enabling precise spot measurements of field magnitude. The Gaussmeter used has an accuracy of 1% of the DC reading in the 16°C to 29°C range.

To ensure spatial accuracy and reproducibility, a fixture made from rigid PVC was constructed by previous Creighton University students [29]. The platform comprises a 300 mm square base and a 280 mm diameter vertical circular plate, perforated with a 5x5 grid of probe-access holes spaced at 20 mm intervals as shown in figure 3.1. Each access point was numerically indexed to facilitate 2D field mapping in the X-Y plane.

Once the field-mapping phantom and Gaussmeter probe are co-aligned, data capture was streamlined using LabVIEW to be sufficiently flexible and precise for our proximity measurements near an MRI. The manufacturer’s default software, AlphaApp, provides basic data-logging, recording, live screen streaming, and plotting of measurements from USB-enabled AlphaLab meters[45]. However, AlphaApp does not expose control over sampling frequency or allow real-time adjustment of acquisition parameter, limiting fine temporal resolution when the probe is moved into steep field



(a) PVC-based mapping platform.



(b) Example field map output from MRI fringe region.

Figure 3.1: PVC-based magnetic field mapping platform. Used for spatial B_0 and ∇B_0 measurement. As shown in Ferreira 2017 [29, 21].

gradients. In contrast, using LabVIEW Virtual Instrument (VI) interface allows for configurable sampling intervals, buffer control, and precise timing protocols, enabling us to push the device for much higher accuracy as the probe approaches and crosses isocontour regions within the MRI fringe. We developed that VI by leveraging the AlphaLab Data Acquisition Communication Protocol [46] to command the device directly via USB, providing control over timing and sample rate.

The data acquisition procedure for magnetic flux mapping is organized in this VI, whose basic logic is summarized in Figure 3.2. Upon startup, the VI initializes serial communication with the Gaussmeter, loads user-defined parameters (such as file name, mode of acquisition, delay time, and probe coordinates), and clears buffers in preparation for logging. The user may select either a continuous or an individual sampling mode. In continuous mode, the VI iterates through a defined number of data points with a fixed delay between samples; in individual mode, each data capture is triggered manually, allowing for precise positioning or timing. For both modes, each cycle involves reading the spatial coordinates, sending a measurement command,

recording the returned magnetic flux value, and updating a graphical display as well as the output file.

While the flowchart reflects the core logic, it does not fully convey the customization added to the VI interface. For example, the front panel includes input fields for patient table (couch) parameters such as couch speed and displacement points. As mentioned above, phantom is discretized with radial and angular indices: angular positions span 12 sectors clockwise from the 12 o'clock position (0 to 11 or A to L), and radial depths range from the center (0) to the outer edge (6). The probe's spatial location is represented in polar coordinates, and the system plots magnetic flux as a function of position rather than time, allowing for intuitive visualization of the MRI fringe field across the phantom surface.

In clinical use, the entire fixture is intended to be shifted axially along the Z-direction of a horizontal bore MRI scanner using controlled couch increments (e.g., 10 cm). This translation allows for volumetric sampling of B_0 over several planes. The spatial magnetic field gradient ∇B_0 can then be estimated numerically using finite difference calculations between adjacent measurement points. This method has previously been applied to MRI mapping in the work by Ferreira [21].

3.2 Translational Force Measurement via Angular Deflection

This magnet was particularly useful for magnetic field and translational forces measurement tests and was operated in a continuous mode; no rest periods were applied between trials due to the time required to stabilize the pendulum after each adjustment.

3.2.1 Measurement Device

To assess MRI-induced translational forces in a laboratory environment, Creighton University developed a pendulum-style apparatus following the geometry and physics outlined in ASTM F2052-15[20]. The vertical post includes a screw clamp mechanism that enables height adjustment; however, a default suspension height of $L = 1$ meter was used for consistency across trials.

The experimental frame was constructed entirely from PVC components, including a vertical post of about 1.5 meters and a rigid base for stabilization. Attached to the pole a set of rings were attached to the pole with a nylon screw to held positions. The lower one features a slit, where a custom made Kydex ruler sits held by smaller nylon screws. This ruler is interchangeable. The upper ring shows a rubber clamp from which a string passes. Then the length of suspension, $L = 1$ meter, was set as the distance between these two rings, specifically from the last contact point of the string to the rubber on the top ring to the sample hanging free at ruler's height as shown in Figure 3.3.

The sample was a solid ferromagnetic cylinder of length = 6 mm, diameter = 3 mm, and mass = 0.3648 g therefore density $\rho = 8.6$ g/cm³). It was suspended by a 955 mm-long sewing thread, tied with a simple knot at its center. For clinical applications, a 0.25 mm nylon monofilament is recommended. A monofilament nylon thread has low stretch, complies with MR-safe properties (Non-metallic, Non-conductive, Non-magnetic), and reduces variability introduced by torsional drift or thread elasticity [25, 20]. The bottom of the sample was free to swing, forming a pendulum under gravity. A horizontal ruler, fixed along the Z-axis, served as the visual reference to quantify lateral displacements.

Lead Holder Frame Design

To accommodate epicardial lead positioning while maintaining MRI compatibility, we propose the use of a lightweight, non-magnetic bee comb mesh fabricated from Polylactic Acid (PLA). The suggested mesh dimensions are 16 mm length by 14 mm wide, with a thickness of 1 mm, for a total volume of less than 100mm^3 equivalent to around a tenth of 1 gram given the 1.24 grams per cubic centimeter (g/cm^3) PLA density. As shown in figure 3.4.

The mesh needs to be suspended such that the lead axis was aligned approximately parallel to the magnetic field gradient (Z-axis). The mesh's lightweight design aimed to minimize its contribution to the total magnetic force, however its mass was not explicitly subtracted from the translational force calculations.

A summary schematic of the apparatus and frame are included in Figures 3.3 and 3.4, with additional engineering drawings available in Appendix A

In Lab Measurement Protocol

Magnetic field measurements were performed using the **AlphaLab Inc. Gaussmeter** described before. The setup consisted of a custom-made solenoid connected to a Pasco power supply capable to deliver up 8 A acting as variable magnetic field generator for our experiment, the subject - a small ferromagnetic rod - was attached to a string pending from the MRI safe pole and angle of deflection was measured visually with a ruler on the subject horizontal displacement towards the coil. The Gaussmeter was positioned such that it allowed for small displacements and magnetic field measurements at the same time as angle deflection.

Figure 3.5 shows the experimental lab setup used to assess the methodology accuracy and reliability with all used components.

To characterize local field gradients, measurements were taken at three positions: at the pendulum's equilibrium position, 0.5 mm below, and 0.5 mm above, yielding

values of $B_{-0.5}$, B_0 , and $B_{+0.5}$, respectively. Each position was sampled nine times per current level, and gradients were computed using python pandas library and the central finite difference method:

$$\frac{dB}{dz} \approx \frac{B_{+0.5} - B_{-0.5}}{1 \text{ mm}} \quad (3.1)$$

Once the pendulum reached equilibrium under each magnetic condition, the horizontal displacement on z was recorded visually using the ruler as a reference. With known suspension length L , the deflection angle α was calculated as:

$$\alpha = \tan^{-1} \left(\frac{x}{L} \right) \quad (3.2)$$

In the clinical MRI environment, B_0 may reach 3 T, but the χ of implanted materials is often orders of magnitude smaller. This inverse balance preserves the translational force regime, and supports translating results from lab simulations to clinical conditions.

All measurements were logged in Microsoft Excel, and photos/videos were captured via smartphone to document behavior. A minimum of three trials were performed for each current level; however, only the final (most consistent) dataset was retained for analysis. Data were exported to a Jupyter Notebook for clean up and processing with pandas. Then plotted to evaluate $\tan \alpha$ vs. field gradient force. Propagated uncertainties in α and dB_0/dz were computed using standard error propagation formulas.

Smallest measurable force

The smallest measurable force can be obtained with geometry, as the pendulum forms a right-angled triangle where the vertical line is the pole itself " L ", the horizontal is the ruler " x " and the hypotenuse is the pendulum's string as depicted on

figure 3.5. Both of these measurements have a $1mm$ accuracy and equips us with a 1m by 1mm triangle

Max and min forces measured

In Clinic Measurement Protocol

To guarantee safety and repeatability, the measurement of MRI-induced translational forces on the test items was carried out in accordance with a structured methodology. Initially, all personal belongings were removed to prevent safety issues. The apparatus, a PVC pole equipped with a non-magnetic ruler aligned with the pendulum string, was positioned at a precise distance from the MRI bore. Two sets of measurements were performed sequentially: first using a magnetically susceptible test object, and then with the epicardial lead attached, suspended from a light basket and a heavy basket - respectively- to assess force variations. Moving closer to the bore, a step-wise method was followed to measure displacement at certain translational points. Each measurement phase was completed as per the flowchart-guided process, with detailed data recorded in the MEASUREMENT WORKSHEET. The comprehensive protocol, including step-by-step instructions and safety considerations, is provided in Appendix

3.3 Torque Measurement via Counter-torque

3.3.1 Torque Measurement Apparatus

On the final part of the assessment, torque on a horizontally oriented subject, as described in the figure ref was measured. To archive this a non-magnetic pole was fabricated with clinical considerations in mind. The pole was made from PLASTIC and is 200 mm tall with 51 mm of diameter it can be attached to a PVC base for support with a nylon screw and it features a space for a ceramic bearing to sit.

This ceramic bearing is meant to reduce as much friction for the rotation as possible while keeping everything non magnetic, the bearing has a plastic notch capable of holding a 10 mm thick ruler or rod to spin. This set up is shown in Figure ref . The induced torque on the subject, from the torque explained in chapter /refch2, would be transmitted mechanically to a non-magnetic ruler which then would apply a force on a custom build force sensor (Gauge sensor). This force sensor would bend on and the counter-force would be measured using strain gauges. The strain-gauge-based force sensor and its circuitry were fabricated in laboratory following a proved methodology [47] and detailed by a previous graduate student. The assembly, consisting of 4 wire, precision strain gauges, and a half-bridge Wheatstone configuration with amplification and filtering, was inherited as a completed system. In the present work, I performed calibration and validation of the sensor response, and subsequently employed it for torque measurements in the experimental setup.

The following space lists all materials used and figure ref shows the whole experimental setup for a) calibration and b) torque measurement

Helmholtz coils, a pair of PASCO scientific 200 turns coils was used to produce the static uniform magnetic field. This coils were chosen for their ability to increase B in magnitude easily, useful for us to mimic changes of the MRI static magnetic field with distance.

Subject (small rod, big rod, lead): to show the effects of the magnetic field on the setup, a big ferromagnetic rod was positioned on top of the ceramic bearing. It was around 10cm long and with it a strong dipole moment could be induced, serving as a visual confirmation that the system is working.

However a smaller rod is needed, this rod would experiment much smaller torques based on size only. And following the same logic as in translational this would be a better test subject at lab scale. With a small magnetic field, high magnetic susceptibility and small volume, following equation ref proportionality is ensured.

Ruler, the torque is mechanically transmitted from the subject to the ruler and then the contratorque is measured by the sensor. Do I need to explain the physics of this? If so where?

Ceramic bearing (why a ceramic bearing? friction and magnets)

Gauge sensor, set of sensors from different materials were fabricated. These included glass, aluminum and clear plastic. As table 3.1 illustrate, they were made of similar sizes to test repeatability.

Table 3.1: Characteristics of the rods used in experiments.

Rod ID	Material	Diameter (mm)	Length (mm)
Rod1	Al	1.6	145.0
Rod2	Al	1.6	182.00
Rod3	Al	1.6	182.00
Rod5	glass	3.2	166.0
Rod7	clear plastic	2.9	180.0

During calibration, aluminum based sensor was proven to be the best. Comparison plots can be found in appendix B

Circuit including noise calibration, should I include a diagram and explanation of this circuit? If so should I attach it to the appendix as well? DAQ, Computer, a VI was developed for the purpose of registering the voltages a flowchart would be useful here as well.

System calibration

For calibration in the lab, the custom-built sensor was flipped so the bar face horizontally and a small cone-shaped basket made out of tape was attached to hold increments of water. Water was added in μL increments (equivalent to milligrams) simulating torque loads from 0 to 800 mg. Initial increments of 10 up to 200 μL covered the expected force range of epicardial leads weight, followed by 50 μL increments to demonstrate linearity and sensor stability.

From Fig B.6 the smallest measurable force the instrument can be determined. Using the slope of the most reliable fit of Aluminum rod $m = -3.4132e - 05(\leq 0.29\%), \chi_{red} = 1.05$.

The slope relates voltage changes to mass changes:

$$\Delta V = \text{slope} \cdot \Delta m$$

so the smallest measurable mass is

$$m_{min} = \frac{\Delta V}{|\text{slope}|}$$

In this case, the standard error in voltage is $\Delta V = 1.4123e - 06$ which results in $m_{min} \sim 0.0414$ mg. This corresponds to a force of roughly $0.41\mu\text{Newton}$, which is significant because forces expected on an epicardial lead under a MRI magnetic field are extremely small.

Along with these measurements we also tested sensitivity along the length of sensor showing that the further out from the gauge bridge the more sensitive the sensor was. This is demonstrated on an appendix B figure B.7.

In order to find the best position for sensor we set the following experiment, a set of neodymium magnets were aligned to the ceramic bearing to get a static magnetic field, and a platform angled at 45° carried the sensor as we moved it inwards.

From theory, we can show that the maximum torque should appear at this angle - see ch ref - , and then we tested for the optimal length and position from the center, once the torque is transmitted from the metallic rod onto the ruler and it applies the force to the sensor. This process was repeated to find the sweet spot on distance from the center up to a 100 mm radius and the best height.

Figure B.7 shows a small voltage for all distances from 50mm to 100mm and a range of voltages once we are high up (far from the bridge) with higher sensitivity near the center at 50mm.

In Lab Measurement Protocol

These features and measurements lead to a new design of the apparatus. One that is more portable and allows to leverage on the sweet spots of the system. A PVC ring with a small tube for the clamp to sit was added and with it more repeatability was ensured.

During the experiment 2 measurements were performed. Magnetic field flux in Gauss using the AlphaLab Inc. Gaussmeter, described before, and Voltage from the strain gauge plus circuit sensor.

The experiment consisted of, with the sensor fixed in the ideal position, vary the magnetic field produced by the Helmholtz coils -mimicking the behavior in distance as a real MRI-increasing as we get closer to isocenter. Then the respective voltage produced by the deformation of the sensor is recorded. Finally, the voltage to weight calibration serves to estimate the induced torque of the system.

In Clinic Measurement Protocol

Torque measurements were conducted ensuring consistency and reproducibility. Prior to setup, both researchers confirmed that all personal belongings and ferromagnetic items had been removed from their pockets. The VI was opened with the necessary parameters configured, and the data acquisition card (DAC) was powered on. A 10-meter jumper wire was connected to the DAC and integrated into the circuit, with the computer system interfaced to the DAC for real-time data collection.

The experimental apparatus was then fitted with the test object—either the magnetically susceptible calibration material or the epicardial lead—mounted on the ro-

tating ruler. Then it was positioned on the MRI room bench at a distance of 1 meter from the bore, measured from the base of the apparatus to the bore face. Finally, the ruler arm was aligned to rest against the strain gauge, oriented as close as possible to 45° relative to the bore axis.

In the control room, torque measurements were acquired according to a predefined flowchart procedure, with results recorded on the MEASUREMENT WORKSHEET. A section of the worksheet was considered complete only when all data fields were marked with an “X.” Section 1 of the worksheet corresponded to measurements performed with the magnetically susceptible calibration object. Following these measurements, the apparatus was retrieved from the MRI room, and the calibration object was replaced with the epicardial lead affixed to the ruler. Section 2 of the worksheet was then completed by repeating the flowchart process with the lead in place.

Data collection in each section was performed at incremental positions along the MRI bore axis. For both the calibration object (Section 1) and the epicardial lead (Section 2), torque measurements were acquired at eleven translational positions: 100, 90, 80, 70, 60, 50, 40, 30, 20, 10, and 0 cm from the bore face. This systematic sampling allowed for direct comparison of torque response between the calibration object and the epicardial lead across the same magnetic field gradient.




Figure 3.2: Flowchart of the Gaussmeter VI data acquisition algorithm.




Figure 3.3: CAD render of the pendulum apparatus created using CATIA.





Figure 3.4: The design on lead holder comprises a rectangular lightweight bee comb mesh to wrap the epicardial lead around and hold it in a pendulum with a nylon string



1. Power Supply with Ammeter $\pm .001$ A
2. Solenoid (1 to 20 Gauss)
3. Ruler (Deflection Angle) ± 1 mm
4. PVC String Pole
5. Ferromagnetic Cylinder
6. AlphaLab, Inc. Gaussmeter ± 0.001 G

Figure 3.5: In-lab experimental setup for MRI translational force assessment. Labeled components include the solenoid, pendulum fixture, measurement tools, and control equipment.



1. Power supply
2. Ammeter
3. Helmholtz coils
4. Universal support with gaussmeter probe and gaussmeter
5. Circuit including noise calibration
6. DAQ
7. Main device
8. Calibration boat, pipet, and 200 μ L tube

Figure 3.6: Experimental equipment and corresponding list.

1. Subject (small rod, big rod, lead)
2. Ruler
3. Ceramic bearing
4. Pole
5. Ring
6. Tube
7. Clamp
8. Gauge sensor
9. Computer




Figure 3.7: Main device close up and corresponding list.

Chapter 4

Results

overall description of the experiments and presentation of the data for the following:

4.1 Magnetic Field Mapping

4.2 Translational

4.3 Torque


Chapter 5

Discussion and Conclusion


Appendix A

Engineering Drawings

Appendix A1: Pole drawing



Properties
Material: PLA
Weight:0.124 g



Dept.	Technical reference	Created by Daniel Juarez	8/5/25	Approved by
		Document type	Document status	
		Title Lead Holder Bee Comb Mesh MRI Translational Force	DWG No.	
		Rev.	Date of issue	Sheet 1/1

Appendix B

Calibration Logs

Additional experimental relationships and fitting diagnostics are presented to support the main analysis.




Figure B.1: Displacement as a function of current through the solenoid.




Figure B.2: Measured angle α versus magnetic field intensity B_0 .




Figure B.3: Computed translational force F_m as a function of B_0 .




Figure B.4: Residuals from linear fit of $\tan(\alpha)$ vs. $B_0 \cdot \frac{dB_0}{dz}$. Error bars indicate propagated uncertainties.




Figure B.5: Propagation of measurement uncertainty through magnetic field analysis. Top: Measured field B_0 with standard deviation and SEM. Middle: Gradient dB/dz with propagated error. Bottom: Final product $B_0 \cdot dB/dz$ with multiple uncertainty estimations (standard, fractional, SEM). This term was used as the independent variable in the susceptibility fit.




Figure B.6: Calibration curves for two aluminum (AL) rods in three different orientations. Linear fits show consistent response across orientations, confirming the reliability of the lab-built sensor (see Methods Section for details).




Figure B.7: Mean voltage response of the sensor as a function of height for different distances from the center (50–100 mm). A small and relatively flat voltage is observed across all radii, while at larger heights (farther from the bridge) the measurements diverge, showing higher sensitivity near the center (50 mm). See Methods Section for details on torque transfer and distance selection.

Appendix C

Copyright permissions

Unless you substantially alter a figure, you are not allowed to use figures from a published document, including journal articles, without copyright permission from the publisher. This is usually easily secured, without cost to you. Go to the journal article or book on the publisher's website, and find the Copyrights/Permissions link. Just fill out the form or follow instructions, and you will be emailed documentation of permission to use the figure in your thesis. For more information on using copyrighted figures in your thesis, see

<http://guides.lib.umich.edu/dissertationcopyright/otherscontent>.

You can include the copyright permissions in an appendix as figures or include a pdf using this command `\includepdf[scale=0.9]{rsna.pdf}`. If you do this, you could reference the appendix in each figure caption with “(See Appendix B for documentation of permission to republish from [cite source].)” Alternatively, you can save your permission documents into a separate document and include them as a separate upload to the Creighton Digital Repository (CDR). Make sure you note in your thesis that you are using the figure with permission. Please talk to Richard Jizba at the Creighton Library for advice.

Glossary

AIMD active implantable medical devices. 6, 8

CDR Creighton Digital Repository. 61

CIED cardiac implantable electronic device. 1, 2, 27

CRT cardiac resynchronization therapy. 27

DAC data acquisition card. 45

ECG electrocardiogram. 1

FEG Frequency Encoding Gradient. 16, 18

HRS Heart Rhythm Society. 1

ICD implantable cardioverter-defibrillators. 27

MRI Magnetic Resonance Imaging. 1, 2, 3, 4, 7, 12, 13, 15, 17, 18, 20, 25, 35, 36, 39, 42, 44

PD Proton Density. 13

PEG Phase Encoding Gradient. 16, 18

PLA Polylactic Acid. 39

PVC Polyvinyl Chloride. 9, 35, 38, 41, 45

RF radiofrequency. 1, 2, 3, 7, 12, 13

SSG Slice Select Gradient. 16, 18

VI LabVIEW Virtual Instrument. 36, 37, 43, 45

References

- [1] Robert A. Pooley. Fundamental physics of mr imaging. *Radiographics*, 25(4):1087–1099, 2005.
- [2] Jerrold T. Bushberg, J. Anthony Seibert, Edwin M. Leidholdt, and John M. Boone. *The Essential Physics of Medical Imaging*. Lippincott Williams & Wilkins, 3rd edition, 2011.
- [3] Hospital for Sick Children / AboutKidsHealth. Pacemaker: Caring for your child at home, 2009. Last updated December 17, 2009.
- [4] Heart Rhythm Society. Heart rhythm 2024 spotlights new developments in cardiac implantable electronic devices and other treatments. <https://www.hrsonline.org/news/hr24-spotlights-new-developments-cieds/>, May 2024. Accessed: 2025-07-07.
- [5] Fathima S Mubarak, Yevinka Ellepola, Kadijah Nyosha Chamba, Sanjay Agrawal, and Maged Makhoul. Complications of epicardial pacing wire removal following adult cardiac surgery: A systematic review. *Cureus*, 15(11):e49076, Nov 2023.
- [6] O. Aboyewa. *Measurement of Radiofrequency Induced Heating in Patients with Retained Post-Surgical Epicardial Leads During MRI*. PhD thesis, Creighton University, 2021.

- [7] G G Hartnell, L Spence, L A Hughes, M C Cohen, R Saouaf, and B Buff. Safety of mr imaging in patients who have retained metallic materials after cardiac surgery. *American Journal of Roentgenology*, 168(5):1157–1159, 1997. PMID: 9129404.
- [8] Pennsylvania Patient Safety Authority. Pennsylvania patient safety advisory—volume 3, issue 2 (june 2006): “mitigating look-alike/sound-alike medication errors”. https://patientsafety.pa.gov/ADVISORIES/Pages/200603_08.aspx, June 2006. Accessed: 2025-07-09.
- [9] M. C. Reade. Temporary epicardial pacing after cardiac surgery: a practical review. *Anaesthesia*, 62(4):364–373, 2007.
- [10] ASTM International. Standard practice for marking medical devices and other items for safety in the magnetic resonance environment, 2023. ASTM F2503–23e01.
- [11] P. G. Poh, C. Liew, C. Yeo, L. R. Chong, A. Tan, and A. Poh. Cardiovascular implantable electronic devices: a review of the dangers and difficulties in mr scanning and attempts to improve safety. *Insights into Imaging*, 8(4):405–418, 2017.
- [12] Rahul G. Muthalaly, Nitesh Nerlekar, Yin Ge, Raymond Y. Kwong, and Arthur Nasis. Mri in patients with cardiac implantable electronic devices. *Radiology*, 289(2):281–292, 2018.
- [13] American College of Cardiology. Current State of MRI With Cardiac Devices. <https://www.acc.org/Latest-in-Cardiology/Articles/2024/05/21/10/30/Current-State-of-MRI-With-Cardiac-Devices>, May 2024. Expert Analysis, published May 21, 2024.

- [14] AM Vuorinen, R Paakkanen, J Karvonen, J Sinisalo, M Holmstrom, S Kivisto, J Peltonen, and T Kaasalainen. Mri safety with abandoned or functional epicardial pacing leads. *European Heart Journal - Cardiovascular Imaging*, 22(Supplement 2), 2021.
- [15] Claudia Meier, Carsten Israel, Michel Eisenblätter, Annika Hoyer, Ferdinand Valentin Stoye, Ali Yilmaz, and Stephan Gielen. Safety of magnetic resonance imaging in patients with cardiac implantable electronic devices and abandoned or epicardial leads: A systematic review and meta-analysis. *Europace*, 26(6):euae165, 2024.
- [16] John F. Schenck. Safety of strong, static magnetic fields. *Journal of Magnetic Resonance Imaging*, 12(1):2–19, jul 2000.
- [17] Robert D. Schaller, Tamara Brunner, Michael P. Riley, Francis E. Marchlinski, Saman Nazarian, and Harold Litt. Magnetic resonance imaging in patients with cardiac implantable electronic devices with abandoned leads. *JAMA Cardiology*, 6(5):549–556, 2021.
- [18] Jana G. Delnoa, Daniel M. Krainak, Stephanie A. Flesher, and Donald L. Miller. Mri-related fda adverse event reports: A 10-yr review. *Medical Physics*, 46(10):e1107–e1116, 2019. U.S. Government work, public domain in the USA.
- [19] Jennifer R. Sawyer, Lance M. Relland, Molly S. Hagele, and Joseph D. Tobias. Ingested magnets found inadvertently during elective magnetic resonance imaging. *Cureus*, 16(7):e65321, 2024.
- [20] Astm f2052-21 standard test method for measurement of magnetically induced displacement force on medical devices in the magnetic resonance environment, 2021. ASTM International.

- [21] A. Ferreira. Predicting angular displacement of medical devices in a mri scanner bore using comsol multiphysics. Master’s thesis, Drexel University, 2017.
- [22] Terry Woods, Jana Delfino, and Sunder Rajan. Assessment of magnetically induced displacement force and torque on metal alloys used in medical devices. *Journal of Testing and Evaluation*, 49:20190096, 03 2021.
- [23] Astm f2213-17 standard test method for measurement of magnetically induced torque on medical devices in the magnetic resonance environment, 2022. ASTM International.
- [24] Hyo-Chang Seo, Yongkwan Lee, and Segyeong Joo. A simple apparatus for safety assessment of magnetically induced torque on active implantable medical devices (aimds) under 1.5 t and 3.0 t mri. *Magnetic Resonance Materials in Physics, Biology and Medicine*, 34(5):767 – 774, 2021. Cited by: 3.
- [25] Dan Stoianovici, Karun Sharma, and Kevin Cleary. Measurement of magnetically induced torque on lightweight medical devices in the magnetic resonance environment for astm f2213. *IEEE Transactions on Biomedical Engineering*, 71(1):36–44, 2024.
- [26] Mojtaba Ghadimi and Alex Thomas. *Magnetic Resonance Imaging Contraindications*. StatPearls Publishing, Treasure Island (FL), 2025. [Updated 2025 May 4].
- [27] U.S. Food & Drug Administration. Testing and labeling medical devices for safety in the magnetic resonance (mr) environment: Guidance for industry and food and drug administration staff. Guidance Document, October 2023. Docket No. FDA-2019-D-2837; “Content current as of 10/10/2023”.
- [28] American College of Radiology. *ACR Manual on MR Safety*, 2024. Accessed: 2025-10-28.

- [29] M.G. Nichols. Safety assessment of translational forces and torques on post-surgical epicardial leads during mri, 2021. Creighton MRI Safety Proposal (unpublished internal document).
- [30] David J. Griffiths. *Introduction to Electrodynamics*. Pearson, 4th edition, 2013.
- [31] Rite Advantage. A comprehensive guide to t1 and t2 mri scans: How they work and what they reveal, 2023. Accessed: 2025-10-31.
- [32] Jerry L. Prince and Jonathan Links. *Medical Imaging Signals and Systems*. Pearson, 2nd edition, 2015. Figure adapted under fair use for educational purposes.
- [33] Siemens Healthineers. Magnetom trio 3t mri scanner, 2025. Accessed: 2025-10-31.
- [34] Lawrence P. Panych and Bruno Madore. The physics of mri safety. *Journal of Magnetic Resonance Imaging*, 47(1):28–43, 2018.
- [35] D. Grainger. Safety guidelines for magnetic resonance imaging equipment in clinical use. Technical report, Medicines and Healthcare Products Regulatory Agency (MHRA), London, UK, 2014. MHRA Safety Guidelines.
- [36] Pascal Defaye, Mauro Biffi, Mikhael El-Chami, Serge Boveda, Michael Glikson, Jonathan Piccini, and Marco Vitolo. Cardiac pacing and lead devices management: 25 years of research at ep europace journal. *Europace*, 25(8):euad202, 2023.
- [37] Andrea M. Russo, Milind Y. Desai, Monika M. Do, Javed Butler, Mina K. Chung, Andrew E. Epstein, Maya E. Guglin, Wayne C. Levy, Jonathan P. Piccini, Nicole M. Bhavé, Andrea M. Russo, Milind Y. Desai, Monika M. Do, Amrut V. Ambardekar, Nancy C. Berg, Kenneth C. Bilchick, G. William Dec, Rakesh Gopinathannair, Janet K. Han, Liviu Klein, Rachel J. Lampert, Gurusher S.

- Panjrath, Ryan R. Reeves, Danita Marie Yoerger Sanborn, Lynne W. Stevenson, Quynh A. Truong, Paul D. Varosy, Todd C. Villines, Annabelle S. Volgman, and Karolina M. Zareba. Acc/aha/ase/hfsa/hrs/scai/scct/scmr 2025 appropriate use criteria for implantable cardioverter-defibrillators, cardiac resynchronization therapy, and pacing. *JACC*, 85(11):1213–1285, 2025.
- [38] Hiroomi Murayama, Masanobu Maeda, Hajime Sakurai, Akihiko Usui, and Yuichi Ueda. Predictors affecting durability of epicardial pacemaker leads in pediatric patients. *The Journal of Thoracic and Cardiovascular Surgery*, 135(2):361–366, 2025/09/30 2008.
- [39] HowToPace Editors. Basics of pacing leads, 2023. Accessed: 2025-10-12.
- [40] Kenneth A. Ellenbogen, Bruce L. Wilkoff, G. Neal Kay, and Chu-Pak Lau. *Clinical Cardiac Pacing, Defibrillation, and Resynchronization Therapy*. Saunders / Elsevier, Philadelphia, PA, 4th edition, 2011.
- [41] LITFL and DerangedPhysiology Editors. Anatomy of the temporary pacemaker circuit, 2023. Accessed: 2025-10-12.
- [42] William D. Callister and David G. Rethwisch. *Materials Science and Engineering: An Introduction*. Wiley, 10th edition, 2018.
- [43] Carpenter Technology Corporation. Mp35n alloy datasheet. <https://www.carttech.com/alloys/mp35n>.
- [44] Astm f2182-19 standard test method for measurement of radio frequency induced heating on or near passive implants during magnetic resonance, 2019. ASTM International.

- [45] AlphaLab Inc. Alphaapp. <https://www.alphalabinc.com/alphaapp/>, 2023. Software for data logging, streaming, and plotting; lacks adjustable sampling frequency control.
- [46] AlphaLab Inc. Alphaslab data acquisition communication protocol. https://www.alphalabinc.com/wp-content/uploads/2018/02/alphaapp_comm_protocol.pdf, 2018. Used to implement custom sampling control via LabVIEW VI.
- [47] Johannes Chiu. Characterization of a low-cost millinewton force sensor for ionic polymer metal composite actuators. <https://api.semanticscholar.org/CorpusID:139053109>, 2016.