LAB WORKSHEET

Cabling Lab

Make, terminate and test network cables, choose the right cable for the job and diagnose faults.

Colour codes

Pin	1	2	3	4	5	6	7	8
T568B	W-O	O	W-G	B	W-B	G	W-Br	Br
T568A	W-G	G	W-O	B	W-B	O	W-Br	Br

- **Straight-through** (same standard both ends): unlike devices, e.g. PC → switch.
- **Crossover** (A one end, B the other): like devices without auto-MDIX.
- **Rollover**: console port.
- Structured cabling: 90 m permanent link + 10 m patch leads = 100 m channel. Fibre beyond that.

Reading the tester

- A dark remote LED = **open**. Two LEDs together = **short**.
- Swapped within a pair = **reversed pair**; between pairs = **crossed pairs**.
- Pins correct but NEXT fails = **split pair**.

Guided steps

1. Learn + quick check.
2. Wire and crimp End A (T568B).
3. End B and test.
4. Make a crossover.
5. Punch down a keystone.
6. Pick the cable for 10 jobs.
7. Diagnose 10 fault tickets.

Instructor: Aaron Cocker-Swanick