Wi-Fi connected but websites do not load

Article: NF-TS-005 | **Owner:** Technical Support
Category: troubleshooting | **Topic:** wifi_no_internet
Audience: customer_assistant | **Applies to:** NovaFiber NF-RTR-200 and household Wi-Fi devices
Reviewed: 2026-10-07 | **Next review:** 2027-01-07
Related articles: NF-TS-001, NF-TS-002, NF-EQ-002, NF-EQ-003

1. Understand the symptom

A Wi-Fi connection confirms the device can communicate with the router, not that the router has internet service. Use this article when the Wi-Fi name is visible and connected but websites or applications fail. Check two unrelated websites and, if available, a second device. If only one website fails while others work, check that service's status instead of resetting broadband equipment.

2. Compare one device with the whole home

If only one device fails, confirm its Wi-Fi connection is to the intended NovaFiber network, not a disconnected extender or old hotspot. Toggle Wi-Fi off and on, then restart that device if appropriate. If you know the correct Wi-Fi password, forgetting and reconnecting to the network may help; do not share the password with Nova. Check whether an optional VPN or custom proxy is blocking that device. Restore the device's normal automatic IP/DNS settings only if you understand how to undo prior custom settings; do not disable security software.

3. Check optical and router indicators

If multiple devices fail, check NF-ONT-100 Power/PON/LOS and NF-RTR-200 WAN/Internet indicators. Red LOS or abnormal PON follows NF-TS-002. Normal optical registration with router Internet amber or off follows NF-TS-001. WAN off can indicate the Ethernet uplink is not established; inspect the accessible Ethernet connection between ONT LAN and router WAN without disturbing fiber. Use the supplied ports rather than changing the router into bridge mode.

4. Use a wired comparison when available

Connect a capable device to a router LAN port with Ethernet, keeping the ONT connection unchanged. If wired browsing succeeds, the fiber service is reachable and Wi-Fi/device configuration is the next focus. If both wired and Wi-Fi browsing fail, contact support after the permitted checks. Do not connect directly to the ONT, enter provider provisioning credentials, or perform a factory reset. If indicators are normal and safe, one controlled restart using NF-TS-001 may be tried.

5. Escalate with relevant evidence

Report whether one or all devices fail, whether a wired comparison worked, indicator states, the start time, and any recent network-setting changes. Account suspension and current outage status need a verified support check. Nova cannot inspect an account or confirm an outage. Do not claim that a DNS problem, unpaid bill, or cable fault is confirmed just because the device shows 'No internet'. The same symptom has several possible causes.

6. Validate recovery and follow related guidance

Confirm that multiple unrelated websites load after a change. A Wi-Fi signal icon by itself is insufficient. If internet works but is slow, use NF-TS-003 and NF-EQ-003. If the issue repeatedly returns, record incidents using NF-TS-004. Router password and network-name changes are described in NF-EQ-002; changing the password is not a general fix for upstream internet loss.