MorseMicro first install checklist

Steps to take on your computer	Steps to take on your radio
☐ Download the AREDN® **sysupgrade.bin** file for your MorseMicro device from **arednmesh.org** ☐ Cable your computer's Ethernet port to the router's LAN port and power on the router ☐ Verify that your computer received an IP address from the device's DHCP service ☐ Open a web browser and navigate to the device's web interface	
	☐ Login and navigate to ***System → Backup/Flash Firmware*** and go to ***Flash new firmware image*** ☐ **Uncheck** the ***Keep Settings*** checkbox ☐ Click ***Choose File*** to select the AREDN® *sysupgrade.bin* file you downloaded ☐ Click ***Flash image*** to upload the new image, then verify the file checksum and click ***Proceed*** ☐ After the firmware image is loaded, the device will reboot to the AREDN® firmware (this process takes several minutes)
☐ Verify that your computer is assigned a new IP address automatically using DHCP. You may need to disconnect & reconnect the Ethernet interface to ensure the new IP address assignment. Verify that your computer can ping the radio at 192.168.1.1. ☐ Open a web browser and enter either http://192.168.1.1 or http://localnode.local.mesh to configure your new node	