

Fahrzeugnummer: 4705-102				Fzg. ID: 230				Wagen: A - 100			
Switch	Switchport	Usage	VLAN ID	Port Type	IP Address		IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-			
	e0-3				-	-	-	-			
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	y	18,0	
	e0-5	Service FIS / CCTV	2	Access	172	17	115	120	120		
	e1-0	Überw. Kamera A7	5	Access	172	18	243	10	10	y	5,0
	e1-1	Überw. Kamera A2	5	Access	172	18	243	11	11	y	5,0
	e1-2	Überw. Kamera A1	5	Access	172	18	243	12	12	y	5,0
	e1-3	Überw. Kamera A5	5	Access	172	18	243	13	13	y	5,0
	e1-4	Überw. Kamera A9	5	Access	172	18	243	14	14	y	5,0
	e1-5	AFZ A1	8	Access	172	20	115	5	5	y	10,0
	e1-6	AFZ A2	8	Access	172	20	115	6	6	y	10,0
	e1-7				-	-	-	-			
	e1-8	Sprechstelle A1	9	Access	172	20	243	5	5	y	7,5
	e1-9				-	-	-	-			
	e1-10				-	-	-	-			
	e1-11				-	-	-	-			
	e1-12	Future use box A5	90	Access	-	-	-	-			
	e1-13	Future use box A6	90	Access	-	-	-	-			
	e1-14	Seitenanzeige A1	3	Access	172	17	243	25	25		
	e1-15	Seitenanzeige A3	3	Access	172	17	243	26	26		
	e2-0	Bildschirm A3	3	Access	172	17	243	50	50		
	e2-1	Bildschirm Werbung A1	3	Access	172	17	243	51	51		
	e2-2	Bildschirm Werbung A5	3	Access	172	17	243	52	52		
	e2-3	Bildschirm A1	3	Access	172	17	243	53	53		
	e2-4	ADU A	9	Access	172	20	243	3	3		
	e2-5	Audio Amp. A1	9	Access	172	20	243	21	21		
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-2				-	-	-	-			
	e0-3				-	-	-	-			
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-			
	e1-0	Überw. Kamera A8	5	Access	172	18	243	15	15	y	5,0
	e1-1	Überw. Kamera A4	5	Access	172	18	243	16	16	y	5,0
	e1-2	Überw. Kamera A3	5	Access	172	18	243	17	17	y	5,0
	e1-3	Überw. Kamera A6	5	Access	172	18	243	18	18	y	5,0
	e1-4	Überw. Kamera A10	5	Access	172	18	243	19	19	y	5,0
	e1-5	AFZ A3	8	Access	172	20	115	7	7	y	10,0
	e1-6	AFZ A4	8	Access	172	20	115	8	8	y	10,0
	e1-7	NVR A	5	Access	172	18	243	5	5		
	e1-8	Sprechstelle A2	9	Access	172	20	243	6	6	y	7,5
	e1-9				-	-	-	-			
	e1-10				-	-	-	-			
	e1-11	Bildschirm Werbung A4	3	Access	172	17	243	100	100		
	e1-12	Future use box A2	90	Access	-	-	-	-			
	e1-13	Future use box A4	90	Access	-	-	-	-			
	e1-14	Seitenanzeige A2	3	Access	172	17	243	27	27		
	e1-15	Seitenanzeige A4	3	Access	172	17	243	28	28		
	e2-0	Bildschirm A4	3	Access	172	17	243	54	54		
	e2-1	Bildschirm Werbung A8	3	Access	172	17	243	55	55		
	e2-2	Bildschirm Werbung A6	3	Access	172	17	243	56	56		
	e2-3	Bildschirm A2	3	Access	172	17	243	57	57		
	e2-4	Bildschirm Werbung A2	3	Access	172	17	243	119	119		
	e2-5	Audio Amp. A2	9	Access	172	20	243	22	22		
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-			
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-			
	e0-3				-	-	-	-			
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-			
	e1-0	Rücksehkamera A1	5	Access	172	18	243	80	80	y	5,0
	e1-1	Rücksehkamera A2	5	Access	172	18	243	81	81	y	5,0
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	y	18,0	
	e1-3				-	-	-	-			
	e1-4	Firewall	2	Trunk	172	17	115	1	1		Kein DHCP Statische Konfiguration STADLER
			3		172	17	243	1			
			5		172	18	243	1			
			6		172	19	115	1			
			7		172	19	243	1			
			8		172	20	115	1			
			9		172	20	243	1			
			12		172	22	115	1			
	e1-5				-	-	-	-			
	e1-6				-	-	-	-			
	e1-7				-	-	-	-			
	e1-8	Sprechstelle A1R	9	Access	172	20	243	5	5	y	7,5
	e1-9	Sprechstelle A2R	9	Access	172	20	243	6	6	y	7,5
	e1-10				-	-	-	-			
	e1-11				-	-	-	-			
	e1-12	Future use box A1	90	Access	-	-	-	-			
	e1-13	Future use box A3	90	Access	-	-	-	-			
	e1-14	Frontanzeige A	3	Access	172	17	243	23	23		
	e1-15				-	-	-	-			
	e2-0	Bildschirm Werbung A3	3	Access	172	17	243	107	107		
	e2-1				-	-	-	-			
	e2-2				-	-	-	-			
	e2-3	Sitzplatzreservierung A	6	Access	172	19	115	10	10		
	e2-4	ADU AR	9	Access	172	20	243	3	3		
	e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127		

IPv4-Schema

Fgz. Nr: 4705 - 102

C1	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
			7		172	19	243	2	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point C1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	115	121	121				
	e1-0	Überw. Kamera C7	5	Access	172	18	243	20	20	y	5,0		
	e1-1	Überw. Kamera C2	5	Access	172	18	243	21	21	y	5,0		
	e1-2	Überw. Kamera C1	5	Access	172	18	243	22	22	y	5,0		
	e1-3	Überw. Kamera C5	5	Access	172	18	243	23	23	y	5,0		
	e1-4	Überw. Kamera C9	5	Access	172	18	243	24	24	y	5,0		
	e1-5	AFZ C1	8	Access	172	20	115	9	9	y	10,0		
	e1-6	AFZ C2	8	Access	172	20	115	10	10	y	10,0		
	e1-7	AFZ C5	8	Access	172	20	115	11	11	y	10,0		
	e1-8	Sprechstelle C1	9	Access	172	20	243	7	7	y	7,5		
	e1-9				-	-	-	-	-				
	e1-10	Bildschirm Werbung C1	3	Access	172	17	243	108	108				
	e1-11	Bildschirm C5	3	Access	172	17	243	62	62				
	e1-12	Future use box C5	90	Access	-	-	-	-	-				
	e1-13	Future use box C6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C1	3	Access	172	17	243	29	29				
	e1-15	Seitenanzeige C3	3	Access	172	17	243	30	30				
C2	e2-0	Bildschirm C3	3	Access	172	17	243	58	58				
	e2-1	Bildschirm Werbung C7	3	Access	172	17	243	59	59				
	e2-2	Bildschirm Werbung C5	3	Access	172	17	243	60	60				
	e2-3	Bildschirm C1	3	Access	172	17	243	61	61				
	e2-4				-	-	-	-	-				
	e2-5	Audio Amp. C1	9	Access	172	20	243	23	23				
	e0-0	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera C8	5	Access	172	18	243	25	25	y	5,0		
	e1-1	Überw. Kamera C4	5	Access	172	18	243	26	26	y	5,0		
	e1-2	Überw. Kamera C3	5	Access	172	18	243	27	27	y	5,0		
	e1-3	Überw. Kamera C6	5	Access	172	18	243	28	28	y	5,0		
	e1-4	Überw. Kamera C10	5	Access	172	18	243	29	29	y	5,0		
	e1-5	AFZ C3	8	Access	172	20	115	12	12	y	10,0		
	e1-6	AFZ C4	8	Access	172	20	115	13	13	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C2	9	Access	172	20	243	8	8	y	7,5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11	Bildschirm Werbung C2	3	Access	172	17	243	109	109				
	e1-12	Future use box C2	90	Access	-	-	-	-	-				
	e1-13	Future use box C4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C2	3	Access	172	17	243	31	31				
	e1-15	Seitenanzeige C4	3	Access	172	17	243	32	32				
C3	e2-0	Bildschirm C4	3	Access	172	17	243	63	63				
	e2-1	Bildschirm Werbung C8	3	Access	172	17	243	64	64				
	e2-2	Bildschirm Werbung C6	3	Access	172	17	243	65	65				
	e2-3	Bildschirm C2	3	Access	172	17	243	66	66				
	e2-4	Bildschirm C6	3	Access	172	17	243	67	67				
	e2-5	Audio Amp. C2	9	Access	172	20	243	24	24				
	e0-0	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
			7		172	19	243	2	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point C3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera C1	5	Access	172	18	243	82	82	y	5,0		
	e1-1	Rücksehkamera C2	5	Access	172	18	243	83	83	y	5,0		
	e1-2	Access point C4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C1R	9	Access	172	20	243	7	7	y	7,5	Redundanz C1	
	e1-9	Sprechstelle C2R	9	Access	172	20	243	8	8	y	7,5	Redundanz C2	
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C1	90	Access	-	-	-	-	-				
	e1-13	Future use box C3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm Werbung C3	3	Access	172	17	243	110	110				
	e2-1	Bildschirm Werbung C4	3	Access	172	17	243	111	111				
	e2-2				-	-	-	-	-				
	e2-3	Sitzplatzreservierung C	6	Access	172	19	115	11	11				
	e2-4				-	-	-	-	-				
	e2-5				-	-	-	-	-				

Version 1.6

E1	e0-0	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-1	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-2				-	-	-	-	-	-				
	e0-3				-	-	-	-	-	-				
	e0-4	Access point E1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	115	123	123					
	e1-0	Überw. Kamera E7	5	Access	172	18	243	40	40	y	5,0			
	e1-1	Überw. Kamera E2	5	Access	172	18	243	41	41	y	5,0			
	e1-2	Überw. Kamera E1	5	Access	172	18	243	42	42	y	5,0			
	e1-3	Überw. Kamera E5	5	Access	172	18	243	43	43	y	5,0			
	e1-4	Überw. Kamera E9	5	Access	172	18	243	44	44	y	5,0			
	e1-5	AFZ E1	8	Access	172	20	115	19	19	y	10,0			
	e1-6	AFZ E2	8	Access	172	20	115	20	20	y	10,0			
	e1-7	AFZ E5	8	Access	172	20	115	21	21	y	10,0			
	e1-8	Sprechstelle E1	9	Access	172	20	243	12	12	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10	Sprechstelle PRM E1	9	Access	172	20	243	13	13	y	7,5			
	e1-11	Sprechstelle PRM WCR	9	Access	172	20	243	16	16	y	7,5			Redundanz WC
	e1-12	Future use box E5	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E7	90	Access	-	-	-	-	-	-				
	e1-14	Seitenanzeige E1	3	Access	172	17	243	37	37					
	e1-15	Seitenanzeige E3	3	Access	172	17	243	38	38					
	e2-0	Bildschirm E3	3	Access	172	17	243	78	78					
	e2-1	Bildschirm Werbung E7	3	Access	172	17	243	79	79					
	e2-2	Bildschirm Werbung E5	3	Access	172	17	243	80	80					
e2-3	Bildschirm E1	3	Access	172	17	243	81	81						
e2-4	ADU E	9	Access	172	20	243	2	2						
e2-5	Audio Amp. E1	9	Access	172	20	243	27	27						
E2	e0-0	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-2				-	-	-	-	-	-				
	e0-3				-	-	-	-	-	-				
	e0-4	Access point E2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-	-				
	e1-0	Überw. Kamera E8	5	Access	172	18	243	45	45	y	5,0			
	e1-1	Überw. Kamera E4	5	Access	172	18	243	46	46	y	5,0			
	e1-2	Überw. Kamera E3	5	Access	172	18	243	47	47	y	5,0			
	e1-3	Überw. Kamera E6	5	Access	172	18	243	48	48	y	5,0			
	e1-4	Überw. Kamera E10	5	Access	172	18	243	70	70	y	5,0			
	e1-5	AFZ E3	8	Access	172	20	115	22	22	y	10,0			
	e1-6	AFZ E4	8	Access	172	20	115	23	23	y	10,0			
	e1-7	AFZ E6	8	Access	172	20	115	24	24	y	10,0			
	e1-8	Sprechstelle E2	9	Access	172	20	243	14	14	y	7,5			
	e1-9	Sprechstelle E1R	9	Access	172	20	243	12	12	y	7,5			Redundanz E1
	e1-10	Sprechstelle PRM E2	9	Access	172	20	243	15	15	y	7,5			
	e1-11	Sprechstelle PRM E1R	9	Access	172	20	243	13	13	y	7,5			Redundanz E1
	e1-12	Future use box E2	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E4	90	Access	-	-	-	-	-	-				
	e1-14	Seitenanzeige E2	3	Access	172	17	243	39	39					
	e1-15	Seitenanzeige E4	3	Access	172	17	243	40	40					
	e2-0	Bildschirm E4	3	Access	172	17	243	83	83					
	e2-1	Bildschirm Werbung E8	3	Access	172	17	243	84	84					
	e2-2	Bildschirm Werbung E6	3	Access	172	17	243	85	85					
e2-3	Bildschirm E2	3	Access	172	17	243	86	86						
e2-4	Bildschirm E6	3	Access	172	17	243	87	87						
e2-5	Audio Amp. E2	9	Access	172	20	243	28	28						
E3	e0-0	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-	-				
	e0-2				-	-	-	-	-	-				
	e0-3				-	-	-	-	-	-				
	e0-4	Access point E3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-	-				
	e1-0	Rücksehkamera E1	5	Access	172	18	243	86	86	y	5,0			
	e1-1	Rücksehkamera E2	5	Access	172	18	243	87	87	y	5,0			
	e1-2	Access point E4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3				-	-	-	-	-	-				
	e1-4				-	-	-	-	-	-				
	e1-5				-	-	-	-	-	-				
	e1-6				-	-	-	-	-	-				
	e1-7				-	-	-	-	-	-				
	e1-8				-	-	-	-	-	-				
	e1-9	Sprechstelle E2R	9	Access	172	20	243	14	14	y	7,5			Redundanz E2
	e1-10	Sprechstelle PRM WC	9	Access	172	20	243	16	16	y	7,5			
	e1-11	Sprechstelle PRM E2R	9	Access	172	20	243	15	15	y	7,5			Redundanz E2
	e1-12	Future use box E1	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E3	90	Access	-	-	-	-	-	-				
	e1-14				-	-	-	-	-	-				
	e1-15	Bildschirm Werbung E1	3	Access	172	17	243	82	82					
	e2-0	Bildschirm Werbung E3	3	Access	172	17	243	112	112					
	e2-1	Bildschirm Werbung E4	3	Access	172	17	243	113	113					
	e2-2	Fahrausweiseinrichtung		Access	-	-	-	-	-	-				Reserviert
e2-3	Sitzplatzreservierung E	6	Access	172	19	115	13	13						
e2-4	ADU ER	9	Access	172	20	243	2	2						
e2-5	Energiezähler E	12	Access	172	22	115	3	3						

[illegible]

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	115	125	125				
	e1-0	Überw. Kamera B5	5	Access	172	18	243	62	62	y	5,0		
	e1-1	Überw. Kamera B2	5	Access	172	18	243	60	60	y	5,0		
	e1-2	Überw. Kamera B1	5	Access	172	18	243	61	61	y	5,0		
	e1-3				-	-	-	-	-				
	e1-4	Überw. Kamera B9	5	Access	172	18	243	63	63	y	5,0		
	e1-5												
	e1-6												
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle B1	9	Access	172	20	243	19	19	y	7,5		
	e1-9	Sprechstelle B3R	9	Access	172	20	243	40	40	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11	ZFR R	2	Access	172	17	115	2	2				
	e1-12	Future use box B5	90	Access	-	-	-	-	-				
	e1-13	Future use box B6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B1	3	Access	172	17	243	45	45				
	e1-15	Seitenanzeige B3	3	Access	172	17	243	46	46				
	e2-0	Bildschirm B3	3	Access	172	17	243	98	98				
	e2-1	Bildschirm Werbung B3	3	Access	172	17	243	99	99				
	e2-2												
	e2-3												
e2-4	ADU B	9	Access	172	20	243	4	4					
e2-5	Audio Amp. B1	9	Access	172	20	243	31	31					
B2	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera B8	5	Access	172	18	243	64	64	y	5,0		
	e1-1	Überw. Kamera B4	5	Access	172	18	243	65	65	y	5,0		
	e1-2	Überw. Kamera B3	5	Access	172	18	243	66	66	y	5,0		
	e1-3	Überw. Kamera B6	5	Access	172	18	243	67	67	y	5,0		
	e1-4	Überw. Kamera B10	5	Access	172	18	243	68	68	y	5,0		
	e1-5	AFZ B3	8	Access	172	20	115	32	32	y	10,0		
	e1-6	AFZ B4	8	Access	172	20	115	33	33	y	10,0		
	e1-7	NVR B	5	Access	172	18	243	6	6				
	e1-8	Sprechstelle B2	9	Access	172	20	243	20	20	y	7,5		
	e1-9												
	e1-10				-	-	-	-	-				
	e1-11	Bildschirm B1	3	Access	172	17	243	118	118				
	e1-12	Future use box B2	90	Access	-	-	-	-	-				
	e1-13	Future use box B4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B2	3	Access	172	17	243	47	47				
	e1-15	Seitenanzeige B4	3	Access	172	17	243	48	48				
	e2-0	Bildschirm B4	3	Access	172	17	243	102	102				
	e2-1	Bildschirm Werbung B8	3	Access	172	17	243	103	103				
	e2-2	Bildschirm Werbung B6	3	Access	172	17	243	104	104				
	e2-3	Bildschirm Werbung B2	3	Access	172	17	243	105	105				
e2-4	Bildschirm Werbung B4	3	Access	172	17	243	106	106					
e2-5	Audio Amp. B2	9	Access	172	20	243	32	32					
B3	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera B1	5	Access	172	18	243	90	90	y	5,0		
	e1-1	Rücksehkamera B2	5	Access	172	18	243	91	91	y	5,0		
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle B3	9	Access	172	20	243	40	40	y	7,5		
	e1-9	Sprechstelle B2R	9	Access	172	20	243	20	20	y	7,5		Redundanz B2
	e1-10	Sprechstelle B1R	9	Access	172	20	243	19	19	y	7,5		Redundanz B1
	e1-11	ZFR	2	Access	172	17	115	2	2				
	e1-12	Future use box B1	90	Access	-	-	-	-	-				
	e1-13	Future use box B3	90	Access	-	-	-	-	-				
	e1-14	Frontanzeige B	3	Access	172	17	243	24	24				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
	e2-3	Sitzplatzreservierung B	6	Access	172	19	115	15	15				
e2-4	ADU BR	9	Access	172	20	243	4	4					
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127					
Firewall		2	N/A	172	17	115	126	126				IP festgehalten fuer die RCU.	
		3	N/A	172	17	243	126	126				Diese ist mit der Firewall verbunden.	
		9	N/A	172	20	243	126	126				Anforderung von STADLER	