

4706 - 101 IPv4-Schema

Fahrzeugnummer: 4706-101				Fzg. ID: 189				Wagen: A - 100					
Switch	Switchport	Usage	VLAN ID	Port Type	IP Adress				IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	94	248	120				
	e1-0	Überw. Kamera A7	5	Access	172	18	222	138	10	y	5,0		
	e1-1	Überw. Kamera A2	5	Access	172	18	222	139	11	y	5,0		
	e1-2	Überw. Kamera A1	5	Access	172	18	222	140	12	y	5,0		
	e1-3	Überw. Kamera A5	5	Access	172	18	222	141	13	y	5,0		
	e1-4	Überw. Kamera A9	5	Access	172	18	222	142	14	y	5,0		
	e1-5	AFZ A1	8	Access	172	20	94	133	5	y	10,0		
	e1-6	AFZ A2	8	Access	172	20	94	134	6	y	10,0		
	e1-7					-	-	-	-				
	e1-8	Sprechstelle A1	9	Access	172	20	222	133	5	y	7,5		
	e1-9	Sprechstelle A3R	9	Access	172	20	222	169	41	y	7,5		Redundanz A3
	e1-10					-	-	-	-				
	e1-11					-	-	-	-				
	e1-12	Future use box A5	90	Access		-	-	-	-				
	e1-13	Future use box A6	90	Access		-	-	-	-				
	e1-14	Seitenanzeige A1	3	Access	172	17	222	153	25				
	e1-15	Seitenanzeige A3	3	Access	172	17	222	154	26				
	e2-0	Bildschirm A7	3	Access	172	17	222	178	50				
	e2-1	Bildschirm A5	3	Access	172	17	222	179	51				
	e2-2	Bildschirm A1	3	Access	172	17	222	180	52				
	e2-3	Bildschirm A3	3	Access	172	17	222	181	53				
	e2-4	ADU A	9	Access	172	20	222	131	3				
	e2-5	Audio Amp. A1	9	Access	172	20	222	149	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera A8	5	Access	172	18	222	143	15	y	5,0		
	e1-1	Überw. Kamera A4	5	Access	172	18	222	144	16	y	5,0		
	e1-2	Überw. Kamera A3	5	Access	172	18	222	145	17	y	5,0		
	e1-3	Überw. Kamera A6	5	Access	172	18	222	146	18	y	5,0		
	e1-4	Überw. Kamera A10	5	Access	172	18	222	147	19	y	5,0		
	e1-5	AFZ A3	8	Access	172	20	94	135	7	y	10,0		
	e1-6	AFZ A4	8	Access	172	20	94	136	8	y	10,0		
	e1-7	NVR A	5	Access	172	18	222	133	5				
	e1-8	Sprechstelle A2	9	Access	172	20	222	134	6	y	7,5		
	e1-9	Sprechstelle A3	9	Access	172	20	222	169	41	y	7,5		
	e1-10					-	-	-	-				
	e1-11					-	-	-	-				
	e1-12	Future use box A2	90	Access		-	-	-	-				
	e1-13	Future use box A4	90	Access		-	-	-	-				
	e1-14	Seitenanzeige A2	3	Access	172	17	222	155	27				
	e1-15	Seitenanzeige A4	3	Access	172	17	222	156	28				
	e2-0	Bildschirm A8	3	Access	172	17	222	182	54				
	e2-1	Bildschirm A6	3	Access	172	17	222	183	55				
	e2-2	Bildschirm A2	3	Access	172	17	222	184	56				
	e2-3	Bildschirm A4	3	Access	172	17	222	185	57				
	e2-4					-	-	-	-				
	e2-5	Audio Amp. A2	9	Access	172	20	222	150	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera A1	5	Access	172	18	222	208	80	y	5,0		
	e1-1	Rücksehkamera A2	5	Access	172	18	222	209	81	y	5,0		
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4	Firewall	2 3 5 6 7 8 9 12	Trunk	172 172 172 172 172 172 172 172	17 17 18 19 19 20 20 22	94 222 222 94 222 94 222 94	129 129 129 129 129 129 129 129	1 1 1 1 1 1 1 1			Kein DHCP Statische Konfiguration STADLER	
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle A1R	9	Access	172	20	222	133	5	y	7,5		Redundanz A1
	e1-9	Sprechstelle A2R	9	Access	172	20	222	134	6	y	7,5		Redundanz A2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A1	90	Access		-	-	-	-				
	e1-13	Future use box A3	90	Access		-	-	-	-				
	e1-14	Frontanzeige A	3	Access	172	17	222	151	23				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm A9	3	Access	172	17	222	233	105				
	e2-1	Bildschirm A10	3	Access	172	17	222	234	106				
	e2-2				-	-	-	-	-				
	e2-3	Sitzplatzreservierung A	6	Access	172	19	94	138	10				
	e2-4	ADU AR	9	Access	172	20	222	131	3				Redundanz A
	e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk		-	-	-	-	127			

C1	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	94	249	121				
	e1-0	Überw. Kamera C7	5	Access	172	18	222	148	20	y	5,0		
	e1-1	Überw. Kamera C2	5	Access	172	18	222	149	21	y	5,0		
	e1-2	Überw. Kamera C1	5	Access	172	18	222	150	22	y	5,0		
	e1-3	Überw. Kamera C5	5	Access	172	18	222	151	23	y	5,0		
	e1-4	Überw. Kamera C9	5	Access	172	18	222	152	24	y	5,0		
	e1-5	AFZ C1	8	Access	172	20	94	137	9	y	10,0		
	e1-6	AFZ C2	8	Access	172	20	94	138	10	y	10,0		
	e1-7	AFZ C5	8	Access	172	20	94	139	11	y	10,0		
	e1-8	Sprechstelle C1	9	Access	172	20	222	135	7	y	7,5		
	e1-9	Sprechstelle C3R	9	Access	172	20	222	170	42	y	7,5		Redundanz C3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C5	90	Access	-	-	-	-	-				
	e1-13	Future use box C6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C1	3	Access	172	17	222	157	29				
	e1-15	Seitenanzeige C3	3	Access	172	17	222	158	30				
	e2-0	Bildschrim C7	3	Access	172	17	222	186	58				
	e2-1	Bildschrim C5	3	Access	172	17	222	187	59				
	e2-2	Bildschrim C1	3	Access	172	17	222	188	60				
	e2-3	Bildschrim C3	3	Access	172	17	222	189	61				
e2-4				-	-	-	-	-					
e2-5	Audio Amp. C1	9	Access	172	20	222	151	23					
C2	e0-0	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera C8	5	Access	172	18	222	153	25	y	5,0		
	e1-1	Überw. Kamera C4	5	Access	172	18	222	154	26	y	5,0		
	e1-2	Überw. Kamera C3	5	Access	172	18	222	155	27	y	5,0		
	e1-3	Überw. Kamera C6	5	Access	172	18	222	156	28	y	5,0		
	e1-4	Überw. Kamera C10	5	Access	172	18	222	157	29	y	5,0		
	e1-5	AFZ C3	8	Access	172	20	94	140	12	y	10,0		
	e1-6	AFZ C4	8	Access	172	20	94	141	13	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C2	9	Access	172	20	222	136	8	y	7,5		
	e1-9	Sprechstelle C3	9	Access	172	20	222	170	42	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C2	90	Access	-	-	-	-	-				
	e1-13	Future use box C4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C2	3	Access	172	17	222	159	31				
	e1-15	Seitenanzeige C4	3	Access	172	17	222	160	32				
	e2-0	Bildschrim C8	3	Access	172	17	222	191	63				
	e2-1	Bildschrim C6	3	Access	172	17	222	192	64				
	e2-2	Bildschrim C2	3	Access	172	17	222	193	65				
	e2-3	Bildschrim C4	3	Access	172	17	222	194	66				
e2-4	Bildschrim C11	3	Access	172	17	222	195	67					
e2-5	Audio Amp. C2	9	Access	172	20	222	152	24					
C3	e0-0	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera C1	5	Access	172	18	222	210	82	y	5,0		
	e1-1	Rücksehkamera C2	5	Access	172	18	222	211	83	y	5,0		
	e1-2	Access point C4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C1R	9	Access	172	20	222	135	7	y	7,5		Redundanz C1
	e1-9	Sprechstelle C2R	9	Access	172	20	222	136	8	y	7,5		Redundanz C2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C1	90	Access	-	-	-	-	-				
	e1-13	Future use box C3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm C9	3	Access	172	17	222	235	107				
	e2-1	Bildschirm C10	3	Access	172	17	222	236	108				
	e2-2	Bistro Telemetrie C1			-	-	-	-	-				Keine Informationen
	e2-3	Sitzplatzreservierung C	6	Access	172	19	94	139	11				
e2-4	Bistro Bezahlinheit C2			-	-	-	-	-				Keine Informationen	
e2-5	Bistro Bildschirm C3			-	-	-	-	-				Keine Informationen	

Seite 3 von 6

[illegible]

F1	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point F1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	94	252	124				
	e1-0	Überw. Kamera F7	5	Access	172	18	222	177	49	y	5,0		
	e1-1	Überw. Kamera F2	5	Access	172	18	222	178	50	y	5,0		
	e1-2	Überw. Kamera F1	5	Access	172	18	222	179	51	y	5,0		
	e1-3	Überw. Kamera F5	5	Access	172	18	222	180	52	y	5,0		
	e1-4	Überw. Kamera F9	5	Access	172	18	222	181	53	y	5,0		
	e1-5	AFZ F1	8	Access	172	20	94	153	25	y	10,0		
	e1-6	AFZ F2	8	Access	172	20	94	154	26	y	10,0		
	e1-7	AFZ F5	8	Access	172	20	94	155	27	y	10,0		
	e1-8	Sprechstelle F1	9	Access	172	20	222	145	17	y	7,5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box F5	90	Access	-	-	-	-	-				
	e1-13	Future use box F6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige F1	3	Access	172	17	222	169	41				
	e1-15	Seitenanzeige F3	3	Access	172	17	222	170	42				
	e2-0	Bildschirm F7	3	Access	172	17	222	216	88				
	e2-1	Bildschirm F5	3	Access	172	17	222	217	89				
	e2-2	Bildschirm F1	3	Access	172	17	222	218	90				
	e2-3	Bildschirm F3	3	Access	172	17	222	219	91				
e2-4				-	-	-	-	-					
e2-5	Audio Amp. F1	9	Access	172	20	222	157	29					
F2	e0-0	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS FIR			-	-	-	-	-				Reserviert
	e0-3	RDC FIR			-	-	-	-	-				Reserviert
	e0-4	Access point F2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera F8	5	Access	172	18	222	182	54	y	5,0		
	e1-1	Überw. Kamera F4	5	Access	172	18	222	183	55	y	5,0		
	e1-2	Überw. Kamera F3	5	Access	172	18	222	184	56	y	5,0		
	e1-3	Überw. Kamera F6	5	Access	172	18	222	185	57	y	5,0		
	e1-4	Überw. Kamera F10	5	Access	172	18	222	186	58	y	5,0		
	e1-5	AFZ F3	8	Access	172	20	94	156	28	y	10,0		
	e1-6	AFZ F4	8	Access	172	20	94	157	29	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle F2	9	Access	172	20	222	146	18	y	7,5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box F2	90	Access	-	-	-	-	-				
	e1-13	Future use box F4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige F2	3	Access	172	17	222	171	43				
	e1-15	Seitenanzeige F4	3	Access	172	17	222	172	44				
	e2-0	Bildschirm F8	3	Access	172	17	222	221	93				
	e2-1	Bildschirm F6	3	Access	172	17	222	222	94				
	e2-2	Bildschirm F2	3	Access	172	17	222	223	95				
	e2-3				-	-	-	-	-				
e2-4	Bildschirm F11	3	Access	172	17	222	225	97					
e2-5	Audio Amp. F2	9	Access	172	20	222	158	30					
F3	e0-0	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS F1			-	-	-	-	-				Reserviert
	e0-3	RDC F1			-	-	-	-	-				Reserviert
	e0-4	Access point F3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera F1	5	Access	172	18	222	216	88	y	5,0		
	e1-1	Rücksehkamera F2	5	Access	172	18	222	217	89	y	5,0		
	e1-2	Access point F4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3	Überw. Kamera F11	5	Access	172	18	222	199	71	y	5,0		
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle F2R	9	Access	172	20	222	146	18	y	7,5		Redundanz F2
	e1-10	Sprechstelle FIR	9	Access	172	20	222	145	17	y	7,5		Redundanz F1
	e1-11				-	-	-	-	-				
	e1-12	Future use box F1	90	Access	-	-	-	-	-				
	e1-13	Future use box F3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm F9	3	Access	172	17	222	241	113				
	e2-1	Bildschirm F10	3	Access	172	17	222	242	114				
	e2-2	Bistro Telemetrie F1			-	-	-	-	-				Keine Information
	e2-3	Sitzplatzreservierung F	6	Access	172	19	94	142	14				
e2-4	Bistro Bezahlinheit F2			-	-	-	-	-				Keine Information	
e2-5	Bistro Bildschirm F3			-	-	-	-	-				Keine Information	

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	94	253	125					
	e1-0	Überw. Kamera B7	5	Access	172	18	222	187	59	y	5,0			
	e1-1	Überw. Kamera B2	5	Access	172	18	222	188	60	y	5,0			
	e1-2	Überw. Kamera B1	5	Access	172	18	222	189	61	y	5,0			
	e1-3	Überw. Kamera B5	5	Access	172	18	222	190	62	y	5,0			
	e1-4	Überw. Kamera B9	5	Access	172	18	222	191	63	y	5,0			
	e1-5	AFZ B1	8	Access	172	20	94	158	30	y	10,0			
	e1-6	AFZ B2	8	Access	172	20	94	159	31	y	10,0			
	e1-7	Sprechstelle B4R	9	Access	172	20	222	172	44	y	7,5		Redundanz B4	
	e1-8	Sprechstelle B1	9	Access	172	20	222	147	19	y	7,5			
	e1-9	Sprechstelle B3R	9	Access	172	20	222	173	45	y	7,5		Redundanz B3	
	e1-10					-	-	-	-	-				
	e1-11	ZFR R	2	Access	172	17	94	130	2					
	e1-12	Future use box B5	90	Access	-	-	-	-	-					
	e1-13	Future use box B6	90	Access	-	-	-	-	-					
B2	e1-14	Seitenanzeige B1	3	Access	172	17	222	173	45					
	e1-15	Seitenanzeige B3	3	Access	172	17	222	174	46					
	e2-0	Bildschirm B7	3	Access	172	17	222	226	98					
	e2-1	Bildschirm B5	3	Access	172	17	222	227	99					
	e2-2	Bildschirm B1	3	Access	172	17	222	228	100					
	e2-3	Bildschirm B3	3	Access	172	17	222	229	101					
	e2-4	ADU B	9	Access	172	20	222	132	4					
	e2-5	Audio Amp. B1	9	Access	172	20	222	159	31					
	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point B2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Überw. Kamera B8	5	Access	172	18	222	192	64	y	5,0			
	e1-1	Überw. Kamera B4	5	Access	172	18	222	193	65	y	5,0			
	e1-2	Überw. Kamera B3	5	Access	172	18	222	194	66	y	5,0			
	e1-3	Überw. Kamera B6	5	Access	172	18	222	195	67	y	5,0			
	e1-4	Überw. Kamera B10	5	Access	172	18	222	196	68	y	5,0			
	e1-5	AFZ B3	8	Access	172	20	94	160	32	y	10,0			
e1-6	AFZ B4	8	Access	172	20	94	161	33	y	10,0				
e1-7	NVR B	5	Access	172	18	222	134	6						
e1-8	Sprechstelle B2	9	Access	172	20	222	148	20	y	7,5				
e1-9	Sprechstelle B4	9	Access	172	20	222	172	44	y	7,5				
e1-10	Sprechstelle B5R	9	Access	172	20	222	174	46	y	7,5		Redundanz B5		
e1-11	Sprechstelle B3	9	Access	172	20	222	173	45	y	7,5				
e1-12	Future use box B2	90	Access	-	-	-	-	-						
e1-13	Future use box B4	90	Access	-	-	-	-	-						
e1-14	Seitenanzeige B2	3	Access	172	17	222	175	47						
e1-15	Seitenanzeige B4	3	Access	172	17	222	176	48						
e2-0	Bildschirm B8	3	Access	172	17	222	230	102						
e2-1	Bildschirm B6	3	Access	172	17	222	231	103						
e2-2	Bildschirm B2	3	Access	172	17	222	232	104						
e2-3				-	-	-	-	-						
e2-4				-	-	-	-	-						
e2-5	Audio Amp. B2	9	Access	172	20	222	160	32						
B3	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point B3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera B1	5	Access	172	18	222	218	90	y	5,0			
	e1-1	Rücksehkamera B2	5	Access	172	18	222	219	91	y	5,0			
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3				-	-	-	-	-					
	e1-4				-	-	-	-	-					
	e1-5				-	-	-	-	-					
	e1-6				-	-	-	-	-					
	e1-7	Sprechstelle B5	9	Access	172	20	222	174	46	y	7,5			
	e1-8				-	-	-	-	-					
	e1-9	Sprechstelle B2R	9	Access	172	20	222	148	20	y	7,5		Redundanz B2	
	e1-10	Sprechstelle B1R	9	Access	172	20	222	147	19	y	7,5		Redundanz B1	
	e1-11	ZFR	2	Access	172	17	94	130	2					
	e1-12	Future use box B1	90	Access	-	-	-	-	-					
	e1-13	Future use box B3	90	Access	-	-	-	-	-					
e1-14	Frontanzeige B	3	Access	172	17	222	152	24						
e1-15				-	-	-	-	-						
e2-0	Bildschirm B9	3	Access	172	17	222	243	115						
e2-1	Bildschirm B10	3	Access	172	17	222	244	116						
e2-2				-	-	-	-	-						
e2-3	Sitzplatzreservierung B	6	Access	172	19	94	143	15						
e2-4	ADU BR	9	Access	172	20	222	132	4				Redundanz B		
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	127					
Firewall	N/A	RCU	2	N/A	172	17	94	254	126			IP für die RCU festgelegt.		
			3	N/A	172	17	222	254	126					
			9	N/A	172	20	222	254	126					