

4706 - 102 IPv4-Schema

Fahrzeugnummer: 4706-XXX				Fzg. ID: 190				Wagen: A - 100					
Switch	Switchport	Usage	VLAN ID	Port Type	IP Address				IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	120	120				
	e1-0	Überw. Kamera A7	5	Access	172	18	223	10	10	y	5,0		
	e1-1	Überw. Kamera A2	5	Access	172	18	223	11	11	y	5,0		
	e1-2	Überw. Kamera A1	5	Access	172	18	223	12	12	y	5,0		
	e1-3	Überw. Kamera A5	5	Access	172	18	223	13	13	y	5,0		
	e1-4	Überw. Kamera A9	5	Access	172	18	223	14	14	y	5,0		
	e1-5	AFZ A1	8	Access	172	20	95	5	5	y	10,0		
	e1-6	AFZ A2	8	Access	172	20	95	6	6	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle A1	9	Access	172	20	223	5	5	y	7,5		
	e1-9	Sprechstelle A3R	9	Access	172	20	223	41	41	y	7,5		Redundanz A3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A5	90	Access	-	-	-	-	-				
	e1-13	Future use box A6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige A1	3	Access	172	17	223	25	25				
	e1-15	Seitenanzeige A3	3	Access	172	17	223	26	26				
	e2-0	Bildschirm A7	3	Access	172	17	223	50	50				
	e2-1	Bildschirm A5	3	Access	172	17	223	51	51				
	e2-2	Bildschirm A1	3	Access	172	17	223	52	52				
	e2-3	Bildschirm A3	3	Access	172	17	223	53	53				
	e2-4	ADU A	9	Access	172	20	223	3	3				
	e2-5	Audio Amp. A1	9	Access	172	20	223	21	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera A8	5	Access	172	18	223	15	15	y	5,0		
	e1-1	Überw. Kamera A4	5	Access	172	18	223	16	16	y	5,0		
	e1-2	Überw. Kamera A3	5	Access	172	18	223	17	17	y	5,0		
	e1-3	Überw. Kamera A6	5	Access	172	18	223	18	18	y	5,0		
	e1-4	Überw. Kamera A10	5	Access	172	18	223	19	19	y	5,0		
	e1-5	AFZ A3	8	Access	172	20	95	7	7	y	10,0		
	e1-6	AFZ A4	8	Access	172	20	95	8	8	y	10,0		
	e1-7	NVR A	5	Access	172	18	223	5	5				
	e1-8	Sprechstelle A2	9	Access	172	20	223	6	6	y	7,5		
	e1-9	Sprechstelle A3	9	Access	172	20	223	41	41	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A2	90	Access	-	-	-	-	-				
	e1-13	Future use box A4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige A2	3	Access	172	17	223	27	27				
	e1-15	Seitenanzeige A4	3	Access	172	17	223	28	28				
	e2-0	Bildschirm A8	3	Access	172	17	223	54	54				
	e2-1	Bildschirm A6	3	Access	172	17	223	55	55				
	e2-2	Bildschirm A2	3	Access	172	17	223	56	56				
	e2-3	Bildschirm A4	3	Access	172	17	223	57	57				
	e2-4				-	-	-	-	-				
	e2-5	Audio Amp. A2	9	Access	172	20	223	22	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera A1	5	Access	172	18	223	80	80	y	5,0		
	e1-1	Rücksehkamera A2	5	Access	172	18	223	81	81	y	5,0		
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4	Firewall	2	Trunk	172	17	95	1	1			Kein DHCP Statische Konfiguration STADLER	
		3	172		17	223	1						
		5	172		18	223	1						
		6	172		19	95	1						
		7	172		19	223	1						
		8	172		20	95	1						
		9	172		20	223	1						
			12	172	22	95	1						
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle A1R	9	Access	172	20	223	5	5	y	7,5		Redundanz A1
	e1-9	Sprechstelle A2R	9	Access	172	20	223	6	6	y	7,5		Redundanz A2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A1	90	Access	-	-	-	-	-				
	e1-13	Future use box A3	90	Access	-	-	-	-	-				
	e1-14	Frontanzeige A	3	Access	172	17	223	23	23				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm A9	3	Access	172	17	223	105	105				
	e2-1	Bildschirm A10	3	Access	172	17	223	106	106				
	e2-2				-	-	-	-	-				
	e2-3	Sitzplatzreservierung A	6	Access	172	19	95	10	10				
	e2-4	ADU AR	9	Access	172	20	223	3	3				Redundanz A
	e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127				

C1	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	121	121				
	e1-0	Überw. Kamera C7	5	Access	172	18	223	20	20	y	5,0		
	e1-1	Überw. Kamera C2	5	Access	172	18	223	21	21	y	5,0		
	e1-2	Überw. Kamera C1	5	Access	172	18	223	22	22	y	5,0		
	e1-3	Überw. Kamera C5	5	Access	172	18	223	23	23	y	5,0		
	e1-4	Überw. Kamera C9	5	Access	172	18	223	24	24	y	5,0		
	e1-5	AFZ C1	8	Access	172	20	95	9	9	y	10,0		
	e1-6	AFZ C2	8	Access	172	20	95	10	10	y	10,0		
	e1-7	AFZ C5	8	Access	172	20	95	11	11	y	10,0		
	e1-8	Sprechstelle C1	9	Access	172	20	223	7	7	y	7,5		
	e1-9	Sprechstelle C3R	9	Access	172	20	223	42	42	y	7,5		Redundanz C3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C5	90	Access	-	-	-	-	-				
	e1-13	Future use box C6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C1	3	Access	172	17	223	29	29				
	e1-15	Seitenanzeige C3	3	Access	172	17	223	30	30				
	e2-0	Bildschrim C7	3	Access	172	17	223	58	58				
	e2-1	Bildschrim C5	3	Access	172	17	223	59	59				
	e2-2	Bildschrim C1	3	Access	172	17	223	60	60				
	e2-3	Bildschrim C3	3	Access	172	17	223	61	61				
e2-4				-	-	-	-	-					
e2-5	Audio Amp. C1	9	Access	172	20	223	23	23					
C2	e0-0	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera C8	5	Access	172	18	223	25	25	y	5,0		
	e1-1	Überw. Kamera C4	5	Access	172	18	223	26	26	y	5,0		
	e1-2	Überw. Kamera C3	5	Access	172	18	223	27	27	y	5,0		
	e1-3	Überw. Kamera C6	5	Access	172	18	223	28	28	y	5,0		
	e1-4	Überw. Kamera C10	5	Access	172	18	223	29	29	y	5,0		
	e1-5	AFZ C3	8	Access	172	20	95	12	12	y	10,0		
	e1-6	AFZ C4	8	Access	172	20	95	13	13	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C2	9	Access	172	20	223	8	8	y	7,5		
	e1-9	Sprechstelle C3	9	Access	172	20	223	42	42	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C2	90	Access	-	-	-	-	-				
	e1-13	Future use box C4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C2	3	Access	172	17	223	31	31				
	e1-15	Seitenanzeige C4	3	Access	172	17	223	32	32				
	e2-0	Bildschrim C8	3	Access	172	17	223	63	63				
	e2-1	Bildschrim C6	3	Access	172	17	223	64	64				
	e2-2	Bildschrim C2	3	Access	172	17	223	65	65				
	e2-3	Bildschrim C4	3	Access	172	17	223	66	66				
e2-4	Bildschrim C11	3	Access	172	17	223	67	67					
e2-5	Audio Amp. C2	9	Access	172	20	223	24	24					
C3	e0-0	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera C1	5	Access	172	18	223	82	82	y	5,0		
	e1-1	Rücksehkamera C2	5	Access	172	18	223	83	83	y	5,0		
	e1-2	Access point C4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C1R	9	Access	172	20	223	7	7	y	7,5		Redundanz C1
	e1-9	Sprechstelle C2R	9	Access	172	20	223	8	8	y	7,5		Redundanz C2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C1	90	Access	-	-	-	-	-				
	e1-13	Future use box C3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm C9	3	Access	172	17	223	107	107				
	e2-1	Bildschirm C10	3	Access	172	17	223	108	108				
	e2-2	Bistro Telemetrie C1			-	-	-	-	-				Keine Informationen
	e2-3	Sitzplatzreservierung C	6	Access	172	19	95	11	11				
e2-4	Bistro Bezahlinheit C2			-	-	-	-	-				Keine Informationen	
e2-5	Bistro Bildschirm C3			-	-	-	-	-				Keine Informationen	

D1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1R	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				Redundanz OBS D1
			7		172	19	223	2	2				
	e0-3	RDC D1R	200, 202	Trunk	-	-	-	-	-				Redundanz RDC D1
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	122	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	223	30	30	y	5,0		
	e1-1	Überw. Kamera D2	5	Access	172	18	223	31	31	y	5,0		
	e1-2	Überw. Kamera D1	5	Access	172	18	223	32	32	y	5,0		
	e1-3	Überw. Kamera D5	5	Access	172	18	223	33	33	y	5,0		
	e1-4	Überw. Kamera D9	5	Access	172	18	223	34	34	y	5,0		
	e1-5	AFZ D1	8	Access	172	20	95	14	14	y	10,0		
	e1-6	AFZ D2	8	Access	172	20	95	15	15	y	10,0		
	e1-7	AFZ D5	8	Access	172	20	95	16	16	y	10,0		
	e1-8	Sprechstelle D1	9	Access	172	20	223	10	10	y	7,5		
	e1-9	Sprechstelle D3R	9	Access	172	20	223	43	43	y	7,5		Redundanz D3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D1	3	Access	172	17	223	33	33				
	e1-15	Seitenanzeige D3	3	Access	172	17	223	34	34				
	e2-0	Bildschirm D7	3	Access	172	17	223	68	68				
	e2-1	Bildschirm D5	3	Access	172	17	223	69	69				
e2-2	Bildschirm D1	3	Access	172	17	223	70	70					
e2-3	Bildschirm D3	3	Access	172	17	223	71	71					
e2-4				-	-	-	-	-					
e2-5	Audio Amp. D1	9	Access	172	20	223	25	25					
D2	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	223	35	35	y	5,0		
	e1-1	Überw. Kamera D4	5	Access	172	18	223	36	36	y	5,0		
	e1-2	Überw. Kamera D3	5	Access	172	18	223	37	37	y	5,0		
	e1-3	Überw. Kamera D6	5	Access	172	18	223	38	38	y	5,0		
	e1-4	Überw. Kamera D10	5	Access	172	18	223	39	39	y	5,0		
	e1-5	AFZ D3	8	Access	172	20	95	17	17	y	10,0		
	e1-6	AFZ D4	8	Access	172	20	95	18	18	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	223	11	11	y	7,5		
	e1-9	Sprechstelle D3	9	Access	172	20	223	43	43	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D2	3	Access	172	17	223	35	35				
	e1-15	Seitenanzeige D4	3	Access	172	17	223	36	36				
	e2-0	Bildschirm D8	3	Access	172	17	223	73	73				
	e2-1	Bildschirm D6	3	Access	172	17	223	74	74				
	e2-2	Bildschirm D2	3	Access	172	17	223	75	75				
e2-3	Bildschirm D4	3	Access	172	17	223	76	76					
e2-4	Bildschirm D11	3	Access	172	17	223	77	77					
e2-5	Audio Amp. D2	9	Access	172	20	223	26	26					
D3	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
			7		172	19	223	2	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	223	84	84	y	5,0		
	e1-1	Rücksehkamera D2	5	Access	172	18	223	85	85	y	5,0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3	Überw. Kamera D11	5	Access	172	18	223	69	69	y	5,0		
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D1R	9	Access	172	20	223	10	10	y	7,5		Redundanz D1
	e1-9	Sprechstelle D2R	9	Access	172	20	223	11	11	y	7,5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm D9	3	Access	172	17	223	109	109				
	e2-1	Bildschirm D10	3	Access	172	17	223	110	110				
e2-2				-	-	-	-	-					
e2-3	Sitzplatzreservierung D	6	Access	172	19	95	12	12					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

E1	e0-0	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	95	123	123					
	e1-0	Überw. Kamera E7	5	Access	172	18	223	40	40	y	5,0			
	e1-1	Überw. Kamera E2	5	Access	172	18	223	41	41	y	5,0			
	e1-2	Überw. Kamera E1	5	Access	172	18	223	42	42	y	5,0			
	e1-3	Überw. Kamera E5	5	Access	172	18	223	43	43	y	5,0			
	e1-4	Überw. Kamera E9	5	Access	172	18	223	44	44	y	5,0			
	e1-5	AFZ E1	8	Access	172	20	95	19	19	y	10,0			
	e1-6	AFZ E2	8	Access	172	20	95	20	20	y	10,0			
	e1-7	AFZ E5	8	Access	172	20	95	21	21	y	10,0			
	e1-8	Sprechstelle E1	9	Access	172	20	223	12	12	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10	Sprechstelle PRM E1	9	Access	172	20	223	13	13	y	7,5		Redundanz PRM E1	
	e1-11	Sprechstelle PRM WCR	9	Access	172	20	223	16	16	y	7,5		Redundanz PRM WC	
	e1-12	Future use box E5	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E7	90	Access	-	-	-	-	-	-				
	e1-14	Seitenanzeige E1	3	Access	172	17	223	37	37					
	e1-15	Seitenanzeige E3	3	Access	172	17	223	38	38					
	e2-0	Bildschirm E7	3	Access	172	17	223	78	78					
	e2-1	Bildschirm E5	3	Access	172	17	223	79	79					
	e2-2	Bildschirm E1	3	Access	172	17	223	80	80					
e2-3	Bildschirm E3	3	Access	172	17	223	81	81						
e2-4	ADU E	9	Access	172	20	223	2	2						
e2-5	Audio Amp. E1	9	Access	172	20	223	27	27						
E2	e0-0	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Überw. Kamera E8	5	Access	172	18	223	45	45	y	5,0			
	e1-1	Überw. Kamera E4	5	Access	172	18	223	46	46	y	5,0			
	e1-2	Überw. Kamera E3	5	Access	172	18	223	47	47	y	5,0			
	e1-3	Überw. Kamera E6	5	Access	172	18	223	48	48	y	5,0			
	e1-4	Überw. Kamera E10	5	Access	172	18	223	70	70	y	5,0			
	e1-5	AFZ E3	8	Access	172	20	95	22	22	y	10,0			
	e1-6	AFZ E4	8	Access	172	20	95	23	23	y	10,0			
	e1-7	AFZ E6	8	Access	172	20	95	24	24	y	10,0			
	e1-8	Sprechstelle E2	9	Access	172	20	223	14	14	y	7,5			
	e1-9	Sprechstelle E1R	9	Access	172	20	223	12	12	y	7,5		Redundanz E1	
	e1-10	Sprechstelle PRM E2	9	Access	172	20	223	15	15	y	7,5			
	e1-11	Sprechstelle PRM E1R	9	Access	172	20	223	13	13	y	7,5		Redundanz PRM E1	
	e1-12	Future use box E2	90	Access	-	-	-	-	-					
	e1-13	Future use box E4	90	Access	-	-	-	-	-					
	e1-14	Seitenanzeige E2	3	Access	172	17	223	39	39					
	e1-15	Seitenanzeige E4	3	Access	172	17	223	40	40					
	e2-0	Bildschirm E8	3	Access	172	17	223	83	83					
	e2-1	Bildschirm E6	3	Access	172	17	223	84	84					
	e2-2	Bildschirm E2	3	Access	172	17	223	85	85					
e2-3	Bildschirm E4	3	Access	172	17	223	86	86						
e2-4	Bildschirm E11	3	Access	172	17	223	87	87						
e2-5	Audio Amp. E2	9	Access	172	20	223	28	28						
E3	e0-0	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera E1	5	Access	172	18	223	86	86	y	5,0			
	e1-1	Rücksehkamera E2	5	Access	172	18	223	87	87	y	5,0			
	e1-2	Access point E4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3				-	-	-	-	-					
	e1-4				-	-	-	-	-					
	e1-5				-	-	-	-	-					
	e1-6				-	-	-	-	-					
	e1-7				-	-	-	-	-					
	e1-8				-	-	-	-	-					
	e1-9	Sprechstelle E2R	9	Access	172	20	223	14	14	y	7,5		Redundanz E2	
	e1-10	Sprechstelle PRM WC	9	Access	172	20	223	16	16	y	7,5			
	e1-11	Sprechstelle PRM E2R	9	Access	172	20	223	15	15	y	7,5		Redundanz PRM E2	
	e1-12	Future use box E1	90	Access	-	-	-	-	-					
	e1-13	Future use box E3	90	Access	-	-	-	-	-					
	e1-14				-	-	-	-	-					
	e1-15				-	-	-	-	-					
	e2-0	Bildschirm E9	3	Access	172	17	223	111	111					
	e2-1	Bildschirm E10	3	Access	172	17	223	112	112					
	e2-2	Fahrausweiseinrichtung		Access	-	-	-	-	-					Reserviert
e2-3	Sitzplatzreservierung E	6	Access	172	19	95	13	13						
e2-4	ADU ER	9	Access	172	20	223	2	2					Redundanz E	
e2-5	Energiezähler F	12	Access	172	22	95	3	3						

F1	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point F1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	95	124	124					
	e1-0	Überw. Kamera F7	5	Access	172	18	223	49	49	y	5,0			
	e1-1	Überw. Kamera F2	5	Access	172	18	223	50	50	y	5,0			
	e1-2	Überw. Kamera F1	5	Access	172	18	223	51	51	y	5,0			
	e1-3	Überw. Kamera F5	5	Access	172	18	223	52	52	y	5,0			
	e1-4	Überw. Kamera F9	5	Access	172	18	223	53	53	y	5,0			
	e1-5	AFZ F1	8	Access	172	20	95	25	25	y	10,0			
	e1-6	AFZ F2	8	Access	172	20	95	26	26	y	10,0			
	e1-7	AFZ F5	8	Access	172	20	95	27	27	y	10,0			
	e1-8	Sprechstelle F1	9	Access	172	20	223	17	17	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10					-	-	-	-	-				
	e1-11					-	-	-	-	-				
	e1-12	Future use box F5	90	Access		-	-	-	-	-				
	e1-13	Future use box F6	90	Access		-	-	-	-	-				
	e1-14	Seitenanzeige F1	3	Access	172	17	223	41	41					
	e1-15	Seitenanzeige F3	3	Access	172	17	223	42	42					
	e2-0	Bildschrim F7	3	Access	172	17	223	88	88					
	e2-1	Bildschrim F5	3	Access	172	17	223	89	89					
	e2-2	Bildschrim F1	3	Access	172	17	223	90	90					
e2-3	Bildschrim F3	3	Access	172	17	223	91	91						
e2-4					-	-	-	-	-					
e2-5	Audio Amp. F1	9	Access	172	20	223	29	29						
F2	e0-0	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	OBS FIR			-	-	-	-	-				Reserviert	
	e0-3	RDC FIR			-	-	-	-	-				Reserviert	
	e0-4	Access point F2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Überw. Kamera F8	5	Access	172	18	223	54	54	y	5,0			
	e1-1	Überw. Kamera F4	5	Access	172	18	223	55	55	y	5,0			
	e1-2	Überw. Kamera F3	5	Access	172	18	223	56	56	y	5,0			
	e1-3	Überw. Kamera F6	5	Access	172	18	223	57	57	y	5,0			
	e1-4	Überw. Kamera F10	5	Access	172	18	223	58	58	y	5,0			
	e1-5	AFZ F3	8	Access	172	20	95	28	28	y	10,0			
	e1-6	AFZ F4	8	Access	172	20	95	29	29	y	10,0			
	e1-7					-	-	-	-	-				
	e1-8	Sprechstelle F2	9	Access	172	20	223	18	18	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10					-	-	-	-	-				
	e1-11					-	-	-	-	-				
	e1-12	Future use box F2	90	Access		-	-	-	-	-				
	e1-13	Future use box F4	90	Access		-	-	-	-	-				
	e1-14	Seitenanzeige F2	3	Access	172	17	223	43	43					
	e1-15	Seitenanzeige F4	3	Access	172	17	223	44	44					
	e2-0	Bildschrim F8	3	Access	172	17	223	93	93					
	e2-1	Bildschrim F6	3	Access	172	17	223	94	94					
	e2-2	Bildschrim F2	3	Access	172	17	223	95	95					
e2-3					-	-	-	-	-					
e2-4	Bildschrim F11	3	Access	172	17	223	97	97						
e2-5	Audio Amp. F2	9	Access	172	20	223	30	30						
F3	e0-0	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	OBS F1			-	-	-	-	-				Reserviert	
	e0-3	RDC F1			-	-	-	-	-				Reserviert	
	e0-4	Access point F3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera F1	5	Access	172	18	223	88	88	y	5,0			
	e1-1	Rücksehkamera F2	5	Access	172	18	223	89	89	y	5,0			
	e1-2	Access point F4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3	Überw. Kamera F11	5	Access	172	18	223	71	71	y	5,0			
	e1-4					-	-	-	-	-				
	e1-5					-	-	-	-	-				
	e1-6					-	-	-	-	-				
	e1-7					-	-	-	-	-				
	e1-8					-	-	-	-	-				
	e1-9	Sprechstelle F2R	9	Access	172	20	223	18	18	y	7,5		Redundanz F2	
	e1-10	Sprechstelle FIR	9	Access	172	20	223	17	17	y	7,5		Redundanz F1	
	e1-11					-	-	-	-	-				
	e1-12	Future use box F1	90	Access		-	-	-	-	-				
	e1-13	Future use box F3	90	Access		-	-	-	-	-				
	e1-14					-	-	-	-	-				
	e1-15					-	-	-	-	-				
	e2-0	Bildschirm F9	3	Access	172	17	223	113	113					
	e2-1	Bildschirm F10	3	Access	172	17	223	114	114					
	e2-2	Bistro Telemetrie F1				-	-	-	-	-				Keine Information
e2-3	Sitzplatzreservierung F	6	Access	172	19	95	14	14						
e2-4	Bistro Bezahlinheit F2				-	-	-	-	-				Keine Information	
e2-5	Bistro Bildschirm F3				-	-	-	-	-				Keine Information	

Seite 6 von 6