

4706 - 103 IPv4-Schema

Fahrzeugnummer: 4706-103				Fzg. ID: 191				Wagen: A - 100					
Switch	Switchport	Usage	VLAN ID	Port Type	IP Address				IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	248	120				
	e1-0	Überw. Kamera A7	5	Access	172	18	223	138	10	y	5,0		
	e1-1	Überw. Kamera A2	5	Access	172	18	223	139	11	y	5,0		
	e1-2	Überw. Kamera A1	5	Access	172	18	223	140	12	y	5,0		
	e1-3	Überw. Kamera A5	5	Access	172	18	223	141	13	y	5,0		
	e1-4	Überw. Kamera A9	5	Access	172	18	223	142	14	y	5,0		
	e1-5	AFZ A1	8	Access	172	20	95	133	5	y	10,0		
	e1-6	AFZ A2	8	Access	172	20	95	134	6	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle A1	9	Access	172	20	223	133	5	y	7,5		
	e1-9	Sprechstelle A3R	9	Access	172	20	223	169	41	y	7,5		Redundanz A3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A5	90	Access	-	-	-	-	-				
	e1-13	Future use box A6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige A1	3	Access	172	17	223	153	25				
	e1-15	Seitenanzeige A3	3	Access	172	17	223	154	26				
	e2-0	Bildschirm A7	3	Access	172	17	223	178	50				
	e2-1	Bildschirm A5	3	Access	172	17	223	179	51				
	e2-2	Bildschirm A1	3	Access	172	17	223	180	52				
	e2-3	Bildschirm A3	3	Access	172	17	223	181	53				
	e2-4	ADU A	9	Access	172	20	223	131	3				
	e2-5	Audio Amp. A1	9	Access	172	20	223	149	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera A8	5	Access	172	18	223	143	15	y	5,0		
	e1-1	Überw. Kamera A4	5	Access	172	18	223	144	16	y	5,0		
	e1-2	Überw. Kamera A3	5	Access	172	18	223	145	17	y	5,0		
	e1-3	Überw. Kamera A6	5	Access	172	18	223	146	18	y	5,0		
	e1-4	Überw. Kamera A10	5	Access	172	18	223	147	19	y	5,0		
	e1-5	AFZ A3	8	Access	172	20	95	135	7	y	10,0		
	e1-6	AFZ A4	8	Access	172	20	95	136	8	y	10,0		
	e1-7	NVR A	5	Access	172	18	223	133	5				
	e1-8	Sprechstelle A2	9	Access	172	20	223	134	6	y	7,5		
	e1-9	Sprechstelle A3	9	Access	172	20	223	169	41	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A2	90	Access	-	-	-	-	-				
	e1-13	Future use box A4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige A2	3	Access	172	17	223	155	27				
	e1-15	Seitenanzeige A4	3	Access	172	17	223	156	28				
	e2-0	Bildschirm A8	3	Access	172	17	223	182	54				
	e2-1	Bildschirm A6	3	Access	172	17	223	183	55				
	e2-2	Bildschirm A2	3	Access	172	17	223	184	56				
	e2-3	Bildschirm A4	3	Access	172	17	223	185	57				
	e2-4				-	-	-	-	-				
	e2-5	Audio Amp. A2	9	Access	172	20	223	150	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera A1	5	Access	172	18	223	208	80	y	5,0		
	e1-1	Rücksehkamera A2	5	Access	172	18	223	209	81	y	5,0		
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4	Firewall	2	Trunk	172	17	95	129	1			Kein DHCP Statische Konfiguration STADLER	
		3	172		17	223	129						
		5	172		18	223	129						
		6	172		19	95	129						
		7	172		19	223	129						
		8	172		20	95	129						
			9	172	20	223	129						
			12	172	22	95	129						
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle A1R	9	Access	172	20	223	133	5	y	7,5		Redundanz A1
	e1-9	Sprechstelle A2R	9	Access	172	20	223	134	6	y	7,5		Redundanz A2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box A1	90	Access	-	-	-	-	-				
	e1-13	Future use box A3	90	Access	-	-	-	-	-				
	e1-14	Frontanzeige A	3	Access	172	17	223	151	23				
e1-15				-	-	-	-	-					
e2-0	Bildschirm A9	3	Access	172	17	223	233	105					
e2-1	Bildschirm A10	3	Access	172	17	223	234	106					
e2-2				-	-	-	-	-					
e2-3	Sitzplatzreservierung A	6	Access	172	19	95	138	10					
e2-4	ADU AR	9	Access	172	20	223	131	3				Redundanz A	
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127					

C1	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	249	121				
	e1-0	Überw. Kamera C7	5	Access	172	18	223	148	20	y	5,0		
	e1-1	Überw. Kamera C2	5	Access	172	18	223	149	21	y	5,0		
	e1-2	Überw. Kamera C1	5	Access	172	18	223	150	22	y	5,0		
	e1-3	Überw. Kamera C5	5	Access	172	18	223	151	23	y	5,0		
	e1-4	Überw. Kamera C9	5	Access	172	18	223	152	24	y	5,0		
	e1-5	AFZ C1	8	Access	172	20	95	137	9	y	10,0		
	e1-6	AFZ C2	8	Access	172	20	95	138	10	y	10,0		
	e1-7	AFZ C5	8	Access	172	20	95	139	11	y	10,0		
	e1-8	Sprechstelle C1	9	Access	172	20	223	135	7	y	7,5		
	e1-9	Sprechstelle C3R	9	Access	172	20	223	170	42	y	7,5		Redundanz C3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C5	90	Access	-	-	-	-	-				
	e1-13	Future use box C6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige C1	3	Access	172	17	223	157	29				
	e1-15	Seitenanzeige C3	3	Access	172	17	223	158	30				
	e2-0	Bildschrim C7	3	Access	172	17	223	186	58				
	e2-1	Bildschrim C5	3	Access	172	17	223	187	59				
	e2-2	Bildschrim C1	3	Access	172	17	223	188	60				
	e2-3	Bildschrim C3	3	Access	172	17	223	189	61				
	e2-4				-	-	-	-	-				
	e2-5	Audio Amp. C1	9	Access	172	20	223	151	23				
	C2	e0-0	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
e0-1		FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
e0-2					-	-	-	-	-				
e0-3					-	-	-	-	-				
e0-4		Access point C2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
e0-5		reserved			-	-	-	-	-				
e1-0		Überw. Kamera C8	5	Access	172	18	223	153	25	y	5,0		
e1-1		Überw. Kamera C4	5	Access	172	18	223	154	26	y	5,0		
e1-2		Überw. Kamera C3	5	Access	172	18	223	155	27	y	5,0		
e1-3		Überw. Kamera C6	5	Access	172	18	223	156	28	y	5,0		
e1-4		Überw. Kamera C10	5	Access	172	18	223	157	29	y	5,0		
e1-5		AFZ C3	8	Access	172	20	95	140	12	y	10,0		
e1-6		AFZ C4	8	Access	172	20	95	141	13	y	10,0		
e1-7					-	-	-	-	-				
e1-8		Sprechstelle C2	9	Access	172	20	223	136	8	y	7,5		
e1-9		Sprechstelle C3	9	Access	172	20	223	170	42	y	7,5		
e1-10					-	-	-	-	-				
e1-11					-	-	-	-	-				
e1-12		Future use box C2	90	Access	-	-	-	-	-				
e1-13		Future use box C4	90	Access	-	-	-	-	-				
e1-14		Seitenanzeige C2	3	Access	172	17	223	159	31				
e1-15		Seitenanzeige C4	3	Access	172	17	223	160	32				
e2-0		Bildschrim C8	3	Access	172	17	223	191	63				
e2-1		Bildschrim C6	3	Access	172	17	223	192	64				
e2-2		Bildschrim C2	3	Access	172	17	223	193	65				
e2-3		Bildschrim C4	3	Access	172	17	223	194	66				
e2-4		Bildschrim C11	3	Access	172	17	223	195	67				
e2-5		Audio Amp. C2	9	Access	172	20	223	152	24				
C3		e0-0	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point C3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera C1	5	Access	172	18	223	210	82	y	5,0		
	e1-1	Rücksehkamera C2	5	Access	172	18	223	211	83	y	5,0		
	e1-2	Access point C4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle C1R	9	Access	172	20	223	135	7	y	7,5		Redundanz C1
	e1-9	Sprechstelle C2R	9	Access	172	20	223	136	8	y	7,5		Redundanz C2
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box C1	90	Access	-	-	-	-	-				
	e1-13	Future use box C3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm C9	3	Access	172	17	223	235	107				
	e2-1	Bildschirm C10	3	Access	172	17	223	236	108				
	e2-2	Bistro Telemetrie C1			-	-	-	-	-				Keine Informationen
	e2-3	Sitzplatzreservierung C	6	Access	172	19	95	139	11				
	e2-4	Bistro Bezahlinheit C2			-	-	-	-	-				Keine Informationen
	e2-5	Bistro Bildschirm C3			-	-	-	-	-				Keine Informationen

D1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1R	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				Redundanz OBS D1
			7		172	19	223	130	2				
	e0-3	RDC D1R	200, 202	Trunk	-	-	-	-	-				Redundanz RDC D1
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	95	250	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	223	158	30	y	5,0		
	e1-1	Überw. Kamera D2	5	Access	172	18	223	159	31	y	5,0		
	e1-2	Überw. Kamera D1	5	Access	172	18	223	160	32	y	5,0		
	e1-3	Überw. Kamera D5	5	Access	172	18	223	161	33	y	5,0		
	e1-4	Überw. Kamera D9	5	Access	172	18	223	162	34	y	5,0		
	e1-5	AFZ D1	8	Access	172	20	95	142	14	y	10,0		
	e1-6	AFZ D2	8	Access	172	20	95	143	15	y	10,0		
	e1-7	AFZ D5	8	Access	172	20	95	144	16	y	10,0		
	e1-8	Sprechstelle D1	9	Access	172	20	223	138	10	y	7,5		
	e1-9	Sprechstelle D3R	9	Access	172	20	223	171	43	y	7,5		Redundanz D3
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D1	3	Access	172	17	223	161	33				
	e1-15	Seitenanzeige D3	3	Access	172	17	223	162	34				
	e2-0	Bildschirm D7	3	Access	172	17	223	196	68				
	e2-1	Bildschirm D5	3	Access	172	17	223	197	69				
e2-2	Bildschirm D1	3	Access	172	17	223	198	70					
e2-3	Bildschirm D3	3	Access	172	17	223	199	71					
e2-4				-	-	-	-	-					
e2-5	Audio Amp. D1	9	Access	172	20	223	153	25					
D2	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	223	163	35	y	5,0		
	e1-1	Überw. Kamera D4	5	Access	172	18	223	164	36	y	5,0		
	e1-2	Überw. Kamera D3	5	Access	172	18	223	165	37	y	5,0		
	e1-3	Überw. Kamera D6	5	Access	172	18	223	166	38	y	5,0		
	e1-4	Überw. Kamera D10	5	Access	172	18	223	167	39	y	5,0		
	e1-5	AFZ D3	8	Access	172	20	95	145	17	y	10,0		
	e1-6	AFZ D4	8	Access	172	20	95	146	18	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	223	139	11	y	7,5		
	e1-9	Sprechstelle D3	9	Access	172	20	223	171	43	y	7,5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D2	3	Access	172	17	223	163	35				
	e1-15	Seitenanzeige D4	3	Access	172	17	223	164	36				
	e2-0	Bildschirm D8	3	Access	172	17	223	201	73				
	e2-1	Bildschirm D6	3	Access	172	17	223	202	74				
	e2-2	Bildschirm D2	3	Access	172	17	223	203	75				
e2-3	Bildschirm D4	3	Access	172	17	223	204	76					
e2-4	Bildschirm D11	3	Access	172	17	223	205	77					
e2-5	Audio Amp. D2	9	Access	172	20	223	154	26					
D3	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
			7		172	19	223	130	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	223	212	84	y	5,0		
	e1-1	Rücksehkamera D2	5	Access	172	18	223	213	85	y	5,0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3	Überw. Kamera D11	5	Access	172	18	223	197	69	y	5,0		
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D1R	9	Access	172	20	223	138	10	y	7,5		Redundanz D1
	e1-9	Sprechstelle D2R	9	Access	172	20	223	139	11	y	7,5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Bildschirm D9	3	Access	172	17	223	237	109				
	e2-1	Bildschirm D10	3	Access	172	17	223	238	110				
e2-2				-	-	-	-	-					
e2-3	Sitzplatzreservierung D	6	Access	172	19	95	140	12					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

E1	e0-0	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	95	251	123					
	e1-0	Überw. Kamera E7	5	Access	172	18	223	168	40	y	5,0			
	e1-1	Überw. Kamera E2	5	Access	172	18	223	169	41	y	5,0			
	e1-2	Überw. Kamera E1	5	Access	172	18	223	170	42	y	5,0			
	e1-3	Überw. Kamera E5	5	Access	172	18	223	171	43	y	5,0			
	e1-4	Überw. Kamera E9	5	Access	172	18	223	172	44	y	5,0			
	e1-5	AFZ E1	8	Access	172	20	95	147	19	y	10,0			
	e1-6	AFZ E2	8	Access	172	20	95	148	20	y	10,0			
	e1-7	AFZ E5	8	Access	172	20	95	149	21	y	10,0			
	e1-8	Sprechstelle E1	9	Access	172	20	223	140	12	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10	Sprechstelle PRM E1	9	Access	172	20	223	141	13	y	7,5		Redundanz PRM E1	
	e1-11	Sprechstelle PRM WCR	9	Access	172	20	223	144	16	y	7,5		Redundanz PRM WC	
	e1-12	Future use box E5	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E7	90	Access	-	-	-	-	-	-				
	e1-14	Seitenanzeige E1	3	Access	172	17	223	165	37					
	e1-15	Seitenanzeige E3	3	Access	172	17	223	166	38					
	e2-0	Bildschirm E7	3	Access	172	17	223	206	78					
	e2-1	Bildschirm E5	3	Access	172	17	223	207	79					
	e2-2	Bildschirm E1	3	Access	172	17	223	208	80					
	e2-3	Bildschirm E3	3	Access	172	17	223	209	81					
e2-4	ADU E	9	Access	172	20	223	130	2						
e2-5	Audio Amp. E1	9	Access	172	20	223	155	27						
E2	e0-0	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-	-				
	e1-0	Überw. Kamera E8	5	Access	172	18	223	173	45	y	5,0			
	e1-1	Überw. Kamera E4	5	Access	172	18	223	174	46	y	5,0			
	e1-2	Überw. Kamera E3	5	Access	172	18	223	175	47	y	5,0			
	e1-3	Überw. Kamera E6	5	Access	172	18	223	176	48	y	5,0			
	e1-4	Überw. Kamera E10	5	Access	172	18	223	198	70	y	5,0			
	e1-5	AFZ E3	8	Access	172	20	95	150	22	y	10,0			
	e1-6	AFZ E4	8	Access	172	20	95	151	23	y	10,0			
	e1-7	AFZ E6	8	Access	172	20	95	152	24	y	10,0			
	e1-8	Sprechstelle E2	9	Access	172	20	223	142	14	y	7,5			
	e1-9	Sprechstelle E1R	9	Access	172	20	223	140	12	y	7,5		Redundanz E1	
	e1-10	Sprechstelle PRM E2	9	Access	172	20	223	143	15	y	7,5			
	e1-11	Sprechstelle PRM E1R	9	Access	172	20	223	141	13	y	7,5		Redundanz PRM E1	
	e1-12	Future use box E2	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E4	90	Access	-	-	-	-	-	-				
	e1-14	Seitenanzeige E2	3	Access	172	17	223	167	39					
	e1-15	Seitenanzeige E4	3	Access	172	17	223	168	40					
	e2-0	Bildschirm E8	3	Access	172	17	223	211	83					
	e2-1	Bildschirm E6	3	Access	172	17	223	212	84					
	e2-2	Bildschirm E2	3	Access	172	17	223	213	85					
	e2-3	Bildschirm E4	3	Access	172	17	223	214	86					
e2-4	Bildschirm E11	3	Access	172	17	223	215	87						
e2-5	Audio Amp. E2	9	Access	172	20	223	156	28						
E3	e0-0	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-	-				
	e1-0	Rücksehkamera E1	5	Access	172	18	223	214	86	y	5,0			
	e1-1	Rücksehkamera E2	5	Access	172	18	223	215	87	y	5,0			
	e1-2	Access point E4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3				-	-	-	-	-	-				
	e1-4				-	-	-	-	-	-				
	e1-5				-	-	-	-	-	-				
	e1-6				-	-	-	-	-	-				
	e1-7				-	-	-	-	-	-				
	e1-8				-	-	-	-	-	-				
	e1-9	Sprechstelle E2R	9	Access	172	20	223	142	14	y	7,5		Redundanz E2	
	e1-10	Sprechstelle PRM WC	9	Access	172	20	223	144	16	y	7,5			
	e1-11	Sprechstelle PRM E2R	9	Access	172	20	223	143	15	y	7,5		Redundanz PRM E2	
	e1-12	Future use box E1	90	Access	-	-	-	-	-	-				
	e1-13	Future use box E3	90	Access	-	-	-	-	-	-				
	e1-14				-	-	-	-	-	-				
	e1-15				-	-	-	-	-	-				
	e2-0	Bildschirm E9	3	Access	172	17	223	239	111					
	e2-1	Bildschirm E10	3	Access	172	17	223	240	112					
	e2-2	Fahrausweiseinrichtung		Access	-	-	-	-	-	-				Reserviert
	e2-3	Sitzplatzreservierung E	6	Access	172	19	95	141	13					
e2-4	ADU ER	9	Access	172	20	223	130	2					Redundanz E	
e2-5	Energiezähler F	12	Access	172	22	95	131	3						

F1	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point F1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	Service FIS / CCTV	2	Access	172	17	95	252	124					
	e1-0	Überw. Kamera F7	5	Access	172	18	223	177	49	y	5,0			
	e1-1	Überw. Kamera F2	5	Access	172	18	223	178	50	y	5,0			
	e1-2	Überw. Kamera F1	5	Access	172	18	223	179	51	y	5,0			
	e1-3	Überw. Kamera F5	5	Access	172	18	223	180	52	y	5,0			
	e1-4	Überw. Kamera F9	5	Access	172	18	223	181	53	y	5,0			
	e1-5	AFZ F1	8	Access	172	20	95	153	25	y	10,0			
	e1-6	AFZ F2	8	Access	172	20	95	154	26	y	10,0			
	e1-7	AFZ F5	8	Access	172	20	95	155	27	y	10,0			
	e1-8	Sprechstelle F1	9	Access	172	20	223	145	17	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10					-	-	-	-	-				
	e1-11					-	-	-	-	-				
	e1-12	Future use box F5	90	Access		-	-	-	-	-				
	e1-13	Future use box F6	90	Access		-	-	-	-	-				
	e1-14	Seitenanzeige F1	3	Access	172	17	223	169	41					
	e1-15	Seitenanzeige F3	3	Access	172	17	223	170	42					
	e2-0	Bildschrim F7	3	Access	172	17	223	216	88					
	e2-1	Bildschrim F5	3	Access	172	17	223	217	89					
	e2-2	Bildschrim F1	3	Access	172	17	223	218	90					
e2-3	Bildschrim F3	3	Access	172	17	223	219	91						
e2-4					-	-	-	-	-					
e2-5	Audio Amp. F1	9	Access	172	20	223	157	29						
F2	e0-0	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	OBS FIR			-	-	-	-	-				Reserviert	
	e0-3	RDC FIR			-	-	-	-	-				Reserviert	
	e0-4	Access point F2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Überw. Kamera F8	5	Access	172	18	223	182	54	y	5,0			
	e1-1	Überw. Kamera F4	5	Access	172	18	223	183	55	y	5,0			
	e1-2	Überw. Kamera F3	5	Access	172	18	223	184	56	y	5,0			
	e1-3	Überw. Kamera F6	5	Access	172	18	223	185	57	y	5,0			
	e1-4	Überw. Kamera F10	5	Access	172	18	223	186	58	y	5,0			
	e1-5	AFZ F3	8	Access	172	20	95	156	28	y	10,0			
	e1-6	AFZ F4	8	Access	172	20	95	157	29	y	10,0			
	e1-7					-	-	-	-	-				
	e1-8	Sprechstelle F2	9	Access	172	20	223	146	18	y	7,5			
	e1-9					-	-	-	-	-				
	e1-10					-	-	-	-	-				
	e1-11					-	-	-	-	-				
	e1-12	Future use box F2	90	Access		-	-	-	-	-				
	e1-13	Future use box F4	90	Access		-	-	-	-	-				
	e1-14	Seitenanzeige F2	3	Access	172	17	223	171	43					
	e1-15	Seitenanzeige F4	3	Access	172	17	223	172	44					
	e2-0	Bildschrim F8	3	Access	172	17	223	221	93					
	e2-1	Bildschrim F6	3	Access	172	17	223	222	94					
	e2-2	Bildschrim F2	3	Access	172	17	223	223	95					
e2-3					-	-	-	-	-					
e2-4	Bildschrim F11	3	Access	172	17	223	225	97						
e2-5	Audio Amp. F2	9	Access	172	20	223	158	30						
F3	e0-0	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	OBS F1			-	-	-	-	-				Reserviert	
	e0-3	RDC F1			-	-	-	-	-				Reserviert	
	e0-4	Access point F3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera F1	5	Access	172	18	223	216	88	y	5,0			
	e1-1	Rücksehkamera F2	5	Access	172	18	223	217	89	y	5,0			
	e1-2	Access point F4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0			
	e1-3	Überw. Kamera F11	5	Access	172	18	223	199	71	y	5,0			
	e1-4					-	-	-	-	-				
	e1-5					-	-	-	-	-				
	e1-6					-	-	-	-	-				
	e1-7					-	-	-	-	-				
	e1-8					-	-	-	-	-				
	e1-9	Sprechstelle F2R	9	Access	172	20	223	146	18	y	7,5		Redundanz F2	
	e1-10	Sprechstelle FIR	9	Access	172	20	223	145	17	y	7,5		Redundanz F1	
	e1-11					-	-	-	-	-				
	e1-12	Future use box F1	90	Access		-	-	-	-	-				
	e1-13	Future use box F3	90	Access		-	-	-	-	-				
	e1-14					-	-	-	-	-				
	e1-15					-	-	-	-	-				
	e2-0	Bildschirm F9	3	Access	172	17	223	241	113					
	e2-1	Bildschirm F10	3	Access	172	17	223	242	114					
	e2-2	Bistro Telemetrie F1				-	-	-	-	-				Keine Information
e2-3	Sitzplatzreservierung F	6	Access	172	19	95	142	14						
e2-4	Bistro Bezahlinheit F2				-	-	-	-	-				Keine Information	
e2-5	Bistro Bildschirm F3				-	-	-	-	-				Keine Information	

Seite 6 von 6