

IPv4-Schema
Fgz. Nr: 4734 - 101



Fahrzeugnummer: 4734-101				Fzg. ID: 1				Wagen: A - 100				
Switch	Switchport	Usage	VLAN ID	Port Type	IP Adress			IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	Service FIS / CCTV	2	Access	172	17	0	248	120			
	e1-0	Überw. Kamera A7	5	Access	172	18	128	138	10	y	5.0	
	e1-1	Überw. Kamera A2	5	Access	172	18	128	139	11	y	5.0	
	e1-2	Überw. Kamera A1	5	Access	172	18	128	140	12	y	5.0	
	e1-3	Überw. Kamera A5	5	Access	172	18	128	141	13	y	5.0	
	e1-4	Überw. Kamera A9	5	Access	172	18	128	142	14	y	5.0	
	e1-5	AFZ A1	8	Access	172	20	0	133	5	y	10.0	
	e1-6	AFZ A2	8	Access	172	20	0	134	6	y	10.0	
	e1-7				-	-	-	-	-			
	e1-8	Sprechstelle A1	9	Access	172	20	128	133	5	y	7.5	
	e1-9				-	-	-	-	-			
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A5	90	Access	-	-	-	-	-			
	e1-13	Future use box A6	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A1	3	Access	172	17	128	153	25			
	e1-15	Seitenanzeige A3	3	Access	172	17	128	154	26			
	e2-0	Bildschirm A7	3	Access	172	17	128	178	50			
	e2-1	Bildschirm A5	3	Access	172	17	128	179	51			
	e2-2	Bildschirm A1	3	Access	172	17	128	180	52			
e2-3	Bildschirm A3	3	Access	172	17	128	181	53				
e2-4	ADU A	9	Access	172	20	128	131	3				
e2-5	Audio Amp. A1	9	Access	172	20	128	149	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2				-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Überw. Kamera A8	5	Access	172	18	128	143	15	y	5.0	
	e1-1	Überw. Kamera A4	5	Access	172	18	128	144	16	y	5.0	
	e1-2	Überw. Kamera A3	5	Access	172	18	128	145	17	y	5.0	
	e1-3	Überw. Kamera A6	5	Access	172	18	128	146	18	y	5.0	
	e1-4	Überw. Kamera A10	5	Access	172	18	128	147	19	y	5.0	
	e1-5	AFZ A3	8	Access	172	20	0	135	7	y	10.0	
	e1-6	AFZ A4	8	Access	172	20	0	136	8	y	10.0	
	e1-7	NVR A	5	Access	172	18	128	133	5			
	e1-8	Sprechstelle A2	9	Access	172	20	128	134	6	y	7.5	
	e1-9	Sprechstelle A1R	9	Access	172	20	128	133	5	y	7.5	Redundanz A1
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A2	90	Access	-	-	-	-	-			
	e1-13	Future use box A4	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A2	3	Access	172	17	128	155	27			
	e1-15	Seitenanzeige A4	3	Access	172	17	128	156	28			
	e2-0	Bildschirm A8	3	Access	172	17	128	182	54			
	e2-1	Bildschirm A6	3	Access	172	17	128	183	55			
	e2-2	Bildschirm A2	3	Access	172	17	128	184	56			
e2-3	Bildschirm A4	3	Access	172	17	128	185	57				
e2-4				-	-	-	-	-				
e2-5	Audio Amp. A2	9	Access	172	20	128	150	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Rücksehkamera A1	5	Access	172	18	128	208	80	y	5.0	
	e1-1	Rücksehkamera A2	5	Access	172	18	128	209	81	y	5.0	
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e1-3				-	-	-	-	-			
	e1-4	Firewall		Trunk		172	17	0	129	1		Kein DHCP Statische Konfiguration STADLER
					172	17	128	129				
					172	18	128	129				
					172	19	0	129				
					172	19	128	129				
					172	20	0	129				
					172	20	128	129				
	e1-5				172	22	0	129				
	e1-6				-	-	-	-	-			
	e1-7				-	-	-	-	-			
	e1-8				-	-	-	-	-			
	e1-9	Sprechstelle A2R	9	Access	172	20	128	134	6	y	7.5	Redundanz A2
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A1	90	Access	-	-	-	-	-			
e1-13	Future use box A3	90	Access	-	-	-	-	-				
e1-14	Frontanzeige A	3	Access	172	17	128	151	23				
e1-15				-	-	-	-	-				
e2-0				-	-	-	-	-				
e2-1				-	-	-	-	-				
e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-				
e2-4	ADU AR	9	Access	172	20	128	131	3				
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127				

G1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					7	172	19	128	130	2			
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	0	250	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	128	158	30	y	5.0		
	e1-1	Überw. Kamera D2	5	Access	172	18	128	159	31	y	5.0		
	e1-2	Überw. Kamera D1	5	Access	172	18	128	160	32	y	5.0		
	e1-3	Überw. Kamera D5	5	Access	172	18	128	161	33	y	5.0		
	e1-4	Überw. Kamera D9	5	Access	172	18	128	162	34	y	5.0		
	e1-5	AFZ D1	8	Access	172	20	0	142	14	y	10.0		
	e1-6	AFZ D2	8	Access	172	20	0	143	15	y	10.0		
	e1-7	AFZ D5	8	Access	172	20	0	144	16	y	10.0		
	e1-8	Sprechstelle D1	9	Access	172	20	128	138	10	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D1	3	Access	172	17	128	161	33				
	e1-15	Seitenanzeige D3	3	Access	172	17	128	162	34				
	e2-0	Bildschirm D7	3	Access	172	17	128	196	68				
	e2-1	Bildschirm D5	3	Access	172	17	128	197	69				
e2-2	Bildschirm D1	3	Access	172	17	128	198	70					
e2-3	Bildschirm D3	3	Access	172	17	128	199	71					
e2-4	Bildschirm D	3	Access	172	17	128	200	72					
e2-5	Audio Amp. D1	9	Access	172	20	128	153	25					
G2	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	128	163	35	y	5.0		
	e1-1	Überw. Kamera D4	5	Access	172	18	128	164	36	y	5.0		
	e1-2	Überw. Kamera D3	5	Access	172	18	128	165	37	y	5.0		
	e1-3	Überw. Kamera D6	5	Access	172	18	128	166	38	y	5.0		
	e1-4	Überw. Kamera D10	5	Access	172	18	128	167	39	y	5.0		
	e1-5	AFZ D3	8	Access	172	20	0	145	17	y	10.0		
	e1-6	AFZ D4	8	Access	172	20	0	146	18	y	10.0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	128	139	11	y	7.5		
	e1-9	Sprechstelle D1R	9	Access	172	20	128	138	10	y	7.5		Redundanz D1
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D2	3	Access	172	17	128	163	35				
	e1-15	Seitenanzeige D4	3	Access	172	17	128	164	36				
	e2-0	Bildschirm D8	3	Access	172	17	128	201	73				
	e2-1	Bildschirm D6	3	Access	172	17	128	202	74				
	e2-2	Bildschirm D2	3	Access	172	17	128	203	75				
e2-3	Bildschirm D4	3	Access	172	17	128	204	76					
e2-4	Bildschirm D11	3	Access	172	17	128	205	77					
e2-5	Audio Amp. D2	9	Access	172	20	128	154	26					
G3	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					7	172	19	128	130	2			
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	128	212	84	y	5.0		
	e1-1	Rücksehkamera D2	5	Access	172	18	128	213	85	y	5.0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle D2R	9	Access	172	20	128	139	11	y	7.5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
e2-2				-	-	-	-	-					
e2-3				-	-	-	-	-					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

[illegible]

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e0-5	Service FIS / CCTV	2	Access	172	17	0	253	125					
	e1-0	Überw. Kamera B7	5	Access	172	18	128	187	59	y	5.0			
	e1-1	Überw. Kamera B2	5	Access	172	18	128	188	60	y	5.0			
	e1-2	Überw. Kamera B1	5	Access	172	18	128	189	61	y	5.0			
	e1-3	Überw. Kamera B5	5	Access	172	18	128	190	62	y	5.0			
	e1-4	Überw. Kamera B9	5	Access	172	18	128	191	63	y	5.0			
	e1-5	AFZ B1	8	Access	172	20	0	158	30	y	10.0			
	e1-6	AFZ B2	8	Access	172	20	0	159	31	y	10.0			
	e1-7				-	-	-	-	-					
	e1-8	Sprechstelle B1	9	Access	172	20	128	147	19	y	7.5			
	e1-9				-	-	-	-	-					
	e1-10				-	-	-	-	-					
	e1-11	ZFR R	2	Access	172	17	0	130	2					
	e1-12	Future use box B5	90	Access	-	-	-	-	-					
	e1-13	Future use box B6	90	Access	-	-	-	-	-					
	e1-14	Seitenanzeige B1	3	Access	172	17	128	173	45					
	e1-15	Seitenanzeige B3	3	Access	172	17	128	174	46					
	e2-0	Bildschrim B7	3	Access	172	17	128	226	98					
	e2-1	Bildschrim B5	3	Access	172	17	128	227	99					
	e2-2	Bildschrim B1	3	Access	172	17	128	228	100					
	e2-3	Bildschrim B3	3	Access	172	17	128	229	101					
	e2-4	ADU B	9	Access	172	20	128	132	4					
	e2-5	Audio Amp. B1	9	Access	172	20	128	159	31					
	B2	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
		e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
e0-2					-	-	-	-	-					
e0-3					-	-	-	-	-					
e0-4		Access point B2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
e0-5		reserved			-	-	-	-	-					
e1-0		Überw. Kamera B8	5	Access	172	18	128	192	64	y	5.0			
e1-1		Überw. Kamera B4	5	Access	172	18	128	193	65	y	5.0			
e1-2		Überw. Kamera B3	5	Access	172	18	128	194	66	y	5.0			
e1-3		Überw. Kamera B6	5	Access	172	18	128	195	67	y	5.0			
e1-4		Überw. Kamera B10	5	Access	172	18	128	196	68	y	5.0			
e1-5		AFZ B3	8	Access	172	20	0	160	32	y	10.0			
e1-6		AFZ B4	8	Access	172	20	0	161	33	y	10.0			
e1-7		NVR B	5	Access	172	18	128	134	6					
e1-8		Sprechstelle B2	9	Access	172	20	128	148	20	y	7.5			
e1-9		Sprechstelle B1R	9	Access	172	20	128	147	19	y	7.5			
e1-10					-	-	-	-	-					
e1-11					-	-	-	-	-					
e1-12		Future use box B2	90	Access	-	-	-	-	-					
e1-13		Future use box B4	90	Access	-	-	-	-	-					
e1-14		Seitenanzeige B2	3	Access	172	17	128	175	47					
e1-15		Seitenanzeige B4	3	Access	172	17	128	176	48					
e2-0		Bildschrim B8	3	Access	172	17	128	230	102					
e2-1		Bildschrim B6	3	Access	172	17	128	231	103					
e2-2		Bildschrim B2	3	Access	172	17	128	232	104					
e2-3		Bildschrim B4	3	Access	172	17	128	233	105					
e2-4					-	-	-	-	-					
e2-5		Audio Amp. B2	9	Access	172	20	128	160	32					
B3		e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
		e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point B3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera B1	5	Access	172	18	128	218	90	y	5.0			
	e1-1	Rücksehkamera B2	5	Access	172	18	128	219	91	y	5.0			
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e1-3				-	-	-	-	-					
	e1-4				-	-	-	-	-					
	e1-5				-	-	-	-	-					
	e1-6				-	-	-	-	-					
	e1-7				-	-	-	-	-					
	e1-8				-	-	-	-	-					
	e1-9	Sprechstelle B2R	9	Access	172	20	128	148	20	y	7.5		Redundanz B2	
	e1-10				-	-	-	-	-					
	e1-11	ZFR	2	Access	172	17	0	130	2					
	e1-12	Future use box B1	90	Access	-	-	-	-	-					
	e1-13	Future use box B3	90	Access	-	-	-	-	-					
	e1-14	Frontanzeige B	3	Access	172	17	128	152	24					
	e1-15				-	-	-	-	-					
	e2-0				-	-	-	-	-					
	e2-1				-	-	-	-	-					
	e2-2				-	-	-	-	-					
	e2-3				-	-	-	-	-					
	e2-4	ADU BR	9	Access	172	20	128	132	4					
	e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127					
	Firewall		2	N/A	172	17	0	254	126				IP festgehalten fuer die RCU.	
			3	N/A	172	17	128	254	126				Diese ist mit der Firewall verbunden.	
		9	N/A	172	20	128	254	126				Anforderung von STADLER		