

IPv4-Schema
Fgz. Nr: 4734 - 109



Fahrzeugnummer: 4734-109				Fzg. ID: 9				Wagen: A - 100				
Switch	Switchport	Usage	VLAN ID	Port Type	IP Adress			IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	Service FIS / CCTV	2	Access	172	17	4	248	120			
	e1-0	Überw. Kamera A7	5	Access	172	18	132	138	10	y	5.0	
	e1-1	Überw. Kamera A2	5	Access	172	18	132	139	11	y	5.0	
	e1-2	Überw. Kamera A1	5	Access	172	18	132	140	12	y	5.0	
	e1-3	Überw. Kamera A5	5	Access	172	18	132	141	13	y	5.0	
	e1-4	Überw. Kamera A9	5	Access	172	18	132	142	14	y	5.0	
	e1-5	AFZ A1	8	Access	172	20	4	133	5	y	10.0	
	e1-6	AFZ A2	8	Access	172	20	4	134	6	y	10.0	
	e1-7				-	-	-	-	-			
	e1-8	Sprechstelle A1	9	Access	172	20	132	133	5	y	7.5	
	e1-9				-	-	-	-	-			
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A5	90	Access	-	-	-	-	-			
	e1-13	Future use box A6	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A1	3	Access	172	17	132	153	25			
	e1-15	Seitenanzeige A3	3	Access	172	17	132	154	26			
	e2-0	Bildschirm A7	3	Access	172	17	132	178	50			
	e2-1	Bildschirm A5	3	Access	172	17	132	179	51			
	e2-2	Bildschirm A1	3	Access	172	17	132	180	52			
e2-3	Bildschirm A3	3	Access	172	17	132	181	53				
e2-4	ADU A	9	Access	172	20	132	131	3				
e2-5	Audio Amp. A1	9	Access	172	20	132	149	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2				-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Überw. Kamera A8	5	Access	172	18	132	143	15	y	5.0	
	e1-1	Überw. Kamera A4	5	Access	172	18	132	144	16	y	5.0	
	e1-2	Überw. Kamera A3	5	Access	172	18	132	145	17	y	5.0	
	e1-3	Überw. Kamera A6	5	Access	172	18	132	146	18	y	5.0	
	e1-4	Überw. Kamera A10	5	Access	172	18	132	147	19	y	5.0	
	e1-5	AFZ A3	8	Access	172	20	4	135	7	y	10.0	
	e1-6	AFZ A4	8	Access	172	20	4	136	8	y	10.0	
	e1-7	NVR A	5	Access	172	18	132	133	5			
	e1-8	Sprechstelle A2	9	Access	172	20	132	134	6	y	7.5	
	e1-9	Sprechstelle A1R	9	Access	172	20	132	133	5	y	7.5	Redundanz A1
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A2	90	Access	-	-	-	-	-			
	e1-13	Future use box A4	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A2	3	Access	172	17	132	155	27			
	e1-15	Seitenanzeige A4	3	Access	172	17	132	156	28			
	e2-0	Bildschirm A8	3	Access	172	17	132	182	54			
	e2-1	Bildschirm A6	3	Access	172	17	132	183	55			
	e2-2	Bildschirm A2	3	Access	172	17	132	184	56			
e2-3	Bildschirm A4	3	Access	172	17	132	185	57				
e2-4				-	-	-	-	-				
e2-5	Audio Amp. A2	9	Access	172	20	132	150	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Rücksehkamera A1	5	Access	172	18	132	208	80	y	5.0	
	e1-1	Rücksehkamera A2	5	Access	172	18	132	209	81	y	5.0	
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e1-3				-	-	-	-	-			
	e1-4	Firewall	2 3 5 6 7 8 9 12	Trunk	172 172 172 172 172 172 172 172	17 17 18 19 19 20 20 22	4 132 132 4 129 4 129 4	129 129 129 129 129 129 129 129	1			Kein DHCP Statische Konfiguration STADLER
	e1-5				-	-	-	-	-			
	e1-6				-	-	-	-	-			
	e1-7				-	-	-	-	-			
	e1-8				-	-	-	-	-			
	e1-9	Sprechstelle A2R	9	Access	172	20	132	134	6	y	7.5	Redundanz A2
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A1	90	Access	-	-	-	-	-			
	e1-13	Future use box A3	90	Access	-	-	-	-	-			
	e1-14	Frontanzeige A	3	Access	172	17	132	151	23			
	e1-15				-	-	-	-	-			
	e2-0				-	-	-	-	-			
	e2-1				-	-	-	-	-			
	e2-2				-	-	-	-	-			
e2-3				-	-	-	-	-				
e2-4	ADU AR	9	Access	172	20	132	131	3				
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127				

IPv4-Schema
Fgz. Nr: 4734 - 109



G1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					172	19	132	130	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	4	250	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	132	158	30	y	5.0		
	e1-1	Überw. Kamera D2	5	Access	172	18	132	159	31	y	5.0		
	e1-2	Überw. Kamera D1	5	Access	172	18	132	160	32	y	5.0		
	e1-3	Überw. Kamera D5	5	Access	172	18	132	161	33	y	5.0		
	e1-4	Überw. Kamera D9	5	Access	172	18	132	162	34	y	5.0		
	e1-5	AFZ D1	8	Access	172	20	4	142	14	y	10.0		
	e1-6	AFZ D2	8	Access	172	20	4	143	15	y	10.0		
	e1-7	AFZ D5	8	Access	172	20	4	144	16	y	10.0		
	e1-8	Sprechstelle D1	9	Access	172	20	132	138	10	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D1	3	Access	172	17	132	161	33				
	e1-15	Seitenanzeige D3	3	Access	172	17	132	162	34				
G2	e2-0	Bildschirm D7	3	Access	172	17	132	196	68				
	e2-1	Bildschirm D5	3	Access	172	17	132	197	69				
	e2-2	Bildschirm D1	3	Access	172	17	132	198	70				
	e2-3	Bildschirm D3	3	Access	172	17	132	199	71				
	e2-4	Bildschirm D	3	Access	172	17	132	200	72				
	e2-5	Audio Amp. D1	9	Access	172	20	132	153	25				
	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	132	163	35	y	5.0		
	e1-1	Überw. Kamera D4	5	Access	172	18	132	164	36	y	5.0		
	e1-2	Überw. Kamera D3	5	Access	172	18	132	165	37	y	5.0		
	e1-3	Überw. Kamera D6	5	Access	172	18	132	166	38	y	5.0		
	e1-4	Überw. Kamera D10	5	Access	172	18	132	167	39	y	5.0		
	e1-5	AFZ D3	8	Access	172	20	4	145	17	y	10.0		
	e1-6	AFZ D4	8	Access	172	20	4	146	18	y	10.0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	132	139	11	y	7.5		
	e1-9	Sprechstelle D1R	9	Access	172	20	132	138	10	y	7.5		Redundanz D1
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
G3	e1-14	Seitenanzeige D2	3	Access	172	17	132	163	35				
	e1-15	Seitenanzeige D4	3	Access	172	17	132	164	36				
	e2-0	Bildschirm D8	3	Access	172	17	132	201	73				
	e2-1	Bildschirm D6	3	Access	172	17	132	202	74				
	e2-2	Bildschirm D2	3	Access	172	17	132	203	75				
	e2-3	Bildschirm D4	3	Access	172	17	132	204	76				
	e2-4	Bildschirm D11	3	Access	172	17	132	205	77				
	e2-5	Audio Amp. D2	9	Access	172	20	132	154	26				
	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					172	19	132	130	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	132	212	84	y	5.0		
	e1-1	Rücksehkamera D2	5	Access	172	18	132	213	85	y	5.0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle D2R	9	Access	172	20	132	139	11	y	7.5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
	e2-3				-	-	-	-	-				
	e2-4				-	-	-	-	-				
	e2-5				-	-	-	-	-				

E1	e0-0	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e0-5	Service FIS / CCTV	2	Access	172	17	4	251	123					
	e1-0	Überw. Kamera E7	5	Access	172	18	132	168	40	y	5.0			
	e1-1	Überw. Kamera E2	5	Access	172	18	132	169	41	y	5.0			
	e1-2	Überw. Kamera E1	5	Access	172	18	132	170	42	y	5.0			
	e1-3	Überw. Kamera E5	5	Access	172	18	132	171	43	y	5.0			
	e1-4	Überw. Kamera E9	5	Access	172	18	132	172	44	y	5.0			
	e1-5	AFZ E1	8	Access	172	20	4	147	19	y	10.0			
	e1-6	AFZ E2	8	Access	172	20	4	148	20	y	10.0			
	e1-7	AFZ E5	8	Access	172	20	4	149	21	y	10.0			
	e1-8	Sprechstelle E1	9	Access	172	20	132	140	12	y	7.5			
	e1-9					-	-	-	-					
	e1-10	Sprechstelle PRM E1	9	Access	172	20	132	141	13	y	7.5			
	e1-11	Sprechstelle PRM WCR	9	Access	172	20	132	144	16	y	7.5		Redundanz WC	
	e1-12	Future use box E5	90	Access	-	-	-	-	-					
	e1-13	Future use box E7	90	Access	-	-	-	-	-					
	e1-14	Seitenanzeige E1	3	Access	172	17	132	165	37					
	e1-15	Seitenanzeige E3	3	Access	172	17	132	166	38					
	E2	e2-0	Bildschirm E7	3	Access	172	17	132	206	78				
		e2-1	Bildschirm E5	3	Access	172	17	132	207	79				
		e2-2	Bildschirm E1	3	Access	172	17	132	208	80				
e2-3		Bildschirm E3	3	Access	172	17	132	209	81					
e2-4		Bildschirm E	3	Access	172	17	132	210	82					
e2-5		Audio Amp. E1	9	Access	172	20	132	155	27					
e0-0		FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-					
e0-1		FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-					
e0-2					-	-	-	-	-					
e0-3					-	-	-	-	-					
e0-4		Access point E2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
e0-5		reserved			-	-	-	-	-					
e1-0		Überw. Kamera E8	5	Access	172	18	132	173	45	y	5.0			
e1-1		Überw. Kamera E4	5	Access	172	18	132	174	46	y	5.0			
e1-2		Überw. Kamera E3	5	Access	172	18	132	175	47	y	5.0			
e1-3		Überw. Kamera E6	5	Access	172	18	132	176	48	y	5.0			
e1-4					-	-	-	-	-					
e1-5		AFZ E3	8	Access	172	20	4	150	22	y	10.0			
e1-6		AFZ E4	8	Access	172	20	4	151	23	y	10.0			
e1-7		AFZ E6	8	Access	172	20	4	152	24	y	10.0			
e1-8		Sprechstelle E2	9	Access	172	20	132	142	14	y	7.5			
e1-9		Sprechstelle E1R	9	Access	172	20	132	140	12	y	7.5		Redundanz E1	
e1-10		Sprechstelle PRM E2	9	Access	172	20	132	143	15	y	7.5			
e1-11		Sprechstelle PRM E1R	9	Access	172	20	132	141	13	y	7.5		Redundanz E1	
e1-12		Future use box E2	90	Access	-	-	-	-	-					
e1-13	Future use box E4	90	Access	-	-	-	-	-						
e1-14	Seitenanzeige E2	3	Access	172	17	132	167	39						
e1-15	Seitenanzeige E4	3	Access	172	17	132	168	40						
E3	e2-0	Bildschirm E8	3	Access	172	17	132	211	83					
	e2-1	Bildschirm E6	3	Access	172	17	132	212	84					
	e2-2	Bildschirm E2	3	Access	172	17	132	213	85					
	e2-3	Bildschirm E4	3	Access	172	17	132	214	86					
	e2-4	Bildschirm E11	3	Access	172	17	132	215	87					
	e2-5	Audio Amp. E2	9	Access	172	20	132	156	28					
	e0-0	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-					
	e0-2				-	-	-	-	-					
	e0-3				-	-	-	-	-					
	e0-4	Access point E3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e0-5	reserved			-	-	-	-	-					
	e1-0	Rücksehkamera E1	5	Access	172	18	132	214	86	y	5.0			
	e1-1	Rücksehkamera E2	5	Access	172	18	132	215	87	y	5.0			
	e1-2	Access point E4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0			
	e1-3				-	-	-	-	-					
	e1-4				-	-	-	-	-					
	e1-5				-	-	-	-	-					
	e1-6				-	-	-	-	-					
	e1-7				-	-	-	-	-					
	e1-8				-	-	-	-	-					
	e1-9	Sprechstelle E2R	9	Access	172	20	132	142	14	y	7.5		Redundanz E2	
	e1-10	Sprechstelle PRM WC	9	Access	172	20	132	144	16	y	7.5			
	e1-11	Sprechstelle PRM E2R	9	Access	172	20	132	143	15	y	7.5		Redundanz E2	
	e1-12	Future use box E1	90	Access	-	-	-	-	-					
e1-13	Future use box E3	90	Access	-	-	-	-	-						
e1-14				-	-	-	-	-						
e1-15				-	-	-	-	-						
e2-0	Energiezähler E	12	Access	172	22	4	131	3						
e2-1				-	-	-	-	-						
e2-2				-	-	-	-	-						
e2-3				-	-	-	-	-						
e2-4				-	-	-	-	-						
e2-5				-	-	-	-	-						

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	4	253	125				
	e1-0	Überw. Kamera B7	5	Access	172	18	132	187	59	y	5.0		
	e1-1	Überw. Kamera B2	5	Access	172	18	132	188	60	y	5.0		
	e1-2	Überw. Kamera B1	5	Access	172	18	132	189	61	y	5.0		
	e1-3	Überw. Kamera B5	5	Access	172	18	132	190	62	y	5.0		
	e1-4	Überw. Kamera B9	5	Access	172	18	132	191	63	y	5.0		
	e1-5	AFZ B1	8	Access	172	20	4	158	30	y	10.0		
	e1-6	AFZ B2	8	Access	172	20	4	159	31	y	10.0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle B1	9	Access	172	20	132	147	19	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11	ZFR R	2	Access	172	17	4	130	2				
	e1-12	Future use box B5	90	Access	-	-	-	-	-				
	e1-13	Future use box B6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B1	3	Access	172	17	132	173	45				
	e1-15	Seitenanzeige B3	3	Access	172	17	132	174	46				
	e2-0	Bildschrim B7	3	Access	172	17	132	226	98				
	e2-1	Bildschrim B5	3	Access	172	17	132	227	99				
	e2-2	Bildschrim B1	3	Access	172	17	132	228	100				
	e2-3	Bildschrim B3	3	Access	172	17	132	229	101				
	e2-4	ADU B	9	Access	172	20	132	132	4				
e2-5	Audio Amp. B1	9	Access	172	20	132	159	31					
B2	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera B8	5	Access	172	18	132	192	64	y	5.0		
	e1-1	Überw. Kamera B4	5	Access	172	18	132	193	65	y	5.0		
	e1-2	Überw. Kamera B3	5	Access	172	18	132	194	66	y	5.0		
	e1-3	Überw. Kamera B6	5	Access	172	18	132	195	67	y	5.0		
	e1-4	Überw. Kamera B10	5	Access	172	18	132	196	68	y	5.0		
	e1-5	AFZ B3	8	Access	172	20	4	160	32	y	10.0		
	e1-6	AFZ B4	8	Access	172	20	4	161	33	y	10.0		
	e1-7	NVR B	5	Access	172	18	132	134	6				
	e1-8	Sprechstelle B2	9	Access	172	20	132	148	20	y	7.5		
	e1-9	Sprechstelle B1R	9	Access	172	20	132	147	19	y	7.5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box B2	90	Access	-	-	-	-	-				
	e1-13	Future use box B4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B2	3	Access	172	17	132	175	47				
	e1-15	Seitenanzeige B4	3	Access	172	17	132	176	48				
	e2-0	Bildschrim B8	3	Access	172	17	132	230	102				
	e2-1	Bildschrim B6	3	Access	172	17	132	231	103				
	e2-2	Bildschrim B2	3	Access	172	17	132	232	104				
	e2-3	Bildschrim B4	3	Access	172	17	132	233	105				
	e2-4				-	-	-	-	-				
e2-5	Audio Amp. B2	9	Access	172	20	132	160	32					
B3	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera B1	5	Access	172	18	132	218	90	y	5.0		
	e1-1	Rücksehkamera B2	5	Access	172	18	132	219	91	y	5.0		
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle B2R	9	Access	172	20	132	148	20	y	7.5		Redundanz B2
	e1-10				-	-	-	-	-				
	e1-11	ZFR	2	Access	172	17	4	130	2				
	e1-12	Future use box B1	90	Access	-	-	-	-	-				
	e1-13	Future use box B3	90	Access	-	-	-	-	-				
	e1-14	Frontanzeige B	3	Access	172	17	132	152	24				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
	e2-3				-	-	-	-	-				
	e2-4	ADU BR	9	Access	172	20	132	132	4				
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127					
Firewall		2	N/A	172	17	4	254	126				IP festgehalten fuer die RCU.	
		3	N/A	172	17	132	254	126				Diese ist mit der Firewall verbunden.	
		9	N/A	172	20	132	254	126				Anforderung von STADLER	