

Fahrzeugnummer: 4734-110				Fzg. ID: 10				Wagen: A - 100				
Switch	Switchport	Usage	VLAN ID	Port Type	IP Address			IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	Service FIS / CCTV	2	Access	172	17	5	120	120			
	e1-0	Überw. Kamera A7	5	Access	172	18	133	10	10	y	5.0	
	e1-1	Überw. Kamera A2	5	Access	172	18	133	11	11	y	5.0	
	e1-2	Überw. Kamera A1	5	Access	172	18	133	12	12	y	5.0	
	e1-3	Überw. Kamera A5	5	Access	172	18	133	13	13	y	5.0	
	e1-4	Überw. Kamera A9	5	Access	172	18	133	14	14	y	5.0	
	e1-5	AFZ A1	8	Access	172	20	5	5	5	y	10.0	
	e1-6	AFZ A2	8	Access	172	20	5	6	6	y	10.0	
	e1-7				-	-	-	-	-			
	e1-8	Sprechstelle A1	9	Access	172	20	133	5	5	y	7.5	
	e1-9				-	-	-	-	-			
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A5	90	Access	-	-	-	-	-			
	e1-13	Future use box A6	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A1	3	Access	172	17	133	25	25			
	e1-15	Seitenanzeige A3	3	Access	172	17	133	26	26			
	e2-0	Bildschirm A7	3	Access	172	17	133	50	50			
	e2-1	Bildschirm A5	3	Access	172	17	133	51	51			
	e2-2	Bildschirm A1	3	Access	172	17	133	52	52			
	e2-3	Bildschirm A3	3	Access	172	17	133	53	53			
e2-4	ADU A	9	Access	172	20	133	3	3				
e2-5	Audio Amp. A1	9	Access	172	20	133	21	21				
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2				-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Überw. Kamera A8	5	Access	172	18	133	15	15	y	5.0	
	e1-1	Überw. Kamera A4	5	Access	172	18	133	16	16	y	5.0	
	e1-2	Überw. Kamera A3	5	Access	172	18	133	17	17	y	5.0	
	e1-3	Überw. Kamera A6	5	Access	172	18	133	18	18	y	5.0	
	e1-4	Überw. Kamera A10	5	Access	172	18	133	19	19	y	5.0	
	e1-5	AFZ A3	8	Access	172	20	5	7	7	y	10.0	
	e1-6	AFZ A4	8	Access	172	20	5	8	8	y	10.0	
	e1-7	NVR A	5	Access	172	18	133	5	5			
	e1-8	Sprechstelle A2	9	Access	172	20	133	6	6	y	7.5	
	e1-9	Sprechstelle AIR	9	Access	172	20	133	5	5	y	7.5	Redundanz A1
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A2	90	Access	-	-	-	-	-			
	e1-13	Future use box A4	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A2	3	Access	172	17	133	27	27			
	e1-15	Seitenanzeige A4	3	Access	172	17	133	28	28			
	e2-0	Bildschirm A8	3	Access	172	17	133	54	54			
	e2-1	Bildschirm A6	3	Access	172	17	133	55	55			
	e2-2	Bildschirm A2	3	Access	172	17	133	56	56			
	e2-3	Bildschirm A4	3	Access	172	17	133	57	57			
e2-4				-	-	-	-	-				
e2-5	Audio Amp. A2	9	Access	172	20	133	22	22				
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Rücksehkamera A1	5	Access	172	18	133	80	80	y	5.0	
	e1-1	Rücksehkamera A2	5	Access	172	18	133	81	81	y	5.0	
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0	
	e1-3				-	-	-	-	-			
	e1-4	Firewall	2	Trunk	172	17	5	1	1			Kein DHCP Statische Konfiguration STADLER
			3		172	17	133	1				
			5		172	18	133	1				
			6		172	19	5	1				
			7		172	19	133	1				
			8		172	20	5	1				
			9		172	20	133	1				
		12	172	22	5	1						
	e1-5				-	-	-	-	-			
	e1-6				-	-	-	-	-			
	e1-7				-	-	-	-	-			
	e1-8				-	-	-	-	-			
	e1-9	Sprechstelle A2R	9	Access	172	20	133	6	6	y	7.5	Redundanz A2
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A1	90	Access	-	-	-	-	-			
e1-13	Future use box A3	90	Access	-	-	-	-	-				
e1-14	Frontanzeige A	3	Access	172	17	133	23	23				
e1-15				-	-	-	-	-				
e2-0				-	-	-	-	-				
e2-1				-	-	-	-	-				
e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-				
e2-4	ADU AR	9	Access	172	20	133	3	3				
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127				

G1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					7	172	19	133	2	2			
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	5	122	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	133	30	30	y	5.0		
	e1-1	Überw. Kamera D2	5	Access	172	18	133	31	31	y	5.0		
	e1-2	Überw. Kamera D1	5	Access	172	18	133	32	32	y	5.0		
	e1-3	Überw. Kamera D5	5	Access	172	18	133	33	33	y	5.0		
	e1-4	Überw. Kamera D9	5	Access	172	18	133	34	34	y	5.0		
	e1-5	AFZ D1	8	Access	172	20	5	14	14	y	10.0		
	e1-6	AFZ D2	8	Access	172	20	5	15	15	y	10.0		
	e1-7	AFZ D5	8	Access	172	20	5	16	16	y	10.0		
	e1-8	Sprechstelle D1	9	Access	172	20	133	10	10	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D1	3	Access	172	17	133	33	33				
	e1-15	Seitenanzeige D3	3	Access	172	17	133	34	34				
	e2-0	Bildschirm D7	3	Access	172	17	133	68	68				
	e2-1	Bildschirm D5	3	Access	172	17	133	69	69				
	e2-2	Bildschirm D1	3	Access	172	17	133	70	70				
e2-3	Bildschirm D3	3	Access	172	17	133	71	71					
e2-4	Bildschirm D	3	Access	172	17	133	72	72					
e2-5	Audio Amp. D1	9	Access	172	20	133	25	25					
G2	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	133	35	35	y	5.0		
	e1-1	Überw. Kamera D4	5	Access	172	18	133	36	36	y	5.0		
	e1-2	Überw. Kamera D3	5	Access	172	18	133	37	37	y	5.0		
	e1-3	Überw. Kamera D6	5	Access	172	18	133	38	38	y	5.0		
	e1-4	Überw. Kamera D10	5	Access	172	18	133	39	39	y	5.0		
	e1-5	AFZ D3	8	Access	172	20	5	17	17	y	10.0		
	e1-6	AFZ D4	8	Access	172	20	5	18	18	y	10.0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	133	11	11	y	7.5		
	e1-9	Sprechstelle D1R	9	Access	172	20	133	10	10	y	7.5		Redundanz D1
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D2	3	Access	172	17	133	35	35				
	e1-15	Seitenanzeige D4	3	Access	172	17	133	36	36				
	e2-0	Bildschirm D8	3	Access	172	17	133	73	73				
	e2-1	Bildschirm D6	3	Access	172	17	133	74	74				
	e2-2	Bildschirm D2	3	Access	172	17	133	75	75				
	e2-3	Bildschirm D4	3	Access	172	17	133	76	76				
e2-4	Bildschirm D11	3	Access	172	17	133	77	77					
e2-5	Audio Amp. D2	9	Access	172	20	133	26	26					
G3	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202	Trunk	-	-	-	-	-				
					7	172	19	133	2	2			
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	133	84	84	y	5.0		
	e1-1	Rücksehkamera D2	5	Access	172	18	133	85	85	y	5.0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle D2R	9	Access	172	20	133	11	11	y	7.5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

E1	e0-0	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point E1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	5	123	123				
	e1-0	Überw. Kamera E7	5	Access	172	18	133	40	40	y	5.0		
	e1-1	Überw. Kamera E2	5	Access	172	18	133	41	41	y	5.0		
	e1-2	Überw. Kamera E1	5	Access	172	18	133	42	42	y	5.0		
	e1-3	Überw. Kamera E5	5	Access	172	18	133	43	43	y	5.0		
	e1-4	Überw. Kamera E9	5	Access	172	18	133	44	44	y	5.0		
	e1-5	AFZ E1	8	Access	172	20	5	19	19	y	10.0		
	e1-6	AFZ E2	8	Access	172	20	5	20	20	y	10.0		
	e1-7	AFZ E5	8	Access	172	20	5	21	21	y	10.0		
	e1-8	Sprechstelle E1	9	Access	172	20	133	12	12	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10	Sprechstelle PRM E1	9	Access	172	20	133	13	13	y	7.5		
	e1-11	Sprechstelle PRM WCR	9	Access	172	20	133	16	16	y	7.5		Redundanz WC
	e1-12	Future use box E5	90	Access	-	-	-	-	-				
	e1-13	Future use box E7	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige E1	3	Access	172	17	133	37	37				
	e1-15	Seitenanzeige E3	3	Access	172	17	133	38	38				
	e2-0	Bildschirm E7	3	Access	172	17	133	78	78				
	e2-1	Bildschirm E5	3	Access	172	17	133	79	79				
	e2-2	Bildschirm E1	3	Access	172	17	133	80	80				
e2-3	Bildschirm E3	3	Access	172	17	133	81	81					
e2-4	Bildschirm E	3	Access	172	17	133	82	82					
e2-5	Audio Amp. E1	9	Access	172	20	133	27	27					
E2	e0-0	FIS Switch E3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point E2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera E8	5	Access	172	18	133	45	45	y	5.0		
	e1-1	Überw. Kamera E4	5	Access	172	18	133	46	46	y	5.0		
	e1-2	Überw. Kamera E3	5	Access	172	18	133	47	47	y	5.0		
	e1-3	Überw. Kamera E6	5	Access	172	18	133	48	48	y	5.0		
	e1-4				-	-	-	-	-				
	e1-5	AFZ E3	8	Access	172	20	5	22	22	y	10.0		
	e1-6	AFZ E4	8	Access	172	20	5	23	23	y	10.0		
	e1-7	AFZ E6	8	Access	172	20	5	24	24	y	10.0		
	e1-8	Sprechstelle E2	9	Access	172	20	133	14	14	y	7.5		
	e1-9	Sprechstelle E1R	9	Access	172	20	133	12	12	y	7.5		Redundanz E1
	e1-10	Sprechstelle PRM E2	9	Access	172	20	133	15	15	y	7.5		
	e1-11	Sprechstelle PRM E1R	9	Access	172	20	133	13	13	y	7.5		Redundanz E1
	e1-12	Future use box E2	90	Access	-	-	-	-	-				
	e1-13	Future use box E4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige E2	3	Access	172	17	133	39	39				
	e1-15	Seitenanzeige E4	3	Access	172	17	133	40	40				
	e2-0	Bildschirm E8	3	Access	172	17	133	83	83				
	e2-1	Bildschirm E6	3	Access	172	17	133	84	84				
	e2-2	Bildschirm E2	3	Access	172	17	133	85	85				
e2-3	Bildschirm E4	3	Access	172	17	133	86	86					
e2-4	Bildschirm E11	3	Access	172	17	133	87	87					
e2-5	Audio Amp. E2	9	Access	172	20	133	28	28					
E3	e0-0	FIS Switch F2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point E3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera E1	5	Access	172	18	133	86	86	y	5.0		
	e1-1	Rücksehkamera E2	5	Access	172	18	133	87	87	y	5.0		
	e1-2	Access point E4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle E2R	9	Access	172	20	133	14	14	y	7.5		Redundanz E2
	e1-10	Sprechstelle PRM WC	9	Access	172	20	133	16	16	y	7.5		
	e1-11	Sprechstelle PRM E2R	9	Access	172	20	133	15	15	y	7.5		Redundanz E2
	e1-12	Future use box E1	90	Access	-	-	-	-	-				
	e1-13	Future use box E3	90	Access	-	-	-	-	-				
	e1-14				-	-	-	-	-				
	e1-15				-	-	-	-	-				
	e2-0	Energiezähler E	12	Access	172	22	5	3	3				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	Service FIS / CCTV	2	Access	172	17	5	125	125				
	e1-0	Überw. Kamera B7	5	Access	172	18	133	59	59	y	5.0		
	e1-1	Überw. Kamera B2	5	Access	172	18	133	60	60	y	5.0		
	e1-2	Überw. Kamera B1	5	Access	172	18	133	61	61	y	5.0		
	e1-3	Überw. Kamera B5	5	Access	172	18	133	62	62	y	5.0		
	e1-4	Überw. Kamera B9	5	Access	172	18	133	63	63	y	5.0		
	e1-5	AFZ B1	8	Access	172	20	5	30	30	y	10.0		
	e1-6	AFZ B2	8	Access	172	20	5	31	31	y	10.0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle B1	9	Access	172	20	133	19	19	y	7.5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11	ZFR R	2	Access	172	17	5	2	2				
	e1-12	Future use box B5	90	Access	-	-	-	-	-				
	e1-13	Future use box B6	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B1	3	Access	172	17	133	45	45				
	e1-15	Seitenanzeige B3	3	Access	172	17	133	46	46				
	e2-0	Bildschirm B7	3	Access	172	17	133	98	98				
	e2-1	Bildschirm B5	3	Access	172	17	133	99	99				
	e2-2	Bildschirm B1	3	Access	172	17	133	100	100				
e2-3	Bildschirm B3	3	Access	172	17	133	101	101					
e2-4	ADU B	9	Access	172	20	133	4	4					
e2-5	Audio Amp. B1	9	Access	172	20	133	31	31					
B2	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2				-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera B8	5	Access	172	18	133	64	64	y	5.0		
	e1-1	Überw. Kamera B4	5	Access	172	18	133	65	65	y	5.0		
	e1-2	Überw. Kamera B3	5	Access	172	18	133	66	66	y	5.0		
	e1-3	Überw. Kamera B6	5	Access	172	18	133	67	67	y	5.0		
	e1-4	Überw. Kamera B10	5	Access	172	18	133	68	68	y	5.0		
	e1-5	AFZ B3	8	Access	172	20	5	32	32	y	10.0		
	e1-6	AFZ B4	8	Access	172	20	5	33	33	y	10.0		
	e1-7	NVR B	5	Access	172	18	133	6	6				
	e1-8	Sprechstelle B2	9	Access	172	20	133	20	20	y	7.5		
	e1-9	Sprechstelle B1R	9	Access	172	20	133	19	19	y	7.5		
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box B2	90	Access	-	-	-	-	-				
	e1-13	Future use box B4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige B2	3	Access	172	17	133	47	47				
	e1-15	Seitenanzeige B4	3	Access	172	17	133	48	48				
	e2-0	Bildschirm B8	3	Access	172	17	133	102	102				
	e2-1	Bildschirm B6	3	Access	172	17	133	103	103				
	e2-2	Bildschirm B2	3	Access	172	17	133	104	104				
e2-3	Bildschirm B4	3	Access	172	17	133	105	105					
e2-4				-	-	-	-	-					
e2-5	Audio Amp. B2	9	Access	172	20	133	32	32					
B3	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-				
	e0-3				-	-	-	-	-				
	e0-4	Access point B3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera B1	5	Access	172	18	133	90	90	y	5.0		
	e1-1	Rücksehkamera B2	5	Access	172	18	133	91	91	y	5.0		
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18.0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle B2R	9	Access	172	20	133	20	20	y	7.5		Redundanz B2
	e1-10				-	-	-	-	-				
	e1-11	ZFR	2	Access	172	17	5	2	2				
	e1-12	Future use box B1	90	Access	-	-	-	-	-				
	e1-13	Future use box B3	90	Access	-	-	-	-	-				
	e1-14	Frontanzeige B	3	Access	172	17	133	24	24				
	e1-15				-	-	-	-	-				
	e2-0				-	-	-	-	-				
	e2-1				-	-	-	-	-				
	e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-					
e2-4	ADU BR	9	Access	172	20	133	4	4					
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127					
Firewall		RCU	2	N/A	172	17	5	126	126				IP festgehalten fuer die RCU.
			3	N/A	172	17	133	126	126				Diese ist mit der Firewall verbunden.
			9	N/A	172	20	133	126	126				Anforderung von STADT ER