

Fahrzeugnummer: 4734-117				Fzg. ID: 17				Wagen: A - 100				
Switch	Switchport	Usage	VLAN ID	Port Type	IP Address			IPID	PoE	[W]	Beschriftung TS	Comment
A1	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	Service FIS / CCTV	2	Access	172	17	8	248	120			
	e1-0	Überw. Kamera A7	5	Access	172	18	136	138	10	y	5,0	
	e1-1	Überw. Kamera A2	5	Access	172	18	136	139	11	y	5,0	
	e1-2	Überw. Kamera A1	5	Access	172	18	136	140	12	y	5,0	
	e1-3	Überw. Kamera A5	5	Access	172	18	136	141	13	y	5,0	
	e1-4	Überw. Kamera A9	5	Access	172	18	136	142	14	y	5,0	
	e1-5	AFZ A1	8	Access	172	20	8	133	5	y	10,0	
	e1-6	AFZ A2	8	Access	172	20	8	134	6	y	10,0	
	e1-7				-	-	-	-	-			
	e1-8	Sprechstelle A1	9	Access	172	20	136	133	5	y	7,5	
	e1-9				-	-	-	-	-			
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A5	90	Access	-	-	-	-	-			
	e1-13	Future use box A6	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A1	3	Access	172	17	136	153	25			
	e1-15	Seitenanzeige A3	3	Access	172	17	136	154	26			
	e2-0	Bildschirm A7	3	Access	172	17	136	178	50			
	e2-1	Bildschirm A5	3	Access	172	17	136	179	51			
	e2-2	Bildschirm A1	3	Access	172	17	136	180	52			
	e2-3	Bildschirm A3	3	Access	172	17	136	181	53			
	e2-4	ADU A	9	Access	172	20	136	131	3			
	e2-5	Audio Amp. A1	9	Access	172	20	136	149	21			
A2	e0-0	FIS Switch A3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch C3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2				-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Überw. Kamera A8	5	Access	172	18	136	143	15	y	5,0	
	e1-1	Überw. Kamera A4	5	Access	172	18	136	144	16	y	5,0	
	e1-2	Überw. Kamera A3	5	Access	172	18	136	145	17	y	5,0	
	e1-3	Überw. Kamera A6	5	Access	172	18	136	146	18	y	5,0	
	e1-4	Überw. Kamera A10	5	Access	172	18	136	147	19	y	5,0	
	e1-5	AFZ A3	8	Access	172	20	8	135	7	y	10,0	
	e1-6	AFZ A4	8	Access	172	20	8	136	8	y	10,0	
	e1-7	NVR A	5	Access	172	18	136	133	5			
	e1-8	Sprechstelle A2	9	Access	172	20	136	134	6	y	7,5	
	e1-9	Sprechstelle AIR	9	Access	172	20	136	133	5	y	7,5	Redundanz A1
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A2	90	Access	-	-	-	-	-			
	e1-13	Future use box A4	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige A2	3	Access	172	17	136	155	27			
	e1-15	Seitenanzeige A4	3	Access	172	17	136	156	28			
	e2-0	Bildschirm A8	3	Access	172	17	136	182	54			
	e2-1	Bildschirm A6	3	Access	172	17	136	183	55			
	e2-2	Bildschirm A2	3	Access	172	17	136	184	56			
	e2-3	Bildschirm A4	3	Access	172	17	136	185	57			
	e2-4				-	-	-	-	-			
	e2-5	Audio Amp. A2	9	Access	172	20	136	150	22			
A3	e0-0	FIS Switch A1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch A2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung A2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point A3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Rücksehkamera A1	5	Access	172	18	136	208	80	y	5,0	
	e1-1	Rücksehkamera A2	5	Access	172	18	136	209	81	y	5,0	
	e1-2	Access point A4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e1-3				-	-	-	-	-			
	e1-4	Firewall	2	Trunk	172	17	8	129	1			Kein DHCP Statische Konfiguration STADLER
			3		172	17	136	129				
			5		172	18	136	129				
			6		172	19	8	129				
			7		172	19	136	129				
			8		172	20	8	129				
			9		172	20	136	129				
		12	172	22	8	129						
	e1-5				-	-	-	-	-			
	e1-6				-	-	-	-	-			
	e1-7				-	-	-	-	-			
	e1-8				-	-	-	-	-			
	e1-9	Sprechstelle A2R	9	Access	172	20	136	134	6	y	7,5	Redundanz A2
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box A1	90	Access	-	-	-	-	-			
	e1-13	Future use box A3	90	Access	-	-	-	-	-			
	e1-14	Frontanzeige A	3	Access	172	17	136	151	23			
	e1-15				-	-	-	-	-			
	e2-0				-	-	-	-	-			
	e2-1				-	-	-	-	-			
	e2-2				-	-	-	-	-			
	e2-3				-	-	-	-	-			
	e2-4	ADU AR	9	Access	172	20	136	131	3			
	e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127			

G1	e0-0	FIS Switch C1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202 7	Trunk	-	-	-	-	-				
					172	19	136	130	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	Service FIS / CCTV	2	Access	172	17	8	250	122				
	e1-0	Überw. Kamera D7	5	Access	172	18	136	158	30	y	5,0		
	e1-1	Überw. Kamera D2	5	Access	172	18	136	159	31	y	5,0		
	e1-2	Überw. Kamera D1	5	Access	172	18	136	160	32	y	5,0		
	e1-3	Überw. Kamera D5	5	Access	172	18	136	161	33	y	5,0		
	e1-4	Überw. Kamera D9	5	Access	172	18	136	162	34	y	5,0		
	e1-5	AFZ D1	8	Access	172	20	8	142	14	y	10,0		
	e1-6	AFZ D2	8	Access	172	20	8	143	15	y	10,0		
	e1-7	AFZ D5	8	Access	172	20	8	144	16	y	10,0		
	e1-8	Sprechstelle D1	9	Access	172	20	136	138	10	y	7,5		
	e1-9				-	-	-	-	-				
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D5	90	Access	-	-	-	-	-				
	e1-13	Future use box D6	90	Access	-	-	-	-	-				
e1-14	Seitenanzeige D1	3	Access	172	17	136	161	33					
e1-15	Seitenanzeige D3	3	Access	172	17	136	162	34					
e2-0	Bildschirm D7	3	Access	172	17	136	196	68					
e2-1	Bildschirm D5	3	Access	172	17	136	197	69					
e2-2	Bildschirm D1	3	Access	172	17	136	198	70					
e2-3	Bildschirm D3	3	Access	172	17	136	199	71					
e2-4	Bildschirm D	3	Access	172	17	136	200	72					
e2-5	Audio Amp. D1	9	Access	172	20	136	153	25					
G2	e0-0	FIS Switch D3	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch E1	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS Reserve D2			-	-	-	-	-				
	e0-3	RDC Reserve D2			-	-	-	-	-				
	e0-4	Access point D2	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Überw. Kamera D8	5	Access	172	18	136	163	35	y	5,0		
	e1-1	Überw. Kamera D4	5	Access	172	18	136	164	36	y	5,0		
	e1-2	Überw. Kamera D3	5	Access	172	18	136	165	37	y	5,0		
	e1-3	Überw. Kamera D6	5	Access	172	18	136	166	38	y	5,0		
	e1-4	Überw. Kamera D10	5	Access	172	18	136	167	39	y	5,0		
	e1-5	AFZ D3	8	Access	172	20	8	145	17	y	10,0		
	e1-6	AFZ D4	8	Access	172	20	8	146	18	y	10,0		
	e1-7				-	-	-	-	-				
	e1-8	Sprechstelle D2	9	Access	172	20	136	139	11	y	7,5		
	e1-9	Sprechstelle D1R	9	Access	172	20	136	138	10	y	7,5		Redundanz D1
	e1-10				-	-	-	-	-				
	e1-11				-	-	-	-	-				
	e1-12	Future use box D2	90	Access	-	-	-	-	-				
	e1-13	Future use box D4	90	Access	-	-	-	-	-				
	e1-14	Seitenanzeige D2	3	Access	172	17	136	163	35				
e1-15	Seitenanzeige D4	3	Access	172	17	136	164	36					
e2-0	Bildschirm D8	3	Access	172	17	136	201	73					
e2-1	Bildschirm D6	3	Access	172	17	136	202	74					
e2-2	Bildschirm D2	3	Access	172	17	136	203	75					
e2-3	Bildschirm D4	3	Access	172	17	136	204	76					
e2-4	Bildschirm D11	3	Access	172	17	136	205	77					
e2-5	Audio Amp. D2	9	Access	172	20	136	154	26					
G3	e0-0	FIS Switch C2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-1	FIS Switch D2	All (except OBS Intercon)	Trunk	-	-	-	-	-				
	e0-2	OBS D1	100, 10, 20, 21, 22, 23, 24, 30, 31, 46, 48, 90, 131, 150, 200, 202 7	Trunk	-	-	-	-	-				
					172	19	136	130	2				
	e0-3	RDC D1	200, 202	Trunk	-	-	-	-	-				
	e0-4	Access point D3	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e0-5	reserved			-	-	-	-	-				
	e1-0	Rücksehkamera D1	5	Access	172	18	136	212	84	y	5,0		
	e1-1	Rücksehkamera D2	5	Access	172	18	136	213	85	y	5,0		
	e1-2	Access point D4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0		
	e1-3				-	-	-	-	-				
	e1-4				-	-	-	-	-				
	e1-5				-	-	-	-	-				
	e1-6				-	-	-	-	-				
	e1-7				-	-	-	-	-				
	e1-8				-	-	-	-	-				
	e1-9	Sprechstelle D2R	9	Access	172	20	136	139	11	y	7,5		Redundanz D2
	e1-10	OBS Reserve D2			-	-	-	-	-				
	e1-11	RDC Reserve D2			-	-	-	-	-				
	e1-12	Future use box D1	90	Access	-	-	-	-	-				
	e1-13	Future use box D3	90	Access	-	-	-	-	-				
e1-14				-	-	-	-	-					
e1-15				-	-	-	-	-					
e2-0				-	-	-	-	-					
e2-1				-	-	-	-	-					
e2-2				-	-	-	-	-					
e2-3				-	-	-	-	-					
e2-4				-	-	-	-	-					
e2-5				-	-	-	-	-					

[illegible]

B1	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch F1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung B1	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point B1	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	Service FIS / CCTV		Access	172	17	8	253	125			
	e1-0	Überw. Kamera B7	5	Access	172	18	136	187	59	y	5,0	
	e1-1	Überw. Kamera B2	5	Access	172	18	136	188	60	y	5,0	
	e1-2	Überw. Kamera B1	5	Access	172	18	136	189	61	y	5,0	
	e1-3	Überw. Kamera B5	5	Access	172	18	136	190	62	y	5,0	
	e1-4	Überw. Kamera B9	5	Access	172	18	136	191	63	y	5,0	
	e1-5	AFZ B1	8	Access	172	20	8	158	30	y	10,0	
	e1-6	AFZ B2	8	Access	172	20	8	159	31	y	10,0	
	e1-7				-	-	-	-	-			
	e1-8	Sprechstelle B1	9	Access	172	20	136	147	19	y	7,5	
	e1-9				-	-	-	-	-			
	e1-10				-	-	-	-	-			
	e1-11	ZFR R	2	Access	172	17	8	130	2			
	e1-12	Future use box B5	90	Access	-	-	-	-	-			
	e1-13	Future use box B6	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige B1	3	Access	172	17	136	173	45			
	e1-15	Seitenanzeige B3	3	Access	172	17	136	174	46			
	e2-0	Bildschirm B7	3	Access	172	17	136	226	98			
	e2-1	Bildschirm B5	3	Access	172	17	136	227	99			
e2-2	Bildschirm B1	3	Access	172	17	136	228	100				
e2-3	Bildschirm B3	3	Access	172	17	136	229	101				
e2-4	ADU B	9	Access	172	20	136	132	4				
e2-5	Audio Amp. B1	9	Access	172	20	136	159	31				
B2	e0-0	FIS Switch B3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch F3	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2				-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point B2 reserved	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Überw. Kamera B8	5	Access	172	18	136	192	64	y	5,0	
	e1-1	Überw. Kamera B4	5	Access	172	18	136	193	65	y	5,0	
	e1-2	Überw. Kamera B3	5	Access	172	18	136	194	66	y	5,0	
	e1-3	Überw. Kamera B6	5	Access	172	18	136	195	67	y	5,0	
	e1-4	Überw. Kamera B10	5	Access	172	18	136	196	68	y	5,0	
	e1-5	AFZ B3	8	Access	172	20	8	160	32	y	10,0	
	e1-6	AFZ B4	8	Access	172	20	8	161	33	y	10,0	
	e1-7	NVR B	5	Access	172	18	136	134	6			
	e1-8	Sprechstelle B2	9	Access	172	20	136	148	20	y	7,5	
	e1-9	Sprechstelle B1R	9	Access	172	20	136	147	19	y	7,5	
	e1-10				-	-	-	-	-			
	e1-11				-	-	-	-	-			
	e1-12	Future use box B2	90	Access	-	-	-	-	-			
	e1-13	Future use box B4	90	Access	-	-	-	-	-			
	e1-14	Seitenanzeige B2	3	Access	172	17	136	175	47			
	e1-15	Seitenanzeige B4	3	Access	172	17	136	176	48			
	e2-0	Bildschirm B8	3	Access	172	17	136	230	102			
	e2-1	Bildschirm B6	3	Access	172	17	136	231	103			
e2-2	Bildschirm B2	3	Access	172	17	136	232	104				
e2-3	Bildschirm B4	3	Access	172	17	136	233	105				
e2-4				-	-	-	-	-				
e2-5	Audio Amp. B2	9	Access	172	20	136	160	32				
B3	e0-0	FIS Switch B1	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-1	FIS Switch B2	All (except OBS Intercon)	Trunk	-	-	-	-	-			
	e0-2	Frontkupplung B2	100, 2, 3, 5, 6, 7, 8, 9, 12	Trunk	-	-	-	-	-			
	e0-3				-	-	-	-	-			
	e0-4	Access point B3 reserved	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e0-5	reserved			-	-	-	-	-			
	e1-0	Rücksehkamera B1	5	Access	172	18	136	218	90	y	5,0	
	e1-1	Rücksehkamera B2	5	Access	172	18	136	219	91	y	5,0	
	e1-2	Access point B4	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	-	y	18,0	
	e1-3				-	-	-	-	-			
	e1-4				-	-	-	-	-			
	e1-5				-	-	-	-	-			
	e1-6				-	-	-	-	-			
	e1-7				-	-	-	-	-			
	e1-8				-	-	-	-	-			
	e1-9	Sprechstelle B2R	9	Access	172	20	136	148	20	y	7,5	Redundanz B2
	e1-10				-	-	-	-	-			
	e1-11	ZFR	2	Access	172	17	8	130	2			
	e1-12	Future use box B1	90	Access	-	-	-	-	-			
	e1-13	Future use box B3	90	Access	-	-	-	-	-			
	e1-14	Frontanzeige B	3	Access	172	17	136	152	24			
	e1-15				-	-	-	-	-			
	e2-0				-	-	-	-	-			
	e2-1				-	-	-	-	-			
e2-2				-	-	-	-	-				
e2-3				-	-	-	-	-				
e2-4	ADU BR	9	Access	172	20	136	132	4				
e2-5	Service VLAN PWLAN	100, 10, 20, 30, 31, 131, 150	Trunk	-	-	-	-	127				
Firewall	RCU		2	N/A	172	17	8	254	126		IP festgehalten fuer die RCU.	
			3	N/A	172	17	136	254	126		Diese ist mit der Firewall verbunden.	
			9	N/A	172	20	136	254	126		Anforderung von STADLER	