

OpenCore

Reference Manual (1.0.8.9)

[2026.11.08]

Copyright ©2018-2026 vit9696

11. `ExtendBTFeatureFlags`
    Type: `plist boolean`
    Failsafe: `false`
    Requirement: 10.8-11
    Description: Set `FeatureFlags` to `0x0F` for full functionality of Bluetooth, including Continuity.

    Note: This option is a substitution for BT4LEContinuityFixup.kext, which does not function properly due to late patching progress.

12. `ExternalDiskIcons`
    Type: `plist boolean`
    Failsafe: `false`
    Requirement: 10.4
    Description: Apply icon type patches to AppleAHCIPort.kext to force internal disk icons for all AHCI disks.

    Note: This option should be avoided whenever possible. Modern firmware typically have compatible AHCI controllers.

13. `ForceAquantiaEthernet`
    Type: `plist boolean`
    Failsafe: `false`
    Requirement: 10.15.4
    Description: Enable Aquantia AQtion based 10GbE network cards support.

    This option enables Aquantia AQtion based 10GbE network cards support, which used to work natively before macOS 10.15.4.

    Note: In order for Aquantia cards to properly function, `DisableIoMapper` must be disabled, `DMAR` ACPI table must not be dropped, and `VT-d` must be enabled in BIOS.

    Note 2: While this patch should enable ethernet support for all Aquantia AQtion series, it has only been tested on AQC-107s based 10GbE network cards.

    Note 3: To address `AppleVTD` incompatibilities after applying this quirk, the `Reserved Memory Region` section of the corresponding device in the `DMAR` ACPI table might be removed. This table should be disassembled and edited, then recompiled to `AML` with tool `iASL`. For the patched `DMAR` table to be added, the original one should be deleted. More details can be found at comment on commit 2441455.

14. `ForceRealtekEthernet`
    Type: `plist boolean`
    Failsafe: `false`
    Requirement: 26
    Description: Enable supported Realtek RTL8125, RTL8126, and RTL8127 Ethernet controllers through the native `AppleEthernetRL` driver.

    Applies firmware, interrupt, legacy packet queue, DMA, and statistics patches on macOS Tahoe (Darwin 25.x) x86_64 kernel collections. All patch locations and the shared queue function layout are checked before writing. Incompatible driver code causes the entire quirk to be skipped. All Tahoe minor versions are eligible; other Darwin versions are skipped.

    Note 1: Requires the native `IOSkywalkFamily` and the other system driver dependencies, including `AppleSkywalkAVB`. Do not block, replace, downgrade, or patch `IOSkywalkFamily`, or combine this option with manual `AppleEthernetRL` patches or replacement drivers. Conflicts are checked according to their architecture and kernel version ranges. Boot-time checks also cover renamed injected bundles and the required `IOSkywalkFamily` member and virtual table layouts. These checks do not authenticate the entire installed driver.

    Note 2: Preserves the existing IOMapper configuration. AVB is disabled. The receive path requires a single DMA segment of at most 4096 bytes; use the standard MTU of 1500. MTU 9000 jumbo frames are unsupported.

15. `ForceSecureBootScheme`
    Type: `plist boolean`
    Failsafe: `false`
    Requirement: 11
    Description: Force `x86` scheme for IMG4 verification.