

VT-AC COMMANDS

	DEC	DESCRIPTION	STANDARD ASCII	# OF BYTES	NOTES
00	0	NULL	YES	1	
01	1	CURSOR HOME	YES	1	
02	2	CURSOR CHARACTER		2	2ND BYTE IS CURSOR CHARACTER, OR \$00 TO TURN OFF DEFAULT = OFF
03	3	CURSOR MODE		1	TOGGLE BETWEEN CURSOR SOLID AND BLINKING DEFAULT = SOLID
04	4	RESET		1	TEXT MODE, CLEAR SCREEN, CURSOR HOME - OFF - SOLID, BG = BLACK, FG = WHITE
05	5	BELL DURATION		2	2ND BYTE IS BELL DURATION IN JIFFIES (I.E., 1/60TH OF A SECOND) DEFAULT = 3C
06	6	BELL FREQUENCY		2	2ND BYTE IS BELL FREQUENCY DEFAULT = 3D
07	7	BELL	YES	1	
08	8	BACKSPACE	YES	1	
09	9	TAB	YES	1	
0A	10	LINE FEED	YES	1	
0B	11	SCREEN MODE		1	TOGGLE BETWEEN TEXT AND GRAPHICS MODES DEFAULT = TEXT
0C	12	CLEAR SCREEN	YES	1	
0D	13	CARRIAGE RETURN	YES	1	
0E	14	SET COLUMN		2	2ND BYTE IS COLUMN = 0 TO 39 DEFAULT = 0
0F	15	SET ROW		2	2ND BYTE IS ROW NUMBER 0 TO 29 DEFAULT = 0
10	16	DELETE TO START OF LINE		1	
11	17	DELETE TO END OF LINE		1	
12	18	DELETE TO START OF SCREEN		1	
13	19	DELETE TO END OF SCREEN		1	
14	20	SCROLL LEFT		1	
15	21	SCROLL RIGHT		1	
16	22	SCROLL UP		1	
17	23	SCROLL DOWN		1	
18	24	FOREGROUND COLOR		2	2ND BYTE IS COLOR DATA AS RGB332 DEFAULT = FF (WHITE)
19	25	BACKGROUND COLOR		2	2ND BYTE IS COLOR DATA AS RGB332 DEFAULT = 00 (BLACK)
1A	26	NEXT BYTE AS DATA		2	ALLOWS 0 TO 31,127 TO BE INTERPRETED AS DATA INSTEAD OF COMMAND
1B	27	ESC	YES	1	RESERVED FOR FUTURE ESCAPE CODE IMPLEMENTATION
1C	28	CURSOR LEFT		1	
1D	29	CURSOR RIGHT		1	
1E	30	CURSOR UP		1	
1F	31	CURSOR DOWN		1	

	DEC	DESCRIPTION	STANDARD ASCII	# OF BYTES	NOTES
20	32	ASCII CHARACTERS	YES	1	SEE ASCII CHART
*					
7E	126				
7F	127	DELETE	YES	1	
80	128	EXTENDED CHARACTERS		1	SEE CHARACTER SET
*					
FF	255				