

Page 1: Common Hardware & Cash-Back Display Symptoms

Symptom A: Cash-Back Other Amount displaying 10x requested amount.

When a customer selects 'Other Amount' for cash-back on the Verifone M400 PIN pad, the screen displays \$100.

Root Cause: Decimal scaling misalignment in register.ini under [PINPAD_CONFIG] section.

Resolution:

1. Access LOC Software SMS Register setup.
2. Open C:\LOC_SMS\Config\register.ini in Notepad.
3. Locate entry: PinpadCashbackScale factor.
4. Set PinpadCashbackScale=1 (default was incorrectly set to 10).
5. Save register.ini and reboot the POS lane terminal.

Symptom B: PIN pad displays 'No Host Connection' or IP loop back error.

1. Check Ethernet cable connection at the base of the M400 stand.
2. Verify static IP address on M400 by pressing 1 + 5 + 9 simultaneously.
3. Subnet mask must match store LAN (255.255.255.0). Gateway must be 192.168.1.1.
4. Ping the terminal IP from the master register server.

Symptom C: M400 PIN Pad screen frozen on AMPM logo during reboot.

Resolution Steps:

1. Perform hard power reset by unplugging the 12V power supply cord from the powered USB/splitter cable.
2. Wait 15 seconds before re-inserting power plug.
3. If screen remains blue, check serial COM port assignment in Device Manager (COM3 required for LOC SMS).
4. Reload M400 OS image via Verifone Direct Loader if firmware corrupted.