Cross-Flow Head-of-Line Blocking in Wi-Fi 7 Multi-Link Operation: Analytical Modeling and Sequence-Aware Scheduling

Research Engineering Group

Abstract—The IEEE 802.11be (Wi-Fi 7) amendment introduces Multi-Link Operation (MLO) to aggregate throughput and reduce latency across multiple radio bands (2.4 GHz, 5 GHz, and 6 GHz). However, under standard multi-link Block Acknowledgment (BA) agreements, all application flows mapped to a given Traffic Identifier (TID) share a single, unified 12-bit sequence-number space and a common receiver reordering buffer. When heterogeneous frames are scheduled across parallel radio links with asymmetric transmission delays, contention backoffs, and frame error rates, out-of-order physical arrivals create severe Head-of-Line (HOL) reordering stalls. Crucially, a delayed frame from a bulk background flow traps successfully received frames from latency-critical flows in the receiver buffer—a phenomenon we define as *Cross-Flow Head-of-Line (CF-HOL) Blocking*.

In this paper, we develop a formal analytical framework and sender-side scheduling policy for CF-HOL blocking under standard IEEE 802.11be receiver semantics. First, we prove an orthogonal decomposition theorem demonstrating that total receiver reorder delay partitions additively and uniquely into intra-flow self-blocking and inter-flow cross-blocking ($\Delta_i = \mathcal{S}_i + \mathcal{X}_i$) as an exact trace accounting identity. Second, we establish the Multi-Link Sequence Divergence model, characterizing the mean-drift crossover boundary $\lambda^* = W/\delta$ and deriving the exact Poisson stall probability $\Pr(N \geq W) = \gamma(W, \lambda_2\delta)/(W-1)!$, showing that approaching the boundary induces severe sliding window stalls with cumulative delay scaling as $\frac{1}{2}\lambda_2\delta^2$. Third, we formulate the pairwise sequence assignment problem, proving that the optimal sequence order between concurrent frames is uniquely determined by a transcendental threshold root $u^*(w_a, w_b)$ solved via Newton-Raphson iteration. Fourth, we establish a symmetric-link causal uncertainty floor $(\min(w_a, w_b)\frac{\sigma_Z}{\sqrt{2\pi}})$ demonstrating that concurrent multi-link dispatch over stochastic Gaussian channels cannot achieve zero cross-flow delay. Guided by these theoretical results, we design *Sequence-Aware Stochastic Partitioning (SASP)*, a transmitter-side Upper MAC scheduling algorithm that suppresses receiver stalls without modifying standard IEEE 802.11be receiver-side protocol semantics. Rigorous simulations across 30 random seeds demonstrate that SASP suppresses cross-flow blocking by 16.1%–17.7% across link asymmetry sweeps, reduces cross-blocking by up to 90.2%–96.8% under near-saturation loads, suppresses high-loss cross-blocking by 36.2%, and delivers up to 20.5% reduction in priority-weighted cost in algorithmic ablation while preserving 100% link goodput and executing in 1.3–4.0 μs per decision for typical topologies.

Index Terms—Wi-Fi 7, IEEE 802.11be, Multi-Link Operation (MLO), Block Acknowledgment, Head-of-Line Blocking, Packet Reordering, Stochastic Scheduling, Upper MAC.

1 Introduction

The IEEE 802.11be Extremely High Throughput (EHT) amendment, commercialized under the trade name Wi-Fi 7, establishes Multi-Link Operation (MLO) as its architectural cornerstone [1]. By allowing affiliated Multi-Link Devices (MLDs) to coordinate transmissions across multiple physical interfaces operating simultaneously in the 2.4 GHz, 5 GHz, and 6 GHz bands, MLO delivers unprecedented multi-gigabit throughput and promises deterministic sub-millisecond latencies for emerging real-time applications such as cloud gaming, augmented reality (XR), and industrial robotics.

To manage parallel radio access without redesigning higher network layers, the IEEE 802.11be MAC architecture is divided into an Upper MAC (U-MAC) and multiple Lower MACs (L-MACs) [2]. The U-MAC is responsible for queue management, multi-link packet scheduling, and flow-level coordination, whereas each L-MAC manages link-specific physical carrier sensing, Enhanced Distributed Channel Access (EDCA) backoff, and Physical Layer Convergence Protocol (PLCP) encapsulation.

Under the 802.11be specification, the Block Acknowledgment (BA) mechanism operates at the U-MAC level per peer MLD and Traffic Identifier (TID $\in \{0, \ldots, 7\}$) [1]:

1) A single, unified 12-bit sequence-number space ($s \in [0, 4095]$) is shared by all MAC Service Data Units (MSDUs) transmitted under a given TID across all active links.
2) The receiver MLD maintains a single sliding receive reordering buffer governed by window size $W \in \{64, 256, 1024\}$ and window base W_{start}.
3) The receiver delivers MSDUs to the upper layers (Logical Link Control/IP) strictly in monotonically increasing sequence-number order.

While this unified sequence space guarantees backward compatibility with legacy 802.11 state machines and prevents out-of-order segment delivery to transport protocols like TCP, it creates an acute performance vulnerability when links exhibit heterogeneous physical channel characteristics [3], [4]. In modern wireless environments, parallel links

Manuscript prepared for journal submission, October 2026. Complete source code, discrete-event simulation engine, experimental datasets across 30 seeds, and test suites are available in the project artifact repository.

inevitably differ in bandwidth (e.g., 20 MHz on 2.4 GHz vs. 160/320 MHz on 5/6 GHz), PHY data rates, channel contention (EDCA contention slot delays), and Frame Error Rates (FER).

When sequence numbers are assigned conventionally in arrival order (FIFO), an earlier-sequenced frame dispatched over a slower, congested, or lossy link will complete physical transmission significantly later than subsequently-sequenced frames dispatched over a clear, high-speed link. Consequently, successfully received frames are trapped inside the receiver reordering buffer awaiting the missing earlier sequence number.

This bottleneck becomes critical when heterogeneous application flows share the same TID. Because the IEEE 802.11 standard defines only eight TIDs mapped to four Access Categories (AC_VO, AC_VI, AC_BE, AC_BK), host operating systems routinely multiplex diverse application flows—such as interactive VoIP, cloud gaming telemetry, and bulk background file synchronization—into the default Best Effort Access Category (TID 0) [3], [5]. In such deployments:

- A bulk packet dispatched on a slow 2.4 GHz link receives sequence number s.
- Latency-critical gaming packets dispatched on a 6 GHz link receive sequence numbers $s+1, s+2, \ldots, s+k$.
- Although the gaming packets arrive physically in fractions of a millisecond, the receiver cannot deliver them to the host network stack until packet s arrives or undergoes retries.

We formally define this phenomenon as **Cross-Flow Head-of-Line (CF-HOL) Blocking**.

Recent empirical measurements by Oliveira et al. [4] in ns-3 confirmed that multi-link reordering causes severe latency degradation. However, existing work suffers from three decisive limitations:

1) *Absence of Mathematical Modeling:* Prior studies [4], [6] treat multi-link reordering empirically without formalizing the stochastic coupling between channel completion variances and sliding BA window dynamics.
2) *Confounded Delay Metrics:* Existing literature measures only aggregate end-to-end latency, failing to mathematically decouple intra-flow self-reordering from inter-flow cross-blocking.
3) *Non-Standard or Receiver-Side Proposals:* Proprietary patents, such as MediaTek US12470496B2 [7], propose receiver-side Deep Packet Inspection (DPI) to construct per-flow reorder queues. This violates standard IEEE 802.11be protocol semantics, requires specialized receiver silicon, and leaves commercial off-the-shelf client devices completely unprotected.

Contributions: In this paper, we resolve these challenges by establishing an analytical model and sender-side scheduling architecture for CF-HOL blocking in Wi-Fi 7:

- **Orthogonal Delay Decomposition (Theorem 1):** We prove that total receiver reordering delay decomposes additively, uniquely, and non-negatively into intra-flow self-blocking and inter-flow cross-blocking ($\Delta_i = \mathcal{S}_i + \mathcal{X}_i$) as an exact trace accounting framework.
- **Sequence Divergence & Stall Probability (Theorem 2):** We establish the mean-drift crossover boundary $\lambda^* = W/\delta$, derive the exact Poisson stall probability $\Pr(N \geq W) = \gamma(W, \lambda_2\delta)/(W-1)!$, and prove quadratic cumulative stall scaling $\frac{1}{2}\lambda_2\delta^2$.
- **Optimal Pairwise Predictive Sequencing Rule (Theorem 3):** We formulate the pairwise sequence assignment problem, proving that the optimal causal sequence order between concurrent candidate frames is uniquely determined by a transcendental threshold root $u^*(w_a, w_b)$ solved via Newton-Raphson in ≤ 4 steps, providing an efficient index heuristic for multi-frame scheduling.
- **Symmetric-Link Uncertainty Floor (Theorem 4):** We prove that concurrent dispatch over symmetric stochastic links has an irreducible cross-flow delay floor $\min(w_a, w_b)\frac{\sigma_Z}{\sqrt{2\pi}}$, while explicitly identifying its falsification boundaries (e.g., Single-Link Operation achieves $\mathcal{X} = 0$).
- **The SASP Algorithm & Validation:** We design *Sequence-Aware Stochastic Partitioning (SASP)*, an Upper MAC algorithm executing in 1.3–4.0 μs typically in Python. Benchmarked across eight baselines and 30 random seeds, SASP reduces cross-flow blocking by 16.1%–17.7% under asymmetry, up to 90.2%–96.8% under buffer load, and 36.2% under loss, while strictly adhering to standard 802.11be receiver semantics.

2 Related Work and State of the Art

2.1 Multi-Link Operation in IEEE 802.11be

The Multi-Link Operation (MLO) architecture defined in IEEE Std 802.11be-2024 provides two primary operational modes: Simultaneous Transmit and Receive (STR) and Non-Simultaneous Transmit and Receive (NSTR) [1]. In STR mode, an MLD can transmit or receive simultaneously on multiple links without cross-band in-device interference (e.g., between 5 GHz and 6 GHz). Carreño et al. [3] conducted early throughput studies of MLO, observing that when links exhibit severe rate asymmetry, naive multi-link aggregation can paradoxically degrade overall performance compared to single-link operation. Levy et al. [8] and Al-Hraishawi et al. [6] analyzed MLO delay under finite queue loads, but both studies assumed single-flow Poisson arrivals and ideal in-order reception.

2.2 Reorder Buffering and Block Acknowledgment Dynamics

The Block Acknowledgment (BA) mechanism originated in IEEE 802.11e and was extended in 802.11n/ac/ax for high-speed frame aggregation (A-MPDU). In 802.11be MLO, the BA agreement operates at the peer MLD level across all links affiliated with a TID [1].

Oliveira, Raposo, and Luís (2026) [4] provided the first in-depth empirical simulation of BA window stalls in ns-3, demonstrating that out-of-order frame arrivals cause substantial buffer occupancy and delay spikes for UDP

traffic. Sangeetha et al. [5] presented an analytical model for unsaturated MLO queues using a multi-dimensional Markov chain, but their formulation assumed that each traffic flow possesses a dedicated TID, sidestepping single-TID multi-flow contention. Choi, Jung, and Kim [2] explored joint L-MAC and U-MAC packet scheduling for NSTR MLO, focusing on power consumption and channel switching overhead rather than sequence number assignment.

2.3 Multipath Transport Schedulers vs. Wireless MAC

Out-of-order packet reordering has been extensively studied at the transport layer, particularly in Multipath TCP (MPTCP) [9]. Schedulers such as BLEST (Blocking Estimation-based MPTCP Scheduler) [9] predict head-of-line receiver blocking by comparing estimated path Round-Trip Times (RTTs).

However, transport-layer schedulers operate on continuous byte streams over long RTT timescales (10–100 ms) with explicit end-to-end ACK feedback. In contrast, wireless Upper MAC scheduling operates on discrete frames at sub-millisecond timescales ($100\,\mu$s–5 ms) under non-stationary EDCA contention backoff, small sliding sequence windows ($W \in \{64, 256\}$), and rapid burst fading. Consequently, MPTCP heuristics cannot be directly applied to the 802.11be U-MAC.

2.4 Architectural Boundary and Patent Landscape

To mitigate MLO reordering stalls, proprietary patent filings have emerged. Most notably, MediaTek patent US12470496B2 [7] proposes a *receiving apparatus* that performs Deep Packet Inspection (DPI) on incoming MPDUs, inspects IP/UDP 5-tuple headers, and demultiplexes packets into separate per-flow receive queues before releasing them to upper layers.

While effective in closed ecosystems, this approach has severe practical drawbacks:

1) It alters standard IEEE 802.11be receiver protocol semantics, which dictate a single TID reordering buffer.
2) It cannot accelerate standard commercial client stations (smartphones, IoT devices) that implement unmodified 802.11be MAC firmware.
3) It requires packet header inspection hardware on power-constrained mobile receivers.

In contrast, our proposed SASP algorithm resides **strictly at the transmitting U-MAC**. The transmitter optimizes link dispatch and sequence numbering such that packets arrive physically in sequential order at the receiver. Standard commercial client devices receive packets within valid sequence windows and deliver them with zero stalls, guaranteeing full protocol compliance and complete independence from receiver-side patents. (We note that this comparison represents an engineering prior-art analysis and does not constitute a formal legal freedom-to-operate opinion.)

3 System Model and Problem Formulation

3.1 Multi-Link MAC Sublayer Architecture

We consider an IEEE 802.11be Access Point (AP) MLD communicating with an affiliated non-AP station MLD over a set of $K \geq 2$ orthogonal radio links $\mathcal{K} = \{1, 2, \ldots, K\}$. We assume Simultaneous Transmit and Receive (STR) operation across non-overlapping frequency bands (Link 1: 2.4 GHz, Link 2: 5 GHz, Link 3: 6 GHz).

A set of $M \geq 2$ distinct application flows $\mathcal{F} = \{1, \ldots, M\}$ generate packets mapped to a single TID (e.g., TID 0, Best Effort). Each flow $f \in \mathcal{F}$ is characterized by an arrival rate λ_f and a delay penalty weight $w_f > 0$. Higher weights denote latency-sensitive traffic (e.g., $w_{\text{gaming}} = 20, w_{\text{bulk}} = 1$). Incoming packets are queued in flow-specific U-MAC buffers $Q_1, \ldots, Q_M$.

3.2 Lower MAC Channel Access and Service Times

Each radio link $k \in \mathcal{K}$ executes an independent EDCA channel access engine with parameters $(\text{AIFS}_k, \text{CW}_{\min,k}, \text{CW}_{\max,k})$ and PHY transmission rate R_k. When packet i of length L_i bits is dispatched to link $\ell_i = k$ at dispatch time t_i^{disp}, its total completion duration until successful Block Ack confirmation is:

$$D_i(k) = \sum_{r=1}^{N_{i,k}} \left(B_{k,r} + T_{\text{frame},k}(L_i) \right) + T_{\text{ack},k} \tag{1}$$

where $N_{i,k} \in [1, N_{\max}]$ is the number of transmission attempts until success, $B_{k,r}$ is the stochastic EDCA backoff slot duration, $T_{\text{frame},k}$ is the PLCP frame transmission time, and $T_{\text{ack},k}$ is the turnaround and Block Ack response time. The physical arrival time of packet i at the receiver is:

$$A_i = t_i^{\text{disp}} + D_i(\ell_i) \tag{2}$$

The link service duration $D_i(k)$ is modeled as a continuous random variable with mean μ_k and variance σ_k^2. Channel error dynamics are captured via a two-state Gilbert-Elliott model alternating between Good and Bad channel states.

3.3 Receiver Block Ack Reorder Buffer

The receiver MLD manages a single reordering buffer of size $W \in \{64, 256, 1024\}$ for the given TID. The active sequence window is $[W_{\text{start}}, W_{\text{start}} + W - 1]$. Upon physical arrival of packet i at time A_i with sequence number s_i:

- If $s_i = W_{\text{start}}$: Packet i is immediately delivered to upper layers, and W_{start} advances to the lowest missing sequence number.
- If $W_{\text{start}} < s_i < W_{\text{start}} + W$: Packet i is retained in the buffer awaiting all missing predecessors $\{s' : W_{\text{start}} \leq s' < s_i\}$.
- If $s_i \geq W_{\text{start}} + W$: The buffer window overflows. To prevent indefinite stalls, W_{start} is forcefully advanced to $s_i - W + 1$, and all missing packets prior to the new W_{start} are declared lost.

Under reliable transmission, packet i is released to the host stack at time:

$$R_i = \max\left(A_i, \max_{k : s_k < s_i} A_k \right) \tag{3}$$

The total reordering delay experienced by packet i is $\Delta_i = R_i - A_i \geq 0$.

TABLE 1: System Model and Simulation Parameters

Parameter	Link 1 (2.4 GHz)	Link 2 (5 GHz)	Link 3 (6 GHz)
Channel Width	20 MHz	80 MHz	160 MHz
Base MCS	MCS 4	MCS 9	MCS 11
PHY Rate (R_k)	39.0 Mbps	480.4 Mbps	1201.0 Mbps
AIFS	3 slots	2 slots	2 slots
$\mathrm{CW}_{\min}/\mathrm{CW}_{\max}$	15 / 1023	15 / 1023	15 / 1023
Slot Time	9 μs	9 μs	9 μs
Base Delay (μ_k)	1.20 ms	0.40 ms	0.25 ms
Jitter (σ_k)	0.35 ms	0.12 ms	0.08 ms
Frame Error Rate	$0.05 - 0.15$	$0.02 - 0.08$	$0.01 - 0.05$

4 Theoretical Analysis and Theorems

4.1 Orthogonal Delay Decomposition

To rigorously study multi-flow interference, we must isolate the delay intrinsic to a flow's own dispersion from the delay imposed by competing flows sharing the TID.

Theorem 1 (Buffer Reorder Accounting Decomposition)**.** *Let packet i belong to flow f_i with physical arrival time A_i and assigned sequence number s_i. On an observed execution trace, define the intra-flow completion boundary:*

$$R_i^{intra} \triangleq \max\left(A_i, \max_{j:f_j=f_i, s_j<s_i} A_j\right) \tag{4}$$

Then the total reordering delay $\Delta_i = R_i - A_i$ admits an exact, non-negative, additive decomposition:

$$\Delta_i = \mathcal{S}_i + \mathcal{X}_i \tag{5}$$

where:

$$\mathcal{S}_i \triangleq R_i^{intra} - A_i = \max\left(0, \max_{j:f_j=f_i, s_j<s_i} A_j - A_i\right) \tag{6}$$

*denotes the intra-flow **Self-Blocking Delay**, and:*

$$\mathcal{X}_i \triangleq R_i - R_i^{intra} = \max\left(0, \max_{k:f_k\neq f_i, s_k<s_i} A_k - R_i^{intra}\right) \tag{7}$$

*denotes the inter-flow **Cross-Flow Blocking Delay**.*

Proof. By IEEE 802.11be in-order delivery semantics, the delivery epoch is $R_i = \max(A_i, \max_{k:s_k<s_i} A_k)$. The set of causal predecessors $\mathcal{P}_i = \{k : s_k < s_i\}$ partitions into disjoint intra-flow predecessors $\mathcal{P}_i^{\text{intra}} = \{j : f_j = f_i, s_j < s_i\}$ and inter-flow predecessors $\mathcal{P}_i^{\text{inter}} = \{k : f_k \neq f_i, s_k < s_i\}$. Hence:

$$R_i = \max\left(R_i^{\text{intra}}, \max_{k\in\mathcal{P}_i^{\text{inter}}} A_k\right) \tag{8}$$

Since $R_i \geq R_i^{\text{intra}} \geq A_i$, both $\mathcal{S}_i \geq 0$ and $\mathcal{X}_i \geq 0$. Summing:

$$\mathcal{S}_i + \mathcal{X}_i = (R_i^{\text{intra}} - A_i) + (R_i - R_i^{\text{intra}}) = R_i - A_i = \Delta_i \tag{9}$$

□

Lemma 1 (Attribution Invariance and Boundary Conditions)**.** *On an observed trace with fixed physical arrival epochs $\{A_i\}$ and sequence numbers $\{s_i\}$, the self-blocking delay $\mathcal{S}_i$ is strictly invariant to the arrival epochs, sequence numbers, and presence of all competing flows $\mathcal{F} \setminus \{f_i\}$.*

Physical Boundary Note: *This invariance is an in-buffer accounting property on a realized trace. In a real shared wireless medium, the physical presence of competing traffic introduces EDCA channel contention, collision-induced backoff escalation, and queuing delay, which dynamically alters $\{A_i\}$. Theorem 1 thus serves as an exact diagnostic metric for isolating in-buffer reordering stalls from channel service time dispersion.*

Proof. By definition, R_i^{intra} depends exclusively on A_i and the set $\{A_j : f_j = f_i, s_j < s_i\}$. Removing all frames of other flows leaves $\mathcal{P}_i^{\text{inter}} = \emptyset$, which forces $R_i = R_i^{\text{intra}}$ and $\mathcal{X}_i = 0$, while $\mathcal{S}_i$ remains unchanged. □

4.2 Multi-Link Sequence Divergence and Buffer Stability

We now analyze the stochastic behavior of the receiver sliding window when flows with asymmetric rates and delays share a TID under standard FIFO sequence assignment.

Theorem 2 (Sequence Divergence and Buffer Stall Probability)**.** *Consider an MLD transmitting bulk flow A on slow Link 1 (μ_1, σ_1^2) and interactive flow B on fast Link 2 (μ_2, σ_2^2) with mean asymmetry $\delta = \mu_1 - \mu_2 > 0$ and negotiated Block Ack window W. Under FIFO sequencing:*

1) *During the completion duration of a frame on Link 1, the sequence divergence N on Link 2 has mean $\mathbb{E}[N] = \lambda_B\mu_1$. Under Poisson arrivals, $\mathrm{Var}(N) = \lambda_B\mu_1 + \lambda_B^2\sigma_1^2$.*
2) *The mean-drift crossover boundary occurs at critical arrival rate:*
$$\lambda^* \triangleq \frac{W}{\delta} \tag{10}$$
When $\lambda_B > \lambda^*$, the mean queue drift into the reorder window is positive ($\mathbb{E}[N] > W$), causing buffer accumulation on average.
3) *For constant completion duration δ on Link 1 and Poisson arrivals at rate λ_B on Link 2, the exact probability that the sequence gap reaches or exceeds window capacity W is:*
$$P_{stall}(\lambda_B, \delta, W) \triangleq \Pr(N \geq W) = 1 - \sum_{k=0}^{W-1} \frac{(\lambda_B\delta)^k e^{-\lambda_B\delta}}{k!} \tag{11}$$
For any finite λ_B, $\Pr(N < W) > 0$. At $\lambda_B = \lambda^*$, $P_{stall} \approx 0.533$ for $W = 16$, with $P(N < W) \approx 0.467$.
4) *The cumulative cross-flow blocking duration per frame of flow A scales quadratically as:*
$$\int_0^{\lambda_B\delta} \left(\delta - \frac{x}{\lambda_B}\right) dx = \frac{1}{2}\lambda_B\delta^2 \tag{12}$$

Proof. Frame a of flow A is dispatched to Link 1 at $t = 0$, completing at D_1 with $\mathbb{E}[D_1] = \mu_1$. Concurrently, frames b_j ($j = 1, 2, \ldots$) are dispatched on Link 2 at rate λ_B with

sequence numbers $s_j = s_a + j$. Frame b_j completes at $A_{b_j} = j/\lambda_B + D_{2,j}$. Whenever $j/\lambda_B + D_{2,j} < D_1$, packet b_j arrives before frame a and is cross-blocked: $\mathcal{X}_{b_j} = \delta - j/\lambda_B$. Integrating across $j \in [0, \lambda_B\delta]$:

$$\int_0^{\lambda_B\delta} \left(\delta - \frac{x}{\lambda_B}\right) dx = \lambda_B\delta^2 - \frac{\lambda_B^2\delta^2}{2\lambda_B} = \frac{1}{2}\lambda_B\delta^2 \tag{13}$$

By the law of total expectation and variance for compounded Poisson arrivals: $\mathbb{E}[N] = \lambda_B\mu_1$, $\mathrm{Var}(N) = \lambda_B\mu_1 + \lambda_B^2\sigma_1^2$. The complement probability of reaching or exceeding window capacity follows directly from the Poisson cumulative distribution function. □

4.3 Optimal Predictive Sequencing Rule (SASP)

We now address the core scheduling problem: given candidate frames ready for transmission across parallel links, how should sequence numbers be assigned to minimize total weighted cross-flow blocking?

Theorem 3 (SASP Optimal Pairwise Threshold Rule)**.** *Let candidate frames a (flow f_a, weight w_a) and b (flow f_b, weight w_b, $f_a \neq f_b$) have completion times $A_a \sim \mathcal{N}(\mu_a, \sigma_a^2)$ and $A_b \sim \mathcal{N}(\mu_b, \sigma_b^2)$. Let $Z \triangleq A_a - A_b \sim \mathcal{N}(\mu_Z, \sigma_Z^2)$, with $\mu_Z = \mu_a - \mu_b$ and $\sigma_Z = \sqrt{\sigma_a^2 + \sigma_b^2}$.*

The sequence assignment decision minimizing expected weighted cross-flow blocking cost:

$$\begin{aligned} C(s_a < s_b) &= w_b\mathbb{E}[(A_a - A_b)^+], \\ C(s_b < s_a) &= w_a\mathbb{E}[(A_b - A_a)^+] \end{aligned} \tag{14}$$

is given by the strictly optimal pairwise threshold rule:

$$s_a < s_b \iff \frac{\mu_a - \mu_b}{\sqrt{\sigma_a^2 + \sigma_b^2}} \leq u^*(w_a, w_b) \tag{15}$$

where u^* is the unique root of the strictly monotonically increasing function:

$$h(u) \triangleq (w_b - w_a)\phi(u) + [w_a(1 - \Phi(u)) + w_b\Phi(u)]\, u = 0 \tag{16}$$

and $\phi(\cdot)$, $\Phi(\cdot)$ are the standard Gaussian PDF and CDF.

Properties of the Root u^*:

1) *When flow weights are equal ($w_a = w_b$), $u^* = 0$, and optimal sequence assignment is sorted strictly by expected completion time: $s_a < s_b \iff \mu_a \leq \mu_b$.*
2) *When flow b has higher priority ($w_b > w_a$), $u^* < 0$, satisfying $|u^*| \leq \sqrt{2\ln(w_b/w_a)}$.*
3) *u^* is transcendental and computed via Newton-Raphson iteration in ≤ 4 steps.*
4) *For $N > 2$ candidate frames, pairwise sorting provides an $\mathcal{O}(M \log M)$ index heuristic whose multi-dimensional maximum is governed by Clark's order-statistics approximation.*

Proof. Using the identity $Z^+ - (-Z)^+ = Z$, we have $\mathbb{E}[(-Z)^+] = \mathbb{E}[Z^+] - \mu_Z$. The condition $C(s_a < s_b) \leq C(s_b < s_a)$ is equivalent to $(w_b - w_a)\mathbb{E}[Z^+] + w_a\mu_Z \leq 0$. For $Z \sim \mathcal{N}(\mu_Z, \sigma_Z^2)$, normalized variable $u = \mu_Z/\sigma_Z$. Truncated normal expectation yields:

$$\mathbb{E}[Z^+] = \sigma_Z\left[\phi(u) + u\Phi(u)\right] \tag{17}$$

Dividing by $\sigma_Z > 0$ yields:

$$(w_b - w_a)\phi(u) + [w_a(1 - \Phi(u)) + w_b\Phi(u)]\, u \leq 0 \tag{18}$$

Taking the first derivative of $h(u)$ with respect to u:

$$\begin{aligned} h'(u) = (w_b - w_a)(-u\phi(u)) + (w_b - w_a)(u\phi(u)) \\ + [w_a(1 - \Phi(u)) + w_b\Phi(u)] \end{aligned} \tag{19}$$

The first two terms cancel identically! Hence:

$$h'(u) = w_a(1 - \Phi(u)) + w_b\Phi(u) > 0, \quad \forall u \in \mathbb{R} \tag{20}$$

Because $h'(u) > 0$ strictly everywhere, $h(u)$ is strictly monotonically increasing from $-\infty$ to $+\infty$. By the Intermediate Value Theorem, $h(u) = 0$ possesses exactly one real root u^*. □

4.4 Symmetric-Link Causal Uncertainty Floor

Theorem 4 (Symmetric-Link Causal Uncertainty Floor)**.** *When candidate frames a and b are dispatched concurrently on stochastic links with equal mean completion times ($\mu_a = \mu_b$, so $u = 0$) and non-zero Gaussian variance $\sigma_Z = \sqrt{\sigma_a^2 + \sigma_b^2} > 0$, the expected weighted cross-flow blocking cost under any binary sequence assignment decision is strictly lower-bounded by:*

$$\min\left(C(s_a < s_b), C(s_b < s_a)\right) = \min(w_a, w_b)\frac{\sigma_Z}{\sqrt{2\pi}} > 0 \tag{21}$$

For arbitrary link asymmetry $u = (\mu_a - \mu_b)/\sigma_Z$, the optimal decision cost attains its global maximum at $u = u^*$ and decays to zero as $|u| \to \infty$.

Falsification Boundaries: *This bound holds strictly conditional on concurrent multi-link dispatch over stochastic channels. Under Single-Link Operation (SLO) or deterministic links ($\sigma_Z = 0$), frames arrive in sequential order, achieving $\mathcal{X}_i = 0$ identically.*

Proof. At $u = 0$, $\phi(0) = \frac{1}{\sqrt{2\pi}}$, $\Phi(0) = \frac{1}{2}$, and $\mu_Z = 0$. Hence $\mathbb{E}[Z^+] = \mathbb{E}[(-Z)^+] = \sigma_Z\phi(0) = \frac{\sigma_Z}{\sqrt{2\pi}}$. Evaluating $C(s_a < s_b) = w_b\frac{\sigma_Z}{\sqrt{2\pi}}$ and $C(s_b < s_a) = w_a\frac{\sigma_Z}{\sqrt{2\pi}}$ gives $\min(C) = \min(w_a, w_b)\frac{\sigma_Z}{\sqrt{2\pi}}$. As $|u| \to \infty$, Mill's ratio ensures $C^*(u) \to 0$. □

5 The SASP Scheduling Algorithm

5.1 Algorithmic Design

Algorithm 1 presents the complete specification of *Sequence-Aware Stochastic Partitioning (SASP)*, implemented at the transmitter U-MAC.

5.2 Parameter Estimation and Complexity

Channel completion parameters $(\hat{\mu}_\ell, \hat{\sigma}_\ell^2)$ are updated at runtime upon receiving Block Ack frames using an Exponentially Weighted Moving Average (EWMA) with smoothing factor $\alpha = 0.125$. The threshold root u^* converges in ≤ 4 Newton-Raphson steps.

- **Computational Complexity:** $\mathcal{O}(M \cdot K \cdot |\mathcal{O}|) \leq \mathcal{O}(M \cdot K \cdot W)$. Decision execution time profiles between $1.3\,\mu$s and $4.0\,\mu$s for typical 2–3 link topologies in Python (reaching $16.3\,\mu$s under an extreme 8-flow/2-link stress topology).
- **Memory Footprint:** $\mathcal{O}(W+K) < 8$ KB, fitting entirely within L1 cache.

Algorithm 1 Sequence-Aware Stochastic Partitioning (SASP)

Require: Queues $\{Q_f\}_{f=1}^{M}$, Links $\mathcal{K}$, Window W, Flow weights $\{w_f\}$.
Ensure: Dispatched tuple (p^*, ℓ^*, s^*).

$\text{Cost}_{\min} \leftarrow \infty, (p^*, \ell^*) \leftarrow \text{None}$
for all available link $\ell \in \mathcal{K}$ **do**
  Read current estimates $(\hat{\mu}_\ell, \hat{\sigma}_\ell)$ from EWMA tracker.
  for all active flow $f \in \mathcal{F}$ with $Q_f \neq \emptyset$ **do**
    $p \leftarrow Q_f.\text{peek}()$
    $\hat{A}_{\text{cand}} \leftarrow t_{\text{curr}} + \hat{\mu}_\ell$
    $\text{Cost} \leftarrow w_f \cdot \hat{\mu}_\ell$
    for all in-flight unacknowledged packet $p_j \in \mathcal{O}$ with $f_j \neq f$ **do**
      $\Delta\mu \leftarrow \hat{A}_j - \hat{A}_{\text{cand}}$
      $\sigma_Z \leftarrow \sqrt{\hat{\sigma}_\ell^2 + \hat{\sigma}_j^2}$
      Compute $u^* \leftarrow \text{SolveRoot}(w_j, w_f)$ via Newton-Raphson.
      if $\Delta\mu/\sigma_Z \geq u^*$ **then**
        $\text{Cost} \mathrel{+}= w_f \cdot \sigma_Z \left[\phi(\frac{\Delta\mu}{\sigma_Z}) + \frac{\Delta\mu}{\sigma_Z}\Phi(\frac{\Delta\mu}{\sigma_Z})\right]$
      else
        $\text{Cost} \mathrel{+}= w_j \cdot \sigma_Z \left[\phi(-\frac{\Delta\mu}{\sigma_Z}) - \frac{\Delta\mu}{\sigma_Z}\Phi(-\frac{\Delta\mu}{\sigma_Z})\right]$
      end if
    end for
    if $\text{Cost} < \text{Cost}_{\min}$ **then**
      $\text{Cost}_{\min} \leftarrow \text{Cost}, p^* \leftarrow p, \ell^* \leftarrow \ell$
    end if
  end for
end for
$p^* \leftarrow Q_{f^*}.\text{pop}()$
Assign $s^* \leftarrow \text{AllocateSequenceNumber}(p^*, \ell^*, W)$.
Dispatch p^* to L-MAC on link ℓ^*.

6 Performance Evaluation

6.1 Experimental Setup

We implement a discrete-event simulation engine in Python modeling IEEE 802.11be multi-link operations, EDCA contention engines, multi-rate PHY modes, Gilbert-Elliott channel errors, sliding BA windows, and orthogonal delay decomposition. We benchmark SASP against eight baselines: Single-Link (SLO), Default FIFO MLO, Round-Robin (RR), Lowest-Latency-First (LLF), Congestion-Aware (CALA), Static Pinning, Retransmission Steering (WARS), and an Offline Non-Causal Oracle. All reported data points represent the mean across 30 independent random seeds, with 95% Student-t confidence intervals.

6.2 EXP-01: Delay Asymmetry Sweep

Fig. 1 evaluates mean cross-flow blocking $\mathbb{E}[\mathcal{X}]$ as link asymmetry $\delta = \mu_1 - \mu_2$ is swept from 0.2 ms to 5.0 ms. Under Single-Link Operation (SLO), cross-flow blocking is identically 0.000 ms. Under Static Pinning, cross-flow blocking escalates severely from 0.064 ms to 1.765 ms, causing p99 latency to swell beyond 240 ms due to link starvation. Under Default FIFO, cross-blocking increases from 0.024 ms to 0.891 ms. SASP optimizes sequence number allocation according to physical completion epochs, reducing cross-blocking to 0.141 ms at $\delta = 1.5$ ms (a **17.7% reduction**) and to 0.747 ms at $\delta = 5.0$ ms (a **16.1% reduction**) while preserving full link goodput (9.55 Mbps).




Fig. 1: Cross-Flow Blocking vs. Link Delay Asymmetry $\delta = \mu_1 - \mu_2$ (EXP-01).




Fig. 2: Throughput Collapse and 99th Percentile Tail Latency vs. Normalized Load λ/λ^* (EXP-02).

6.3 EXP-02: Multi-Link BA Window Stall Collapse

Fig. 2 validates Theorem 2. When normalized arrival load λ/λ^* sweeps from 0.2 to 2.0 ($W = 16, \mu_{\text{slow}} = 8.0$ ms), the 99th percentile latency surges from 11.40 ms to 190.02 ms across the collapse boundary as the receiver buffer nears saturation. Crucially, SASP reduces cross-flow blocking by **71.2% at normalized load 1.0** (from 0.981 ms to 0.283 ms) and by **96.8% at load 1.5** (from 0.737 ms to 0.024 ms), reducing p99 latency by 24.5% (from 133.1 ms to 100.5 ms) without sacrificing goodput.

6.4 EXP-03: Priority Heterogeneity

Fig. 3 evaluates priority weight ratios $w_{\text{inter}}/w_{\text{bulk}} \in [1, 50]$. As priority asymmetry widens, Theorem 3's threshold root u^* shifts into the negative domain ($u^* \leq -0.85$). This systematically shields the interactive flow from bulk reorder delays, reducing weighted cross-flow blocking cost by **16.5%** at ratio 10 (from 1.4241 to 1.1885) and by **16.5%** at ratio 50 (from 6.6431 to 5.5491).

6.5 EXP-04: Contention and Burst Frame Loss

Fig. 4 sweeps frame error rates up to 25% under two-state Gilbert-Elliott channel fading. As retransmissions accumulate on Link 0, Default FIFO cross-blocking surges from 0.214 ms to 0.960 ms. SASP limits cross-blocking to 0.311 ms at 10% FER (**19.8% reduction**) and to 0.613 ms at 25% FER (**36.2% reduction**), demonstrating robust resilience to wireless link impairment.




Fig. 3: Interactive Flow Protection vs. Priority Weight Ratio $w_{\text{inter}}/w_{\text{bulk}}$ (EXP-03).




Fig. 4: Cross-Flow Blocking under Frame Loss and Contention (EXP-04).

6.6 EXP-05 & EXP-06: Scalability and Robustness

EXP-05 confirms that SASP scales across topologies up to 4 radio links and 8 flows, with measured decision overhead ranging between 1.27 μs and 16.26 μs in Python ($1.3-4.0\,\mu$s typically). Fig. 5 evaluates sensitivity to variance estimation errors $\epsilon_\sigma \in [-50\%, +50\%]$. Even under $\pm 50\%$ variance bias, SASP stably maintains an **18.2% relative advantage** over FIFO (0.2044 ms vs. 0.2499 ms) because the mean asymmetry $\Delta\mu = 2.0$ ms dominates link variance $\sigma \approx 0.1$ ms by over an order of magnitude, preserving optimal sequence decisions unconditionally.

6.7 EXP-07 & Targeted Priority Ablation

Fig. 6 isolates the contribution of each algorithmic component:

- *Default FIFO Baseline:* Cross-blocking = 0.3411 ms, weighted cost = 1.8845.
- *Dispatch-Only (Congestion-Aware):* Cross-blocking = 0.3456 ms, weighted cost = 1.9124.
- *Mean-Only Sequencing:* Cross-blocking = 0.2816 ms, weighted cost = 1.5000 (20.4% cost reduction).
- *Full SASP (Theorem 3 Threshold Engine):* Cross-blocking = 0.2811 ms, weighted cost = 1.4988 (**20.5% cost reduction**).

A dedicated 2,160-run paired ablation campaign reveals that while predictive sequencing itself drives the broad




Fig. 5: Sensitivity to Parameter Estimation Bias $\epsilon_\sigma \in [-50\%, +50\%]$ (EXP-06).




Fig. 6: Algorithmic Ablation Breakdown Across 30 Seeds (EXP-07).

performance leap over FIFO across all regimes (up to 78.1% cost reduction), the Theorem 3 threshold root u^* provides a statistically significant **3.5% to 4.9% reduction ($p < 0.05$)** over Mean-Only Sequencing in the specific operating regime of **high priority asymmetry ($w \in [5, 50]$) with near-equal link means ($\Delta\mu \leq 0.2$ ms)**.

7 Discussion and Threats to Validity

7.1 Standards Compliance and Firmware Deployment

SASP requires zero modifications to receiver hardware or protocol stacks. Transmitted frames adhere to IEEE 802.11be MAC header formats and remain within standard BA window boundaries. Commercial AP vendors can deploy SASP purely as a firmware or host driver update within the U-MAC scheduler.

7.2 Threats to Validity

To uphold scientific rigor, we explicitly disclose the methodological limitations of this study:

1) *Custom Discrete-Event Simulator:* Experiments were conducted in a custom Python discrete-event simulation package rather than an established network simulator like ns-3 or Omnet++. While verified by 39 unit and property tests, absolute latency numbers should be viewed as indicative.
2) *Absence of Physical Hardware Measurements:* Experiments reflect simulated radio channels rather than commercial Wi-Fi 7 silicon (e.g., Qualcomm FastConnect 7800 or Intel BE200). Proprietary firmware in

existing chipsets currently prevents custom sequence assignment.

3) *Gaussian Service-Time Approximation:* Link completion times are modeled with Gaussian distributions. Under severe multipath fading or heavy retry escalation, completion times exhibit discrete multimodal tails.
4) *Link Independence Assumption:* We assume orthogonal frequency bands with negligible in-device cross-talk. Under Non-STR (NSTR) operation, channel switching and self-interference introduce coupling.
5) *Traffic Model Characteristics:* Background and interactive flows were modeled with Poisson and periodic packet arrivals. Real application workloads exhibit burstiness that may intensify buffer pressure.
6) *BA Window Advance Realism:* Forced window advances follow standard IEEE 802.11be rules, but real vendor chipsets may implement proprietary advance heuristics.
7) *Baseline Scope:* We benchmarked against eight representative algorithms, but proprietary vendor schedulers may incorporate undisclosed cross-layer heuristics.
8) *Platform Profiling vs. Silicon Timing:* Decision overhead was measured in interpreted Python. Real embedded AP SoCs running compiled C/microcode are expected to achieve significantly lower overhead.
9) *TID vs. Flow Identity:* SASP assumes the transmitter can distinguish flow weights within TID 0. In Linux, this relies on internal `sk_buff` priority markings or DSCP inspection at the AP.
10) *Patent Positioning Disclaimer:* Our literature and patent audit represents an engineering comparison to highlight technical novelty and does not constitute a formal legal opinion on freedom to operate.

8 Conclusion

In this paper, we investigated Cross-Flow Head-of-Line (CF-HOL) blocking in Wi-Fi 7 Multi-Link Operation. We proved an orthogonal delay decomposition theorem ($\Delta_i = \mathcal{S}_i + \mathcal{X}_i$), characterized the Multi-Link Sequence Divergence model with exact Poisson stall probability, derived the optimal pairwise threshold root rule $u^*(w_a, w_b)$, and proved the symmetric-link causal uncertainty floor. Guided by these theoretical findings, we designed SASP, a transmitter Upper MAC scheduling algorithm that reduces cross-flow blocking by 16.1%–17.7% across link asymmetry sweeps, up to 96.8% under buffer loads, and 36.2% under frame loss, without modifying receiver semantics.

References

[1] *IEEE Standard for Information Technology–Telecommunications and Information Exchange between Systems Local and Metropolitan Area Networks–Specific Requirements - Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications Amendment 8: Enhancements for Extremely High Throughput (EHT)*, IEEE Std. IEEE Std 802.11be-2024, 2024.

[2] S. Choi, S. Jung, and H. Kim, "Joint design of L-MAC transmission mechanism and U-MAC packet scheduling for NSTR MLO operations in Wi-Fi 7," *Computer Networks*, vol. 257, p. 111895, 2025.

[3] S. Carreño, A. Garcia-Rodriguez, L. Giordano, and D. Lopez-Perez, "IEEE 802.11be multi-link operation: When the best could be to use only a single interface," 2021.

[4] R. Oliveira, D. M. G. Raposo, and M. Luís, "Characterizing block acknowledgment window reordering in multi-link wi-fi," *IEEE Open Journal of the Communications Society*, vol. 7, pp. 1–14, 2026.

[5] R. G. Sangeetha, H. C., K. T. Ankitha, and A. Jaiswal, "IEEE 802.11be WLANs: Performance assessment of multi-link operation with unsaturated queues," *Computer Networks*, vol. 259, p. 112187, 2026.

[6] H. Al-Hraishawi, M. Lou, M. Cha, and S. Chatzinotas, "Delay analysis of IEEE 802.11be multi-link operation under finite load," 2022.

[7] C.-H. Huang, Y.-H. Tseng, C.-Y. Wu, and W.-W. Lin, "Data reordering method and apparatus thereof," Patent US12 470 496B2, 2025, uS Patent Application US20240244007A1, published July 18, 2024.

[8] T. Levy, W. Rhee, and H. Kwon, "Multi-link operation in IEEE 802.11be WLANs," 2022.

[9] S. Ferlin, T. Dreibholz, and O. Alay, "BLEST: Blocking estimation-based MPTCP packet scheduler for heterogeneous networks," *IEEE Transactions on Network and Service Management*, vol. 15, no. 2, pp. 793–805, 2018.