
2000V 6 A DC Power Supply Software Configuration:

1. RS232 Communication Port Settings:

COM Port	COM1...2...3...
Baud Rate	9600
Word Length	7
Parity	Even
Stop Bits	1

2. Ethernet Communication Port Settings:

IP	192.168.0.200
Port	502

3. Device ID: 1

4. Function Register: 03

5. Register Address:

Sr.No.	Description	Mapping Address	Length (bit)
1	Read Voltage actual	4x404246	16
2	Read Current actual	4x404247	16
3	Write HV ON/OFF	4x404250	16
4	Write Voltage	4x404251	16
5	Write Current	4x404252	16
6	Write Password	4x404253	32

6. PASSWORD: 01062000