

1. Images tend to be easier to work with than raw audio files, as they extract meaningful information from audio and get rid of information that isn't useful. What actually matters in keyword recognition is the frequency component's evolution over time. This isn't captured well in audio files as they only show amplitude fluctuation. Image representation of sound encodes time on one axis, frequency on another, and intensity in color. This allows us to run a convolution neural network just like we would on an image. This is just a clever way of using information we already have into more efficient features.
2. Representative datasets help in the conversion of floats to INT8's. This dataset is used to learn the numerical fluctuations in one's model, so that these numbers can be compressed to lower resolution (INT8) with the least possible drop in accuracy.
3. `get_data()` is a command that fetches samples from the required audio dataset. It has functionalities to tackle reproducibility of test results, and specify background noise levels.
4. `G_model` is the literal byte representation of the tflite model. The Arduino must have local access to the model to be able to operate. This hex array is exactly that, the version of the model hardware actually understands. `G_model_len` is the length of this hex array. Incorrect entry of this value can lead to either truncation or introduction of corrupted data.

5. 