Queueing analysis of a battery-backed electrical vehicle charging system

Andres Ferragut
Universidad ORT Uruguay
Montevideo, Uruguay
ferragut@ort.edu.uy

Sebastián Bibiloni *
Universidad de la República
Montevideo, Uruguay
sebastianbibiloni@ingener.com

ABSTRACT

We study a battery-buffered electric vehicle fast charging station modeled as a piecewise-deterministic Markov process. A battery buffer mediates between a grid connection and one or more chargers, delivering fast service when charged and falling back to the grid rate when depleted. For the single-server loss system we derive the stationary distribution in closed form, uncovering a decoupling property whereby the charger state and battery level are independent in steady state, and obtain explicit formulas for blocking probability, mean charging time, and a slowdown factor quantifying service degradation as a function of car energy demand. We extend the analysis to the multi-server loss system, showing that the stationary densities retain an exponential form with occupancy weights governed by a simple recurrence, and that the classical Erlang-B formula is recovered at the critical load where the mean battery drift vanishes.

Keywords

Piecewise deterministic Markov processes, Electrical Vehicles.

1. INTRODUCTION

The rapid adoption of electric vehicles is placing increasing demands on electrical infrastructure. A key challenge is the provisioning of public fast charging: modern DC fast chargers can deliver 150 kW or more per port, requiring grid connections sized for their peak output. Yet in practice a charging station is not used continuously; vehicles arrive stochastically and the chargers are idle most of the time. Sizing the grid connection for worst-case simultaneous demand is therefore wasteful, and utility demand charges (fees based on peak power draw within a billing cycle) can represent the dominant operating cost of a fast charging site [8]. A battery buffer placed between the grid and the chargers resolves this mismatch: the battery trickle-charges from the grid at a steady, modest rate and discharges at high power during the brief intervals a vehicle is present, enabling a much smaller and cheaper grid connection. Battery storage at EV stations has been studied primarily in the context of renewable energy integration, where the battery smooths intermittent solar or wind supply [1, 6, 10]; the low-utilization motivation is equally compelling for purely grid-connected stations.

The central analytical question this raises is a queueing one: given that vehicles arrive randomly and the battery recharges during idle periods, how often does a vehicle arrive to find the battery depleted, forcing service at the slower grid rate? This coupling between the continuous battery state and the discrete service rate is what distinguishes the battery-buffered station from a standard loss queue, and it has not been captured in the existing EV charging literature, which models charging with a fixed service rate [2, 5, 9].

We model the station as a Piecewise-Deterministic Markov Process (PDMP) [3, 4]: the battery level evolves deterministically between random events, while car arrivals and departures trigger instantaneous mode switches. The state is the pair (n, x) of charger occupancy and battery level. The generator of this process is derived explicitly, and from it the stationary distribution is obtained in closed form for the single-server loss system. A key structural finding is a *decoupling property*: in steady state the charger occupancy and battery level are conditionally independent given the interior of the state space, so that the stationary density factors as a product of an exponential in x and a mode-dependent weight. This yields explicit formulas for the blocking probability, mean charging time, and a *slowdown factor* quantifying the service degradation as a function of a car's energy demand. We then extend the analysis to a loss system with s parallel chargers sharing a common battery. The exponential form of the stationary density is preserved, with the mode weights now governed by a simple recurrence, and the classical Erlang-B blocking formula is recovered in the critical case where the mean battery drift vanishes.

The paper is organized as follows. Section 2 introduces the single-server model and its PDMP formulation. Section 3 derives the stationary distribution and performance metrics. Section 4 treats the many-server case. Section 5 concludes.

2. SINGLE-SERVER MODEL

We consider a single EV charging station consisting of one charger connected to the electrical grid, equipped with a battery buffer of capacity $B > 0$. Cars arrive according to a Poisson process of rate $\lambda > 0$, each carrying an energy demand $Y \sim \text{Exp}(\mu)$. The station operates as a *loss system*: a car that arrives when the charger is busy is turned away.

The system is characterized by the following power rates: $p_0 > 0$, the rate at which the grid recharges the battery when the charger is idle; $p_1 > p_0$, the maximum grid supply

*This work was partially supported by ANII Uruguay under grant CF_1_2024_1_182277.

IFIP Performance '26. 3-5 November 2026, Ghent, Belgium
Copyright is held by author/owner(s).

rate; $p_2 > p_1$, the fast charging rate delivered to a car when the battery is positive; and $c = p_2 - p_1 > 0$, the net battery discharge rate during fast charging. The ordering $p_0 \le p_1 < p_2$ reflects a practical constraint: the battery recharges slowly to extend its life, while fast charging draws power simultaneously from both grid and battery.

When a car is admitted, service proceeds in at most two phases. In *Phase 1* (fast charging), while the battery level $x > 0$, the car charges at rate p_2 and the battery discharges at rate c. In *Phase 2* (slow charging), once the battery is exhausted ($x = 0$), the car charges at rate p_1 and the battery remains at zero. A car with small demand may complete service entirely in Phase 1. With exponential demands, the instantaneous departure rate is $\mu p(x)$, where $p(x) = p_2\,\mathbf{1}_{x>0} + p_1\,\mathbf{1}_{x=0}$.

The system state at time t is the pair $Z(t) = (n(t), x(t))$, where $n(t) \in \{0, 1\}$ is the charger status (0 = idle, 1 = busy) and $x(t) \in [0, B]$ is the battery level. The state space is $E = \{0, 1\} \times [0, B]$. Between events, the battery evolves deterministically according to $\dot{x} = r(n, x)$, where

$$r(n,x) = \begin{cases} p_0 & n = 0,\ x < B, \\ 0 & n = 0,\ x = B, \\ -c & n = 1,\ x > 0, \\ 0 & n = 1,\ x = 0. \end{cases} \tag{1}$$

The jumps are spontaneous events: *arrivals* at $(0, x)$ occur at rate λ and transition to $(1, x)$; *departures* at $(1, x)$ with $x > 0$ occur at rate μp_2 and transition to $(0, x)$; *departures* at $(1, 0)$ occur at rate μp_1 and transition to $(0, 0)$. In all cases the battery level is unchanged at the jump epoch.

The process $Z(t)$ fits the PDMP framework of Davis [3, 4], though the standard theory requires an open state space and forces the process to jump before reaching the boundary. Neither condition holds here: E is compact and the flow reaches $x = 0$ and $x = B$ in finite time without a jump. Nevertheless, the vector field (1) is bounded and monotone on each mode, so the flow is globally well-defined. The strong Markov property follows from the martingale-problem approach, which extends to this setting since all jump rates are bounded and the jump kernel leaves x unchanged.

Note that an arriving car always finds $x > 0$ with probability one. During any idle period the battery charges at rate $p_0 > 0$, and since the idle time before the next arrival is $\mathrm{Exp}(\lambda)$ (positive a.s.), the battery is strictly positive at every arrival epoch. The state $(n = 0, x = 0)$ therefore has zero probability under any stationary distribution.

The extended generator $\mathcal{A}$ of $Z(t)$ has domain $\mathcal{D}(\mathcal{A})$ consisting of functions $\psi : E \to \mathbb{R}$ such that $\psi(n, \cdot)$ is absolutely continuous on $[0, B]$ for each n. For $\psi \in \mathcal{D}(\mathcal{A})$,

$$\mathcal{A}\psi(0,x) = r(0,x)\,\psi_0'(x) + \lambda\,[\psi(1,x) - \psi(0,x)], \tag{2}$$

$$\mathcal{A}\psi(1,x) = r(1,x)\,\psi_1'(x) + \mu p(x)\,[\psi(0,x) - \psi(1,x)], \tag{3}$$

where $\psi_n' = \partial_x \psi(n, \cdot)$ is defined Lebesgue-a.e. The first term in each line is the flow contribution; the second is the jump contribution. For any $\psi \in \mathcal{D}(\mathcal{A})$, the process $M_t^\psi := \psi(Z(t)) - \psi(Z(0)) - \int_0^t \mathcal{A}\psi(Z(s))\,ds$ is a local martingale [3].

A stationary distribution π satisfies $\int \mathcal{A}\psi\,d\pi = 0$ for all $\psi \in \mathcal{D}(\mathcal{A})$, which is the weak form of the Kolmogorov forward equation $\mathcal{A}^*\pi = 0$. We seek π as a mixed measure with densities on $(0, B)$ and point masses at the boundary points where flow accumulates. Substituting this form into $\int \mathcal{A}\psi\,d\pi = 0$ and integrating by parts yields a system of ODEs on $(0, B)$ and flux-balance conditions at the boundary, which we solve in the next section.

3. SINGLE-SERVER STEADY-STATE ANALYSIS

Since E is compact and $Z(t)$ is irreducible (every open rectangle $\{n\} \times (a, b)$ is reachable with positive probability from any starting point, by a combination of deterministic drift and Poisson events), the process is ergodic with a unique stationary distribution π [7].

Following the approach outlined at the end of Section 2, we write π in the mixed form

$$\pi = f_0(x)\,dx + f_1(x)\,dx + \pi_{0,B}\,\delta_{(0,B)} + \pi_{1,0}\,\delta_{(1,0)}, \tag{4}$$

where $f_n \ge 0$ are densities on $(0, B)$ and $\pi_{0,B}, \pi_{1,0} \ge 0$ are point masses at the corners where the flow accumulates: $x = B$ in mode 0 (since $r(0, \cdot) = p_0 > 0$) and $x = 0$ in mode 1 (since $r(1, \cdot) = -c < 0$). The other two corners carry no atoms.

Steady-state equations. Setting $\mathcal{A}^*\pi = 0$ and using (2)–(3), the stationarity condition $\int \mathcal{A}\psi\,d\pi = 0$ for all $\psi \in \mathcal{D}(\mathcal{A})$ yields, after integration by parts, the following system. The *interior equations* on $(0, B)$ are

$$p_0\,f_0'(x) = -\lambda\,f_0(x) + \mu p_2\,f_1(x), \tag{5}$$

$$-c\,f_1'(x) = \quad \lambda\,f_0(x) - \mu p_2\,f_1(x). \tag{6}$$

The *boundary flux equations* are obtained by flux conservation at each boundary point: mass arriving at a boundary via the flow must equal mass leaving via jumps. At $x = 0$ in mode 1, the inward flow $c\,f_1(0^+)$ feeds the atom $\pi_{1,0}$, which drains via departures at rate μp_1:

$$c\,f_1(0^+) = \mu p_1\,\pi_{1,0}. \tag{7}$$

At $x = 0$ in mode 0, the atom $\pi_{1,0}$ is created by departures and immediately carried into the interior by the flow at rate p_0:

$$p_0\,f_0(0^+) = \mu p_1\,\pi_{1,0}. \tag{8}$$

At $x = B$ in mode 0, the inward flow $p_0\,f_0(B^-)$ feeds the atom $\pi_{0,B}$, which drains via arrivals at rate λ:

$$p_0\,f_0(B^-) = \lambda\,\pi_{0,B}. \tag{9}$$

At $x = B$ in mode 1, arrivals from $\pi_{0,B}$ feed the interior flow at rate λ:

$$c\,f_1(B^-) = \lambda\,\pi_{0,B}. \tag{10}$$

These are supplemented by normalization: $\int_0^B (f_0 + f_1)\,dx + \pi_{0,B} + \pi_{1,0} = 1$.

We can now state the main result of this section.

THEOREM 3.1. *Let $\theta = \mu p_2/c - \lambda/p_0$. The unique stationary distribution of $Z(t)$ has the form* (4) *with*

$$f_0(x) = \frac{e^{\theta x}}{K}, \qquad f_1(x) = \frac{p_0}{c} \cdot \frac{e^{\theta x}}{K}, \qquad x \in (0, B), \tag{11}$$

$$\pi_{1,0} = \frac{p_0}{\mu p_1\,K}, \qquad \pi_{0,B} = \frac{p_0\,e^{\theta B}}{\lambda\,K}, \tag{12}$$

where the normalization constant is

$$K = \frac{p_0 + c}{c} \cdot \frac{e^{\theta B} - 1}{\theta} + \frac{p_0}{\mu p_1} + \frac{p_0\,e^{\theta B}}{\lambda}, \tag{13}$$

with the convention $(e^{\theta B} - 1)/\theta = B$ when $\theta = 0$.

PROOF PROOF SKETCH. **Decoupling.** Adding (5) and (6) gives $\frac{d}{dx}[p_0 f_0 - c f_1] = 0$, so $p_0 f_0 - c f_1$ is constant on $(0, B)$. Equations (7) and (8) together give $p_0 f_0(0^+) = c f_1(0^+)$, so the constant is zero: $f_1(x) = (p_0/c)\, f_0(x)$ for all $x \in (0, B)$.

Exponential solution. Substituting $f_1 = (p_0/c) f_0$ into (5) yields $f_0'(x) = \theta\, f_0(x)$ with $\theta = \mu p_2/c - \lambda/p_0$, whose solution is $f_0(x) = f_0(0^+)\, e^{\theta x}$.

Atoms and normalization. The atoms follow directly from (8) and (9). One can verify that (10) is automatically satisfied, confirming consistency. Setting $f_0(0^+) = 1/K$ and imposing normalization determines K as in (13).

Boundary conditions at $x = B$. Equations (9)–(10) are both satisfied by the exponential solution with the atoms given in (12), confirming that no additional constraint on θ arises: the parameter θ is determined entirely by the interior ODE, not by the boundary. □

The parameter θ has a natural physical interpretation: it is the net drift of the battery level that would prevail in the absence of boundary effects. When $\theta > 0$ (lightly loaded) the battery tends to fill and mass concentrates near $x = B$; when $\theta < 0$ (heavily loaded) the battery tends to drain and mass concentrates near $x = 0$; when $\theta = 0$ the density is uniform.

We now derive the key performance metrics directly from Theorem 3.1.

PROPOSITION 3.2 (BLOCKING PROBABILITY). *By PASTA, P_B is the stationary probability the charger is busy:*

$$P_B = \int_0^B f_1(x)\, dx + \pi_{1,0} = \frac{p_0}{K}\left(\frac{e^{\theta B} - 1}{c\,\theta} + \frac{1}{\mu p_1}\right). \quad (14)$$

As $B \to 0$, $P_B \to \lambda/(\lambda + \mu p_1)$, the blocking probability of an $M/M/1/1$ queue at rate p_1. As $B \to \infty$ with $\theta > 0$, $P_B \to \lambda/(\lambda + \mu p_2)$, corresponding to service always at the fast rate p_2. When $\theta < 0$, P_B converges to a value strictly between these two limits even as $B \to \infty$, reflecting the residual probability of finding the battery depleted.

PROPOSITION 3.3 (MEAN CHARGING TIME). *By Little's law, the mean service time of an admitted car is*

$$\mathbb{E}[T] = \frac{P_B}{\lambda(1 - P_B)}. \quad (15)$$

PROPOSITION 3.4 (SLOWDOWN FACTOR). *Given admission at level x with demand $Y = y$, let $T(x, y) = y/p_2 + (p_1^{-1} - p_2^{-1}) \max(y - p_2 x/c, 0)$ be the charging time. The* slowdown factor *$S(y) = \mathbb{E}[T \mid Y = y]/(y/p_2) \geq 1$ quantifies degradation relative to ideal fast charging. With $\tilde{x}(y) = cy/p_2$ the critical battery level:*
For $y < p_2 B/c$ (battery may survive):

$$S(y) = 1 + \frac{p_2 - p_1}{p_1\, y\, K(1 - P_B)\,\theta}\left[\frac{p_2}{c\,\theta}\left(e^{\theta c y/p_2} - 1\right) - y\right]. \quad (16)$$

For $y \geq p_2 B/c$ (battery always depletes):

$$S(y) = 1 + \frac{p_2 - p_1}{p_1\, y\, K(1 - P_B)}\left\{\frac{1}{\theta}\left[(y - \tfrac{p_2 B}{c})e^{\theta B} - y + \tfrac{p_2(e^{\theta B} - 1)}{c\theta}\right] + \tfrac{p_0 e^{\theta B}}{\lambda}(y - \tfrac{p_2 B}{c})\right\}. \quad (17)$$

$S(y)$ satisfies $S(y) \geq 1$, is increasing in y, tends to 1 as $y \to 0$ or $B \to \infty$, and tends to p_2/p_1 as $y \to \infty$ or $B \to 0$.

4. THE MANY-SERVER CASE

We now extend the model to $s \geq 1$ parallel chargers sharing a single battery buffer of capacity B and a single grid connection of rate p_1. The station continues to operate as a loss system: a car that arrives when all s chargers are busy is turned away.

Assumptions. We impose $p_1 < s p_2$, so the grid alone cannot sustain all s chargers simultaneously at full rate; the battery is essential at full occupancy. We also set $p_0 = p_1$, so the idle recharge rate equals the grid supply rate; this simplifies the structure of the vector field.

State space and dynamics. The state is $Z(t) = (n(t), x(t))$ with $n(t) \in \{0, \ldots, s\}$ busy chargers and $x(t) \in [0, B]$; $E = \{0, \ldots, s\} \times [0, B]$ is compact. With n busy chargers each drawing p_2 and the grid supplying p_1, the net drift is $r_n = p_1 - n p_2$. Setting $p_0 = p_1$ makes this hold for all n: the battery charges at rate p_1 when idle and drains at rate $n p_2 - p_1$ when $n > p_1/p_2$. The vector field is

$$\dot{x} = \begin{cases} r_n & 0 < x < B,\ r_n \neq 0, \\ 0 & \text{otherwise (boundary reflection).} \end{cases} \quad (18)$$

Define the *critical occupancy* $n^* = \lfloor p_1/p_2 \rfloor \in \{0, \ldots, s-1\}$; the battery charges when $n \leq n^*$ and drains when $n > n^*$.

The jumps are: arrivals at rate λ when $n < s$, transitioning $n \to n+1$ with x unchanged; departures at total rate $n\mu p_2$ when $x > 0$, and at rate μp_1 when $x = 0$ (the grid supplies p_1 shared equally, giving total throughput μp_1 regardless of occupancy), each transitioning $n \to n-1$ with x unchanged.

The process $Z(t)$ is again a PDMP on a compact state space, and the same martingale-problem argument as in Section 2 establishes the strong Markov property. Irreducibility follows by the same reachability argument, so $Z(t)$ is ergodic with a unique stationary distribution.

Form of the stationary distribution. The flow direction at each boundary point now depends on the occupancy level n. Atoms accumulate at (n, B) for $n \leq n^*$ (where the flow pushes toward $x = B$) and at $(n, 0)$ for $n > n^*$ (where the flow pushes toward $x = 0$). We therefore seek a stationary distribution of the form

$$\pi = \sum_{n=0}^{s} f_n(x)\, dx + \sum_{n=0}^{n^*} \pi_n^{(B)}\, \delta_{(n,B)} + \sum_{n=n^*+1}^{s} \pi_n^{(0)}\, \delta_{(n,0)}, \quad (19)$$

where $f_n \geq 0$ are densities on $(0, B)$ and $\pi_n^{(B)}, \pi_n^{(0)} \geq 0$ are point masses.

Interior equations. Setting $\mathcal{A}^* \pi = 0$ on $(0, B)$ gives, for $0 \leq n \leq s$,

$$r_n f_n'(x) = \lambda f_{n-1}(x)\, \mathbf{1}_{n>0} + (n+1)\mu p_2\, f_{n+1}(x)\, \mathbf{1}_{n<s} - (\lambda\, \mathbf{1}_{n<s} + n\mu p_2)\, f_n(x). \quad (20)$$

THEOREM 4.1. *Let $\rho = \lambda/(\mu p_2)$. There exists a unique $\theta \in \mathbb{R}$, determined by the boundary flux equations together with normalization, such that the stationary densities take the form*

$$f_n(x) = C\, a_n(\theta)\, e^{\theta x}, \qquad x \in (0, B),\ n = 0, \ldots, s, \quad (21)$$

where $C > 0$ is a normalization constant and the coefficients $a_n(\theta)$ satisfy the recurrence $a_0 = 1$ and

$$a_{n+1} = \frac{\theta\, S_n + \lambda\, a_n}{(n+1)\mu p_2}, \qquad S_n = \sum_{k=0}^{n} r_k\, a_k, \quad n = 0, \ldots, s-1. \quad (22)$$

When $\theta = 0$, the recurrence yields $a_n = \rho^n/n!$ and the distribution reduces to the classical Erlang-B form with uniform density in x. For $\theta \neq 0$, the blocking probability

$$P_B = C\, a_s\, \frac{e^{\theta B} - 1}{\theta} + \pi_s^{(0)}\, \mathbf{1}_{n^* < s} \tag{23}$$

deviates from the Erlang-B value, with the battery shifting mass toward $x = B$ when $\theta > 0$ and toward $x = 0$ when $\theta < 0$.

Proof Proof sketch. Summing (20) from $k = 0$ to n telescopes the right side to $-\lambda f_n + (n+1)\mu p_2 f_{n+1}$. The exponential form $f_n = C a_n e^{\theta x}$ then yields (22). The value of θ is fixed by the boundary flux equations together with normalization. For $s = 1$ and $p_0 = p_1$, one recovers $\theta = \mu p_2/c - \lambda/p_1$ of Theorem 3.1. □

The parameter θ admits the same physical interpretation as in the single-server case. In the unconstrained system (infinite battery), the occupancy evolves as an $M/M/s/s$ queue with Erlang-B stationary weights $\pi_n \propto \rho^n/n!$, giving a mean battery drift $\bar{r} = p_1 - (\lambda/\mu)(1 - P_B^{\text{Erlang}})$. The sign of $\bar{r}$ determines the sign of θ: positive when the grid can sustain the average load (battery fills in the long run) and negative otherwise. The case $\theta = 0$ corresponds exactly to $\bar{r} = 0$, at which point the Erlang-B distribution is recovered.

Performance metrics. The blocking probability is given by (23). By PASTA and Little's law the mean charging time follows from P_B exactly as in Propositions 3.2 and 3.3. The slowdown factor $S(y)$ generalizes directly: the admitted battery level has the same exponential density $f_0(x)/(1 - P_B)$ on $(0, B)$ (now with s-server normalization), and the conditional charging time $T(x, y)$ is unchanged, so the formulas of Proposition 3.4 apply with the updated P_B and $K = 1/C$.

5. CONCLUSIONS

We have studied a battery-buffered EV fast charging station using the framework of piecewise-deterministic Markov processes. For the single-server loss system we derived the stationary distribution in closed form, establishing a decoupling property that separates the battery level from the charger state in steady state, and obtained explicit expressions for the blocking probability, mean charging time, and slowdown factor. We extended the analysis to a loss system with s parallel chargers sharing a common battery, showing that the stationary densities retain an exponential form in the battery level with occupancy-dependent weights governed by a simple recurrence. In both cases the key parameter θ, the sign of the mean battery drift, determines whether the system operates in a battery-rich or battery-scarce regime and controls the deviation of the blocking probability from the classical Erlang-B value.

The analysis highlights a structural difference from standard fluid queues: the state-dependent service rate at $x = 0$ couples the discrete and continuous components in a way that prevents a product-form solution in the multi-server case while still admitting an exponential form in x. Numerical illustrations of the performance metrics and a study of the optimal battery sizing problem are left for future work.

6. REFERENCES

[1] I. S. Bayram, G. Michailidis, M. Devetsikiotis, S. Bhattacharya, A. Chakrabortty, and F. Granelli. Local energy storage sizing in plug-in hybrid electric vehicle charging stations under blocking probability constraints. In *Proc. IEEE International Conference on Smart Grid Communications (SmartGridComm)*, pages 78–83, 2011.

[2] I. S. Bayram, G. Michailidis, M. Devetsikiotis, and F. Granelli. Electric power allocation in a network of fast charging stations. *IEEE Journal on Selected Areas in Communications*, 31(7):1235–1246, 2013.

[3] M. H. A. Davis. Piecewise-deterministic Markov processes: a general class of non-diffusion stochastic models. *Journal of the Royal Statistical Society: Series B*, 46(3):353–388, 1984.

[4] M. H. A. Davis. *Markov Models and Optimization*. Chapman & Hall, London, 1993.

[5] A. Dupont and Y. Hayel. A loss queueing game for electric vehicle charging performance evaluation. *Performance Evaluation*, 161:102365, 2023.

[6] M. E. Kabir, C. Assi, M. H. K. Tushar, and J. Yan. Optimal scheduling of EV charging at a solar power-based charging station. *IEEE Systems Journal*, 14(3):4221–4231, 2020.

[7] S. P. Meyn and R. L. Tweedie. *Markov Chains and Stochastic Stability*. Springer, London, 1993.

[8] National Renewable Energy Laboratory. Battery energy storage for electric vehicle charging stations. Technical report, U.S. Department of Energy, 2023. Available at driveelectric.gov.

[9] X. Tan, B. Sun, and D. H. K. Tsang. Queueing network models for electric vehicle charging station with battery swapping. In *Proc. IEEE International Conference on Smart Grid Communications (SmartGridComm)*, pages 1–6, 2014.

[10] V. T. Tran, M. R. Islam, K. M. Muttaqi, and D. Sutanto. An efficient energy management approach for a solar-powered EV battery charging facility to support distribution grids. *IEEE Transactions on Industry Applications*, 55(6):6517–6526, 2019.