Rockchip Linux6.12 SDK Release Note

ID: RK-FB-YF-A66

Release Version: V0.0.1

Release Date: 2026-03-20

Security Level: □Top-Secret □Secret □Internal ■Public

DISCLAIMER

THIS DOCUMENT IS PROVIDED “AS IS”. ROCKCHIP ELECTRONICS CO., LTD.(“ROCKCHIP”)DOES NOT PROVIDE ANY WARRANTY OF ANY KIND, EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY, COMPLETENESS,MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME DUE TO THE UPGRADES OF THE PRODUCT OR ANY OTHER REASONS.

Trademark Statement

"Rockchip", "瑞芯微", "瑞芯" shall be Rockchip’s registered trademarks and owned by Rockchip. All the other trademarks or registered trademarks mentioned in this document shall be owned by their respective owners.

All rights reserved. ©2026 Rockchip Electronics Co., Ltd.

Beyond the scope of fair use, neither any entity nor individual shall extract, copy, or distribute this document in any form in whole or in part without the written approval of Rockchip.

Rockchip Electronics Co., Ltd.

No.18 Building, A District, No.89, software Boulevard Fuzhou, Fujian,PRC

Website: www.rock-chips.com

Customer service Tel: +86-4007-700-590

Customer service Fax: +86-591-83951833

Customer service e-Mail: fae@rock-chips.com

Preface

Overview

The document presents Rockchip Linux6.12 SDK release notes, aiming to help engineers get started with Linux6.12 universal SDK development and related debugging faster.

Intended Audience

This document (this guide) is mainly intended for:

Technical support engineers

Software development engineers

Chipset and System Support

Chipset	Buildroot	Debian	Yocto
RK3572	Y	Y	Y

Revision History

Date	Version	Author	Revision History
2026-03-20	V0.0.1	Weiye Chen	Alpha version
2026-03-30	V0.0.1	Weiye Chen	Remove Hardware Development Guide

Contents

Rockchip Linux6.12 SDK Release Note

1. Overview
2. Main Functions
3. How to Get the SDK
    - 3.1 Download Authorization
    - 3.2 Get Source Code from Rockchip Code Server
    - 3.3 Get Source Code from Local Compression Package
4. Software Development Guide
5. SSH Public Key Operation Introduction
    - 5.1 Key Authority Management
    - 5.2 Reference Documents

1. Overview

This SDK supports three systems based on Buildroot 2025.02, Debian 13, and Yocto5.0, with the kernel based on Kernel 6.12 and the bootloader based on U-boot v5. It is suitable for RK3572 EVB development boards and all Linux products developed based on this board.

The development kit is applicable to, but not limited to, AIoT solution-related application scenarios and products such as industrial motherboards, robots, NVRs, drones, and conference audio/video systems. It provides flexible data path combination interfaces to meet customers' customized needs for free combination. For specific function debugging and interface descriptions, please refer to the documents under the project's docs/ directory.

2. Main Functions

Function	Module Name
System	Debian, Buildroot, Yocto
Partition table	uboot, misc, boot, recovery, rootfs, oem, userdata
File System Type	EXT2/3/4, VFAT, NTFS, UBIFS, SquashFS
Upgrade Recovery	OTA, AB, Recovery
Secure Boot	SecureBoot
Stress Test Tool	ROCKCHIP_TEST
Data communication	Wi-Fi, Ethernet card, USB, SD card, SATA, PCI-e interface
Applications	Multimedia Playback, Camera Preview, Desktop UI, Browser

3. How to Get the SDK

The SDK is distributed via Rockchip's official code repository and can only be downloaded with **authorized access**. For offline acquisition, you may request a **local source code package** (contact Rockchip's technical support team for assistance). For details on the compilation and development environment, refer to Chapter 4, Software Development Guide.

3.1 Download Authorization

If you have completed the account creating and need to generate your own HTTPS password before downloading the code, please download the repository `https://gerrit.rock-chips.com:8443/repo-release/tools/script` and download the authorization through the `script/Generate-Credential.sh` under the repository, this is shown below.

```
mkdir ~/rk_gerrit_password
cd ~/rk_gerrit_password
git clone https://gerrit.rock-chips.com:8443/repo-release/tools/script
cd ./script
./Generate-Credential.x
```

The log of running the authorization script is as follows:

```
Adding configuration for Gerrit server to /home/Test123/rk_gerrit_password
********************************************************************************
********************************************************************************
**************************************************
 Copyright Statement

 Copyright (C) 2026 Rockchip Electronics Co., Ltd. All rights reserved.

 BY OPENING OR USING THIS FILE, RECEIVER HEREBY ACKNOWLEDGES AND AGREES THAT THE
SOFTWARE/FIRMWARE AND ITS DOCUMENTATIONS ("ROCKCHIP SOFTWARE") RECEIVED FROM ROCKCHIP ON AN
"AS-IS" BASIS ONLY WITHOUT ANY AND ALL WARRANTIES,
 EITHER EXPRESS, IMPLIED OR STATUTORY, INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OR
CONDITION WITH RESPECT TO TITLE, MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE, OR
NON-INFRINGEMENT.
 NEITHER DOES ROCKCHIP PROVIDE ANY WARRANTY WHATSOEVER WITH RESPECT TO ANY OPEN SOURCE
TECHNOLOGIES, THIRD-PARTY TECHNOLOGIES OR ANY STANDARD TECHNOLOGIES WHICH MAY BE SUPPORTED
BY, INCORPORATED IN, OR SUPPLIED WITH THE ROCKCHIP SOFTWARE.
 RECEIVER EXPRESSLY ACKNOWLEDGES THAT IT IS RECEIVER'S SOLE RESPONSIBILITY TO OBTAIN AND
MAINTAIN ALL NECESSARY LICENSES AND RIGHTS FROM THEIR RESPECTIVE OWNERS TO USE ANY SUCH
THIRD-PARTY TECHNOLOGIES OR ANY STANDARD TECHNOLOGIES.
 RECEIVER'S SOLE AND EXCLUSIVE REMEDY AND ROCKCHIP'S ENTIRE AND CUMULATIVE LIABILITY WITH
RESPECT TO THE ROCKCHIP SOFTWARE RELEASED HEREUNDER WILL BE, AT ROCKCHIP 'S OPTION, TO
REVISE OR REPLACE THE ROCKCHIP SOFTWARE AT ISSUE,
 OR REFUND ANY FEES OR CHARGE PAID BY RECEIVER TO ROCKCHIP FOR SUCH ROCKCHIP SOFTWARE AT
ISSUE.
********************************************************************************
********************************************************************************
**************************************************
Do you agree to the above terms? (yes/no) yes
Please input your username (make sure to use the username exactly the same as the one in RK
email!!): Test123
Please input your email (make sure to use the company email address!!): Test123@rock-
chips.com
Please input your SSH private key filename (e.g. id_rsa):
Your Credential check has passed
New git credential will be added into your history!!
You are All Set!!
```

3.2 Get Source Code from Rockchip Code Server

To get RK3572 Linux SDK software package, customers need an account to access the source code repository provided by Rockchip. In order to be able to obtain code synchronization, please provide SSH public key for server authentication and authorization when apply for SDK from Rockchip technical window. About Rockchip server SSH public key authorization, please refer to Chapter 6 SSH Public Key Operation Introduction.

Linux6.12 SDK download command is as follows:

Download address:

```
repo init --repo-url https://gerrit.rock-chips.com:8443/repo-release/tools/repo \
-u https://gerrit.rock-chips.com:8443/linux/rockchip/platform/manifests -b \
linux6.12 -m rockchip_linux6.12_release.xml
```

Server mirror download:

```
repo init --repo-url https://gerrit.rock-chips.com:8443/repo-release/tools/repo \
-u https://gerrit.rock-chips.com:8443/linux/rockchip/platform/manifests -b \
linux6.12 -m rockchip_linux6.12_release.xml --mirror
```

repo is a script written by Google in Python that calls git, mainly used to download and manage software repositories of projects. The download address is as follows:

```
git clone https://gerrit.rock-chips.com:8443/repo-release/tools/repo
```

3.3 Get Source Code from Local Compression Package

For quick access to SDK source code, Rockchip Technical Window usually provides corresponding version of SDK initial compression package. In this way, developers can get SDK source code through decompressing the initial compression package, which is the same as the one downloaded by repo. Take ROCKCHIP_LINUX6.12_SDK_ALPHA_V0.0.1_20260320.tgz as an example. After getting an initialization package, you can get source code by running the following command:

```
mkdir rockchip_linux6.12
tar xvf ROCKCHIP_LINUX6.12_SDK_ALPHA_V0.0.1_20260320.tgz -C rockchip_linux6.12
cd rockchip_linux6.12
.repo/repo/repo sync -l
.repo/repo/repo sync -c
```

Developers can update via `.repo/repo/repo sync -c` command according to update introductions that are regularly released by FAE window.

If you encounter issues downloading the repository, you can use the `--force-sync` parameter to force an update, as in `.repo/repo/repo sync -c --force-sync`. Before doing so, please ensure that any local modifications have been backed up.

After updating the SDK code, a clean operation is required. For example: `./build.sh cleanall`

> Note: The software release version can be viewed through engineering XML, as follows:

```
.repo/manifests$ realpath rockchip_linux6.12_release.xml
e.g., the printed version is v0.0.1 and the update time is 20260320
<SDK>/.repo/manifests/release/rockchip_linux6.12_alpha_v0.0.1_20260320.xml
```

4. Software Development Guide

For software development, please refer to the quick start documents in the project directory:

```
<SDK>/docs/en/Release/Rockchip_Quick_Start_Linux_EN.pdf
```

5. SSH Public Key Operation Introduction

Please follow the introduction in the “Rockchip_User_Guide_SDK_Application_And_Synchronization_EN” to generate an SSH public key and send the email to sw.fae@rock-chips.com, to get the SDK code. This document will be released to customers during the process of applying for permission.

5.1 Key Authority Management

Server can monitor download times and IP information of a key in real time. If an abnormality is found, download permission of the corresponding key will be disabled.

Keep the private key file properly. Do not grant second authorization to third parties.

5.2 Reference Documents

For more details, please refer to document
“/docs/en/Others/Rockchip_User_Guide_SDK_Application_And_Synchronization_EN.pdf”